

EDN[®]

Evaluate the tradeoffs in
linear-semicustom designs
Accurate sampling techniques
Display-driver ICs
Designing to
telecomm standards

ELECTRONIC TECHNOLOGY FOR ENGINEERS AND ENGINEERING MANAGERS

Simulators zoom in on ASIC requirements



A breakthrough in op amps: golden opportunities for precision system upgrades!

Higher speed and precision, plus ultra-low noise!

Our op amps have broken out of the old performance limits shell — so you can hatch new designs that upgrade system performance. In your process control, test and medical equipment. In military systems like avionics and sonar.


Use our HA-5147 op amp for closed-loop gains of 10 or greater. It delivers 35 V/ μ s slew rate, only 3 nV/ $\sqrt{\text{Hz}}$ noise, and these outstanding specs:

- 10 μ V offset voltage
- 0.2 μ V/ $^{\circ}\text{C}$ offset drift
- 120 MHz gain bandwidth
- 126 dB CMRR/PSRR

There's more: voltage gain of 1.8 million, and temperature ranges for military, industrial and commercial applications. Packaging: TO-99 cans, 8-pin cerdips, plus leadless chip carriers (LCCs) for space-saving surface mounting.

For system upgrades by the dozen, use our HA-5147. Or choose our HA-5127 or HA-5137 as plug-in replacements for OP27 and OP37.

For details contact: Harris/MHS Semiconductor Sales Ltd., Eskdale Road, Winnersh, Wokingham, Berks, RG11 5TR, England.



FOR YOUR INFORMATION,
OUR NAME IS
HARRIS

Harris Semiconductor: Analog - CMOS Digital
Gallium Arsenide - Semicustom - Custom




*"Look: this one's got
speed, precision, and
ultra-low noise!"*

*"Another designer cracks
the secret of the HA-5147."*



Solutions




**Chosen for
high visibility
and versatility.**

Dale Displays.

When you need exceptional viewing characteristics and compact size, Dale plasma panel displays offer extra value and reliability. Our versatile display module family includes bar graphs, alpha-numeric displays and graphics displays. All offer high brightness (up to 100 ft. lamberts) and a wide (150°) viewing angle. In addition, most models accept serial or parallel inputs and can be provided with STD Bus interface. For fast, personal attention to your display needs, contact Dale Electronics, Inc., 2064 12th Avenue, Columbus, NE 68601.

For more details, call: **402-564-3131**

Circle No. 1



**You can
see the
advantages.**

Dale Displays.

Bright. Legible. Versatile. We're ready to help you use the advantages of plasma panel displays wherever you need to convey information. Our new bar graph models handle a wide range of control and indication needs. Each has dual linear graphs with 201 or 101 elements, resolution down to 1/2% and requires a minimum of drive circuits. In addition, standard segmented and dot matrix styles with up to 256 characters are available with complete drive electronics. To get more details contact: Dale Electronics, Inc., 2064 12th Ave., Columbus, NE 68601

For complete information: **402-564-3131**


Circle No. 2

Dale makes your basics better.



G'day Mate!

Announcing Prem's latest series of telephone/modern interconnect transformers has been approved by Telecom Australia (approval file number RA-87/117).



Available from stock, this new series compliments the almost 100 other Prem interconnects that have been designed for use in FCC, DOC, BSI, and other worldwide applications. Custom designs are also available.

Whatever your marketplace, Prem's **FREE CATALOG** contains a full line of interconnect products (with detailed specifications) designed to meet your requirements.

See our Telecommunication Magnetics and Power Transformer Catalog in 1987-88 EEM. Standard Inductor Catalog and our custom power spec sheet available upon request.

FREE Catalog

PREM[®]
MAGNETICS,
INCORPORATED

3521 North Chapel Hill Road
McHenry, IL 60050
Phone 815-385-2700
TWX 910-642-3763
FAX 815-385-8578

SURFACE MOUNT MIXERS



\$2.49
(1,000 qty)

The opportunity for automated, low-cost assembly is a key benefit of surface-mount technology, but is often wiped out by the high price of surface-mount components. Now, Mini-Circuits offers a new series of mixers to meet the pricing demands of SMT ... only \$2.49 in 1,000 quantity (\$3.75 ea. in quantity of 10) ... at a cost even lower than most conventionally-packaged mixers.

The SCM-1 spans 1 to 500MHz with only 6.0dB conversion loss, 45dB LO-RF isolation, and 40dB LO-IF isolation. Housed in a rugged, non-hermetic 0.4 by 0.8 by 0.3 in. high (maximum dimensions) plastic/ceramic package. Spacing between connections is 0.2 in. The mixer is offered with leads (SCM-1L) or without leads (SCM-1NL) to meet a wide range of pc board mounting configurations.

Each SCM-1 is built to meet severe environmental stresses including mechanical shock/vibration as well as temperature shock. The operating and temperature storage range is -55°C to +100°C. Each SCM-1, designed and built to meet today's demanding reliability requirements, carries Mini-Circuits' exclusive 0.1% AQL guarantee of no rejects on every order shipped (up to 1,000 pieces).

When you think SMT for low-cost production, think of Mini-Circuits' low-cost SCM mixers.

SPECIFICATIONS (typical)

FREQ. RANGE (MHz)

LO, RF
IF

CONVERSION LOSS (dB)

Mid-Band (10-250MHz)
Total Range (1-500)

ISOLATION (dB)

Low-Band (1-10MHz)
Mid-Band (10-250MHz)
High-Band (250-500MHz)

PRICE \$2.49 (1,000 qty)
\$3.75 (10-49)

SCM-1L (with leads)

SCM-1NL (no leads)

1-500
DC-500

6.3
7.5

	(L-R)	(L-I)
Low-Band (1-10MHz)	60	45
Mid-Band (10-250MHz)	45	40
High-Band (250-500MHz)	40	35

Units are shipped in anti-static plastic
"tubes" or "sticks" for automatic insertion.

CIRCLE NO 83

finding new ways ...
setting higher standards


Mini-Circuits

A Division of Scientific Components Corporation
P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500
Fax (718) 332-4661 Domestic and International Telexes: 6852844 or 620156

C115 REV. ORIG.

99¢

from



dc to 2000 MHz amplifier series


SPECIFICATIONS

MODEL	FREQ. MHz	GAIN, dB				• MAX. PWR. dBm	NF dB	PRICE \$ Ea.	Qty.
		100 MHz	1000 MHz	2000 MHz	Min. (note)				
MAR-1	DC-1000	18.5	15.5	—	13.0	0	5.0	0.99	(100)
MAR-2	DC-2000	13	12.5	11	8.5	+3	6.5	1.50	(25)
MAR-3	DC-2000	13	12.5	10.5	8.0	+8 □	6.0	1.70	(25)
MAR-4	DC-1000	8.2	8.0	—	7.0	+11	7.0	1.90	(25)
MAR-6	DC-2000	20	16	11	9	0	2.8	1.29	(25)
MAR-7	DC-2000	13.5	12.5	10.5	8.5	+3	5.0	1.90	(25)
MAR-8	DC-1000	33	23	—	19	+10	3.5	2.20	(25)

NOTE: Minimum gain at highest frequency point and over full temperature range.

- 1dB Gain Compression
- +4dBm 1 to 2 GHz

designers amplifier kit, DAK-2
5 of each model, total 35 amplifiers
only **\$59.95**



Unbelievable, until now...tiny monolithic wide-band amplifiers for as low as 99 cents. These rugged 0.085 in.diam., plastic-packaged units are 50ohm* input/output impedance, unconditionally stable regardless of load*, and easily cascable. Models in the MAR-series offer up to 33 dB gain, 0 to +11dBm output, noise figure as low as 2.8dB, and up to DC-2000MHz bandwidth.

*MAR-8, Input/Output Impedance is not 50ohms, see data sheet.
Stable for source/load impedance VSWR less than 3:1

Also, for your design convenience, Mini-Circuits offers chip coupling capacitors at 12 cents each.†

Size (mils)	Tolerance	Temperature Characteristic	Value
80 x 50	5%	NPO	10, 22, 47, 68, 100, 470, 680, 100 pf
80 x 50	10%	X7R	2200, 4700, 6800, 10,000 pf
120 x 60	10%	X7R	.022, .047, .068, .1µf

† Minimum Order 50 per Value

finding new ways ...
setting higher standards

Mini-Circuits

A Division of Scientific Components Corporation
P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500
Fax (718) 332-4661 Domestic and International Telexes: 6852844 or 620156



On the cover: Digital-ASIC simulation packages keep chip designs on course. See pg 118. (Photo courtesy Ikos Systems)

DESIGN FEATURES

ASIC simulators

118

Sophisticated digital simulators can help you develop your application-specific IC (ASIC) designs. Simulators can prevent chip-level design problems and can often come up with good test-vector sets, but they can't correct failures resulting from the old engineering bugaboo—inadequate design specifications.—*Margery S Conner, Regional Editor*

Consider the tradeoffs when evaluating linear-semicustom ICs

135

System designers face special problems when creating analog circuits for semicustom IC fabrication. Unlike digital circuits, which you can readily subdivide into simple gates, analog circuits are highly irregular, require different design methods, and frequently need nonintegrable external components.—*Bruce Moore, Raytheon Semiconductor, and Will Ritmanich, Consultant*

S/H amp-ADC matrimony provides accurate sampling

153

When using an A/D converter to capture samples of moving signals, you usually need a sample-and-hold amplifier to hold the voltage steady at the converter's input. If you don't choose the right S/H amplifier for the application, signal degradation in the form of distortion and reduced dynamic range invariably results.—*Al Little and Bob Burnett, Harris Corp*

Heed local norms when designing telecomm interfaces

175

In designing customer-premises telecomm equipment for foreign markets, you must account for the respective countries' national telecommunications standards. These norms often differ in significant ways from the FCC Rules Part 68, which governs telecomm equipment in the US.—*Glen Dash, Dash, Straus & Goodhue Inc*


Continued on page 7



VBPA ABP



EDN® (ISSN 0012-7515) is published 38 times a year (biweekly with 1 additional issue a month) by Cahners Publishing Company, A Division of Reed Publishing USA, 275 Washington Street, Newton, MA 02158-1630. Terrence M McDermott, President; Frank Sibley, Electronics/Computer Group Vice President; Jerry D Neth, Vice President/Publishing Operations; J J Walsh, Financial Vice President/Magazine Division; Thomas J Dellamaria, Vice President/Production and Manufacturing. Circulation records are maintained at Cahners Publishing Company, 44 Cook Street, Denver, CO 80206-5191. Telephone: (303) 388-4511. Second-class postage paid at Denver, CO 80206-5191 and additional mailing offices. POSTMASTER: Send address corrections to EDN® at the Denver address. EDN® copyright 1988 by Reed Publishing USA; Saul Goldweitz, Chairman; Ronald G Segel, President and Chief Executive Officer; Robert L Krakoff, Executive Vice President; William M Platt, Senior Vice President. Annual subscription rates for nonqualified people: USA, \$95/year; Canada/Mexico, \$110/year; Europe air mail, \$135/year; all other nations, \$135/year for surface mail and \$200/year for air mail. Except for special issues where price changes are indicated, single copies of regular issues are available for \$6, \$8, and \$10 (USA, Canada/Mexico, and foreign). Please address all subscription mail to Eric Schmierer, 44 Cook Street, Denver, CO 80206-5191.



A NEW WORLD OF HIGH POWER FLEXIBILITY



Westcor's PowerCage™ and PowerCards™ comprise a modular power supply system of galactic power (7200 watts max.), flexibility (36 outputs max.) and efficiency (80% typ.). More like an expandable computer mainframe in design and concept than a standard high power supply, the PowerCage offers space-age alternatives to users of outdated 5x8x11 inch box switchers.

Measuring 19x10.5x11.25 inches deep the PowerCage fits into a standard NEMA rack and powers 18 slots for single or dual output PowerCards or dummy cards. PowerCage backplanes provide connections for easy configuration by the user.

Low profile (.8") PowerCards supply single outputs from 2 to 75 VDC at up to 400 watts (outputs from 2 to 5 VDC limited to 60 amperes). Dual output cards source two isolated outputs each at half of the above ratings. Single output cards can be paralleled with current sharing to provide kilowatts via simple backplane configuration.


The nucleus of each PowerCage system is Westcor's patented 1 MHz, high power density, high reliability converter. Consider these benefits and features: 208 VAC 3 phase input; remote/local sense on all outputs; TTL power good signal and status LED's; designed to meet UL, CSA and VDE safety requirements; TTL inhibit; over-temperature, over-current, over-voltage protection; "hot" card insertion; full power at 50°C.

Future options include: DC input; IEEE-488 programmability; fault tolerant operation and battery backup. To discover a new world of high power flexibility, please contact us.




WESTCOR CORPORATION • 485-100 Alberto Way • Los Gatos, CA 95032 • (408) 395-7050 • FAX (408) 395-1518 • TWX 910-240-2108.

CIRCLE NO 142



With today's new generation of calibrators and digital multimeters, you can attain accuracy previously impossible to achieve outside of a standards lab (pg 57).

EDN magazine now offers Express Request, a convenient way to retrieve product information by phone. See the Reader Service Card in the front for details on how to use this free service.

Express Request 

TECHNOLOGY UPDATE

High-performance DMMs and calibrators bring standards-lab specs to the benchtop 57

To satisfy their customers' demands for improved performance, engineers who design and test products such as data converters and automatic test equipment (ATE) must make increasingly accurate basic measurements in their labs, in production, and in systems.—*Dan Strassberg, Associate Editor*

Innovations in monolithic display drivers improve flat-panel cost/performance ratios 75

Generally it's hard to beat the cost/performance ratio of complete flat-panel display systems, but you may have an application in which it makes sense to build, rather than buy, the displays.—*Jim Wiegand, Associate Editor*

Plug-in boards let your personal computer perform parallel-processing tasks 89

You can now select from a number of IBM PC-compatible expansion cards that give your desktop computer computational power approaching that of a Cray supercomputer.—*J D Mosley, Regional Editor*

PRODUCT UPDATE

PLD design software 101

Digital precision motion controller 104

DESIGN IDEAS

Soft-start and delay protects power supply 189

Pulse-burst generator is programmable 190

Power circuit has constant full scale 192

Switched signal powers analog switch 196

Zero-current sensor protects relay contacts 196

Continued on page 9

Cahners Publishing Company, A Division of Reed Publishing USA ☐ Specialized Business Magazines for Building & Construction ☐ Manufacturing ☐ Foodservice & Lodging ☐ Electronics & Computers ☐ Interior Design ☐ Printing ☐ Publishing ☐ Industrial Research & Technology ☐ Health Care ☐ and Entertainment. Specialized Consumer Magazines: ☐ American Baby ☐ and Modern Bride.



~~1600~~ 1400 PROGRAMMABLE REASONS TO MOVE UP TO THE 29B.

With support for an additional 200 devices, the 29B Universal Programming System continues to program virtually every device on the market, including the latest one megabit EPROMs and PLDs in PLCC packages. And the 29B continues to support more devices than any other programmer, because no one is more committed to keeping pace with the semiconductor manufacturers than Data I/O®.

THE 29B GIVES YOU A PROGRAMMING FUTURE. While the 29B supports more than 1600 devices, you don't have to buy support for every device all at once. Its modular system of paks gives you the flexibility to build a universal programming system at your own pace—whether

gradually or all at once. For example, you can start with gang and set programming for EPROMs and EEPROMs. Later, expand your system by adding logic or bipolar PROM programming.

MANUFACTURER-APPROVED ALGORITHMS FOR RELIABILITY. The 29B provides manufacturer-approved algorithms for superior programming. So, whether you operate the system in the stand-alone mode, from a terminal, or from a personal computer using PROMlink™ programmer interface software, you're guaranteed reliable, trouble-free programming and maximum yields. It's this dedication to superior performance and complete device support that's made the 29B the leader, year after year.

UPGRADE

For a limited time only, you'll receive a credit towards a new 29B mainframe, UniPak 29B™, or GangPak™ when you upgrade your equivalent Data I/O equipment, including the 17, 19, 100A or 29A mainframe; UniPak; or 24/28-Pin Gang Module.

TRADE IN

Or trade in any other programmer (from any manufacturer), and you'll receive a credit towards the 29B Memory, Logic, or Gang Programming System.

Call to find out exactly how much your programmer is worth. But hurry! This offer ends March 31, 1988.

1-800-247-5700
Dept. 452

Data I/O Corporation 10525 Willows Road N.E., P.O. Box 97046, Redmond, WA 98073-9746, U.S.A. (206) 881-6444/Telex 15-2167
FutureNet 9310 Topanga Canyon Boulevard, Chatsworth, CA 91311-5728 (818) 700-0691/Telex 910-494-2681
Data I/O Canada 6725 Airport Road, Suite 302, Mississauga, Ontario L4V 1V2 (416) 678-0761/06968133
Data I/O Europe World Trade Center, Strawinskylaan 653, 1077 XX Amsterdam, The Netherlands (20) 622866/Telex 16616 DATAIO NL
Data I/O Japan Sumitomoseimei Higashishinbashi Bldg., 8F, 2-1-7, Higashi-Shinbashi, Minato-ku, Tokyo 105, Japan (03) 432-6991/Telex 2522685 DATAIO J

©1987 Data I/O Corporation.

DATA I/O

VP/Publisher
F Warren Dickson

VP/Associate Publisher/Editorial Director
Roy Forsberg

Editor
Jonathan Titus

Managing Editor
John S Haystead

Assistant Managing Editor
Joan Morrow

Special Projects
Gary Legg

Home Office Editorial Staff
275 Washington St, Newton, MA 02158
(617) 964-3030

Tom Ormond, *Senior Editor*
Deborah Asbrand, *Associate Editor*
Joanne Clay, *Associate Editor*
Tarlton Fleming, *Associate Editor*
John A Gallant, *Associate Editor*
Clare Mansfield, *Associate Editor*
Dave Pryce, *Associate Editor*
Cynthia B Rettig, *Associate Editor*
Charles Small, *Associate Editor*
Dan Strassberg, *Associate Editor*
Chris Terry, *Associate Editor*
Jim Wiegand, *Associate Editor*
Ron Gilbert, *Staff Editor*
Valerie Lauzon, *Staff Editor*
Helen McElwee, *Staff Editor*
Steven Paul, *Senior Production Editor*

Editorial Field Offices

Margery S Conner, *Regional Editor*
Los Osos, CA: (805) 528-0833

Doug Conner, *Regional Editor*
Los Osos, CA: (805) 528-0864

Bob Cushman, *Special Features Editor*
Port Washington, NY: (516) 944-6524

Steven H Leibson, *Regional Editor*
Boulder, CO: (303) 494-2233

J D Mosley, *Regional Editor*
Arlington, TX: (817) 465-4961

Richard A Quinnell, *Regional Editor*
San Jose, CA: (408) 296-0868

David Shear, *Regional Editor*
San Jose, CA: (408) 997-5452

Maury Wright, *Regional Editor*
San Diego, CA: (619) 748-6785

Peter Harold, *European Editor*
0603-630782
(St Francis House, Queens Rd,
Norwich, Norfolk NR1 3PN, UK)

Contributing Editors
Robert Pease, Bob Peterson,
Don Powers, Bill Travis

Editorial Services
Kathy Leonard, *Office Manager*
Loretta Curcio, Nancy Weiland,
Sharon Gildea

Art Staff
Kathleen Ruhl, *Art Director*
Ken Racicot, *Assistant Art Director*
Chin-Soo Chung, *Graphic Designer*
Cathy Filipski, *Graphic Designer*

Production/Manufacturing Staff
William Tomaselli, *Production Supervisor*
Donna Pono, *Production Manager*
Andrew A Jantz, *Production Assistant*
Diane Malone, *Composition*

Graphics Director
Norman Graf

VP/Production/Manufacturing
Wayne Hulitzky

Director of Production/Manufacturing
John R Sanders

Director of Research
Deborah Virtue

Marketing Communications
Janice Molinari, *Manager*
Jennifer Ware, *Communications Manager*
Corie Rand, *Promotion Coordinator*
Anne Foley, *Promotion Assistant*

EDITORIAL

53

Instead of taking seriously the calls for reform, the IEEE has adopted a siege mentality that is leading to extinction.

NEW PRODUCTS

Components & Power Supplies	203
Computers & Peripherals	212
Integrated Circuits	219
Test & Measurement Instruments	226
CAE & Software Development Tools	233

PROFESSIONAL ISSUES

251

Placement Agencies: Let the job hunter beware.—*Deborah Asbrand, Associate Editor*


LOOKING AHEAD

263

Fax machines should see 25%/annum growth through 1991 . . . Humidity/moisture devices to gross \$113.9M by 1992.

DEPARTMENTS

News Breaks	23
News Breaks International	26
Signals & Noise	34
Calendar	46
Readers' Choice	111
Leadtime Index	114
Literature	246
Business/Corporate Staff	248
Career Opportunities	254
Advertisers Index	262



SINGLE PRECISION WHETSTONE LEAGUE



INMOS.
IMS T800 TRANSPUTER.
4.6 MEGAWHETSTONES.



INTEL.
386/387 16 MHz
1.8 MEGAWHETSTONES.





MOTOROLA.
68020/68881 20 MHz
1.5 MEGAWHETSTONES.



DEC.
VAX 11/780/FPA
1.1 MEGAWHETSTONES.

DOUBLE PRECISION WHETSTONE LEAGUE



ONE T800 TRANSPUTER GIVES
2.5 DOUBLE PRECISION
MEGAWHETSTONES...
SO WHEN IT COMES TO
PROCESSING POWER SEVEN
INMOS T800 CHIPS COULD
GIVE THE MIGHTY CRAY T3E,
RATED AT 16.1 MEGAWHETSTONES
A REAL RUN FOR ITS MONEY!



MORE MULTIPROCESSOR MUSCLE. MORE RAW PERFORMANCE.

When you're out in the trenches fighting it out with ordinary microprocessors, running out of muscle is all too easy. That's why you should look to the new T800 Transputer from INMOS.

The T800 is the fastest 32-bit, single chip, floating-point microprocessor available today. A quick glance at its statistics will show why nothing else is in its league...

32-bit enhanced RISC processor...64-bit on-chip IEEE floating-point processor...4K Bytes on-chip 50ns static RAM...Four 20 MBits/sec interprocessor communication links...Eight independent DMA engines. All on a single chip capable of sustained 1.5 MFLOPS...and 4.6M Whetstones!

And, if that's not enough raw power, the T800's links allow multiprocessor systems to be constructed quickly and easily - giving you 6 MFLOPS with four T800's...30 MFLOPS with 20...150 MFLOPS with 100...In fact, there's no limit to the number of Transputers you can use!

Programming Transputers couldn't be easier, with compilers for C, Fortran and Pascal, and the world's first concurrent programming language OCCAM.

Want to turbocharge your current system? No problem. Our exclusive Link Adaptor IC's allow Transputers to be connected to other

microprocessors or peripherals.

Other team members include the pin compatible T414 Transputer, offering lower cost, 10 MIP performance and 0.75M Whetstones. Lined-up to provide all the I/O processing you need, the T212 16-bit Transputer is the ideal high performance controller and the M212 Disk Processor combines disk controller hardware and a Transputer on a single chip, supporting both Winchester and floppy disks. And the C004 Link Switch makes the design of software reconfigurable multiprocessor systems as easy as kicking an extra point.

Whatever field you're in - from real-time distributed systems to high-performance graphics, from fault-tolerant systems to robotics, Transputer technology can give you scalable performance at a cost you can afford.

Transputers are manufactured using an advanced 1.5 micron CMOS process which keeps the power consumption under one watt. So your system stays cool while under fire.

Transputers to MIL-STD 883C will be available in the first half of 1988.

If all this sounds like your kind of game, put the ball in play by contacting your local INMOS sales office today. And get ready to score.

DESCRIPTION			PERFORMANCE		AVAILABILITY		PACKAGE
Part No.	Word Length	Clock MHz	Integer Drystones	Floating Point Whetstones	Commercial	Military	
IMST800-20	32-Bit	20	9500	4.6 Million	Now	Q2 88	84 PGA
IMST414-20	32-Bit	20	9500	0.75 Million	Now	Q2 88	84 PGA
IMST212-17	16-Bit	17	8000	-	Now	Q2 88	68 PGA
IMST212-20	16-Bit	20	9500	-	Now	Q2 88	68 PGA
IMSM212-17	16-Bit	17	8000	-	Now	-	68 PGA
NETWORK SUPPORT PRODUCTS					AVAILABILITY		PACKAGE
Part No.	Description	Communication Speed			Commercial	Military	
IMSC004	Software configurable 32 way link switch	10 + 20 MBits/sec			Now	Q2 88	84 PGA
IMSC011	Link to system bus	10 + 20 MBits/sec			Now	-	24 Pin DIP
IMSC012	Link to system bus	10 + 20 MBits/Sec			Now	Q2 88	24 Pin DIP

THE TRANSPUTER TEAM



INMOS, Colorado Springs, Colorado 80935. Tel. (303) 630-4000.

Orange County - 714-957-6018
Santa Clara - 408-727-7771

Denver - 303-252-4100
Minneapolis - 612-932-7121


Dallas - 214-490-9522
Boston - 617-366-4020

Baltimore - 301-995-6952
Atlanta - 404-242-7444

- ☐ Send me information on the Transputer Team. ☐ Send me the Transputer White Pages, a listing of third-party manufacturers' transputer-based products and services.
☐ Please have a Field Applications Engineer call. ☐ Please have a salesman call.

Name _____ Title _____
Company _____ Address _____
_____ Zip _____ Tel _____

INMOS Transputer and IMS are trademarks of the INMOS Group of Companies.



**“ASICs CREATE A
SET OF TEST PROBLEMS.
WE NEED A WHOLE NEW**



WHOLE NEW DOESN'T THAT MEAN TEST STRATEGY?"

IT SURE DOES.

It's easy to see that the tremendous potential of ASICs has only just begun to be tapped. What's not so evident is the fact that developing these unique ASIC devices carries with it some unprecedented test problems. Problems that traditional test approaches and traditional ATE simply are not equipped to handle.


At ASIX Systems our focus has always been exclusively on ASICs. From the start we recognized the unique ASIC test problems. That's why we took an entirely different approach to solving these problems. For instance, we saw that adapting existing ATE to fit the needs of ASICs didn't make sense. Designing a totally new, focused ASIC test system did. Test programs needed to be automated, developed from the design data base, and simple to change. The test system itself needed to be easy to use, designed for its particular environment, and a cost-effective alternative to the huge, expensive, complicated ATE.

TEST SOLUTIONS FOR THE WHOLE ASIC COMMUNITY.

Our unique perspective allowed us to understand that the ASIC world is not Design Engineers, Test Engineers and Quality Engineers performing separate functions. It's actually a "community" of specialists whose tasks are intrinsically linked. So we made sure that we could provide another crucial element. Communication. In order to capture the vital time-to-market edge, what ASIC designers and vendors really need is the opportunity to use the same test programs and the same tester. Because when both environments are working from a common frame of reference there can be some real communication about test results. That's a whole new way of looking at ASIC testing. That's the ASIX-1 family of test systems.

ASIX-1: ASIC TEST SYSTEMS THAT MAKE SENSE.

This isn't the place to tell you everything the ASIX-1 family has to offer. But here are a few things to think about: automatic, menu-guided programming; data base management; ATE architecture and flexibility at an affordable cost; 256 true I/O pins; "zero footprint"; fully integrated PMU; automatic calibration; simple fixturing; no cabling; high MTBF. Enough. You get the point. You really ought to see the ASIX-1 for yourself. And the sooner the better. ASIX Systems Corporation • 47338 Fremont Blvd • Fremont, CA 94538.



CALL: 1-800-FOR-ASIX

ASIX
SYSTEMS

**REAL ASIC TEST SOLUTIONS.
FROM THE REAL ASIC TEST COMPANY.**

Argentina
 Buenos Aires
 (01) 541 - 7141 to 7747
Australia
 Artamon, N.S.W.
 (02) 439 3322
Austria
 Wien
 (0222) 60101-820
Belgium
 Bruxelles
 (02) 525 61 11
Brazil
 Sao Paulo
 (011) 211-2600
Canada
 Scarborough
 (416) 292-5161
 Signetics Etobicoke
 (416) 626-6676
Chile
 Santiago
 (02) 7738 16
Colombia
 Bogota, D.E.
 (01) 249 7624
Denmark
 Copenhagen
 (01) 54 11 33
Finland
 Helsinki
 (90) 1 72 71
France
 Issy-Les-Moulineaux,
 Cedex
 (01) 40 93 80 00
Germany
 (Fed. Republic)
 Hamburg
 (040) 3296-0
Greece
 Tavros
 (01) 48 94 339/4894 911
Hong Kong
 Kwai Chung
 (0) 24 51 21
India
 Bombay
 (022) 4930311/4930590
Indonesia
 Jakarta
 (021) 51 79 95
Ireland
 Dublin
 (01) 69 33 55
Italy
 Milano
 (02) 6752.1
Japan
 Signetics Japan Ltd.
 Tokyo (03) 230-1521
Korea (Republic of)
 Seoul
 (02) 794-5011
Malaysia
 Pulau Pinang
 (04) 87 00 44
Netherlands
 Eindhoven
 (040) 78 37 49
New Zealand
 Auckland
 (09) 605-914
Norway
 Oslo
 (02) 68 02 00
Pakistan
 Karachi
 (021) 72 57 72
Peru
 Lima
 (014) 707080
Philippines
 Makati-Rizal
 (02) 86 89 51 to 59
Portugal
 Lisboa Codex
 (019) 68 31 21
Singapore
 Singapore
 35 02 000
South Africa
 Johannesburg
 (011) 402-4600/07
Spain
 Barcelona
 (03) 301 63 12
Sweden
 Stockholm
 (08) 7821000
Switzerland
 Zurich
 (01) 488 22 11
Taiwan
 Taipei
 (02) 7120500
Thailand
 Bangkok
 (02) 233-6330-9
Turkey
 Istanbul
 (01) 143 59 10
United Kingdom
 London
 (01) 580 6633
United States
 Signetics Corporation
 Sunnyvale
 (408) 991-2000
Uruguay
 Montevideo
 (02) 98 53 95
Venezuela
 Caracas
 (02) 239 39 31


Philips- far ahead with FAST.



Ogilvy & Mather

FAST is a trademark of the Fairchild Semiconductor Corporation





Philips offers you 182 types of Advanced low-power Schottky TTL ICs – 30% more than any other supplier. And they're all available in either DIL or SO packages.


When it comes to FAST, you go further with Philips.

If you'd like to meet the leader in FAST, contact your local Philips organization (see left).

**Our quality:
One standard.
Zero Defects.**


Philips Components Division, Building BA,
P.O. Box 218, 5600 MD Eindhoven,
The Netherlands.
Telex: 3500 phtc nl/nljevmc.

For Advanced Schottky TTL ICs,
the name is Philips.




Shows $< \pm 0.7$ LSB code width variation from ideal (definitely no missed codes)


CS5016 16-BIT DIFFERENTIAL NONLINEARITY AT 16µSEC CONVERSION TIME




CSZ5116 FFT PLOT WITH 1kHz FULL SCALE INPUT



CSZ5412 FFT PLOT WITH 100kHz FULL SCALE INPUT



SMART Analog TEMPERATURE STABILITY VS. COMPETITIVE 16-BIT HYBRID



**OUR 12-TO 16-BIT
CMOS A/D
CONVERTERS LOOK
GREAT ON PAPER.**

**AND ARE THE WORLD'S
BEST IN ACTION.**

Anyone can promise the world's best performance from monolithic CMOS A/D converters. Only Crystal can prove it.

Get your hands on the evaluation board of a Crystal SMARTAnalog™ device and you'll believe the breakthrough performance the plots on the opposite page promise.

Dynamic performance really is 92 dB SNR over a 25 kHz bandwidth, or 70 dB over 500 kHz.

Differential Non-Linearity of 16 bits with no missing codes is so outstanding we've published a DNL plot no one else dares to.

Stability over temperature is dramatically better than the competition across the entire military range.

Our reliability far surpasses the alternatives, with less than 52 failures per billion operating hours (FITs).

What the plots don't show, you already know: monolithic A/D converters using CMOS technology mean lower design and assembly costs, higher reliability,

DEVICE	STATIC-TESTED ADCs				DYNAMIC FFT-TESTED ADCs			
	CS5016	CS5014	CS5012	CS7820	CSZ5412	CSZ5316	CSZ5116	CSZ5112
Resolution	16	14	12	8	12	16	14	12
Conversion Time (μsec)	16	14	7	1.3	1.25	16	14	7
Throughput Speed (kHz)	50	56	100		1000	20	56	100
Static Specifications:								
Linearity Error (% FS, max)	+/- .0015	+/- .003	+/- .012	+/- .2	+/- .01			
No Missing Codes (Bits)	16	14	12	8	12	16	14	12
Dynamic Specifications:								
THD (%)					.02	.007	.001	.003
S/(N + D) (dB)					70	84	92	83
Power Dissipation (mW)	120	120	120	40	700	220	120	120
On-Chip Sample and Hold	YES	YES	YES	YES	YES	YES	YES	YES

The proof behind the promise: monolithic CMOS performance that beats even hybrids.

bility, lower power consumption, easier manufacturing and faster deliveries than hybrid or discrete designs can manage.

And our SMARTAnalog devices are the first with self-calibration at any time/temperature. Which ensures accuracy throughout their operating lives, correcting for gain, offset and even linearity errors. Automatically.

If that weren't enough, Crystal's SMARTAnalog line is the first line of 12- to 16-bit A/D converters with the converter, track/hold, digital interface, calibration circuitry and timing all on a single chip. So you can forget designing, building and characterizing discrete

devices while trying to correlate component specifications with system requirements.

Prove to yourself how our revolutionary SMARTAnalog technology makes hybrids a very expensive proposition, indeed. Call 512-445-7222 today for your very own 12-, 14- or 16-bit evaluation board. Or ask for a demonstration at your facility.

Either way, you'll know why seeing a SMARTAnalog converter in action makes our promises on the opposite page seem flat by comparison.

CRYSTAL
SEMICONDUCTOR CORPORATION


P.O. Box 17847, Austin, TX 78760

CIRCLE NO 48



512-445-7222: CALL TODAY

How To Wring Workstation-Level



P-CAD's new Master Designer turns an ordinary PC into a full-fledged PCB workstation.

When you need to wring every drop of performance out of your next PCB design, you need Master Designer™ software.


Master Designer provides all the horsepower, features and bells and whistles you'd expect only from workstations priced from \$50K, to as much as \$200K.

P-CAD®'s price? A tiny fraction of the cost of a workstation for the same performance. All on a PC!


With Master Designer you can tackle the really big jobs. Board designs with 500 EICs, 32,000 pins and 2,500 nets are just the beginning.

P-CAD's Master Designer routes multiple layers simultaneously cutting the number of vias and subnets in half. So you'll wring out cleaner designs and higher completion rates (up to 100%).

For forward annotation of logic changes and "history independent"



PCB Designs Out Of Your PC.



back annotation, Master Designer also has an ECO processing option.

And Master Designer supports all PCB design technologies. Including SMT, with a library of over 3,300 symbols and 4,600 parts.

Still not convinced?

If you're interested in wringing every penny out of your PCB design station instead of wringing your hands, ring P-CAD. Let P-CAD show you how to turn a PC into a high-powered workstation overnight.

P-CAD
1290 Parkmoor Avenue
San Jose, California 95126 USA
Telex: 371-7199

FAX: 408-279-3752

800-523-5207 U.S.

800-628-8748 CA

408-971-1300 Hdqtrs.

P-CAD is a registered trademark of
Personal CAD Systems, Inc. Master
Designer is a trademark of
Personal CAD Systems, Inc.





p-cad
PERSONAL CAD SYSTEMS INC.

CIRCLE NO 61

MT-2ST

HALF-HEIGHT DIGITAL CASSETTE DATA STREAMERS: AN IDEA WHOSE TIME HAS COME



60MB OF DATA VINTAGE 1987

**FAST, SIMPLE AND
RELIABLE BACKUP WITH
INTERCHANGEABLE
MEDIA**

Every year is a "vintage" when it comes to hard disk backup. No one can afford to have 60MB of data go sour. Use the TEAC MT-2ST data streamer for day-to-day backup or archival storage. Data cassettes are rugged, compact, ultrareliable, and cost-competitive. Direct reel drive enables precise speed/positional control without time-consuming media preformatting. Store anything from a single file to entire disk image under DMA control. And do it in 4 minutes (20MB), 10 (50MB) or 12 (60MB).

Full media compatibility means that complete data bases can be sent through the mail. D/CAS-05 (QIC-02), SCSI, or D/CAS-15 (QIC-36) interfaces available. Built-in data formatter for excellent space factor.

TEAC®

For Memories You'll Be Glad To Have

TEAC CORPORATION: 3-7-3 NAKA-CHO, MUSASHINO, TOKYO, JAPAN
TEL: (0422) 53-1111 TLX: 2822451 FAX: (0422) 55-2554

■ Hong Kong, Nissei Sangyo Co. Ltd. Hong Kong Branch tel: 3-343441-6; KARIN ELECTRONIC SUPPLIES CO., LTD. tel: 3-898252 ■ Singapore, Nissei Sangyo Pte. Ltd. tel: 65-7372011; UAC CORPORATION tel: 7450082 ■ New Zealand, Northrop Instruments & Systems Ltd tel: 856-658 ■ Australia, Electrical Equipment Limited tel: 888-9000 ■ Indonesia, CHUGAI BOYEKI CO. LTD. tel: 370824 ■ Philippines, COMPEX INTERNATIONAL INC. tel: 213020 ■ India, Priya Electronics & Chemicals Limited tel: 2863611 ■ Kuwait, Bader Al Mulla & Brothers Co. W.L.L. tel: 2423250 ■ South Africa, EPSIDON TECHNOLOGY (PTY) LTD. tel: (011) 787-1030/33 ■ United Kingdom, TEKDATA LIMITED tel: 0782 813631 ■ F.R. Germany, nbn Elektronik GmbH tel: 08152/390 ■ Austria, nbn Elektronik GmbH tel: 04762/5444 ■ Netherlands, SIMAC ELECTRONICS B.V. tel: 040-582911 ■ Belgium and Luxembourg, SIMAC ELECTRONICS SPRL/PVBA tel: 02-219.24.53 ■ France, TEKELEC AIRTRONIC S.A. tel: (1) 4534-75-35 ■ Italy, A.E.S.E. S.p.A tel: 02-54.64.741-2-3 ■ Spain, ATAIO Instrumentos S.A. tel: 733 05 62 ■ Switzerland, WENGER PERIPHERALS AG tel: 01/83075 55 ■ Denmark, Dansk Binaer Teknik A/S tel: 03-662020 ■ Sweden, MACROTEK AB tel: 08-733 02 20 ■ Norway, SCANTELE AS tel: (2) 65 69 20 ■ Finland, INSTRUMENTARIUM ELEKTRONIIKKA tel: 0-5284350

* If no distributor is listed above in your area, please contact us directly for further details about our products.

NEWS BREAKS

EDITED BY JOANNE CLAY

PLUG FOUR SMD DRIVES INTO YOUR SUN WORKSTATION

You can use the V/SMD 4400 Phoenix disk-controller board from Interphase (Dallas, TX, (214) 350-9000) to plug as many as four SMD or SMD/E disk drives into a Sun workstation. The board's BusPacket interface preformats packets of data in its high-speed bank of FIFO memory before acquiring control of the workstation's VME Bus. Then, once the BusPacket has control of the bus, the FIFO bank transfers the data as quickly as the bus and memory allow. This approach produces data-transfer rates over the VME Bus in excess of 30M bytes/sec. The board comes with installation software, boot ROMs, a queuing driver, a run-time formatter, and other utilities. You can purchase the board in single quantities for \$3350.—J D Mosley

SCHEMATIC-ENTRY PC-BOARD CAD SOFTWARE SELLS FOR \$395

The Capfast CF1000 software package for IBM PC/AT, PS/2, and compatible computers allows you to create pc-board schematics with an unlimited number of hierarchy levels. The package, from Phase Three Logic (Hillsboro, OR, (503) 640-2422), includes schematic and symbol editors, a symbol library containing more than 2000 components, a net-list extractor, a program for generating parts lists, and a plotting utility. The company claims that the software offers workstation-type features, such as on-line checking of electrical rules, dynamic panning, and split-screen capability.—Steven H Leibson

CMOS, MONOLITHIC 12-BIT A/D CONVERTER OFFERS 1-MHz SPEED

If you've been waiting for someone to develop a monolithic 12-bit A/D converter with the speed and accuracy of a hybrid device, you'll be pleased to learn that Crystal Semiconductor (Austin, TX, (512) 445-7222) now offers the CSZ5412-JC1—a CMOS device that operates at speeds as high as 1 MHz while consuming only 700 mW. Using a 2-step flash A/D conversion to achieve its high speed and accuracy, the CSZ5412 incorporates self-calibrating circuitry, pipelined acquisition and settling times, and overlapped conversion cycles. The chip also includes a track-and-hold amplifier, a 6-bit flash A/D converter, a 6-bit D/A converter, and a differential amplifier.

You can connect the CSZ5412 directly to a μ P's data and control buses because it comes with an overrange output, 3-state output buffers, and a flexible control interface. Alternatively, the device can operate in stand-alone mode, independently of microprocessor control. The CSZ5412-JC1 costs \$180 (100), and it includes the sample-and-hold circuitry that you must add to many competing hybrid devices. You can also order a similar device, the CSZ5412-JC2, which has a 500-kHz conversion rate and costs \$115 (100).—J D Mosley

E- AND D-SIZE ELECTROSTATIC PLOTTERS PRODUCE PRINTS AT 1 IN./SEC

The 8500 Series monochrome plotters from Versatec (Santa Clara, CA, (408) 988-2800) employ electrostatic raster-printing technology that results in a 1-in./sec plotting speed. You can use the 24- and 36-in.-wide plotters as a department or network resource because of the fast output speed. The Model 8524 plots on 24-in.-wide (D-size) paper and costs \$19,900; the Model 8536 uses 36-in.-wide (E-size) paper and sells for \$24,900. The 8500 Series includes a controller that performs a vector-to-raster conversion. The controller accepts input in the Hewlett-Packard Graphics Language (HPGL) and Calcomp 906/907 vector data formats. You can choose among various types of media, including opaque, translucent, and vellum paper and clear and matte polyester films. The plotters are available now.—Maury Wright

NEWS BREAKS

AC/DC CLAMP-ON PROBE EXTENDS YOUR DMM'S CAPABILITIES

To measure current in awkwardly located cables, you can use the Model 159 ac/dc clamp-on current probe from Simpson Electric Co (Elgin, IL, (312) 697-2260). Specifying a dc to 400-Hz frequency band for current ranging from 0.1 to 500A, this autoranging probe lets you gain access to cables mounted in almost any position without breaking the circuit you're measuring. The maximum jaw opening of the clamp is 1.3 in. You can use the Model 159 with digital or analog meters. Its maximum operating voltage is 660V rms, and it sells for \$169.—J D Mosley

\$995 INK-JET PRINTER PRODUCES 2 PAGES/MINUTE AT 300 DOTS/IN.

Offering the look of laser printing without the high cost, the Deskjet printer from Hewlett-Packard Co (Palo Alto, CA, phone local office) emulates the company's Laserjet laser printer but costs \$995. The Deskjet incorporates a drop-on-demand ink jet, and it can print text with graphics on plain paper at a rate of 2 pages/minute and with a resolution of 300 dots/in. It can print high-resolution or draft-quality text at 120 and 240 cps, respectively.

The printer's integral, front-loading sheet feeder accepts 100 sheets of paper and accommodates US letter, legal, and European A4 paper sizes. You can feed the printer #10 envelopes manually. The printer incorporates three built-in fonts—Courier, Courier Bold, and Courier Compressed—and accepts additional font cartridges through two accessory-cartridge ports. Each cartridge contains four or more fonts and costs \$75 to \$125. The printer's ink cartridge costs \$18.95 and lasts for 200 to 400 pages, depending on the amount of graphics printed.—Steven H Leibson

SOCKET SUITS TEST AND BURN-IN OF VLSI LCC DEVICES

Suitable for use during the test and burn-in of VLSI devices packaged in ceramic leadless chip carriers (LCCs), the 132-contact Textool socket from 3M (Austin, TX, (512) 834-6792) has leads on 0.025-in. centers. The socket is made of glass-fortified polyphenylene sulfide, and the contacts are of beryllium copper plated with 30 μ in. of gold over 50 μ in. of nickel. A thruster spring in the body of the socket applies a constant pressure to the chamfered corner of the device, so that the device is properly and securely seated during use. A specially designed latching cover and two stainless-steel posts in the socket's body help reduce socket wear. The socket costs \$38.94 (1000).—J D Mosley

80386-BASED WORKSTATIONS WILL RUN UNIX-BASED OPERATING SYSTEM

To create a common operating system for its line of 80386-based workstations, Daisy Systems Corp (Mountain View, CA, (415) 960-6591) has signed an agreement with Sun Microsystems whereby Sun will provide its Unix-based SunOS for Daisy's 80386-based workstations and Sun 4-based file servers. Daisy plans to release the SunOS-based workstations in the second half of 1988. The operating system will also incorporate the TCP/IP communications protocol (pioneered by the US Department of Defense) and Sun's Open Network Computing/Network File System (ONC/NFS).

The standard Unix-based environment will allow the workstation users to take advantage of the wide variety of available software-development tools and standard communications packages for integrating CAE networks with existing computer environments. The initial terms of the agreement between Daisy and Sun cover a 5-year period, during which Daisy will receive all enhancements made to the operating system, including any enhancements resulting from the joint development efforts of Sun and AT&T. Daisy doesn't plan to port SunOS to any of its 80286-based workstations.—Joanne Clay

Speed Reading.



A big book, packed full of record breaking, highest performance, lowest power parts.

Required reading for designers who are building faster systems that run cooler, and use less power.

Read all about:

CMOS high speed SRAM. From our 7ns 1K to our family of 25ns 64K SRAMs, with 30 + parts in between.

CMOS high speed PROM. Reprogrammable, if you wish. In a family with speeds as fast as 25ns and in sizes to 128K.

CMOS high speed PLD. Including the fastest, coolest CMOS 22V10 with 25ns quarter power performance, and optional reprogrammable versions.

CMOS high speed Logic. Highlighted by our 30ns 16-bit slice, and our 35MHz FIFO family in cool, cool CMOS.

And read about: Our expanding military product line. Our QuickPro™ for easy programming and diagnostics using any PC-compatible. Our newest products. And our applications notes.

624 pages of parts and ideas you can use to design faster, cooler systems.

Yours fast, for a toll-free phone call.

1-800-952-6300, ask for Dept. C48

1-800-423-4440 (In CA), ask for Dept. C48

(32) 2-672-2220 (In Europe). (416) 475-3922 (In Canada).



CYPRESS
SEMICONDUCTOR

Cypress Semiconductor 3901 North First Street, San Jose, CA 95134. Phone (408) 943-2666. Telex 821032 CYPRESS SNJ UD, TWX 910-997-0753. QuickPro is a trademark of Cypress Semiconductor.
©1987 Cypress Semiconductor.

NEWS BREAKS: INTERNATIONAL

μP PERIPHERAL CHIPS SUIT MILITARY AND SPACE APPLICATIONS

Marconi Electronic Devices Ltd (Lincoln, UK, TLX 56380; in the US, phone (516) 231-7710) has introduced several μ P peripheral chips fabricated in the company's radiation-hard SOS (silicon-on-sapphire) technology, which makes the chips suitable for use in military and space applications. The MAS8237A 4-channel DMA controller, MAS8255A peripheral interface adapter, and MAS8251A universal synchronous/asynchronous receiver transmitter (USART) are pin and function compatible with the equivalent Intel parts. Military-grade versions of the chips sell for £280, £220, and £250 (100), respectively. For the same prices, you can obtain similar parts (the MAS28137, MAS28155, and MAS28151, respectively) that have the drive and timing requirements necessary for use with the McDonnell Douglas MDC-281 MIL-STD-1750A processor. You can also obtain the 54HST630, a radiation-hardened 16-bit parallel error-detection and error-correction IC. A military-grade version of this part costs £170 (100).—Peter Harold

VME BUS MODULE EASES SYSTEM INTEGRATION

By using the \$2000 CVMEBS1 VME Bus stimulator module from Concise Technology (Aylesbury, UK, TLX 975646), you can exercise your operating-system and device-driver software before all your system's hardware is installed. The module allows you to generate VME Bus interrupts on any interrupt level and bus requests on any bus-request level. For interrupts, you can select the eight least significant bits (LSBs) of the 8-, 16-, or 32-bit Status/ID word, which the module places on the VME Bus during the interrupt-acknowledge cycle.

In addition to generating legal VME Bus conditions, the module can also generate spurious interrupts or bus requests, allowing you to test the system's response to ghost conditions. A special mode allows you to slow down the response of the module's interrupter and bus requester. The module also allows you to generate VME Bus SYSFAIL*, SYSRESET*, and ACFAIL* signals. Although it normally occupies two VME Bus slots, the CVMEBS1 has a detachable control panel that allows you to operate the module in a single VME Bus slot.—Peter Harold

MITI ASKS JAPANESE ELECTRONICS FIRMS TO BUY MORE US SEMICONDUCTORS

In the wake of renewed complaints from the US government, the Japanese Ministry of International Trade and Industry (MITI) has asked 10 of Japan's major electronics companies to purchase more US semiconductor products. MITI reportedly expects to see an increase of at least 10% in the procurement of US semiconductors by the major Japanese electronics companies, which include NEC, Toshiba, Hitachi, Fujitsu, Matsushita, and Mitsubishi. The Japanese government has apparently promised that US semiconductor firms will have a 20% share in the Japanese semiconductor market by the year 1991. MITI claims that the American share in the Japanese market has already grown to 12.7%.—Joanne Clay

FUNCTIONAL TRANSISTOR ACHIEVES 5.5 PSEC AT ROOM TEMPERATURE

Fujitsu Ltd has developed a resonant tunneling bipolar transistor that can operate at 5.5 psec at room temperature. Resonant tunneling bipolar transistors can replace six or seven conventional transistors. Previous versions of this type of transistor could operate only at very low temperatures, however. To create this room-temperature version, Fujitsu replaced the traditional materials—gallium arsenide and aluminum gallium arsenide—with indium gallium arsenide and indium aluminum arsenide.

—Joanne Clay



PHILIPS

JOIN THE REVOLUTION!

TEST & MEASUREMENT - OSCILLOSCOPES



Our new PM 3055 50 MHz oscilloscope has started a revolution in the field of test and measurement instrumentation.

In design and technology, it's **the most advanced oscilloscope** of its type in the world.

Yet it costs **less** than you would expect!

Check its high performance, incredible ease of use, sophisticated styling and

remarkable low cost with any other 50 MHz scope on the market.

There's simply **no comparison!**

So make a **change for the better** with the revolutionary PM 3055. The scope with a high IQ for a very low price!

And as the PM 3055 is backed by the resources of one of the world's largest electronics companies, **product credibility** in technology, technique, quality and service is assured.

MADE TO MEASURE

Write to: Philips I&E, T&M department, Building HKF70, 5600 MD Eindhoven, The Netherlands or call your local supplier: **Austria** (222) 629 141; **Belgium** (2) 5256692/94; **Denmark** (1) 572222; **Finland** (0) 5257225; **France** (1) 49428000; **Germany** (561) 5010; **Great Britain** (0223) 358866; **Ireland** (1) 693355; **Italy** (39) 3635 240/8/9; **Netherlands** (40) 782808; **Norway** (2) 680200; **Portugal** (1) 683121; **Spain** (1) 4042200; **Sweden** (8) 7821800; **Switzerland** (1) 4882211.

**Advanced technology
made to measure**



value-packed filters **\$995** from

dc to 3GHz

- less than 1dB insertion loss over entire passband
- greater than 40dB stopband rejection
- 5 section, 30dB per octave roll-off
- VSWR less than 1.7 (typ)
- over 100 models, immediate delivery
- meets MIL-STD-202
- rugged hermetically sealed package (0.4 x 0.8 x 0.4 in.)
- BNC, Type N, SMA available

finding new ways ...
setting higher standards

Mini-Circuits

A Division of Scientific Components Corporation
P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500
Fax (718) 332-4661 Domestic and International Telexes: 6852844 or 620156

LOW PASS	Model	*LP-	10.7	21.4	30	50	70	100	150	200	300	450	550	600	750	850	1000
Min. Pass Band (MHz) DC to			10.7	22	32	48	60	98	140	190	270	400	520	580	700	780	900
Max, 20dB Stop Frequency (MHz)			19	32	47	70	90	147	210	290	410	580	750	840	1000	1100	1340


Prices (ea.): P \$9.95 (6-49), B \$24.95 (1-49), N \$27.95 (1-49), S \$26.95 (1-49)

HIGH PASS	Model	*HP-	50	100	150	200	250	300	400	500	600	700	800	900	1000
Pass Band (MHz) start, max.			41	90	133	185	225	290	395	500	600	700	780	910	1000
end, min.			200	400	600	800	1200	1200	1600	1600	1600	1800	2000	2100	2200
Min. 20dB Stop Frequency (MHz)			26	55	95	116	150	190	290	365	460	520	570	660	720

Prices (ea.): P \$12.95 (6-49), B \$27.95 (1-49), N \$30.95 (1-49), S \$29.95 (1-49)

* Prefix P for pins, B for BNC, N for Type N, S for SMA [example: PLP-10.7](#)

RF transformers



3 KHz-800 MHz
over 50 off-the-shelf models
from \$2⁹⁵

Choose impedance ratios from 1:1 up to 36:1, connector or pin versions (plastic or metal case built to meet MIL-T-21038 and MIL-T-55631 requirements*). Fast risetime and low droop for pulse applications; up to 1000M ohms (insulation resistance) and up to 1000V (dielectric withstanding voltage). Available for immediate delivery with one-year guarantee.

Call or write for 64-page catalog or see our catalog in EBG, EEM, Gold Book or Microwaves Directory.

*units are not QPL listed

finding new ways ...
setting higher standards

Mini-Circuits

A Division of Scientific Components Corporation
P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500
Domestic and International Telexes: 6852844 or 620156

C71 Rev. A

The GE/RCA ASIC cell library



where best-sellers begin.

With one of the largest standard cell and gate array libraries, and a first-time success rate of virtually 100%, GE Solid State has all the tools you need to design leading-edge products.

Our library of hundreds of verified cells and functions is one of the broadest in the industry.

We have cells with effective gate length as small as 1.5μ ($.9\mu$ coming soon). And double-level metal for higher-density chips that handle higher clock speeds.

You can choose from a wide range of Super-cells, including core micros, RAMs, analog functions and bit-slice processors. Right now, we're working on new editions, including Advanced CMOS Logic, EPROMs and high-voltage cells. Additionally, we can generate custom cells to meet your requirements.

So you can easily reduce an entire system onto a single ASIC chip, and get the ASIC benefits of smaller power supplies, lower system cost and higher reliability.

Plus a full library of gate arrays.

If your design calls for gate arrays, you can select from a broad line with up to 13,000 gates. With alternate sourcing on the LSI/Toshiba series.

Our gate arrays have effective gate lengths as small as 1.2μ . And they're compatible with the industry standard.

Writing made easy.

We've made it easy for you to write your best-selling design.

Our designer-friendly software gets you up to speed in as little as the three days it takes to complete our training course.

And our software supports the major workstations in the industry, including Daisy,[™] Mentor

Graphics,[™] Valid,[™] P-CAD[®] and FutureNet.[®]

Through the use of Twins, our transparent workstation interface system, you can complete or revise your design at practically any workstation.

We're also in the forefront of silicon compiler technology. So we can offer you the ability to create designs that are heavily BUS-structured, with your ROMs, RAMs, PLAs and ALUs compiled right into the design.

The best editors in the business.

We know how important accurate performance modeling is to you. That's why we've developed the industry's most advanced simulation and parasitic extraction programs, which make it easy to create designs that work. In fact, our first-time success rate is virtually 100%.

And you can count on our ASICs specialists for technical support from design through production. One other thing you can count on with GE Solid State: there are no hidden charges in addition to your NRE.

On the best-seller list for years.

We've been the CMOS company since the day we invented the technology. We've produced one best-selling CMOS circuit after another. And built the industry's broadest line of High-Rel CMOS parts, including super radiation-hardened Silicon-on-Sapphire.

With all this behind you, think how easy it could be to design a best-seller.

For more information, call toll-free 800-443-7364, ext. 14. Or contact your local GE Solid State sales office or distributor.

In Europe, call: Brussels, (2) 246-21-11; Paris, (1) 39-46-57-99; London, 0276-685911; Milano, (2) 82-291; Munich, (89) 63813-0.

Daisy[™] is a trademark of Daisy Systems Corp.
Mentor Graphics[™] is a trademark of Mentor Graphics Corp.
Valid[™] is a trademark of Valid Logic Systems Inc.
FutureNet[®] is a registered trademark of FutureNet, a Data I/O Company.
P-CAD[®] is a registered trademark of Personal CAD Systems, Inc.



GE Solid State

GE/RCA/Intersil Semiconductors

These three leading brands are now one leading-edge company. Together, we have the resources — and the commitment — to help you conquer new worlds.

How To Keep All Your Horsepower From Running Around In Circles.



To really understand your performance problem, just turn traditional thinking around.

You see, your CPU is really more like a peripheral—it's usually your storage subsystem that sets the pace.

When you look at the problem that way, it's a horse of a different color. The solution, of course, isn't a CPU upgrade. It's better management of the data.

At System Industries, that's an

idea we've championed all along. And the same one behind our new CLUSTOR™ family of shared data storage systems.

CLUSTOR allows you to integrate MicroVAXs and other small VAX CPUs, with or without DEC's bigger, high ticket iron. And it takes over most of the I/O functions that normally bog down those CPUs.

CLUSTOR is built around a true multitasking controller, capable of

CLUSTOR is a registered trademark of System Industries. VAX is a registered trademark of Digital Equipment Corporation.



overlapped seeks and simultaneous data transfers. Between up to 8 CPUs and 16 high performance mass storage devices.


As for what it costs, let's put it this way. When was the last time you saved six figures getting more performance? Up to 90% more, in I/O intensive environments.

And you can saddle it with complex multi-host configurations with no drop in performance.

CLUSTOR is just one example of how our systems can improve the performance of yours. We have a whole company full of people dedicated to doing nothing but that.

Including the largest, best-equipped, best-trained service and support organization this side of Route 128.

Give us a ring at **800-333-2220**. We'll have all your horses pulling together in no time.



**SYSTEM
INDUSTRIES**

CIRCLE NO 64

SIGNALS & NOISE

A transimpedance amp by any other name . . .

In his article, "Use of transimpedance amplifiers minimizes design tradeoffs" (EDN, November 26, 1987, pg 205), Alan Hansford of Analog Devices uses the term "transimpedance amplifier" in a misleading way.

According to longstanding usage, that term refers to the function being performed, namely, actively converting a current to a voltage, not to the type of amplifier used as the active element. Any electronic negative-feedback amplifier having inverting and noninverting inputs will perform as a transimpedance amplifier if it's connected in the correct manner. The amplifier that the article describes has a -3-dB bandwidth that's nearly independent of closed-loop voltage gain—a nice feature, but transimpedance amplifiers have neither voltage-gain nor gain-



bandwidth independence.

So, if the amplifier isn't a conventional voltage-feedback op amp, (as Mr Hansford states in his article), and if transimpedance amplifier is an improper name, then what is the correct description? The accepted

term is "current-feedback op amp." Comlinear introduced the term in 1982 to describe the first op amp with gain-bandwidth independence, a -3-dB bandwidth, and an extremely fast settling time. Current feedback is the key to this performance, but it's not an inherent property of a transimpedance amplifier, contrary to what Mr Hansford says. Comlinear has described the operation of its current-feedback op amps in numerous magazines and application notes since 1982.

The author's conceptual model of operation (pg 210) bears little resemblance to the op amp design that he describes. Rather, the described op amp is designed in accordance with the design that Comlinear invented, patented, and has used in op amps such as the CLC231. I'm flattered by Analog Devices' imitation of our products, but by failing to reference our pioneering work, it

From Layout to Finished Board ... In Minutes



Paths of insulation around copper traces are created by the precision router. The LPKF unit also performs drilling and contour milling to complete the circuit board production.


Now you can use the LPKF circuit board plotter with any Gerber CAD files to create a ready-to-stuff circuit board. This unique plotter is excellent for prototypes, film production, and even front-plate engraving.

- Mechanically plots double- and single-sided boards
- Boards can take surface-mounted components
- Single-sided boards in 10-15 minutes; complex, dense boards in 2 hours or less
- Compatible with any CAD system Gerber output
- No more waiting for prototypes or small runs

LPKF CAD/CAM
SYSTEMS, INC.

See us at NEPCON, Booth #7135

LPKF CAD/CAM Systems, Inc.
18935 Monte Vista Drive
Saratoga, CA 95070
FAX: 408-395-5153
TEL: 408-354-1102
Distributor Inquiries Invited



CIRCLE NO 4

Finally . . . PRECISION IN SURFACE MOUNT DEVICES

Yes, finally! Precision in a small package.

PMI's precision bipolar analog and CMOS converter product line is now offered in SMD. Write for our SMD brochure which lists the availability of 65 devices in various surface mount packages.

PMI's precision SMDs are available in commercial and industrial temperature ranges. The surface mount offerings include SO, SOL, LCC, and PLCC versions.

To get your SMD brochure, circle the reader service number or call . . . 1-800-843-1515.

You'll also receive a free copy of our new 1988 Data Book!

Precision Monolithics Inc.

A Bourns Company
Santa Clara, California, USA
408-727-9222

FRANCE: (1) 40 03 35 93; GERMANY: (0711) 22 93-0; BENELUX: (070) 87 54 04; SWITZERLAND: (042) 33 33 33;
UNITED KINGDOM: (0276) 692 392; HONG KONG: (852) 570-2171; JAPAN: (03) 260-1411; ARGENTINA: (46) 5776/0628/0864/2214;
AUSTRALIA: (02) 439-4655; AUSTRIA: (0222) 43 26 39; DENMARK: (02) 98 63 33; FINLAND: (90) 565 38 77; INDIA: 641 7902;
ISRAEL: (23) 924 09 25; ITALY: (02) 569 57 46; KOREA: (02) 244-7492; NORWAY: (06) 83 20 00; SINGAPORE: (65) 339 331;
SPAIN: (91) 405 42 13; SWEDEN: (08) 768 05 60; TAIWAN: (02) 752 2200; YUGOSLAVIA: (041) 42 37 46

CIRCLE NO 118



The precision solution.

Faster than a speeding bullet... well, almost.

Citizen's New DP-600 Series Dot Matrix Printer Mechanism

Citizen's new high speed DP-600 series printers are twice as fast as Citizen's DP-500 series (and you know how fast they are).

Just think of how well a DP-600 series print mechanism will work in your point-of-sale, medical testing, pay telephone or scientific equipment.

Imagine a fast, reliable DP-600 in your cash register system, banking equipment, time clock or "you name the application." Citizen's new DP-600 series dot matrix printers can do the job faster and better without sacrificing Citizen's dedication to quality.

CITIZEN

CBM America Corp. 2999 Overland Ave., Suite 203
Los Angeles, CA 90064-4243 Phone (213) 558-0961
Toll free (800) 421-6516 Fax (213) 836-1140

Call or write for complete information and pricing.



CIRCLE NO 5

Introducing MiniZap™, the New ESD Simulator for Company Wide Test Programs.

Pulses correlate with all other Series 2000 simulators.

Two models starting at \$2,850.*

LED display measures actual discharge voltage at the tip, even in high rep rate operation.

Realistic, repeatable pulses to ± 15 KV.

TRUE-ESD™ air discharge and FR/CI™ current injection modes meet existing and proposed IEC specs.

Single shot and repetitive pulses.

One piece, rugged, portable, battery or AC operated for routine field use.

For literature on MiniZap and the growing 2000 family of ESD simulators, call (617) 658-0880.



KeyTek®

KeyTek Instrument Corporation
260 Fordham Road
Wilmington, MA 01887
Phone (617) 658-0880
TELEX 951389

*USA price list

CIRCLE NO 6

SIGNALS & NOISE

makes one wonder if the company is trying to take credit for this new and useful class of op amp.

David Nelson
President
Comlinear Corp
Ft Collins, CO

Analog Devices responds:

Mr Nelson's comments are insightful and interesting. Two statements are slightly misleading, however, and require clarification.

The implication is that Analog Devices violated a Comlinear patent by bringing the AD9610 to market; a second implication is that Comlinear did the "pioneering work" in the field of "current-feedback op amps." Analog Devices is aware of the patents in question, and the AD9610 does not infringe on any Comlinear patent. As for the issue of pioneering work, current-feedback amplifiers have a long and well-documented history in the electronics industry. Innumerable textbooks contain references to and examples of current-feedback amplifiers. Many of these books were printed and copyrighted long before 1982.

Analog Devices identified a segment of users that was not totally satisfied with existing high-speed amplifiers, and subsequently introduced the AD9610. We stand by our products, our technology, and our reputation as leaders in this industry. Competition is the cornerstone of the American free-enterprise system.

Thomas Gratzek
Linear Products Marketing
Manager
Analog Devices, Computer
Labs Div
Greensboro, NC

WRITE IN

Send your letters to the Signals and Noise Editor, 275 Washington St, Newton MA 02158. We welcome all comments, pro or con. All letters must be signed, but we will withhold your name upon request. We reserve the right to edit letters for space and clarity.

***MULTIBUS II
TAKES YOU
BACK TO
THE BASICS***

...AND INTO THE FUTURE


MULTIBUS II OPENS UP ADVANCED APPLICATIONS IN WAYS NO OTHER BUS CAN.

When the architects of Multibus II set out to create an advanced bus, they set their sights far beyond just another souped-up traditional bus.

They went back to the basics and created a truly *advanced* bus.

A bus capable of supporting vast new levels of microcomputer performance. To make possible low cost microcomputer systems that outperform minis, and rival mainframes.

An inherently more reliable bus, suitable for applications that process huge volumes of data at unprecedented speeds.



BASIC #2: HARDWARE-ASSISTED MESSAGE PASSING.

This advanced technique gives Multibus II a true sustained bandwidth of 32 megabytes per second. Standardized in a single silicon chip, message passing simplifies system design, and makes it possible to mix totally different microprocessor architectures and operating systems in the same application.

A more maintainable bus, to reduce the cost and complexity of configuration, trouble-shooting and repair.

A bus solid enough to gain the support of a broad base of hardware and software vendors, and ensure that all products would work

together efficiently and dependably.

It would be the ideal advanced bus—the perfect higher performance alternative to Multibus I, VME and other traditional architectures.

MULTIBUS II IS CHANGING THE WORLD!

The advanced bus of the future is here today, to the delight of designers needing to transcend the limitations of today's other bus alternatives.



BASIC #3:

AUTO CONFIGURATION.

Like a chameleon, Multibus II boards automatically configure themselves when system power is turned on, eliminating DIP switch hassles during configuration and maintenance.



BASIC #1: PARITY.

Multibus II's parity error detection provides the basic protection needed by advanced applications that process large volumes of data at high speeds.

For example, NCR and Prime based their newest Tower™ and EXL™ systems on Multibus II. Both provide several times the power of a VAX™ 11/780 minicomputer,

TRADITIONAL VS. AD

	CHARACTERISTICS	TRADITION
		MULTIBUS I
BASIC FEATURES	TIMING (Synchronous or Asynch)	ASYNCH
	PIN USAGE (MPX) Multiplexed (NON) Non-Multiplexed	NON
	ARBITRATION (CENT)ralized (DIST)ributed	CENT.
	INTERRUPTS (DED)icated (VIR)tual	DED.
	GLOBAL MEMORY Communications	YES
ADVANCED FEATURES	PARITY	NO
	AUTO-CONFIGURATION (Geographic Addresses)	NO
	MESSAGE PASSING (Hardware)	NO
	BUS I/F SILICON	NO
OTHER FEATURES	ADDRESS WIDTH (Bits)	20,24
	DATA WIDTH	8,16
	BOARD AREA (sq. in.)	84
	CONNECTOR TYPE	EDGE
	MAX. 5V POWER (Per slot)	24A

*Implemented outside IEEE 1014 using several proprietary schemes.


at a fraction of the price.

A major U.S. department store chain has put into operation a revolutionary home shopping network, based on Multibus II.

In Europe, Multibus II was chosen by a leading automation company as its

URE.

architecture
for the
future for
advanced
factory
automation
applications.



MULTIBUS II:
The world's fastest
growing open system
architecture!

And two leading aerospace
companies are using
Multibus II to build the
world's most advanced

ADVANCED ARCHITECTURES

ADVANCED ARCHITECTURES		
AL BUSES	ADVANCED BUSES	
VME	MULTIBUS II	VAX BI
ASYNCH	SYNCH	SYNCH
NON	MPX	MPX
CENT.	DIST.	DIST.
DED.	VIR.	VIR.
YES	YES	YES
NO	YES	YES
NO	YES	YES
NO*	YES	YES
AVAIL. '88	YES	YES
24, 32	32	32
8, 16, 24, 32	8, 16, 24, 32	8, 16, 24, 32
59.8	80	73.4
DIN	DIN	ZIF
6A	15A	Not Published

aircraft flight simulators.
Throughout the world,
these and scores of other
companies have introduced

BASIC #4: MULTI-VENDOR COMPATIBILITY.

A host of unique features ensure
that Multibus II boards will work
together efficiently and depend-
ably. The IEEE 1296 specifica-
tion is complete and concise.
And, the Multibus II Message
Passing Coprocessor (MPC),
now universally available,
ensures compatibility even between
boards using different processor architec-
tures and operating system software.

or are now
developing
Multibus II
applications that
set new standards
of performance,
price and reliability.

BUILD YOUR OWN MULTIBUS II LIBRARY.

The broad base of Multi-
bus II hardware, software,
accessories and systems is
growing almost daily. Yet
it's easy for you to keep
up to date.

Just circle the reader service
number, and each of the com-
panies on the back of this ad
will send you in-depth tech-
nical data on their complete
Multibus II prod-
uct lines. Plus
timely updates
and new product
announcements.

And, to keep
your Multibus II
library organized, the Multi-
bus Manufacturers Group
will send you this convenient
indexed bookshelf binder.
Absolutely free!




CIRCLE NO. 99



MULTIBUS MANUFACTURERS GROUP

P.O. Box 6208 Aloha, OR 97007 (503) 629-8497

Multibus® is a trademark of Intel Corp.
EXL™ is a trademark of Prime Computer Inc.
Tower™ is a trademark of NCR Corp.
VAX™ is a trademark of Digital Equipment Corp.



BASIC #5: MECHANICAL INTEGRITY.

Naturally, Multibus II uses DIN connec-
tors, for the most reliable mechanical
connections. But, it also incorporates built-
in front panels for EMI shielding. And, its
standard Eurocard form factor provides
enough board space (a full 80 sq. in.) to
accommodate complex designs.

So don't delay. Get the
whole story on Multibus II
and discover the new levels
of performance and reliability

that are possible
with a truly
advanced bus.

Multibus II.
The bus of your
future is here
today.

WE'RE HERE FOR YOU!


The companies listed below would like you to know that Multibus II is now in full swing. These industry leaders offer a complete selection of Multibus II boards, software, systems and accessories—everything you need to develop advanced, high performance applications today.

For your free Multibus II Data Book

plus future new product announcements, just return the reader service card. Or, for faster response, call the MMG or one of the participating companies listed below.

Discover what the world's most advanced OEM microcomputer bus can do for *your* next generation applications.

CPU's	Digital I/O	Analog I/O	Special I/O	Periph Cont	Comm/Net	Graphics	Memory	Software	Packaging	Systems
-------	-------------	------------	-------------	-------------	----------	----------	--------	----------	-----------	---------

 <p>P.O. Box 1037 Attleboro, MA 02703 Contact: Dept. X2403 (617) 222-2202 FAX (617) 226-5257</p>	<table><tr><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td></tr></table>																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																	

The Multibus Manufacturers Group, or MMG, is dedicated to the proposition that everyone benefits from strong, open standards. Membership is open to hardware and software manufacturers, application integrators, end users and even students.

To learn more about what the MMG can do for you, contact Dan Fink, MMG executive director.

Use this convenient product reference guide to quickly locate the companies that offer the types of Multibus II products you need.

CIRCLE NO. 99






Uncover solder defects with Augat's VisInPak sockets and this amazing inspection instrument.

Wouldn't it be more efficient if you could spot solder defects before the boards went to testing? Well, Augat has introduced a removable carrier for DIP, SIP, ZIP, QUAD, pin grid and custom footprints that makes it possible.

Visual Inspection Package (VisInPak) Sockets. They work without an insulator. So you can tell by visual inspection—or, just by looking for soldering voids where the contacts join the plated through holes. During manufacturing. Before testing.

Also, without an insulator,



After the VisInPak socket is wave soldered into place, the carrier is removed to permit visual inspection of the terminals.

the air flow that keeps your device cool is improved. And repairs are easier because each contact can be repaired individually.

Plus, the VisInPak family of sockets can be made to any custom footprint easily and quickly to eliminate loose loading terminals.

Find out how else they can improve your designs and increase your success rate. Send in the coupon for some eye-opening data

sheets and a demonstrator.

The VisInPak family of sockets. More sockets. More innovation that works from the people who listen to what you need. Augat. A company worth keeping an eye on.

Seeing is believing. Send me your VisInPak socket family design guide and demonstrator showing how to help me cut down on defects.

Name

Title

Company

Street Address

City State

Zip Telephone

EDN 020488

Mail to: Augat, Inc. Interconnection Components Division, 33 Perry Avenue, Attleboro, MA 02703
(617) 222-2202.
FAX: 617 222 0693



AUGAT INTERCONNECTION COMPONENTS

Quality and Innovation

TEK UNIX-BASED WORKSTATIONS

THE NEW GRAPHICS WORKSTATIONS THAT RAISE YOUR SIGHTS WITHOUT CHANGING YOUR STANDARDS.




Combine Tek's unsurpassed graphics capabilities with the leading industry standards, and you have a breakthrough in workstation performance.

A breakthrough achieved by the optimum combination of a 32-bit compute engine and 32-bit graphics engine. A graphics engine featuring parallel pipelined architecture with five custom gate arrays to make you more productive than ever: 450,000 2D vectors/second; 340,000 3D vectors/second; and 20,000 Gouraud shaded polygons/second.

Add to that horsepower the security of industry standards like UNIX, 68020 processors, Ethernet, TCP/IP, X Windows, and Tek quality. Plus compatibility with more than 300,000 PLOT 10® applications. And finally, the flexibility to mix and match the world's broadest line of compatible standalone workstations and high-performance terminals.

Whether your need is for bit-mapped or vector graphics, software engineering or 2D drafting, 3D shaded surface modeling, or true stereoscopic



3D viewing, Tek's 4300 Series has an answer.

Let us raise your sights to the new graphics workstations that won't change your standards. For more information on the 4300 Series, contact your local Tek representative today.
Or call 1-800-225-5434.
In Oregon, 1-235-7202.



Tektronix®
COMMITTED TO EXCELLENCE

V25: the most powerful 16-bit single-ch



*Yukio Maehashi
Manager
Microcomputer Division.*

microcomputer.

"My masterpiece!"

NEC

SEMICUSTOM ON TIME — OR YOU DON'T PAY*



To remain competitive in the world of electronics, you have to get your product to market without delay.

To help keep you competitive, Gennum offers the following unique guarantee:

WE WILL DELIVER YOUR LINEAR SEMICUSTOM IC ON TIME AND ON BUDGET, OR YOUR NEXT PROTOTYPING JOB WITH US IS FREE!*

It's that simple.

We offer this unique guarantee because we take the time to find the best possible solution to your problem, before we start designing.

That means fewer trips 'back to the drawing board'.

That's why companies in 18 countries rely on Gennum IC's. Call or write for our free brochure and ask about our SEMICUSTOM DESIGN PACKAGE.

*Details of Gennum's unique Delivery Warranty are included with our Design Package.

P.O. Box 284
Buffalo, N.Y.
14220
Toll Free: 1-800-263-9353



P.O. Box 489, Stn. "A"
Burlington, Ontario
Canada L7R 3Y3
(416) 632-2996
Fax: (416) 632-2055

GENNUM CORPORATION IS AN LTI COMPANY
We developed the science of listening.

CIRCLE NO 7

DID YOU KNOW?

EDN is distributed
at every major
electronics/computer show in the
U.S., France, and Germany.

EDN

CALENDAR

American Association for the Advancement of Science Annual Conference, Boston, MA. AAAS, 1333 H St NW, Washington, DC 20005. (202) 326-6448. February 11 to 15.

Semicustom Circuit Program Conference, San Diego, CA. Mackintosh Consultants, 209 W Central St, Natick, MA 01760. (617) 655-0001. February 17 to 19.

Software Development '88, San Francisco, CA. Miller Freeman Publications, 500 Howard St, San Francisco, CA 94105. (415) 995-2426. February 17 to 19.


Digital Signal Microprocessor and Microcomputer Chips and Development Systems (seminar), Palo Alto, CA. Amnon Aliphas, DSP Associates, 18 Peregrine Rd, Newton, MA 02159. (617) 964-3817. February 22 to 24.

Compcon Spring '88 (33rd IEEE Computer Society International Conference), San Francisco, CA. Hasan AlKhatib, Dept of EECS, Santa Clara University, Santa Clara, CA 95053. (408) 927-1818. February 29 to March 4.

Microwave IC Technology (seminar), Fullerton, CA. California State University, Office of Extended Education, Fullerton, CA 92634. (714) 773-3080. March 4.

Personal Computer Interfacing for Scientific Instrumentation Automation (short course), Blacksburg, VA. Linda Leffel, CEC, Virginia Tech, Blacksburg, VA 24061. (703) 961-4848. March 10 to 12.

Modern Electronic Packaging (seminar), San Diego, CA. Technology Seminars, Box 487, Lutherville, MD 21093. (301) 269-4102. March 15 to 17.




MICRO-CAP II.™

The CAE tool with fully interactive analog simulation for your PC.

Spectrum Software's MICRO-CAP II® is fast, powerful, and feature rich. This fully interactive, advanced electronic circuit analysis program helps engineers speed through analog problems right at their own PCs.


MICRO-CAP II, which is based on our original MICRO-CAP software, is a field-proven, second-generation program. But it's dramatically improved.



Schematic Editor

MICRO-CAP II has faster analysis routines. Better resolution and color. Larger libraries. All add up to a powerful, cost-effective CAE tool for your PC.

The program has a sophisticated integrated schematic editor with a pan capability. Just sketch and analyze. You can step



Transient Analysis


component values, and run worst-case scenarios—all interactively. And a 500-type* library of standard parts is at your fingertips for added flexibility.

MICRO-CAP II is available for IBM® PCs and Macintosh.™ The IBM version is CGA, EGA, and Hercules® compatible and costs only \$895 complete. An evaluation version is available for \$100. Call or write today for our free brochure and demo disk. We'd like to tell you more about analog solutions in the fast lane.

- Integrated schematic editor
- Fast analysis routines
- High-resolution graphic output
- Standard parts library of 500* types

*IBM versions only.

- Transient, AC, DC, and FFT routines
- Op-amp and switch models
- Spec-sheet-to model converter*
- Printer and plotter* hard copy



AC Analysis

Spectrum

1021 S. Wolfe Road, Dept. E
Sunnyvale, CA 94087
(408) 738-4387

MICRO-CAP II is a registered trademark of Spectrum Software.


Macintosh is a trademark of McIntosh Laboratory, Inc. and is being used with express permission of its owner.

Hercules is a registered trademark of Hercules Computer Technology

IBM is a registered trademark of International Business Machines, Inc.

CY525 3rd generation STEPPER MOTOR CONTROLLER

most intelligent controller offers
linear ramping, 10,000 steps/sec,
unlimited stepping, change
rate on the fly, read
position on the
fly, and
much
more.



CY512
compatible,
40 pin, +5 volt
TTL, 8 bit I/O interface
to μ computer. \$195 ea (\$80/100)
Prototyping board available.




Cybernetic Micro Systems

P.O. Box 3000, San Gregorio, CA 94074
(415) 726-3000 Telex: 171-135 attn: Cybernetic

CIRCLE NO 8

DC-300 MHz Amplifier:

\$950



- 4 independent channels
- Gain of 5/channel (cascaded gain: 625)
- 10 μ V/ $^{\circ}$ C dc stability
- 25 μ V input noise

You can use the SR440 as a general purpose amplifier to improve the sensitivity of oscilloscopes, digitizers and spectrum analyzers. Power the SR440 with 120 or 240 V ac. NIM module format for dc operation also available: \$850 (model SR240).

Stanford Research Systems

1290 D Reamwood Avenue, Sunnyvale, CA 94089
TLX 706891 SRS UD, FAX 4087449049, TEL (408) 744-9040

CIRCLE NO 9

CALENDAR

Microelectronic Packaging and Surface Mounting (seminar), Fullerton, CA. California State University, Office of Extended Education, Fullerton, CA 92634. (714) 773-3080. March 18.

10th Annual Conference for Inventors and Entrepreneurs, Denver, CO. Rocky Mountain Inventors Congress, Box 4365, Denver, CO 80204. (303) 443-3818. March 18 to 19.

Neural Networks for Artificial Intelligence, Arlington, VA. Technology Transfer Institute, 741 10th St, Santa Monica, CA 90402. (213) 394-8305. March 21 to 23.

Digital Signal Microprocessor and Microcomputer Chips and Development Systems (seminar), Cambridge, MA. Amnon Aliphas, DSP Associates, 18 Peregrine Rd, Newton, MA 02159. (617) 964-3817. April 4 to 6.

Microcircuit Interconnections and Assembly Methods (seminar), Fullerton, CA. California State University, Office of Extended Education, Fullerton, CA 92634. (714) 773-3080. April 7.

Electrostatic Discharge (ESD): Concern or Over-concern? (seminar), Fullerton, CA. California State University, Office of Extended Education, Fullerton, CA 92634. (714) 773-3080. April 12.

Hybrid Microcircuit Technology (seminar), Fullerton, CA. California State University, Office of Extended Education, Fullerton, CA 92634. (714) 773-3080. April 18.

American Power Conference, Chicago, IL. Robert Porter, Chicago Institute of Technology, Chicago, IL 60618. (312) 567-3202. April 18 to 20.


WATCH WHAT YOU'RE DOING.



Introducing UniLab 8620 analyzer-emulator with InSight.

■ There's nothing like InSight™. A feature of the new 8620 that lets you actually **watch** your program go through its paces. So you can debug faster. And speed up microprocessor development. For demanding applications like the automotive controller shown.

■ An exciting industry first, InSight blends analyzer/emulator techniques to give you continuous, real time monitoring of key processor functions. See changing register contents, I/O lines, ports, user-defined memory windows. With your own labels. And all at once. Interactively. Without stopping your program.



■ InSight is made possible by the 8620's advanced bus state analyzer, its 2730-bus-cycle trace buffer, and a new high-speed parallel interface that eliminates RS-232 bottlenecks.

■ The fast interface also speeds data throughput. From your hard drive, you can load a 64K program into emulation memory in five seconds.

■ On top of that, you get a new, crystal-controlled 1 μ sec clock for super precise event timing.

■ Computer integrated instruments from Orion prove debugging needn't be costly or tedious. For more than 150 processors. Like all our analyzer-emulators, the 8620 debugs by symptom. Via advanced truth table triggering. Always included is enough breakpointing and single stepping (now faster than ever) to assure optimum efficiency. We even provide a stimulus generator and built-in EPROM programmer to help finish the job.

■ Get serious about price/performance. Save big on design, test, and support costs. UniLab 8620 analyzer-emulator.


■ Look into it.

Toll free: 800/245-8500. In CA: 415/361-8883.

ORION
INSTRUMENTS

Computer Integrated Instrumentation
702 Marshall Street, Redwood City, CA 94063
Telex: 530942

*InSight is a trademark of Orion Instruments, Inc.



You wouldn't do this with your Analog VLSI devices.

You'll have to if you go to most ATE companies for a solution to today's sophisticated "system silicon" testing problems. Because all you'll get is a make-shift tester. And that means resigning yourself to man-months of custom hardware work integrating analog and digital instrumentation. And putting up with the long hours of low-level software development that go with custom solutions. Worse, you can expect these delays to cut your chances of getting your product to market on time.

Teradyne now has a simple answer to this complex testing problem. The A500 Analog VLSI Test System. It's the first of a new generation of systems specifically for AVLSI "system silicon" devices. A test system that can help you cut critical product development time by months or even years.

One Test System, Once and for All


With AVLSI devices you won't get fast design feedback, unless you test individual components—the

"building blocks" of system silicon. And you won't comply with customer and industry requirements if you don't do complete "system" functional testing. With conventional test systems it means two of everything. Two testers, two test programs, two insertions, two data bases. And more than twice the time to get to market.

The A500 allows you to do it all with one system. So there's only one system to program. One insertion to make for both component and functional testing. And only one data base to work with. Which means significantly less time to market.

Vector Bus II™: the Great Integrator

The heart of the A500 is Teradyne's unique Vector Bus II architecture. It integrates analog and digital VLSI test capability at the system level. Which means you won't have to build special applications hardware for every new device you design. Vector Bus II eliminates that costly custom-work bottleneck



Why accept it in an Analog VLSI Test System?

with such features as TimeMaster™ Synchronization, Mixed-Signal Event Control, and MultiSource Data Mixing.

A Picture's Worth a Thousand Keystrokes

The A500 also revolutionizes program development. Our IMAGE™ (Interactive Menu-Assisted Graphics Environment) software gives you graphics programming as powerful as device designers' CAD/CAE tools. Using a mouse to control multiple windows, pop-up menus and software "power tools," you move ideas rapidly from mind to screen. And much faster to market.

Teradyne's new A500 is the only test system with the features you need to win the race for Analog VLSI market opportunities. To find out more, call Beth Sulak at (617) 482-2700, ext. 2746. Or call your nearest Teradyne sales office or write: Teradyne, Inc., 321 Harrison Avenue, Boston, MA 02118.



TERADYNE

We measure quality.

WHAT DRIVES A LEADER?

You do.

We do.

On one hand, there's your drive to find new applications and new markets. On the other, there's our drive to meet your needs.

And as partners, we both end up in the lead.

You give us the impetus to stay a generation or more ahead of the competition. And we give you the products to do the same.

Like our high-performance, high-capacity Winchester drive families, from 85MB to 760MB. And our first high-capacity optical product, a 5 1/4-inch, 800MB WORM drive.

So keep pushing us.

Because the further you drive Maxtor, the further we'll drive you.

Maxtor Corporation, 211 River Oaks Parkway, San Jose, CA 95134, (408) 432-1700, TELEX 171074.



Sales offices: Atlanta (404) 455-4226, Austin (512) 345-2742, Boston (617) 872-8556, New Jersey (201) 747-7337, Orange County (714) 472-2344, San Jose (408) 435-7884, Woking, England (44)/4862-29814, Tokyo, Japan 81-3-431-8940.

Distributed by Anthem Electronics, (714) 768-4444, (408) 295-4200, (617) 657-5170, Future Electronics, (514) 694-7710, Pioneer Standard Electronics, Inc., (216) 587-3600, (301) 921-0660, Quality Components, Inc., (214) 733-4300, Storex Corporation, (617) 769-3400.

© 1987 Maxtor Corporation

EDITORIAL

The IEEE faces extinction



Since Irwin Feerst gathered a respectable number of votes in the IEEE's 1986 annual election, the organization has renewed its determination to prevent dissidents from participating in IEEE affairs. Now, instead of facing up to the need for internal reform and external action on behalf of its members, the IEEE's board of directors is dabbling in election-policy changes. Those changes are driving the organization closer to extinction.

Because Feerst split—and almost won—the 3-way contest for president-elect in 1986, the IEEE decided to nominate only one IEEE-sanctioned candidate for the president-elect position in future elections. No more split elections, if you please. However, the hue and cry against having a single candidate was so great that the IEEE's board of directors has reconsidered. You'll now choose from two IEEE-backed candidates for president-elect.

But to ensure that no petition candidate splits an election with the two sanctioned candidates, the IEEE has adopted "approval" voting. In such a scheme, IEEE members get the chance to cast an "approval" vote for each candidate on a ballot. Thus, by not casting a vote, they withhold approval from a candidate. It's worth noting that the board of directors modified the election procedure by changing the organization's bylaws, not by asking members to amend the organization's constitution. The IEEE's board of directors has a case of siege mentality. Once an organization is infected with that disease, it's headed for extinction.

So, instead of real reforms or calls for action by the IEEE's "leaders," you'll see more of the same plodding and self-preserving moves that now characterize the IEEE. Working engineers will observe no action on tax or pension reforms, no action on age discrimination, and no action on other professional concerns. In short, no action at all.

The besieged IEEE will continue publishing journals and periodicals, but that hardly forms the heart of a vital *professional* organization—one that should be improving its members' profession and working environment. So, when it's time to renew your IEEE membership, consider the cost carefully. Are those journals and group life-insurance policies really worth it? If you still think the IEEE has a chance of surviving as a *professional* organization and you renew your membership, send Irwin Feerst's Committee of Concerned EEs a check for an equal amount. You may not agree with everything Feerst says and does, but he has probably done more to change the IEEE than anyone else who has won one of its lopsided elections.


Jon Titus
Editor

Instant Grat

Go ahead. Indulge yourself. And say hello to BUSTER. The first user-configurable MPU peripheral. And the fastest and easiest way yet to get your proprietary design from concept to silicon.

Finally there's a way to get the off-the-shelf convenience of TTL. Without dealing with acres of board space.

In fact, with BUSTER you'll get the performance and single chip advantages of ASICs. While avoiding the painful NRE, long development cycles and inventory burdens.

You can program BUSTER for almost any peripheral function you can name. Counter/timers, data converters, configurable I/O ports, data communication transceivers and lots more.

And it'll work perfectly with just about any MPU. Including 8, 16 and 32 bit parts from Intel, Motorola, National, Zilog and others. Even when they're running at 25 MHz with no wait states.

BUSTER's amazingly flexible. It combines a fast, bus organized architecture with a powerful 20 macrocell CMOS EPLD. Giving you 52 register bits, an 8 bit I/O, cascadable to greater widths, a 24 mA bus port and a long list of other features. More than enough, in fact, to give you plenty of performance and functions for almost any application. Including those using the IBM Micro Channel bus or MIL-STD-1750A processors.

Best of all, you make it happen — concept to silicon — in hours. Not days or weeks. All you need is your PC and our powerful A+PLUS software and development system. You'll enter your design using macrofunctions based on over 100 TTL devices. And you'll program your parts in minutes. It's about as close as you can get to instant gratification.

So find out how BUSTER can help make short work of your peripheral designs. Call us today for data sheets or more information.

You'll be gratified you did.

Call (408) 984-2800.

ALTERA

3525 Monroe Street
Santa Clara, CA 95051



© 1987 ALTERA CORPORATION.
BUSTER and A+PLUS are trademarks of Altera Corporation. IBM and Micro Channel are registered trademarks of International Business Machines Corporation. Distributed in U.S. by Alliance, Pioneer, Quality Components, Schweber, Wyle and Hall-Mark. In Canada, distributed by Future and Semiad.

ification.



WHO YA GONNA CALL TO ICE 68020 BUGS? ATRON BUGBUSTERS!

We recently received a competitive analysis written by a billion-dollar competitor of ours. In it, they rank in-circuit emulation companies in order of importance. We were number one.

SO WHO'S ATRON?

Today, Atron is the number-one supplier of hardware-assisted software debuggers for 8088/80286/80386-based PCs. Nine of the top ten software packages were written by Atron customers. Everybody from AST to Borland to Oracle to Zenith. Now, we can make the same claim in the 68020 marketplace.

Everybody from Apple (MAC IIs) to Wellfleet (datacom) will attest to the superiority of Atron's 68020 debugging technology. One Atron customer even said, "We sent our non-Atron ICE unit out several months ago for repairs; nobody around here seems to know or care if it's back yet. The Atron unit is the tool of choice."

25-MHZ, REAL-TIME, EMULATION: SOONER OR LATER, YOU KNOW YOU'LL NEED IT.

Why invest in a slower emulator (especially one that costs more)? Some bugs only occur in real time, and you know your next design will be 25 mhz. Before Atron's state-of-the-art design, there was no such thing as a 25-mhz emulator. There still isn't another one anywhere near our price.

PROBE CAN TRACE IT THROUGH THE PIPELINE, SO YOU WON'T LOSE YOUR MIND.

The 68020 has an on-board pre-fetch pipeline. Without Atron's 68020 PROBE, your best software engineer will spend a lot of time figuring out which instructions actually execute, and then, which bus cycles go with those instructions. The 68020 PROBE eliminates all these


tedious mental translations and displays what the processor really did. The technology, called pipeline dequeuing, is only available from Atron. Because the Atron bugbusters are the only ones anywhere who've figured out how to do it. And it took us 100,000 lines of code. Consider it our contribution to your sanity. (It was a dirty job, but somebody had to do it.)

68020 PROBE SPECIFICATIONS	
Clock speed	25 mhz
Execution	Transparent
Trace	2048 cycles by 96 bits Qualified trace region Dequeued trace data Pre and center triggered Includes symbols and source Dynamic cache control
Breakpoints	8 hardware on execute Read, write, fetch, logic Single or range addresses 16 software breakpoints Sequential triggers - 4 terms Real-time pass counter Guarded access on memory Output lines for cross trigger Input lines for external logic
Mapped RAM	512K
Source debug	Yes for C, Pascal, Assembler S, Tek, Cof, 4.2 BSD, SUN and IEEE formats
Symbolic debug	Limited only by AT disk size
Symbol table	Multiple windows and menus
User interface	Yes, and conditional execution
Macros	To target system at 375k baud
Download	68881, 68851
Coprocessor	

LET THE SOURCE BE WITH YOU.

Why spend all day doing mental translations between your C source code and the machine code in your target? These tedious operations are eliminated with Atron's source-level debugging capabilities.

Since PROBE uses a PC AT as its instrumentation chassis, you can get compiled code to its target via Ethernet, VAXNet, SUNNet, SCSI or RS-232. And whether you are compiling on a PC, a workstation or a VAX, Atron supports more object-module formats than anybody else (see specification box).



YOU'LL BE A BELIEVER AFTER A SHORT DEMONSTRATION.

So who ya gonna call? Bugbusters! Today. At 408/741-5900. Or send in the attached coupon.

My business card or company letterhead is attached:

- ☐ I've got to see this for myself. Please have a representative call me to schedule a demonstration.
- ☐ Please send me your 36-page 68020 PROBE user's guide, with its command summary and examples of use.



BUGBUSTERS

A division of Northwest Instrument Systems, Inc.

Saratoga Office Center • 12950 Saratoga Avenue
Saratoga, CA 95070 • Call 408/253-5933 today.

EDN 020488

TECHNOLOGY UPDATE

High-performance DMMs and calibrators bring standards-lab specs to the benchtop

Dan Strassberg,
Associate Editor

To satisfy their customers' continuing demands for improved performance, engineers who design and test products such as data converters and automatic test equipment (ATE) must make increasingly accurate basic measurements in their labs, in production, and in systems. Manufacturers of digital multimeters (DMMs) and voltage/current/resistance calibrators are providing tools to meet these tightened measurement requirements. This new generation of rugged, affordable, and easy-to-use instruments offers accuracy that, until recently, was possible only in the cloistered and sacrosanct standards-laboratory environment. To realize the accuracy these instruments promise, however, you must apply them with consummate care.

DMMs measure ac and dc voltage and current, resistance, and voltage and resistance ratios. Not all the meters discussed here can make every one of these measurements. **Table 1** lists some representative high-precision DMMs. All of these DMMs offer resolution of $6\frac{1}{2}$ digits or more; some provide resolution as high as $8\frac{1}{2}$ digits. Depending on how the vendor defines a half digit and how it defines full-scale range (FSR), an $8\frac{1}{2}$ -digit meter may be able to resolve an input change as small as 2.5 parts per billion of FSR.

A question frequently posed about such high-resolution meters is, "Who needs so many digits?" In many cases, the ability to resolve six digits or more doesn't make previously impossible measurements possible—it just makes possible meas-



You don't have to take these meters out of service to calibrate them. In Racal-Dana's Series 6000 DMMs, all components that affect calibration are in a module—removable from the rear of the instrument—that you can exchange when the unit needs calibration.

urements much easier. For example, if you're measuring the temperature coefficient (TC) of a low-TC resistor, you might find it easier to read resistance directly from a DMM than to rebalance a bridge each time you want a reading.

If you're determining the accuracy of an attenuator, you could use a precision voltage divider (for example, a Kelvin-Varley divider) and a null meter. Alternatively, you could use an $8\frac{1}{2}$ -digit DMM and read the divider ratio with resolution as fine as 1 ppm, even when the output of the divider you're testing is only 1% of its input. To measure the divider ratio as accurately with a DMM that has lower resolution, you'd need to change DMM ranges. Range changing introduces the possibility of incurring additional errors. In both of these examples, the built-in computational capabilities of many available meters could make the job even easier—for instance, by computing the TC after you enter the temperature change, or by calculating and

displaying the percent error in the attenuator.

If you're designing a process to test measuring equipment (A/D converters, for example), you could supply a signal to the unit under test (UUT) from a relatively inaccurate source having a low-noise, short-term-stable output that you monitor with a very accurate meter. Instead of using the meter and low-accuracy source, you can use a calibrator—a low-noise, stable, and highly accurate source of voltage, current, or resistance. Although the meter and low-accuracy source are more general-purpose instruments than the calibrator and might appear to offer a better value, you might achieve higher test throughput, and possibly even improved test accuracy, by using the calibrator directly. **Table 2** gives an overview of the capabilities of several representative calibrators.

The almost universal application of μ Ps and related components in high-performance DMMs and calibrators accounts for many recent

A STRIKING NEW COMBINATION OF SPEED, RESOLUTION, ACCURACY AND RECORD LENGTH!

200 MS/s., 10-bit resolution, +.4% gain accuracy, and 64K record length: the best balance in high-resolution digitizers is clearly the new RTD 710 from Tektronix.

The RTD 710 lets you work with fast transients, from DC to 100 MHz, in standalone, semi-automated or fully automated test and measurement environments.

You can partition its 64K memory to store signals of different lengths. Acquire data simultaneously on two different channels. Switch sampling speeds up to five times in a single acquisition.

Add a TV triggering option for video applications. And choose from a variety of computer-based measurement packages.

Call 1-800-835-9433 for more information or to arrange a personal demonstration.



Tektronix
COMMITTED TO EXCELLENCE

TECHNOLOGY UPDATE

advancements in the instruments' stability and ease of use. Remember, though, that a very large portion of each of these instruments consists of circuits that are inherently analog, and computer technology can't solve all the analog measurement problems. For example, it's difficult to imagine (and probably impossible to construct) a dc-voltage-measuring digital meter that doesn't include a stable voltage reference and some type of voltage divider (or its functional equivalent).

The reference and divider, as well as the meter's A/D converter, are analog circuits. Note that although the reference must be stable over time, it really needn't be accurate. As long as you, or a standards lab, can compare the reference voltage against the accurately known output of another reference source, and store the amount by which the meter's reference differs from the ideal, you can correct your meter's readings so that they're more accurate than the internal reference is.

Basically, to calibrate is to determine how meter readings (or source outputs) differ from the ideal, and to insert corrections. The use of digital technology has significantly im-



Incorporating an easy-to-use self-calibrator, the 8½-digit Model 1281 DMM from Datron also has a separate voltage reference, as well as dividers based on transformer turns ratios.

proved the ease and speed of instrument calibration, and has made it possible to eliminate major sources of calibration drift (that is, changes in calibration over time). Calibration used to require removing the covers from an instrument and adjusting potentiometers inside, an operation a prudent person would entrust only to a standards lab. Many newer instrument designs eliminate calibration potentiometers entirely, replacing them with nonvolatile memory that stores corrections, and μ Ps that apply the corrections to the

A/D converter's output before driving the display.

Calibration under μ P control offers several advantages. In some cases, you can perform it yourself, and thereby eliminate the need to take the instrument out of service for a trip to the standards lab. If an instrument receives heavy use, the ability to calibrate it on location can save the cost of a backup unit. The covers can stay on, so critical analog components will remain at the temperatures they experience in actual operation. And unlike potentiome-

TABLE 1—REPRESENTATIVE HIGH-PERFORMANCE DMMs

MANUFACTURER	MODEL	DIGITS	SPEED (READINGS/SEC)			UNCERTAINTY ³		FREQUENCY RANGE FOR BEST AC ACCURACY	PRICE ⁴
			MAX	AT MAX RESOLUTION ¹	AT 6½ DIGITS ²	DC	AC		
DATRON	1061A	6½	35	1.5	1.5	30+80	1000+3000	45 Hz TO 2 kHz	\$4140
	1281	8½	150	0.04	35	7.5+4	90+200	40 Hz TO 10 kHz	\$7950
FLUKE	8506A	7½	500	5	500	15+70	250+0	40 Hz TO 20 kHz	\$6265
HEWLETT-PACKARD	3457A	7½	1350	0.25	53	35+190	2300+2800	100 Hz TO 20 kHz	\$2800
	3458A	8½	100,000	6	8000	8+1	80+200	45 Hz TO 1 kHz	\$6000
KEITHLEY	193A	6½	25	25	25	80+300	2500+10,000	50 Hz TO 10 kHz	\$2395
	196A	6½	1000	0.3	9	80+300	1500+10,000	200 Hz TO 10 kHz	\$1395
RACAL-DANA	SERIES 6000	6½	34,000	10	35	30+100	800+7000 ⁶	100 Hz TO 20 kHz	\$5960
SCHLUMBERGER	7061	7½	1500	0.5	5	25+20	450+1500	40 Hz TO 10 kHz	\$2995
	7081	8½	100	0.019	2.5	7+4	220+700	40 Hz TO 10 kHz	\$7595
YOKOGAWA	2501A	6½	1.67	1	1	50+507	700+3600 ⁷	50 TO 500 Hz	\$6000+

NOTES:

SPECIFICATIONS SHOWN ARE ABBREVIATED. CONSULT MANUFACTURERS' DATA SHEETS FOR FULL SPECS.

1. SPEED SELECTED TO MINIMIZE UNCERTAINTY.

2. HIGHEST SPEED AT WHICH VENDOR CLAIMS 6½-DIGIT RESOLUTION.

3. \pm (PPM OF READING + μ V), 10V RANGE, 1 YEAR, 18 TO 28°C

4. US LIST. EQUIPPED FOR DC/AC VOLTS AND RESISTANCE. IEEE-488 IS INCLUDED, EVEN IF OPTIONAL.

5. AVERAGE FROM 2⁰ TO 2¹⁷ READINGS. WITH 60-Hz LINE AND 2¹⁷ SAMPLES AVERAGED, READING TIME IS 546 SEC.

6. AC UNCERTAINTY GIVEN IS FOR SIX MONTHS. DATA SHEET DOES NOT INDICATE 1-YEAR SPEC.

7. UNCERTAINTY GIVEN IS FOR 90 DAYS. DATA SHEET DOES NOT INDICATE 1-YEAR SPEC.

TECHNOLOGY UPDATE

ter settings, which could shift because of vibration or temperature changes, the digital correction values remain constant.

Although it may be simple to store corrections in a μ P-based instrument, you will still need a calibration reference source. If your facility uses several high-performance meters, you might find it worth the investment to have a calibrator on the premises. Datron Instruments, now a subsidiary of Wavetek, provides an independent self-calibrator in the recently intro-

duced Model 1281 8½-digit DMM. This calibrator uses an internal voltage reference that's separate from the meter's reference, and a voltage divider based on inherently stable transformer turns ratios.

Racal-Dana houses all components that can affect the calibration of its Series 6000 DMMs in a small module that a user can replace from the rear of the instrument. If you can't afford to relinquish the meter periodically for calibration, you simply stock a spare module. When it's time to calibrate, you don't send the

meter to the standards lab—you swap modules. Schlumberger Instruments (formerly Solartron) provides lifetime calibration specifications for its 7000 Series DMMs. Schlumberger also publishes tighter specs for situations in which you calibrate the instruments on a periodic basis. Currently, few—if any—other instruments offer lifetime specs, independent internal calibrators, or interchangeable calibration modules.

If you maintain an on-premises calibrator, you must decide whether


TABLE 2—SPECIFICATION ABSTRACTS FOR REPRESENTATIVE CALIBRATORS

MANUFACTURER	MODEL	STIMULI PROVIDED	AMPLITUDE RANGE	FREQUENCY RANGE	BASIC ACCURACY ¹ [\pm (% SETTING + % RANGE) EXCEPT WHERE OTHERWISE NOTED]
BALLANTINE ³	1620A-OPT20 ²	DC CURRENT AC CURRENT	20 μ A TO 100A 20 μ A TO 100A	DC DC TO 10 kHz	\pm (0.02%+0.02%) \pm (0.15%+0.1%)
	6400A-OPT84	AC VOLTS AC CURRENT	10 μ V TO 1100V 9 μ A TO 2A	10 Hz TO 1 MHz 10 Hz TO 5 kHz	\pm 0.0375% ABSOLUTE \pm (0.035%+0.01%)
DATRON ³	4000A	DC VOLTS DC CURRENT RESISTANCE	100 μ V TO 1000V 100 μ A TO 1A 1 Ω TO 10 M Ω	DC DC —	\pm (0.0007%+0.000025%) \pm (0.005%+0.0005%) \pm 0.001% SETTING
	4700A	DC VOLTS AC VOLTS DC CURRENT AC CURRENT RESISTANCE	1 nV TO 1100V 90 μ V TO 1100V 9 μ A TO 2A 9 μ A TO 2A 10 Ω TO 100 m Ω	DC 10 Hz TO 1 MHz DC 10 Hz TO 5 kHz	\pm (0.0015%+1 μ V) \pm (0.018%+0.004%) \pm (0.01%+0.001%) \pm (0.035%+0.01%) \pm 0.002%
DOWTY RFL	829M	AC VOLTS DC VOLTS AC CURRENT DC CURRENT RESISTANCE	20 nV TO 1100V 20 nV TO 1100V 200 pA TO 2A 200 pA TO 2A 10 Ω TO 10 M Ω	10 Hz TO 20 kHz DC 10 Hz TO 1 kHz DC	\pm (0.02%+0.03%+70 μ V) \pm (0.002%+0.003%+5 μ V) \pm (0.03%+0.03%+1 μ A) \pm (0.01%+0.01%+0.01 μ A) \pm 0.005%
		DC VOLTS	0.1 TO 1000V	DC	\pm 0.002% SETTING
		AC VOLTS	10 nV TO 111.111V	10 Hz TO 100 kHz	\pm (0.04% +0.004%)
		AC VOLTS	1 mV TO 100V	10 TO 100 kHz	\pm (0.02% SETTING+10 μ V)
ELECTRONIC DEVELOPMENT	520A	DC VOLTS	0.1 TO 1000V	DC	\pm 0.002% SETTING
	4503	AC VOLTS	10 nV TO 111.111V	10 Hz TO 100 kHz	\pm (0.04% +0.004%)
	5200A-05	AC VOLTS	1 mV TO 100V	10 TO 100 kHz	\pm (0.02% SETTING+10 μ V)
	5205A	AC VOLTS DC VOLTS	TO 1100V TO 1500V	10 TO 100 kHz DC	\pm 0.05% GAIN UNCERTAINTY \pm 0.05% GAIN UNCERTAINTY
	5215A	AC VOLTS	TO 1100V	10 TO 100 kHz	\pm (0.04%+0.002%) GAIN UNCERTAINTY
FLUKE ³	5440B/ 5442A	DC VOLTS	0 TO 1100V	DC	\pm (0.00035%+5 μ V)
	5450A	RESISTANCE	1 Ω TO 100 M Ω	—	\pm 0.0012%
	263	DC AMPS DC VOLTS CHARGE	50 aA TO 20 mA 5 μ V TO 20V 0.5 fC TO 20 μ C	DC DC —	\pm (0.025%+0.005%) \pm (0.0125%+0.0025%) \pm (0.5+0.005%)
KEITHLEY	610B	DC VOLTS AC VOLTS DC CURRENT AC CURRENT RESISTANCE	1 μ V TO 1000V 10 mV TO 1000V 1 nA TO 10A 100 μ A TO 1A 1 Ω TO 10 M Ω	DC 40 Hz TO 20 kHz DC 40 Hz TO 20 kHz	\pm (0.002%+0.001%) \pm (0.025%+0.0025%+10 μ V) \pm (0.02%+0.002%+50 nA) \pm (0.05%+0.005%) \pm 0.005%
		DC VOLTS AC VOLTS DC CURRENT AC CURRENT RESISTANCE	1 μ V TO 1000V 1 mV TO 1000V 1 nA TO 1A 10 μ A TO 1A 1 Ω TO 10 M Ω	DC 10 Hz TO 100 kHz DC 40 Hz TO 20 kHz	\pm (0.002%+0.0002%) \pm (0.025%+0.0025%) \pm (0.02%+0.002%+50 nA) \pm (0.05%+0.005%) \pm 0.02%
		DC VOLTS	1.2 TO 1200V	DC	\pm (0.0008%+0.0001%)
		RESISTANCE	100 μ Ω TO 11 G Ω	—	\pm 0.0007%+2 m Ω
VALHALLA ³	2701C	DC VOLTS	1.2 TO 1200V	DC	\pm (0.0008%+0.0001%)
	2724A	RESISTANCE	100 μ Ω TO 11 G Ω	—	\pm 0.0007%+2 m Ω

NOTES:

1. BASIC ACCURACIES MAY APPLY TO LIMITED VALUES, RANGES, OR STABILITY PERIODS. CONSULT VENDORS' CATALOGS FOR DETAILS.
2. TRANSCONDUCTANCE AMPLIFIER CURRENT SOURCE DRIVEN BY ANY DC/AC VOLTAGE STIMULUS (MAX DRIVE 2V).
3. VENDOR ALSO SUPPLIES COMPUTER-BASED CALIBRATION SYSTEMS.

The One Week Analog ASIC.



The leading technology . . . the best support . . . go!

The leading analog ASIC family: RLA80, RLA120, and RLA160 user-configurable macrocell arrays. On-chip thin film SiCr resistors and dual-layer metal for ease of interconnect routing and maximum array utilization and performance. Wide supply voltage range — $\pm 1V$ to $\pm 16V$. And simplified design procedures that take days, not weeks.

Configurable macrocells: 8, 12, or 15 gain blocks in any combination as general purpose op amps, open collector output comparators, or as input amplifiers with ground sensing function for single-supply systems. RLA160 has a preconfigured on-board adjustable ± 30 ppm voltage reference.

Thin-film resistors: on-chip SiCr resistors exhibit 1% matching and temperature drift characteristics comparable to discrete film resistors. High performance and high values (1.25 k Ω to 150 k Ω) handle a wide variety of applications.

Design support: The RLA Breadboarding Kit contains complete design and applications documentation, 200x plots, a pre-drilled printed circuit board, and 23 ICs. Friendly RLA Model software includes menu-driven user interface program for PSPICE¹, SPICE² model library for RLA series, documentation files, and full screen editor. Not to mention the attention you get from applications engineers who have 15 years experi-

ence meeting custom and semi-custom requirements.

Call Raytheon for access to RLA program information and details on the RLA Macrocell Array Breadboarding Kit. We promise you a week that will go down in history.

Raytheon Company
Semiconductor Division
350 Ellis Street
Mountain View, CA 94039-7016
(415) 966-7716

¹PSPICE is a trademark of MicroSim Corporation.
²SPICE developed by University of California.

Access to the right technology

Raytheon

TECHNOLOGY UPDATE

you will bring it to the instruments you're calibrating or bring the instruments to it. In any case, you must either keep both the calibrator and the instruments continuously under power, or wait three to 24 hours after restoring power so that they'll be at thermal equilibrium during calibration. You can keep most DMMs and many calibrators running during a 5- to 15-minute trip with a small uninterruptible power supply (UPS) of the type often used to provide backup power for personal computers. Unless you're prepared to wait for the instrument to reach thermal equilibrium at its destination, be sure to keep it at its normal ambient temperature while you're moving it.

Calibration labs never forget

When you send a high-accuracy instrument to a standards lab for calibration, the lab does more than verify instrument accuracy and make the necessary adjustments. Standards labs keep meticulous records of changes in calibration corrections over time. These records form a part of the mechanism that establishes a link to nationally accepted reference standards. For example, the records serve to substantiate a claim that the accuracy of the product you're testing is traceable to the National Bureau of Standards (NBS).

If you perform on-site equipment calibration and fail to keep good records, you may be unable to provide satisfactory evidence of traceability, even though the accuracy of your measurements might be acceptable. Several calibrator manufacturers offer personal-computer-based software packages to facilitate the maintenance of calibration records. If traceability is important to you, you should consider adding a personal computer and calibration record-keeping software to your on-site calibration system.

Schlumberger Instruments has studied how calibration corrections change over time in its Series 7000



Called a "system multimeter" by its manufacturer, Hewlett-Packard, the Model 3458A performs 100,000 conversions/sec at 16-bit resolution. For a year after calibration, on its 10V dc range it delivers 8½-digit readings accurate to 8 ppm of reading plus 1 µV at 6 conversions/sec.

DMMs. A very good fit exists between calibration drift and a square-root curve. This relationship may also hold for other manufacturers' instruments. For example, suppose you have a large number of DMMs and, under constant ambient conditions, you use them to monitor the output of some reference source (such as a standard cell) for four months. If you compute the average of the change in readings from all the meters after one month and again after four months, you can expect that the 4-month-average


change will be double the 1-month figure. Schlumberger specifies the long-term drift of its DMMs according to the formula

$$(\text{ppm of reading})/\sqrt{T},$$

where T is the time in years. From the formula, you can infer that an old instrument will drift much less than a new one will. However, it's doubtful that anybody was building instruments 10 years ago whose stability was as good as that of units manufactured today.


If you need all the accuracy your instrument's vendor specifies, and you rely on an off-site standards lab for calibration services, you'd be well advised to determine how closely the operating environment in which you use the instrument approaches the standards-lab environment. In a well-run standards lab, temperature and humidity are under much tighter control than they are in a typical R&D lab or production-test area. Furthermore, when high-accuracy instruments are in actual use, it's quite common to see other instruments stacked on top of them, or to find them tilted at an angle that makes it easier to view the display.

Stacking instruments that dissipate a significant amount of power on top of a high-accuracy meter, or operating a meter or calibrator in a position different from that which its designers intended, can upset the meter's calibration. If these re-



This computer-controlled, mobile, configurable calibration station is Fluke's Model A123. You can bring the station to the instruments you need to calibrate.

CHOOSE YOUR CERAMIC.



4SZ-7123

SPRAGUE MONOLYTHIC® CAPS... HIGH RELIABILITY, LOW-COST.

MONOLYTHIC® Multilayer Ceramic Capacitors from Sprague: a complete line of ceramic caps featuring economy, high-performance and reliability in a variety of popular ratings and EIA temperature characteristics.

Get fast delivery on multilayer ceramic chip caps for general purpose, high-voltage, high-temperature and

high-frequency applications. Sprague ceramic chips are available in bulk pack or may be supplied on tape and reel to EIA 481A. Also available: molded-case DIPs and SIPs supplied in plastic carriers. Conformally-coated

radial-lead capacitors are also available in quantity, supplied in bulk pack or on tape and reel. For technical data, write for the new Sprague Catalog WF-100 to Technical Literature Service, Sprague Electric Company, P.O. Box 9102, Mansfield, MA 02048-9102.



TECHNOLOGY UPDATE

strictions appear to place unreasonable constraints on your use of high-accuracy instruments, consider obtaining instruments that you can calibrate right where you use them, and calibrators that you can bring to them.

Transfer mode enhances accuracy

An alternative to performing a full on-premises DMM calibration is to use the meter in "transfer mode." You can obtain extremely accurate readings if you first determine a correction by using the DMM to measure a quantity whose value is accurately known. Then, under constant conditions and after a minimal delay, you apply the correction to the measurement of an unknown quantity whose value is very close to that of the accurately known quantity. Some vendors publish separate specs covering the use of DMMs in transfer mode; as you might expect, transfer accuracy is even better than absolute accuracy 24 hours after calibration if the meter's temperature is held within $\pm 1^\circ\text{C}$ of the calibration temperature.

To measure ac voltages, DMMs convert ac voltage to dc and then



A rarity in the DMM marketplace, lifetime calibration specs are the hallmark of Schlumberger's Series 7000 DMMs. After nine years of use, measurement uncertainty is specified at three times the 1-year figure.

measure the dc voltage. As with dc current, when a DMM measures ac current it first converts the current to a proportional voltage. Today, nearly all high-accuracy DMMs having ac ranges either use or offer the option of true rms-to-dc conversion, as opposed, for example, to sine-wave-calibrated, half-cycle average-to-dc or peak ac-to-dc conversion. However, it really isn't sufficient to characterize the ac-to-dc conversion technique as true rms-to-dc conversion. The latter process embraces several circuit approaches.

With the exception of a single

specification, crest factor, vendors specify DMMs' ac-measurement accuracy for sine-wave inputs only. Crest factor is the ratio of the repetitive peak value of an ac waveform to the rms value. The crest factor of a sine wave is 1.41. Many possible waveforms exist for a given crest factor. Therefore, attempts to characterize crest-factor error might yield only an estimate of the inaccuracy in measuring *your* non-sinusoidal waveform. (Crest-factor error is the difference between readings for a nonsinusoidal signal having a given fundamental fre-

NBS goes into the standard-volts business

Most engineers don't think of the National Bureau of Standards as being in the business of selling hardware, but in a very limited sense, NBS *is* in the hardware business. To maintain NBS traceability, standards laboratories have, for decades, transported their dc-voltage references (unsaturated standard cells) to NBS facilities for periodic calibration. Because the cells are very fragile, labs can't entrust them to a common carrier, such as a package-delivery service. The usual practice is for someone from the lab to carry the cells *by hand*. If a flight is involved, the cells travel as passengers, not baggage. The process is obviously time consuming and expensive, and as the number of standards labs grows, existing NBS facilities might find themselves unable to handle the workload.

After 10 years of working on the problem, NBS

in Boulder, CO, has developed a practical voltage standard that requires no calibration. Based on Josephson-junction technology, the standard uses an NBS-developed chip that operates at cryogenic temperatures. Clark Hamilton of NBS believes that organizations wishing to replicate NBS's setup can do so for about \$100,000. If your company would like to own an inherently accurate voltage calibrator, write to Clark Hamilton at the National Bureau of Standards, Electromagnetic Technology Div MS 724.03, Boulder, CO 80303, or phone him at (303) 497-3740. If you can allocate funds to support a calibrator project, NBS will arrange for you to visit its facility. You can come away with the critical hardware items and the know-how you need to construct a standard like NBS's.

**Because you're
thinking fast...**

you need responsive suppliers as well as fast parts. Comlinear is tuned in. With high quality, high speed products. Assistance from R&D-level applications engineers to help develop your ideas quicker. Sales and distribution that get you what you need fast. Quality product documentation with guaranteed specs so you don't waste time. In your business, time is everything. Count on us for the speed you need.

Introducing monolithic op amps with 10ns settling times and 150-200MHz bandwidths.


Now, only from Comlinear, monolithic op amps with incredible high-speed, fast-settling performance.

Our new 200MHz CLC400 is designed for low-gain applications (± 1 to ± 8) and settles in a mere 10ns to 0.1%. For gains greater than 7, choose our 150MHz CLC401, with the same 10ns settling time. Both feature low power (150mW), low distortion, stability without compensation, plus overload and short circuit protection. They're ideal as flash A/D drivers and D/A current-to-voltage converters, or in video distribution and line driving applications.

Our experience in high speed amplifiers now brings you monolithic op amps with numbers like you've never had before. A new dimension in performance is now available for your analog designs.

Try one. Fast.

That's fast!



 **Comlinear
Corporation**
Solutions with speed

4800 Wheaton Drive
Fort Collins, Colorado 80525
(303)226-0500

© 1987 Comlinear Corporation

CIRCLE NO 129

TECHNOLOGY UPDATE

quency and crest factor, and a sinusoidal signal having the same frequency and rms value.) Consequently, many DMM vendors merely specify the highest crest-factor signal their meters can accept without malfunctioning.

True rms is tough to measure

In theory, if you know all the frequency components and their respective amplitudes in a non-sinusoidal ac waveform, and you know the waveform's crest factor, you can predict how accurately a meter will measure the waveform's rms value. Don't count on making this prediction in practice, however. One reason why DMMs have difficulty in matching their sine-wave accuracy specs when measuring nonsinusoidal waveforms is that almost all of them, even those having thermal rms-to-dc converters, have active circuits in the signal path. These circuits have finite bandwidth and slew-rate capability, a limitation that can cause distortion and errors in measuring nonsinusoidal waveforms.

Bear in mind also that DMM accuracy is usually specified in terms of digits plus ppm of reading. For ac ranges, the vendor provides a table of specs covering different frequency bands. As the frequency rises, you'll find that both components of the error expression increase. The frequency dependence of the "digits" term implies that if you insist on making measurements at a small percentage of full scale, you'll experience degraded accuracy, particularly at higher frequencies.

Most high-accuracy meters provide a 4-wire ohms-measurement capability. The 4-wire, or Kelvin, configuration allows you to exclude the resistance of the current-carrying leads from the measurement. Another useful feature of some DMMs is a low-current ohms-measurement mode. At the expense of reduced accuracy, the low-current mode lets you limit the voltage across the resistor you're measur-



Translator software confers chameleon-like qualities on Keithley's Model 193 DMM. By storing new command definitions in its nonvolatile memory, you can make the DMM's IEEE-488 vocabulary mimic that of competitive meters.

ing. This ability might let you make a reasonably accurate measurement of the value of a resistor shunted by a diode, or it might minimize the self-heating of a temperature-sensitive resistor.

Getting rid of noise

One of the prices you pay for high resolution in most DMMs is increased measurement time. Most of

the high-accuracy meters will make faster measurements if you reduce the number of digits displayed. In a given instrument, increasing measurement time improves the repeatability of readings and allows a higher-resolution display. Truly random noise has a zero average value. Line-frequency-related "noise" (aka hum), averaged over an integral number of line cycles, also has a

For more information . . .

For more information on the DMMs, calibrators, and computer-controlled calibration systems described in this article, circle the appropriate numbers on the Information Retrieval Service card or contact the following manufacturers directly.

Ballantine Laboratories Inc
Box 97
Boonton, NJ 07005
(201) 335-0900
Circle No 718

Datron Instruments
c/o Wavetek Corp
9191 Town Center Dr, Suite 450
San Diego, CA 92122
TLX 756953
Circle No 719

Datron Instruments Ltd
Hurricane Way, Norwich Airport
Norwich NR6 6JB England
(0603) 404824
TLX 975173
Circle No 720

Dowty RFL Industries Inc
Powerville Rd
Boonton, NJ 07005
(201) 334-3100
Circle No 721

Electronic Development Corp
11 Hamlin St
Boston, MA 02127
(617) 268-9696
TLX 951596
Circle No 722

Hewlett-Packard Co
1820 Embarcadero Rd
Palo Alto, CA 94093
Phone local sales office
Circle No 723

John Fluke Mfg Co Inc
Box C9090
Everett, WA 98206
(206) 347-6100
Circle No 724

Keithley Instruments Inc
28775 Aurora Rd
Cleveland, OH 44139
(216) 248-0400
TLX 985469
Circle No 725

Racal-Dana Instruments Inc
Box C-19541
Irvine, CA 92713
(714) 859-8999
TLX 678341
Circle No 726

Rotek Instrument Corp
Box 504
Waltham, MA 02254
(617) 899-4611
Circle No 727

Schlumberger Instruments
20 North Ave
Burlington, MA 01803
(617) 229-4825
Circle No 728

Solartron/Schlumberger Instruments
Victoria Rd, Farnborough
Hampshire GU147PW, UK
(0252) 544433
TLX 858245
Circle No 729

Valhalla Scientific Inc
9955 Mesa Rim Rd
San Diego, CA 92121
(619) 457-5576
TLX 181750
Circle No 730

Yokogawa Corp of America
Box 2719
Peachtree City, GA 32069
(404) 487-1471
Circle No 731

It's a trap.

Trap tricky hardware and software bugs, precisely.

Powerful debug commands aren't worth much if they're too difficult to use. We've designed the SA98 to trap bugs based on simple, well defined, and detailed commands.

Quick Change Artistry

No more running up and down command trees to change or modify an emulator condition. Change commands without stopping the emulator. Define in-depth breakpoints. Call up help menus and files as you need them. And you can go from 8- to 32-bit microprocessors quickly.

You Set the Rules

Define your own soft keys and macro commands. With the PC/AT

or XT function keys configured for emulation functions, you can type in and modify commands directly.

Powerful Commands

The SA98 command structure is so powerful and precise, comparing it to other systems is tough on them. Let the power of the SA98 trap your toughest problems and break out of conventional traps.

More Than Expected

Call for a demonstration, and see how good a trap it really is. You'll see fast, well defined solutions.

Call Toll-Free Today

1-800-824-9294 (US)

1-800-724-6706 (CA)

Sophia systems.

Dedicated to MDS/ICE Support

CIRCLE NO 63

U.S. & European Headquarters:

Sophia Computer Systems, Inc.
3337 Kifer Road
Santa Clara, CA 95051 (408) 733-1571

Corporate Headquarters:

Sophia Systems Co., Ltd.
NS Bldg. 8F
2-4-1 Nishishinjuku, Shinjuku-ku
Tokyo 160 03-348-7000

©1988 Sophia Computer Systems, Inc.
Sophia Systems is a registered trademark of
Sophia Computer Systems, Inc.
ICE is a registered trademark of Intel Corporation.
MDS is a registered trademark of
Mohawk Data Science Corporation.
IBM PC/AT and XT are registered trademarks
of International Business Machines Corporation.



TECHNOLOGY UPDATE

value of zero. The longer the period over which you compute the average, the more closely it will approach zero.

Most DMMs obtain noise rejection by using inherently slow integration, but some DMMs, such as Fluke's 8505A and 8506A, use a high-speed conversion technique and reject noise by averaging measurements. Although averaging large numbers of measurements can make such instruments very slow, Fluke's design lets you separately select the number of digits displayed and the number of samples averaged. Therefore, if noise doesn't invalidate the data represented by the digits of low significance, the instruments can make high-precision measurements at high speed.

Many meters allow you to switch in a normal-mode filter on dc ranges to improve the rejection of noise superimposed on the signal. If you

opt to use the filter and attempt to make measurements at the meter's maximum rate, you'll probably find that after you change the input voltage, you must wait for several measurement periods to obtain a stable reading. The settling time of most such filters is greater than the DMM's measurement time.


All the DMMs and most of the calibrators discussed here offer an IEEE-488 interface, either as a standard feature or as an option. The commands you use to invoke specific functions vary from product to product—sometimes even within a single company's line. If you plan to control one of these instruments via the IEEE-488 bus, before you purchase the instrument be sure to ask the vendor for a manual that explains the programming language. Although you're unlikely to find that you *can't* program a particular instrument to do what you want, before you spend your compa-

ny's money you should understand approximately what you'll have to do to write control programs for the unit of your choice.

To alleviate the problem of incompatibility among the command sets of different instruments, Keithley's Model 193, a 6½-digit DMM, includes a software package called Translator. This software lets you define a new command set for the 193—for example, to emulate a competitive instrument—and then store the command library in nonvolatile memory. If you're replicating an existing test system (for example, to increase capacity), the 193's user-definable command set enables you to substitute Keithley's meter for a competitive unit without rewriting the control software. **EDN**

Article Interest Quotient
(Circle One)

High 512 Medium 513 Low 514



CADdy's UNIQUE INTEGRATION

...because doing part of the job is not enough!

■ **Schematic capture:** Dynamic symbol call-up...automatic naming/numbering...rubberbanded connections...edge-of-sheet and bus symbols...expandable library.

■ **Component data base:** Defines/manages data flow between schematic and PC Board. Automatic features - file naming, multi-sheet management, B.O.M., netlist optimization, back-annotation, layer management, project archiving.

■ **PCB Layout:** Components dynamically positioned with rotate or mirror (for SMD)...auto-ratsnest...pin/gate/component swapping...component dragging with connections...ground planes with hatching...user-defined pads, vias, trace widths...output to major pen plotters...optional Gerber and Excellon.

■ **CADdy Autorouter:** Standard and High-performance.

■ **Full-Featured Drafting:** Mechanical auto-dimensioning with tolerancing, construction aids, calculators, savable parameters, and more.

For additional information call:
Toll-free 1-800-CADDY11 (in Illinois 1-312-394-7755).

CADdy Corporation
3 Crossroads of Commerce
Rolling Meadows, IL 60008



Avoid Shocking Disconnects!

Protect your CRTs from unexpected disconnects.
Specify our **CRT SOCKETS** with exclusive
Tube Neck Retaining Clamps.

Quality features make Quality CRT Sockets . . .

- Non-conductive, 94V-0 Tube Neck Retaining Clamps.
- Tapered lead-ins for easy insertion.
- Rugged and resilient assembly.
- Wrap-around Contacts for low resistance.
- Protective Spark Gaps.
- Quality sockets your way, prototype to production.
- In-line Components available.



CONNECTOR CORPORATION


6025 N. Keystone Ave. • Chicago, IL 60646-5290 • 312/539-3108 • TWX 910-221-6059

EDN February 4, 1988

What do you need to build
on a rough application concept?



AT&T The comp



onents of success.



Whether you're building a visionary home—or a breakthrough product or system—getting from concept to completion demands more than bricks and mortar, or metal and silicon.

There are other components that can make a critical difference in meeting your market window on time, and on budget.

We call them the components of success—ready for immediate delivery from AT&T.

The component of commitment: here today, here tomorrow.

AT&T is in the components business to stay. We have formed a separate unit, AT&T Microelectronics, to bring our more than 100 years of electronic components experience to the marketplace. And, we have the capital, people, and technical savvy to meet our commitment to the future.

The component of innovation: AT&T Bell Labs.

Count on Bell Laboratories to help make your 'blue-sky' designs a reality. With everything from DSPs and optical data links, to custom designed products such as ASICs, multilayer boards, and power supplies. And throughout planning and manufacturing, count on AT&T to keep your product up to the minute with the latest Bell Labs advances.

The component of quality.

Through our Integrated Quality System, Bell Labs engineers work with our quality professionals to meet customer-defined criteria. At AT&T quality is

our history—and our future.

The component of management involvement.

AT&T Microelectronics gives you total support, right up to its president, Bill Warwick. If our solutions aren't on the money, call him at 1 201 771-2900.

The component of quick response.

With 12 plants and an extensive network of design centers and sales offices worldwide, AT&T is ready to meet your volume demand for components. Ready with everything you need to get ideas off the ground and in the market—successfully.

To learn why AT&T is more than ever the right choice, just give us a call.

DIAL 1 800 372-2447

AT&T Microelectronics

Major Product Lines:

ASICs
Digital Signal Processors
Communication ICs
32-bit Microprocessors
and Peripherals
Solid State Relays
Multilayer Circuit Boards
HICs
Optical Data Links
Fiber Optic Components
Power Products
Transformers and Inductors
Wound Film Capacitors

© 1987 AT&T



AT&T

The right choice.

***Keep telling yourself
it's only a game.
it's only a game.
it's only a game.
it's only a game.
it's only a game.
it's only a game.***

it's only a game.

it's only a game.

it's only a game.

0
(r is it?)





Diagram of Cramoisy Brigade camp. You'll need this to complete your mission.



Life's a game, or so we are told. And yet, when you're in a critical development mode and you encounter a buried "bug" it can seem like you're the victim. Now, ZAX challenges you to strike back by experiencing the ultimate in investigative tactics with Ground Zero! Ground Zero is an intriguing computer game that solicits shrewd thinking, lightning reflexes and sturdy nerves—plus the ability to face the sometimes unfavorable consequences of your actions.

Armed with your trusty ZAX in-circuit emulator, you'll parachute into the camp of the dreaded *Cramoisy Brigade*, a terrorist group plotting to assemble and then deploy a small, nuclear bomb. Your mission: Infiltrate the camp, discover the location of the bomb, dismantle it, and then retreat to safety.

With the map shown here you can begin playing Ground Zero, right now! Simply use your computer and modem

and call the number below (8 bits/no parity/1 stop bit). Not only will you enjoy the challenge of matching wits against a cagey adversary, you'll learn how ZAX emulators can help you track down and destroy those hideous bugs that threaten to sabotage your development projects. Because after all, in the game of life the stakes are for real.

To play Ground Zero, call:

1-800-PLA GRD 8
(in CA 1-714-474-1177).

No modem? Call 1-800-421-0982 (in CA 1-800-233-9817) for the Ground Zero game diskette or write ZAX Corporation, 2572 White Road, Irvine, CA 92714.

ROHM Optoelectronics

Brilliant ideas with
lasting appeal.



Brighter colors, colors that match, uniform intensity, wider viewing angles and long, trouble-free life. That's what sets ROHM opto products apart. It takes rigid control of raw materials, automated production lines of our own design, adherence to proven statistical process control meth-

ods and dedicated people. Ask for our new catalog. It's a full array of standard lamps, displays, light bars, IR emitters and detectors, plus many special configurations, including new surface mounts. Contact ROHM Corporation, 8 Whatney, Box 19515, Irvine, CA 92713; (714)

855-2131. Outside California, dial 1-800-854-3386, Ext. 29. TWX: 910-595-1721.

ROHM

Innovations in monolithic display drivers improve flat-panel cost/performance ratios

Jim Wiegand, Associate Editor

Generally it's hard to beat the cost/performance ratio of complete flat-panel display systems, but you may have an application in which it makes sense to build, rather than buy, the displays. There are driver ICs available that make it economical to configure flat-panel displays that meet your specific needs.

Consider an example of a build-vs-buy situation: If your product must operate in a harsh environment, then you must purchase and integrate the display's glass module and MIL-spec versions of the driver ICs. Also, the display configuration you need might not be available from high-volume manufacturers.

In such a case you must develop your own display. In this and similar applications, then, the best approach (although it might be counter-intuitive) is for you to purchase the glass panels and driver chips separately, then integrate them yourself. If you must build your own displays, it's useful to become acquainted with the various display-driver ICs and how you can use them.

Row and column drivers

Display drivers are generally configured to let you build displays in multiples of 20, 32, or 34 pixels. Drivers are of two types: row drivers and column drivers. The row drivers supply the negative high-voltage output (-200V or greater) necessary for driving thin-film electroluminescent (TFEL) displays; the column drivers provide the positive output (approximately 60V) required to bring the voltage on the designated pixel to the luminescence threshold level. (Most of the




Fig 1—The basic similarities of TFEL (thin-film electroluminescent) row (a) and column (b) drivers are obvious in these block diagrams. The row drivers must, however, drive voltages as great as -225V , whereas the column drivers need to sustain only 60V at their outputs.


driver chips also operate with ac-plasma display panels, but that's beyond this article's scope.)

A row driver typically consists of a 20-, 32-, or 34-bit shift register having output-enable and strobe lines that you can use to turn all 20 (or 32 or 34) output lines on or off. You feed data into the shift register on a high-to-low clock transition, and a logical one put into a register causes its corresponding output to pull low.

In a typical application, you clock a single logical one through the shift register and pull each of the rows low one at a time by using the chip's output-enable signal. After a complete scan, you then pull the substrate's common pin high, thereby pulling all the outputs high. The block diagram of Fig 1a illustrates the structure of a typical row driver.

Like a row driver, a column driver (Fig 1b) contains a 32-bit shift register having a serial output that you

Make the connection with Emerald.



Touch Terminal, CGA Monitor, RS232 Terminal and 26" Plasma Monitor (rear)

EMERALD saves you time and money with complete systems, interfaces and controllers that let you connect your system to a flat panel display without altering or customizing existing circuits.

As great as flat panel displays are, they have one major drawback. They don't easily connect to any existing CRT-based system. Until now you've had only two options: spend a lot of time and money engineering a product yourself, or buy a potentially overpriced or inadequate product.

Emerald offers a better solution. You can purchase a high-performance unit from us, ready to connect. Emerald manufactures an array of products: terminals and monitors (some with touch input), sub-assemblies, and board level interfaces and controllers. Emerald supports all technologies: EL, Plasma, VF and LCD. For specialized, high-volume applications, we custom design anything from board level products to complete systems.

So, to make your connection easily and economically, talk to Emerald. We are the most experienced and diversified flat panel display people in the industry.

Here's a sample of what you can get, at prices you can afford.*

• Terminals	\$1,595
• Touch Terminals	1,995
• Monitors	1,550
• LCD VT100 Terminals	1,095
• Subsystems	1,295
• Text and Graphics RS232	220
• RGB-EGA to 640x400	180
• RGB-CGA to 640x200	110



*Based on the purchase of 1,000 units.



EMERALD™

7324 S.W. Durham Rd.
Portland, OR 97224
(503) 620-6094
FAX (503) 639-7932

LCD, Plasma, EL Touch and EL Modules



Interface and Controller Boards

TECHNOLOGY UPDATE

use to cascade column data into additional driver ICs. In the column driver, however, data enters the shift register on a low-to-high clock transition. A logical one turns on the corresponding output. In the on state, the driver's output sources current from its high-voltage Darlington stage, thereby producing an "on" pixel.

Column drivers also contain a 32-bit latch that lets you store currently displayed information while you clock a new set of data through the shift register. You transfer the data from the shift register to the latch by using the chip's latch-enable signal.

The configurations commonly available in these driver ICs let you readily build displays that have an overall configuration of 512×512 pixels, a popular display format. But suppose your application requires a 96×96-pixel display area. Such a configuration is uncommon, so it's not available in volume; therefore, you can probably produce such a display as inexpensively as the display manufacturers can. Furthermore, you'll need to use only three row drivers and three column drivers in your circuit.

Home-brewed boards cut costs

One of the most compelling reasons to integrate your own display panels, however, is not to obtain an odd-sized display; rather, it is to combine your own peripheral-control circuitry with the circuits that drive the display. If your system is relatively simple (a μ P, RAM, ROM, and minimal I/O, for example), chances are that you can include these chips on the display's pc board. Such an inclusion might seem to be an insignificant factor, but take a close look at your system's costs. You'll discover that this approach can reduce production costs significantly.

For example, suppose your system consists of interconnected control units, each of which requires a flat-panel display. You might imple-




Fig 2—Packaging density is high in flat-panel displays, as is evident in this photo of a board in one of Cherry Electric's dc TFEL displays. If you want to include your own peripheral circuitry along with a display-driver circuit like the one you see here, you should maintain high density to obtain the full economic benefit of the design integration.

ment the control circuits by using the previously mentioned μ P, RAM, ROM, and a few ICs for I/O operations. Therefore, you could integrate this circuitry with the display-driving ICs on a practical-size pc board.

If you use two separate pc boards—one for the display and one for the control circuits—you'll be in for an unpleasant surprise at design-review time. Although the cost of the ICs (μ P, ROM, etc) for your design may be as low as \$30, don't forget the cost of the connectors, cables, standoffs, nuts, bolts, and assembly labor needed to construct a 2-board design. You'll quickly find that your product's cost is double or possibly triple the \$30 cost of the ICs. So, combining the control and display-driver circuits on one board often makes economic sense. Now it's worth looking at several specific ICs that can help answer your display-driving needs.

A variety of driver ICs for TFEL display panels is available from Texas Instruments. TFEL drivers include row (SN65563 and -4; SN75563 and -4) and column (SN65567 and -8; SN75567 and -8) drivers. The row drivers control 34 high-voltage outputs; the column drivers control 32 outputs. The chips employ BIFET technology,

which puts bipolar, double-diffused, n- and p-channel MOS transistors on one chip.

All inputs to TI's TFEL drivers are CMOS compatible. The sequence of the -4 devices' output lines is the reverse of that on the -3 devices. Similarly, the -8 devices' output-line sequence is the reverse of that on the -7 devices. The reversed-sequence availability greatly facilitates your board-layout task if you want to install these devices on both sides of your pc board or along all edges of a display module.

The row drivers are available with either open-drain or open-source outputs, which have ratings of 225V and 70 mA. The column drivers' totem-pole outputs are rated at 60V and 15 mA. Both the column and the row drivers feature serial inputs and outputs, so you can cascade the drivers easily for large-area displays. The 75563 and 75564 drivers, the most recently available of these ICs, cost \$5.89 (1000).

Thin-film electroluminescent displays hold a great deal of promise for the future. A scrutiny of the ICs in Cherry Electric Corp's (Waukegan, IL) TFEL display (Fig 2) shows that Siliconix plans to help develop that market. In fact, Siliconix developed the Si9559 in conjunction with Cherry specifically for

TECHNOLOGY UPDATE

driving dc TFEL displays. The Si9559 constant-current column driver features 32 outputs, each rated at 90V and 15 mA. The chip costs \$8.93 in quantities of 1000.

The company also offers the 34-output Si9560 electroluminescent symmetric row driver. Each output has a 235V push-pull structure that can source or sink 70 mA. Now available in prototype quantities, the Si9560 carries a price of \$20.55 in 1000-piece quantities. In addition to the chips' intended application of driving flat-panel displays, Siliconix finds that they are being used in nonimpact printers, facsimile machines, and high-voltage line drivers. Those applications take advantage of the chips' high-voltage push-pull outputs.

Another source of TFEL display-driver ICs is the Semiconductor Group of Sprague Electric Co. Sprague manufactures the UCN5851 and UCN5852 BiMOS II TFEL row drivers and the UCN5853 and UCN5854 TFEL column drivers. The row drivers, rated at 225V and 120 mA, feature DMOS outputs. The column drivers offer totem-pole outputs that can source or sink 25 mA and can withstand 60V. The row driver and the column driver are both 32-bit devices that include clock, serial-input, serial-output, and output-enable lines. The 5851 and 5852 row-driver chips each cost \$4.80 (1000).

To take full advantage of the TFEL drivers' features, be sure to consider your system's overall requirements. For instance, when a flat-panel display replaces a traditional CRT, the EL display's circuits usually use a raster-scanning refresh approach that is compatible with existing CRT systems. The refresh rates vary from 60 to 500 Hz. As you increase the refresh rate, you also increase the panel's power consumption and its brightness. At refresh rates lower than 500 Hz, the panel's brightness varies linearly with the refresh rate.

The scanning sequence for a




Fig 3—The output sequence that TFEL displays require is illustrated here. Traditionally, the refresh pulses supplied to the displays have not been symmetrical, but if you design your circuit in such a way that the refresh pulses are symmetrical, you'll minimize the latent-image problem common with TFEL displays.


TFEL panel begins with all columns grounded. All the rows then receive a positive refresh pulse from the row drivers. This refresh pulse may be as high as 225V in some systems (Fig 3). Next, the refresh signal turns on the row-driver IC; the row driver's outputs then follow the composite signal back to ground and allow the cell capacitances to discharge. The rows are left floating until each row is in turn selected by the row driver, which then drives the row to a negative potential.

You achieve the threshold voltage for light emission, approximately 210V, by driving the rows to -160V and then driving the columns to 50V. The difference between these outputs, 210V, is the voltage that appears across the cells you want to emit light.


Before you select a row, you must have the column data ready. First, you transfer the column bits into the column-driver chip's shift register and then latch the data for the output drivers. You can clock data for subsequent display lines into the shift register as soon as the current data enters the output latches. After the column and row bits are available, you enable the column drivers and force the row driver's output to a negative voltage.

Because the row-driver substrates are connected to the composite-row drive, you have to shift the logic levels of all the clock, data, strobe, and enable signals that connect to the row drivers. You can use optical isolators (logic levels on the inputs, high voltage on the outputs) to shift these signals. The column

Display technology is often the last thing you specify.



And the first thing your customer sees.



LCD display and Planar EL display photographed under identical ambient lighting conditions.

From a customer's viewpoint, there's only one real window into your product.

The display.

If it's inferior, your product is judged inferior. No matter how good it really is.

For flat panel displays, there's a simple, yet elegant solution. Planar's electroluminescent (EL) display. Why is EL the preferred display technology? Better viewing angle. Better brightness. Better contrast.

It adds up to superior performance.

So contact us today. Choose the flat panel display that surpasses all others from every-one's point of view.


For a brochure, please phone either 503-690-1100 or 503-690-1102, or write to

PLANAR SYSTEMS, INC.
1400 N.W. Compton Drive
Beaverton, Oregon 97006

PLANAR

MCI introduces three new low cost temperature controllers.

In Stock for Immediate Delivery



SAS Bi-Metal Switch

- Operated by 1/2" dia. bimetal disc
- Good for 100,000 cycles
- 5°C to 175°C in 5° increments
- Large or small quantities available
- Many non-standard terminal configurations offered at no extra cost
- U.L., C.S.A. Approved
- Competitively priced

SAH Hermetic Bi-Metal Switch

- Hermetically sealed T-05 case allows wave soldering
- Good for 10,000 cycles
- PC board mountable
- 30°C to 120°C in 10° increments
- Large or small quantities available
- U.L., C.S.A. Approved
- Competitively priced

MTS Reed Switch

- Hermetically sealed in glass
- Low contact resistance (100 Milliohms or less)
- 3,000,000 operations at a full rated load
- Smaller size for faster response
- -5° to 115°C in 5° increments
- Tight reset tolerances
- U.L. Approved
- Competitively priced

All three switches available in normally open and normally closed configurations.

Call or write for your free temperature control manual and engineering sample.

MIDWEST COMPONENTS INC.

Midwest Components, Inc.
P.O. Box 787
1981 Port City Boulevard
Muskegon, MI 49443
(616) 777-2602 FAX 616-773-4307

CIRCLE NO 10

TECHNOLOGY UPDATE

drivers use ground as their reference; therefore, they don't require logic-level shifting.

Trouble in paradise

Beyond the architectural considerations previously discussed, you should be aware that TFEL displays have a tendency to display latent images. This latent-image problem—a differential-aging effect—results from using asymmetrical waveforms to drive the displays.

When TFEL-display panels are driven by an asymmetrical waveform, the pixels are driven by pulses of alternating polarity. Because the pulses, labeled illuminate and refresh, vary in amplitude and duration, as well as in polarity, a charge is left on the pixels. The charge can, in turn, "burn" pixels in the display. These burned pixels remain partially on, even when they aren't selected, causing latent images to appear on the display.

The key to solving the latent-image problem lies in eliminating—or at least compensating for—the asymmetric display-driving waveforms. Adding a compensation pulse both before and after the refresh pulse is one way to compensate for the asymmetry. The amplitude of these compensation pulses should be lower than the illumination-threshold voltage of the display, but their duration must be long enough to compensate for the charge buildup in the display.

Another compensation technique involves periodically moving the refresh pulse with respect to the panel's scan timing. This technique

lengthens the time between the refresh pulse and the illuminating pulse, but it does so without degrading the displayed information. The extra time between pulses is long enough for the charge to bleed off each row, thereby eliminating charge buildup.

Although the described compensation methods reduce the differential-aging effect, such aging still takes place. By using a symmetrical-drive method—that is, if you drive each pixel with pulses of equal amplitude and duration but of alternating polarity—you eliminate the net dc charging of the pixels and, consequently, you eliminate burned pixels.

In addition, when you eliminate the refresh pulses, you improve the display's contrast ratio and reduce its power consumption. Until recently, however, you couldn't develop the symmetrical-drive waveform using integrated drivers, and using discrete-component drivers is an impractical approach.

To drive TFEL displays symmetrically, the row driver must combine logic-level input circuitry with 225V, 3-state output capabilities. Driver-IC manufacturers have just recently satisfied such output capabilities. The devices from Siliconix, Texas Instruments, and Sprague described here all fulfill these requirements.

EDN

Article Interest Quotient
(Circle One)

High 515 Medium 516 Low 517

For more information . . .

For more information on the display-driver ICs described in this article, circle the appropriate numbers on the Information Retrieval Service card or contact the following manufacturers directly.

Siliconix Inc
2201 Laurelwood Rd
Santa Clara, CA 95054
(408) 988-8000
Circle No 715

Sprague Electric Co
115 Northeast Cutoff
Worcester, MA 01606
(617) 853-5000
Circle No 716

Texas Instruments
Box 655474
Dallas, TX 75265
(214) 995-2011
Circle No 717

Pulse generators

Taking the lead in VERSATILITY and SPEED!

Philips' new PM5785 and PM5786 pulse generators set the pace in speed, versatility and ease of operation.

Fast because they cover virtually any linear and digital requirement with speeds up to 125 MHz/1 ns transition time.

Versatile because they feature dual output channels with a choice of bipolar, positive and negative pulses and a very wide selection of external trigger and gate functions.

And they're **Easy to use** because erroneous time settings are clearly indicated, and a preset burst mode (optional) facilitates testing: memories, shift registers, counters and other digital circuits.



Made to measure

The PM5786 features continuously variable rise/fall times from 2 ns to 0.1 s while the extra fast PM5785 has fixed selectable rise/fall times of 1 ns, 1.5 ns or 2 ns (from 700 ps for 20%...80% for ECL).

Product credibility in technology, technique, quality and service also is assured because the PM 5785 and PM 5786 are backed by the resources of one of the world's largest electronics companies.



Advanced technology made to measure


Write to: Philips I & E, T & M department, Building HKF70, 5600 MD Eindhoven, The Netherlands or call your local supplier: **Austria** (222) 629141; **Belgium** (2) 5256692/94; **Denmark** (1) 572222; **Finland** (0) 5257225; **France** (1) 49428000; **Germany** (561) 5010; **Great Britain** (0223) 358866; **Ireland** (1) 693355; **Italy** (39) 3635240/8/9; **Netherlands** (40) 782808; **Norway** (2) 680200; **Portugal** (1) 683121; **Spain** (1) 4042200; **Sweden** (8) 7821800; **Switzerland** (1) 4882211



**Test &
Measurement**

PHILIPS

GOOD NEWS
FOR THOSE
WHO DON'T
HAVE THE GUTS
TO MAKE IT
ALONE.



Yamaha® is known for its motorcycles. Its musical instruments. Sporting goods. And audio equipment.

But when it comes to LSI chips, board-level products and computers, Yamaha may be the best kept secret in the world.

OUR CHIPS ARE YOUR CHIPS.

For more than 15 years, Yamaha has done some of its best work for companies you probably know.

If you've heard a CD player lately, you've probably heard our signal processing chip in action.

And if you've gazed into the popular laptop computers, you've seen the handiwork of our graphics controller chips.

Yamaha manufactures sound chips. Graphics chips. Communications chips. And signal processing chips.

Chips that synthesize voices. Go into audio equipment. Home computers. Video games. Graphics terminals and a whole lot more.

So whatever you design, it's highly likely Yamaha can bring your ideas to life.

You can order our chips as is or we can always tailor them.

And if you need full-custom, we do that too.

OUR BOARDS ARE YOUR BOARDS.

Yamaha can make your next product sound like a cow. Or its graphics display

Yamaha CRT and flat panel display controllers are in many popular laptop computers.

look like a million.

But, if all you want to do is take advantage of our highly automated manufacturing facilities, that's fine with us, too.

Just bring Yamaha the schematic and we'll build it in quantity. On time and on budget.

No problem.

Yamaha has the facility to build the latest in surface-mount boards.

We'd like nothing better than to show you how well it works.

OUR TERMINALS ARE YOUR TERMINALS.

Yamaha can probably put your name on a great-looking terminal for a lot less than you'd expect.

Our color graphics terminals are known for high quality, high performance and low price.

That's why some of the best-selling terminals in the U.S. and Japan are made by you-know-who.

OUR QUALITY IS YOUR QUALITY.

Reliability.

It's an attribute that generally takes years to acquire. But if you do business with Yamaha, it's a totally different story.

Whether we're making parts for you or ourselves, Yamaha enforces the same stringent quality controls every step of the way.

Yamaha has no double standards. It's the only way we work.

AND YOU CAN BORROW OUR BEST PEOPLE IF YOU PROMISE TO RETURN THEM.

When Yamaha enters into an OEM agreement, we put our best people on the job.


People ready, willing and able to stretch your imagination to the limit and help solve your design and manufacturing problems, as well.

To put this multi-billion dollar international company to work for you, call 800-521-9074.

In California, 800-544-9939.

Or write to our National Sales Manager, Yamaha Systems Technology Division, P.O. Box 6600, Buena Park, California 90622-6600.

With your brains and our guts, there's no telling how far we can go.



Yamaha engineers use the latest CAD/CAM techniques to customize the functions of a chip.



Yamaha can design and manufacture boards with the latest surface-mount technology or less sophisticated assembly techniques.



Many popular CD players use Yamaha DSP chips and surface-mount, flexible circuits.



Enter into a partnership with Yamaha and you have the resources and stability of a multi-billion dollar partner working on your behalf.



YAMAHA®

Systems Technology

© 1987, Yamaha Corporation of America, USA



It's really quite simple: others offer you a product, we offer a company. And a commitment.

It's also simple to prove. Next time the rep who fills your miniature lamp needs is in, ask him for performance data, too. Or a competitive analysis, or quarterly product audit and reliability test data. Or a legacy of excellence like we began with Chicago Miniature.

You get the idea. VCH not only has these capabilities and credentials, but we can provide them to you *in this country*. If you need help, VCH will send a specialist who talks your language and can be available in a few hours for design engineering assistance or applications advice.

Why you'll find us to be the beacon of miniature lamps.

Compare that with the infuriating alternatives: transoceanic phone calls and cables, garbled facts and data, and unfulfilled next-day promises.

VCH looks at commitment as much more than a management buzzword. We're putting a new plant, an eager staff, and considerable resources where our mouth is. All this shows our dedication to the proposition that...nobody is going to out-service us. Nobody.

VCH...Three letters that stand for a whole new level in miniature lamp performance. We've rewritten the industry standards before, with Chicago Miniature. Now we're ready to do it again.

We're out to be the beacon of miniature lamps.

CIRCLE NO 71



vch
INTERNATIONAL
CHICAGO MINIATURE BRAND
Buffalo Grove, IL • 312-459-3400

HVCMOS[®] IMAGING




Supertex inc.

Leadership in CMOS/DMOS Technologies

Pushing the leading edge of display technologies, the Supertex family of HVCMOS* drivers permit major breakthroughs in electroluminescent, gas plasma, LCD & vacuum fluorescent displays. This advanced smart power technology also opens up a wide range of applications in medical ultrasound imaging, robotics, telecommunications, test systems, high performance printers, power supplies, motor controls and solid-state relays.

The Supertex high density HVCMOS drivers, listed below, feature high speed with low power consumption to produce bright, high-resolution images. Investigate HVCMOS . . . a most attractive alternative to cumbersome boards or hybrids.

For more information or custom designs, write or call: Supertex, Inc., 1225 Bordeaux Drive, Sunnyvale, CA 94088; Tel. (408) 744-0100; Telex 6839143 SUPTX and FAX (408) 734-5247.



HV03 & 05	220 & 300V	64 Channel, Serial to Parallel Converters with N-Channel Open Drain Outputs
HV04 & 06	60 & 80V	64 Channel, Serial to Parallel Converters with Push-Pull Outputs
HV08**	60V	24 Channel, 16 Gray Shade Level Driver with Source Follower Outputs
HV10 - 18	140 & 160V	4 & 8 Channel Bilateral Analog Switches
HV30	180V	7 Segment Decoder with Open Drain Outputs
HV41 & 42, HV45 & 46	-220 & -300V	32 Channel, Serial to Parallel Converters with P-Channel Open Drain Outputs
HV51 & 52, HV55 & 56	220 & 300V	32 Channel, Serial to Parallel Converters with N-Channel Open Drain Outputs
HV53 & 54, HV57 & 58	60 & 80V	32 Channel, Serial to Parallel Converters with Push-Pull Outputs
HV500 & 501	100V	32 Channel, AC Plasma Driver with Push-Pull Outputs
HV6810**	80V	10 Channel, Vacuum-Fluorescent Driver with Push-Pull Outputs
AN01, AP01, HT01	160 to 400V	3 Chip Set for 8 Channel Level Translation with Low Leakage Push-Pull Outputs

CIRCLE NO 65

*HVCMOS is a registered trademark of Supertex, Inc.
**Available 2nd Quarter, 1988



DEECO SEALTOUCH® DISPLAY SYSTEM. SEALS IN PERFORMANCE. SEALS OUT DIRT AND MOISTURE.

If there's one thing you don't need, it's dirt and moisture seeping into your display system and disrupting its performance. The Deeco SealTouch display system is the best solution for your most demanding industrial applications.

Designed especially for harsh environments, SealTouch delivers consistently reliable performance under the most threatening conditions.

The SealTouch display system is a 3-part module consisting of flat-panel display and sealed I-R Touch panel, mounted on a controller card with VT100 text emulation and extensive drawing graphics. All within an absolute minimum footprint.

Easy-to-use touch software, pop-up menus and convenient button draw routines make SealTouch easy to design-in and simple to use. The system's programmable touch sensitivity allows you to easily implement protection against annoying false triggers. What's more, the SealTouch infra-red beam diagnostics continuously monitor system performance, assuring you of consistent reliability.

Don't take chances with any other display system. Call or write for full product information. Let SealTouch seal in performance for your design. And seal out dirt and moisture.

deeco

Digital Electronics Corporation, 31047 Genstar Road, Hayward, CA 94544-7831 (415) 471-4700

SealTouch and Deeco are registered trademarks of Digital Electronics Corporation.



"We bet our entire company's future on our partnership with Hitachi."

—Jim Balkcom
President and Chief Executive Officer
Humminbird® Depth Sounders
Techsonic Industries, Inc.

"As the second largest manufacturer of depth-sounding equipment, we were determined to become the leader. We knew it would take a breakthrough in meeting the fisherman's needs.

"In strategic partnership with Hitachi, we developed the LCD technology that redefined the depth-sounder market and ultimately quadrupled its size. Our share went from 20 to over 50%. The new technology was a big risk for us. We laid the whole future of our company in Hitachi's hands, and it paid off."


"Whether between two people, or two companies, trust is what makes partnerships work."

"We've shared technologies, design concepts, marketing plans and other critically confidential information across both sides

of the table. That's partnership. Trust makes it work . . . and continue to grow."

"Hitachi defines quality the same way we do—meeting customers' needs."

"Hitachi gives Techsonic the technological edge, and more. We've learned it's a waste of time to do incoming testing on Hitachi LCDs. And when we sold over three times our forecast, they were flexible enough to come through for us. Whatever support we need, we get.



And the best part is, we never have to ask for it."

"Hitachi makes it clear that their most important product is our product."

"We needed to team up with an LCD supplier who had the expertise, the capabilities, and the desire to work with us to develop the right solutions. Partnering with Hitachi made Humminbird No. 1, and we're sure it's going to keep us there."

To learn about how partnering with Hitachi can benefit your company, call Tom Klopce or David Ross at (312) 843-1144. Or write to Hitachi America, Ltd., Electron Tube Division, 300 N. Martingale Road, Suite 600, Schaumburg, IL 60173.



HITACHI®

Hitachi America, Ltd.
Electron Tube Division

Plug-in boards let your personal computer perform parallel-processing tasks


J D Mosley, *Regional Editor*

You can now select from a number of IBM PC-compatible expansion cards that give your desktop computer computational power approaching that of a Cray supercomputer. These cards each contain a μ P that works in conjunction with the host CPU to execute software faster than a single μ P could.

When you plug multiple processing cards into your PC or compatible computer, you increase the number of CPUs available for number crunching and problem solving. However, using such boards entails considerations that don't apply to the use of the typical Von Neumann serial-processing architecture found in most computers. The efficient use of multiple processors requires intelligent task parsing (process allocation) among the available processors as well as provisions for interprocessor communication.

The PC-based parallel-processing market is currently divided into three segments: boards based on Intel's 80386, ones based on Inmos's Transputer, and ones based on RISC (reduced-instruction-set computer) CPUs. Each has benefits and drawbacks, and your choice will depend on your application, on your programming skill, and on how receptive you are to learning new techniques.

If, besides writing multiprocessor applications, you also want to run several MS-DOS programs concurrently at the fastest possible speed, then you should consider the 80386-based cards. If you want to concentrate on parallel-processing development and prefer using a programming language designed specifically for that task, take a look



Housing a maximum of four Transputers in a steel enclosure, the Transputer Evaluation System (TES) from Sension Ltd lets you build a large Transputer network while monopolizing only one expansion slot in your PC.

at the Transputer boards and Inmos's Occam language. But, if your need for processing speed is greater than your need for programming flexibility, the RISC boards may be your best choice.

Although several expansion cards with an 80386 CPU are available, few are designed to work with the host CPU in your desktop computer. Expansion boards that require the removal of the host CPU are generally known as accelerator boards. The Inboard 386/PC from Intel Corp, for example, requires that you remove the host CPU from your PC/XT-compatible mother board, leaving the Inboard's 80386 μ P as the sole processor—and obviously negating any chance for developing multiprocessing applications. You cannot link boards such as these together, either physically or with software, to provide a multiprocessing environment.

Conversely, coprocessor boards work in concert with the host CPU: The coprocessor performs CPU-intensive tasks, leaving the host CPU to perform housekeeping duties like I/O and task parsing. As a result, a

coprocessor board doesn't accelerate such I/O tasks as display output, disk access, or printer control. For example, an 8088-based PC with a coprocessor board installed will execute a program slower than would a PC/AT-compatible or 80386-based host with the same board installed—the more I/O activity, the greater the difference.

In addition, though the coprocessor board can readily perform 32-bit-wide operations, to transport the results to you, the board must translate its 32-bit output into the 8-bit data patterns required for propagation along the host's bus. As a result, I/O-intensive MS-DOS software may actually run slower on a computer with a coprocessor board than it would on an unmodified PC.

To deal with this problem, Applied Reasoning Corp includes utility software with its PC-Elevator 386 coprocessor board that lets you decide whether to run an application on the coprocessor board or on the host CPU. So, even with the 386 board installed, you can run all of your MS-DOS application programs—even the ones with timing or



**MOVE UP
TO A
NEW LINE**

**FROM
HOUSTON
INSTRUMENT**

Prepare to be impressed. Meet the new line of high-performance plotters from Houston Instrument.™ HI's sleek new DMP-60 series is designed to impress even the most demanding CAD professional.

Discover unprecedented flexibility—blended with ultra-fine resolution, speed, and software compatibility. Benefit from HI's rigorous standards for quality, reliability, and service. All at prices starting from \$4,695.*

Watch the DMP-60 series double as a scanner with HI's unique SCAN-CAD™ option. Quickly produce multicolored drawings when you use the Multi-Pen adaptor. Plot several originals—without tying up your PC when you add HI's buffer expansion board.


Select media as small as 8½"×11" or as large as 36"×48". Load either DM/PL™ or HP-GL 758X-compatible software. Then watch as your plotter quickly produces a drawing polished to a precise resolution of 5 ten-thousandths of an inch. Smile when you see smoothly formed circles, curves, and lettering.

Explore HI's host of support

programs including an overnight plotter-replacement service. And then relax, knowing that HI's new plotters rest on 27 years of engineering excellence.

Move up. To a fine, new line. From Houston Instrument. Begin by calling 1-800-444-3425 or 512-835-0900 or writing Houston Instrument, 8500 Cameron Road, Austin, TX 78753.

*U.S. suggested retail price.



**HOUSTON
INSTRUMENT**

A DIVISION OF **AMETEK**

Houston Instrument, SCAN-CAD, and DM/PL are trademarks of AMETEK, Inc.




**NEW
MODELS**

TECHNOLOGY UPDATE

hardware sensitivity. A simple Up or Down command enables or disables coprocessor control.

In addition, you can plug as many as six PC-Elevator 386 boards into one PC-compatible computer. Thus, if you use an 80386-based PC for the host, you can tap the processing power of seven 80386 CPUs, which yields the potential computing power of 3.4 MIPS per processor. Each board sports a 16-MHz 80386 and 1M bytes of 100-nsec RAM with 4-way interleaving for zero-wait-state operation. The Norton index for this board is 18.7, which the manufacturer claims is 10 to 20 times the speed of an IBM PC/XT, 3 to 4 times that of an IBM PC/AT, and 10% faster than a Compaq 386.

You can add an extra 12M bytes of RAM by using as many as three daughter boards. Devoid of onboard ROM, the PC-Elevator 386 is controlled by disk-based software, which Applied Reasoning supplies. The manufacturer will provide PLAs to circumvent I/O-address limitations that ordinarily arise when you attempt to add more than four coprocessor boards to a PC host.



You can pack six PC-Elevator 386 boards into a single PC-compatible computer and still maintain MS-DOS compatibility. Applied Reasoning Corp provides PLAs that overcome the I/O address limitations likely to occur if you install more than four boards in your computer.

The host computer uses eight consecutive I/O locations for coprocessor control, and it uses a 64k-byte window to read from and write to the onboard memory. An 8259 controls interrupt requests on board, but the host emulates all I/O and interrupt-acknowledge cycles. Therefore, the host's control program can detect error conditions in the coprocessor board and simulate any configuration of interrupt controllers. For \$500, you can buy a software developer's kit that includes code and examples for programs that use more than one board

for parallel-processing applications.


One program that the developer's kit includes and which illustrates the PC-Elevator 386's prowess in a multiprocessing application is based on the Mandelbrot set of complex numbers. Your computer displays this set as a 2-dimensional plane with an infinitely intricate border—a figure commonly referred to as a fractal and which is discussed at length in **Ref 1**.

Because the Mandelbrot set can offer an unending stream of computations, it's particularly well suited to illustrate the time savings attainable by applying more and more processors to the generation of the fractal pattern. This computationally intensive task presents an almost linear improvement in execution speed as you apply one to six boards to the problem.

The PC-Elevator 386 costs \$1995; an 80387 arithmetic coprocessor adds \$795; and each 4M-byte RAM daughter board costs \$2000. For programming, you can use any language available for use with MS-DOS computers.

Another 80386-based coprocessor for PCs is the 386 Hummingboard from A I Architects. Using a 32-bit C language Dhrystone benchmark as a basis for comparison, the manufacturer claims that a 386 Hummingboard with a 20-MHz CPU runs 10.7 times faster than a 6-MHz IBM PC/AT running Microsoft C.

Best known as the hardware foun-



The 386 Hummingboard includes a board-resident operating system called OS/386, which provides extended, protected-mode 32-bit DOS services to applications running on the board. Developed by A I Architects, the OS/386 runs in conjunction with DOS, so you can run real- and protected-mode software simultaneously on the host and Hummingboard CPUs.

TECHNOLOGY UPDATE


dation for Gold Hill Computers' (Cambridge, MA) line of Lisp-based expert-system software packages for artificial-intelligence development on PCs, the Hummingboard also runs in parallel with your PC's CPU. Software support includes 16- and 32-bit versions of C, Pascal, Fortran, and Ada, as well as an assembler and a software developer's kit for the company's DOS extenders for 80286 and 80386 μ Ps.

Because the Hummingboard appears to the host CPU as a dual-port EMS-compatible memory card, the design simplifies interprocessor communication through a shared memory scheme that provides the host μ P with a 64k-byte window into the 24M bytes of 120-nsec physical memory that you can pack onto a single Hummingboard. The host μ P controls I/O while the Hummingboard assumes central-processing control via its resident OS/386 DOS-extending operating system. As a result, certain MS-DOS programs that are sensitive to timing and hardware configurations may not run properly on a Hummingboard.

Although there is currently no software that specifically lets you use multiple Hummingboards in a PC for parallel operation, the company claims to have successfully installed four Hummingboards in a personal computer to execute a custom-designed application.

A 16-MHz 386 Hummingboard with 2M bytes of RAM sells for \$2895; a 20-MHz version costs \$3395. Pricing for a fully populated 24M-byte, 20-MHz 386 Hummingboard is \$18,950. You can add a \$695 16-MHz or a \$1195 20-MHz 80387 numeric coprocessor to the board, and you can select from several software options ranging in price from a \$495 software developer's kit to a \$895 32-bit C, Pascal, or Fortran compiler.

If you're looking for a board that's specifically designed to execute multiprocessing applications in a PC, you can select from a variety of



Sporting four Transputers on one board, the Quadputer from MicroWay provides as much as 10 MIPS per μ P and suits parallel-processing applications. The board comes with an Occam-2 compiler for optimized program development.

plug-in cards based on Inmos's T414 or T800 Transputer μ Ps. These 32-bit processors can crank out 10 MIPS, and the T800—which is a T414 with dedicated high-speed graphics functions and on-chip floating-point numeric processing—clocks in at 4 million Whetstones. Technically, these figures indicate that the T800 should perform about 12 times faster than an 80386 with an 80387 coprocessor, and six times faster than a 68020 with a 68881 coprocessor. A network of 64 T800s theoretically offers the throughput of a Cray supercomputer.

A Transputer has four bidirectional lines that let it directly communicate with as many as four other Transputers. Accordingly, you can build a network of Transputers in either a hypercube or a ring configuration to maximize efficiency in your multiprocessing application. Furthermore, these processors have 2k bytes of 50-nsec static RAM on chip, so each Transputer can execute a task independent of the other μ Ps and simultaneously share data stored in its on-chip RAM with the other processors in the network.

Converting your present programs for execution by a Transputer will require that you change compilers, because the Transputer's instruction set is completely different from the one that Intel uses. Accordingly, Inmos has developed the Occam assembly language for use with its Transputers. Specifically suited to the development of parallel-processing applications, Occam exploits the Transputer's interprocessor communication facilities, lets you specify which sections of code should run serially or in parallel, and supports time slicing for concurrent processing.

One company that gives you an Occam-2 compiler when you buy a Transputer board is MicroWay. Its single-Transputer board—the \$1495 Monoputer—comes populated with 2M bytes of 100-nsec RAM and a 20-MHz T414 Transputer. The T800 version costs \$1995. The company also offers Transputer-compatible compilers for C, Fortran, Pascal, and Prolog, however, which sell for \$750 each. In addition, MicroWay sells boards with either two or four Transputers at prices varying from \$3495 to \$8000. Memory upgrades range from \$1400 to \$5600 for 1M to 16M bytes of RAM.

MicroWay's line of Transputer boards uses a link adapter to interface to your host PC. Besides providing I/O for host-to-Transputer communication, the link adapter also generates control signals in the event of a μ P error. On board, the Transputers function via a Von Neumann architecture.

Unfortunately, much of the speed advantage of the Transputer is consumed in the host-to-Transputer communication process. Using a file-server program that runs on your host PC under DOS, an Occam-2 program can only implement I/O functions such as reading the keyboard or writing to the CRT by passing messages to the Occam file server, which in turn passes them to the PC, which executes the task and relays the result via the file server

The first good reason in 5 years to buy new 8-bit development tools.

We asked design engineers to describe the ideal 8-bit development system. Then we designed it.

Introducing the EL-800: real-time transparent emulation, the most powerful event system available plus lots of trace memory...all for under \$5000.

The second good reason.

The EL-800's triggers and breakpoints let you quickly identify complex bugs. Our powerful Advanced Event System controls emulation with a combination of address, data, status, counters and logic fields. And you can specify up to 1 Megabyte of overlay memory.

But we didn't stop there.

The EL-800 also comes with symbolic debug as well as a quick and easy way to define up to 1 million breakpoints. And it provides closely coupled interfaces to high level debuggers...all for much less than you'd expect to pay for an Applied Microsystems emulator.

What's more, the new modular design makes it easy to add additional capabilities and new processors without switching to a new operating environment or discarding your emulator.

Ask us about our plans to develop a library of options for the EL-800, performance analysis, post processing of real-time trace, and software development tools. And let us show how we can extend support to your particular 8-bit microprocessor or microcontroller.

To find out more, call 1-800-426-3925 (in WA, 206-882-2000). Or mail us the coupon below.

SPECIFICATIONS

- Emulation at fully rated clock speeds of CPUs.
- Less than 5 ns signal skew at probe tip.
- Full use of all interrupts and memory.
- Advanced real time events qualified by address/range, data, status, delay/pass counts.
- Control of state transitions from event to event.
- Two complex input and two complex output triggers.
- 64K to 1 M of real time address breakpoints qualified as read, write, or either read/write.
- Full symbolic debug.
- EL-800 supports 64180, Z80H. EC-7000 supports 8051 and 68HC11 families. EM supports 8080, 8085, 8048 family, 6800/2/8, 6809/E, Z80, MK3880 and NSC-800.

Applied Microsystems Corporation, P.O. Box 97002, Redmond, WA 98073-9702

To learn more about the new EL-800 emulator, I'd like to receive:

- ☐ Free literature ☐ A free demonstration ☐ A free demo disk
☐ Free application note on cross-triggering with 8- and 16-bit emulators
☐ Free 10 day evaluation

EDN 020488

Name _____
Title _____
Company _____
Address _____
City _____ State _____ Zip _____

CIRCLE NO 41




Applied
Microsystems
Corporation

back to the Occam program. MicroWay reports that an IBM AT with a Monoputer performs benchmark tests 50% faster than an 80386-based PC—not quite the speed advantage one would expect from its 10-MIPS CPU, but clearly a significant figure when you realize that you can theoretically network an infinite number of Transputers.

MicroWay prides itself on the software support it offers its customers. A \$1500 Transputer Development System (TDS) provides an extra software layer that helps you link multiple boards by configuring a map of the system and determining what piece of code should go to which Transputer. The Occam language includes calls to access the TDS.

The Fast17 from Quintek Ltd sports seventeen Transputers on a single board to provide as much as 25M-flops processing power for your application. One Transputer, design-




Convertible for use either with PC- or VME-based systems, the Megaframe line of Transputer boards from Parsytec provides a bus-free, communications-oriented architecture for industrial computer systems.

nated the master, has 4M bytes of local RAM for program code and data. The master controls a set of 16 slave Transputers coupled in a ma-

trix-switched reconfigurable network. A link interface channels communications to the host CPU, and three 8-link connectors let you net-

Samsung's Advanced CMOS Logic Family



TECHNOLOGY UPDATE

work the board to others. The Fast17 ranges in price from £12,050 to £16,450, depending on the Transputer you specify. The company also sells 4-Transputer boards; prices for these start at £3995.

Another company that offers multiple Transputers on a plug-in PC board is Definicon Systems. The \$4990 DSI-T4 board has four Transputers and 1M bytes of RAM per computing section, and it comes with program development tools and a Parallel-C compiler with an assembler and linker. The package includes host server software, a macro assembler, a disassembler, and a debugging tool that lets you probe the memory of a specific Transputer. You can network these boards, but linking more than four boards requires the extensive use of jumper cables from an array of pins that line one long edge of the board.

Sension Ltd sells a Transputer Evaluation System (TES) that ex-

ternally houses one to four T414s and 1M bytes of RAM and whose cost ranges from £1365 to £4750. A link-adaptor board plugs into your PC to connect the TES cabinet to the host CPU. You have to purchase the software separately: A single-Transputer version of Occam-2 costs £300, and an Occam-to-IBM editor/compiler/configurer costs £1500 for a single-user license or £3000 for a multiuser system.

If you're considering parallel processing for an industrial application, you may want to consider the Megaframe/IBM board, which Par-sytec has for sale. The basis of this company's line of Transputer boards is a set of Transputer modules that you can alter from VME Bus to PC bus compatibility by swapping interchangeable adapters, called bus bridges, which connect to the modules via a linking cable. The cable facilitates bidirectional signal transmission at a speed of 20M bps over a

distance as great as 10m. The modules include boards with one to four Transputers, 1280×1024×8-dot graphics-display modules, a frame grabber, mass-storage controllers, and a 50M-byte/sec I/O interface. The Megaframe/PC adapter costs \$595, and the Transputer modules sell for \$1050 to \$5650.

You can even purchase, from Levco, Transputer processor modules for your Macintosh II or SE computer. Priced at \$2499 for the Mac II and \$1899 for the Mac SE, starter kits include a Translink plug-in card, a 15-MHz Transputer module with 256k bytes of RAM, and a software tool kit. You can select from various other Transputer modules ranging in price from \$1299 to \$3499.

Finally, you also have the alternative of choosing a coprocessing board that uses a RISC processor instead of a full-featured μ P. Acorn Computers' Springboard is mar-


How to stay current on glue logic.

Samsung's Advanced AHCT CMOS Logic Family meets the demands of your new 16- and 32-bit designs for high speed, high drive and low power.

Available now.

Our Advanced AHCT CMOS Logic Family has a selection of 109 part types available in production quantities now, increasing to 157 parts by 2Q '88. This means you can design AHCT into your product now and move immediately into production.

If you need to reduce power in your existing designs, Samsung's AHCT gives you pin-for-pin, part-for-part replacement for ALS and FAST™. It fits right in and reduces power ten-fold. Yet Samsung



KST4AHCT PARTS LIST

Gates and Inverters	Flip-Flops	Transceivers/Registered Transceivers	Multiplexers
00 20 73 399	01 21 74 534	242* 645 658*	151 253
02 22 76 564	03 27 78 574	243* 646 659*	153 257
04 30 107 670	05 32 109 794*	640 651* 665*	157 258
06 32 109 794*	08 51 112 821*	643 652*	158 262
09 58 173 822*	10 86 174 823*	Counters	Shift Registers
11 132 175 824*	12 133 273 825*	160 169 390*	164 299*
14 266 374 826*	16 377 826*	161 190 393	165 595
		162 191 590*	166 596
		163 192 591*	194 597
		168 193 592*	
		593*	Arithmetic Circuits
Buffers & Line Drivers	Latches	Decoders/Encoders	181* 522*
125 367 75* 793*	42 148* 238		182* 679
126 368 77* 841*	139 154 239		183 680
210 465* 259 842*	139 155		290 682
240 466* 373 843*			516* 684*
241 467* 533 844*			519 686*
244 468* 563 845*			520* 688
365 540 573 846*			521 689*
366 541			Logic Level Converters
			4049 4050*

*Part types available in 2Q '88. All other part types available now.

AHCT does not have a premium price. It costs the same as ALS. Plus, our surface-mount (SOIC) package option is moving into production.

Rugged and reliable.

Designed into each part is a minimum of 200mA latch up protection and a minimum of 2000V ESD protection. So you won't have to worry about them.

Write or call Samsung AHCT CMOS Logic Marketing at 408/434-5400 for free samples and a data book.

Setting the pace.



SAMSUNG

Semiconductor

3725 North First Street
San Jose, CA 95134-1708

FAST is a trademark of Fairchild Semiconductor, Inc.
© 1988 Samsung Semiconductor, Inc.

CIRCLE NO 11

keted in the US for \$2500 through VLSI Technology, and is built around a 32-bit Acorn RISC Machine (ARM) processor, which VLSI Technology manufactures. Because of the reduced number and simplified nature of the processor instructions available to RISC chips, such chips can execute code faster than standard μ Ps can. In addition, the ARM processor uses pipelined operation and hard-wired instruction decoding to further enhance the chip's performance.

The result is a plug-in board that performs twice as fast as the fastest Symbolics workstation, according to the manufacturer. Although the company primarily markets the Springboard for artificial-intelligence development, languages available for the board include ARM versions of C, Fortran, Lisp, Prolog, Basic, and Pascal—each priced at \$500.

Another RISC coprocessor board

for PC-compatible computers is the PC4000, which features a 16-bit Novix NC4016 RISC processor. Silicon Composers, the manufacturer of the PC4000, specifies the board's performance in the 4- to 8-MIPS range, or approximately twice the speed of a VAX 11/780. You can plug as many as six PC4000s into your PC, or more with an expansion chassis.

The PC acts as an I/O server, and the PC4000 has direct memory access to PC disks, I/O, and memory-to-memory transfers. Each board shares the PC bus and a minimum of 16k bytes of RAM with the host CPU to facilitate communications and data transmission. A 5-MIPS single-processor board costs \$1295; a 6-processor 40-MIPS board sells for \$9150.

The coprocessor boards that Opus Systems manufactures feature Intergraph's 32-bit, 33-MHz Clipper RISC chip and run Unix System V

Release 3. The Personal Mainframe Series coprocessor boards provide processing speeds as fast as 5 MIPS (300PM models). Pricing for these models ranges from \$3070 with 4M bytes of RAM to \$6700 with 16M bytes. The price tag includes a C compiler and a Fortran-77 compiler, a device-driver library, and a real-time I/O executive that has provisions for scheduling, data management, and interprocessor communications.

EDN

Reference

1. Dewdney, A K, "Computer Recreations," *Scientific American*, August 1985, Vol 253, No 2, pg 16.

Article Interest Quotient
(Circle One)

High 518 Medium 519 Low 520

Samsung's flash converters



TECHNOLOGY UPDATE

For more information . . .

For more information on the PC-based parallel-processing boards described in this article, contact the following manufacturers directly or circle the appropriate numbers on the Information Retrieval Service card.

A I Architects Inc
1 Kendall Square
Cambridge, MA 02139
(617) 577-8052
FAX (617) 577-9774
Circle No 701

Acorn Computers Ltd
Cambridge Technopark
645 Newmarket Rd
Cambridge CB5 8PB, UK
(0223) 214411
TLX 81152 ACNNMR G
Circle No 702

Applied Reasoning Corp
86 Sherman St
Cambridge, MA 02140
(617) 492-0700
TLX 6714194
Circle No 703

Definicon Systems Inc
1100 Business Center Circle
Newbury Park, CA 91320
(805) 499-0652
TLX 272849
Circle No 704

Levco Corp
6160 Lusk Blvd, Suite C-203
San Diego, CA 92121
(619) 457-2011
Circle No 705

MicroWay Inc
Box 79
Kingston, MA 02364
(617) 746-7341
TLX 503014
Circle No 706

MicroWay (Europe) Ltd
32 High St
Kingston-Upon-Thames
Surrey, KT1 1HL, UK
(01) 541-5466
TLX 9413790 MCRWAY G
Circle No 707

Opus Systems
20863 Stevens Creek, Bldg 400
Cupertino, CA 95014
(408) 446-2110
TLX 323114
Circle No 708

Parsytec
c/o C&C Marketing
708 Mandrake Dr
Box 280
Batavia, IL 60510
(312) 879-7003
TLX 4974811
Circle No 709

Parsytec GmbH
Jülicher Strasse 338
D-5100 Aachen, West Germany
(241) 182-2275
Circle No 710

Quintek Ltd
Southfield House
2 Southfield Rd
Westbury-on-Trym
Bristol BS9 3BH, UK
(0272) 628196
TLX 449683
Circle No 711

Sension Ltd
Denton Dr
Northwich
Cheshire CW9 7LU, UK
(0606) 44321
TLX 666468
Circle No 712

Silicon Composers
210 California Ave, Suite K
Palo Alto, CA 94306
(415) 322-8763
Circle No 713


VLSI Technology Inc
8375 S River Parkway
Tempe, AZ 85284
(602) 752-8574
Circle No 714

How to get A/D-D/A in one.

The pacesetter technology of our single-chip KSV3110 A/D-D/A flash converter provides independent 8-bit A/D converter functions and 10-bit R-2R D/A converter functions over an operating range of DC to 20MHz.

High performance at low cost.

Not only does the new KSV3110 operate from DC to 20MHz, it also gives TTL-compatible input/output, has



1% absolute non-linearity, and selectable input peak level or keyed clamping—all for less than half the cost.

Introducing a low-cost 20 MHz KSV3208 8-bit A/D converter.

The impressive linear characteristics of the KSV3110

FLASH CONVERTER PARTS LIST

Part	Resolution A/D	D/A	Linearity A/D	D/A	Conversion Speed	Industry Part
KSV3110N-10	8 bits	10 bits	$\pm \frac{1}{2}$ LSB	$\pm \frac{1}{2}$ LSB	20 MSPS	
KSV3110N-9	8 bits	10 bits	$\pm \frac{1}{2}$ LSB	± 1 LSB	20 MSPS	
KSV3110N-8	8 bits	10 bits	$\pm \frac{1}{2}$ LSB	± 2 LSB	20 MSPS	
KSV3110N-7	8 bits	10 bits	$\pm \frac{1}{2}$ LSB	± 4 LSB	20 MSPS	
KSV3100AN-8	8 bits	10 bits	$\pm \frac{1}{2}$ LSB	± 2 LSB	20 MSPS	UVC3101
KSV3100AN-7	8 bits	10 bits	$\pm \frac{1}{2}$ LSB	± 4 LSB	20 MSPS	UVC3101
KSV3208N	8 bits		$\pm \frac{1}{2}$ LSB		20 MSPS	

are shared by our new KSV3208. It provides the same features for those applications that don't require D/A conversion.

Samsung also offers the support chips needed to ease the integration of our flash converters into video applications: the KA2606 Sync Separate IC, the KA2153 Chrominance Signal Processor for NTSC systems, and the KA2154 Video Chroma Deflection System for NTSC and PAL systems.

Write or call Samsung Flash Converter Marketing today at 408-434-5400 for samples, data books, and a full listing of our data converter products.

Setting the pace.



SAMSUNG

Semiconductor
3725 North First Street
San Jose, CA 95134-1708

FOR REAL-TIME DESIGNERS THAT DEMAND THE MOST, THE CONTROLLER THAT DEMANDS THE LEAST.



Our new 80C196 delivers the highest performance and the highest integration of any 16-bit

microcontroller available. While demanding the least power, the least design time, the

least hassle. Which means you can spend more time perfecting the rest of your application.


The 12 MHz 80C196 is the latest member of our proven MCS-96 family of embedded controllers. It offers the low-power requirements of CMOS technology while doubling the performance of the 16-bit 8096. Which means that it can perform a 16 x 16 multiply in 2.3 micro-seconds. That's faster than any other microcontroller.

Yet you still get all the features of the 8096. And more. Resident on the highly-integrated 80C196 are a 16-bit cpu with an 8/16-bit bus (reconfigurable), 256 bytes of RAM, PWM, 10-bit A/D, two 16-bit timer/counters, 40 I/O pins, full duplex serial port, and a high-speed I/O subsystem. And speaking of getting more features in less space, we're working on an EPROM version of the 80C196 for an even easier design path (available Q2 1988).

Our low cost ICE™-196 PC development tool gives you more for less, too. Together with high-level languages like PL/M and C,

it delivers the easiest, lowest-cost design support you can get.

Further support is available from the world's largest network of field applications engineers. Plus customer workshops to get you up to speed fast.



So you see, there's really no easier or more powerful answer to embedded real-time control than Intel's 80C196. For complete technical information, call toll-free (800) 548-4725 and ask for Literature Department W398.


Do it now. And relax.

Because we're ready to meet your demands.

intel®

ICE is a trademark of Intel Corporation. ©1987 Intel Corporation

Turn to the Masters of RF Amplifier Design



RF Devices has the talent and the experience it takes. We are RF amplifier performance artists. With our palette of products and capabilities, we can meet your needs – from RF and microwave power transistors and hi-rel hybrids to complete UHF high-power modules and systems – from 100KHz to 4GHz, from under 1W to 1KW.

And not just with standard products. We team up with you to create special and original solutions – and every design bears our industry-leading figure of merit – power at frequency with low distortion.

We've developed RF linear hybrids featuring high gain, very high dynamic range and very low distortion. Our feed-forward techniques in these hybrids are meeting demands for faster speeds in CATV systems and wideband LANs.

We're delivering the gain needed in

high-power cellular base stations with our power-combining and feed-forward technology. And, our high-voltage drivers with sub-three nanosecond rise time are reducing the cost of high-resolution monitors and VLSI test equipment.

Your solution will have quality, reliability and manufacturability built-in right from the beginning, starting with



our own die design and wafer fab. And, with our high-volume production facility, you'll get a total capability that can handle your largest requirement.

Your challenge will bring out the best in us – and the RF amplifier that's just right for your design. Call us about your application at 213.536.0888 and ask for RF Amplifier Solutions. Or write for our free brochure to TRW RF Devices, 14520 Aviation Blvd., Lawndale, CA 90260. Attn: RF Amplifier Solutions.

Let us paint you a masterpiece.

©TRW Inc. 1987 — 713A00887

TRW

TRW RF Devices Division


PLD design software accepts designs as schematics, waveforms, or tables

Featuring an interactive, graphics user interface, the Model 74150A PLD Design System software allows you to design PLD-based circuits by using any combination of Boolean equations, schematics, waveforms, or tabular data. The software runs on the company's Model 9000 Series 300 workstations. It takes your design, simulates the circuit's operation, checks for glitches, partitions the design to fit in one or more PLDs, and generates a fuse map and test vectors. You can select the target devices or use the software to automatically fit your design into appropriate PLDs.

The PLD Design System accepts circuit designs as schematics, state-transition diagrams, waveforms, Boolean equations, or truth tables. You can also take advantage of the software's hierarchical structure to break your design into modules and then use different design-entry methods to describe each module. In effect, the software allows you to match the design-entry method to the circuit or subsystem that you're developing.

The software's schematic editor provides an entry method similar to most CAD schematic-capture packages and allows you to attach simulated switches, oscillators, and logic probes to circuit nodes to aid debugging and verification efforts. A batch-mode debugger coupled with the schematic editor allows you to simulate your design's operation with input waveforms defined graphically in a separate stimulus file.

For synchronous circuit design, you can create state-transition diagrams (STDs) with a special STD editor that shows individual states as boxes linked with transition arrows. Pop-up transition tables allow



With the PLD Design System, you can design PLD-based circuits by using either waveforms, schematics, or state-transition diagrams.

you to enter state-transition conditions in tabular form. An interactive debugger coupled to the STD editor enables you to step through state transitions or to advance multiple states one at a time.

The software's waveform editor allows you to define a PLD, using timing diagrams that are especially useful for developing asynchronous circuits. The waveform display represents cause-and-effect relationships—causalities—using curved arrows that link the related waveforms.

The waveform editor and its debugger support six types of causalities: input edge to output edge, input value to output edge, input edge to output value, input edge and value to output value, and input edge and value to output edge. You can also define a PLD's structure with Boolean equations and truth tables, for-

mats established by early PLD design tools. The PLD Design System minimizes equations automatically.

The software accepts designs without regard to a target PLD; this device independence allows you to try out various PLDs and find the most appropriate device for your design. You can also ask the PLD Design System to select the most appropriate device automatically from its PLD library, and you can narrow its choices by specifying parameters that pertain to your application—vendor type, inventory, or power consumption, for example. The PLD library currently contains device information about PLDs available from Altera, AMD, Intel, Lattice, Monolithic Memories, NEC, Ricoh/Panatech, Signetics, and VTI.

If your design won't fit into one PLD, the software allows you to partition the circuitry manually, or

WORLD-CLASS IC PRODUCTS

SPOTLIGHT #34
IN A SERIES



At Silicon Systems, here are the product lines we have developed in response to your market needs.

MICROPERIPHERAL IC's: We offer more than 50 ASIC chips serving the mass storage market. It includes the industry's most comprehensive line of read/write amplifier IC's for disk drives as well as complete chip sets covering such other disk drive electronic functions as pulse detection; data recovery; head positioning; spindle motor control; and buffer, storage, and interface control. We also offer circuits for optical, floppy, and tape drives; and we are continuously expanding the line.

TELECOMMUNICATIONS IC's: For U.S. or world-wide telecom systems operating at 300 to 2400 BPS data transfer speeds, Silicon Systems can provide the industry's most advanced family of software/hardware compatible, single-chip modem IC's available. These pin-out and register-compatible K-Series chips allow for easy product upgrading over the entire Bell and CCITT ranges, and Silicon Systems also offers more than a score of other telecom IC's for a variety of applications in tone signaling, telephony, and digital communications.

CUSTOM / SEMICUSTOM IC's: And beyond its lines of standard ASIC's, Silicon Systems continues to offer—as it has since its inception—its innovative bipolar and CMOS design and manufacturing capabilities as a unique resource for complex custom/semicustom products.

For more information, contact: **Silicon Systems**, 14351 Myford Road, Tustin, CA 92680. Phone: (714) 731-7110, Ext. 575.

silicon systems
INNOVATORS IN INTEGRATION

CIRCLE NO 13

UPDATE

you can ask the software to perform the partitioning automatically. If your design has speed-sensitive signal paths, you can assign the critical signals manually and have the software to finish the job.

Once you've defined and compiled your design for a particular PLD or set of devices, the PLD Design System creates the appropriate fuse maps. The software supplies these maps to a PLD programmer as JEDEC fuse-map files via the host workstation's RS-232C or IEEE-488 interface ports. It can also read JEDEC fuse maps back from the programmer, including maps for existing PLDs designed with other design tools; thus you can more easily incorporate existing PLDs into new designs. Currently, the software supports PLD programmers from Data I/O and Stag, but any PLD programmer that accepts JEDEC fuse maps is compatible with the PLD Design System.

The company is marketing the software as part of its Electronic Design System, a collection of CAE software tools for electronics engineers. The PLD Design System exchanges circuit and simulation data with the other software tools in the Electronic Design System, using a proprietary representation format for schematic information and GenRad-compatible HILO-3 data files for simulation data. This data interchange allows the PLD Design System to convert circuits (or portions of circuits) designed with the Electronic Design System into PLD designs; it also allows more complete simulation of PLD designs by the Electronic Design System package's HILO simulator.

The PLD Design System costs \$8000 to \$14,500, depending on options. You can expect delivery approximately 12 weeks ARO.

—Steven H Leibson

Hewlett-Packard Co, 1820 Embarcadero Rd, Palo Alto, CA 94303.
Phone local office.

Circle No 700

EDN NEWS



HOT NEWS OF PRODUCTS, TECHNOLOGY, AND CAREERS

EDN NEWS

EDN February 4, 1988

SERVING WORLD-WIDE NICHE WITH WORLD-CLASS IC PRODUCTS

What is a niche?

To many companies, a niche is a market segment targeted by the sales department. At Silicon Systems, a niche is a segment of the market in need of specialized products and services, a segment not well served by the large general-purpose companies. We target such niches at the highest level of our company—well in advance of the actual market needs. In this way, we have brought forth some of the industry's most innovative products.

The Microperipheral Niche.

While pioneering the development of single-chip read/write amplifiers for disk drives, we very early recognized the need for a family of highly integrated disk drive IC's. Today, as the leading supplier of read/write amplifiers, we also offer the industry's most complete line of integrated circuits for every other major function in disk drive electronics.

The Telecommunications Niche.

In 1979, when we were first to fully integrate a complete dual tone multiple frequency (DTMF) circuit on a chip, we also selected telecommunications as yet another important niche in need of special products and services. Today, Silicon Systems leads the industry with its highly-integrated, pin-out and register-compatible, K-Series family of modem IC's to serve operating modes world-wide.


The Custom / Semicustom Niche.

And because we started life as a custom design house, superior design and engineering shall always remain paramount at Silicon Systems. It's a superiority that allows us to create and produce complex analog and digital designs on the same chip, to create special bipolar and CMOS monolithic circuits that other companies are unable to produce. It is a capability key to our success—a capability available to you for your most demanding custom and semicustom designs.

Call Now!
(714) 731-7110, Ext. 575

For more information on our company, our products or our capabilities, contact: **Silicon Systems**, 14351 Myford Road, Tustin, CA 92680.

silicon systemsTM
INNOVATORS IN INTEGRATION



"Where we design to your applications."

Digital precision motion controller simplifies control of dc motors


The LM628 motion-control processor simplifies the control of dc and brushless dc motors by performing real-time computational tasks. Using this motion-control processor, you can build a servo system that requires only a dc motor, an optical incremental encoder, a DAC, and a power amplifier. A host processor controls the system via an 8-bit I/O port that uses a byte serial format wherein the data words follow the command word.

The host processor programs a trapezoidal velocity profile and a digital compensation filter. The trapezoidal velocity profile defines the operation of the motor in terms of maximum acceleration, maximum velocity, maximum deceleration, and final position.

The digital compensation filter is a proportional-integral-derivative (PID) filter. It modifies the output of the controller to keep the servo system stable, and it compensates for the control loop. The LM628 subtracts the actual position, which is determined by feedback from the optical encoder, from the desired, or profile-generator, position. The PID filter processes the resulting position error to drive the motor to the desired position. The LM628 holds the motor at the desired position by subjecting it to a restoring force proportional to the position error, the integral of the error, and the derivative of the error.

An optical incremental encoder linked to the motor sends a 2-phase quadrature signal back to the LM628 to detect the direction of the motor's rotation and position. The motion-control processor uses this signal to control an up/down counter that keeps track of the actual position of the motor.

When the LM628 is in the position



The LM628 provides precision motion control of dc and brushless dc motors and minimizes the parts count of a dc servo system.

mode, you specify the motor's acceleration, maximum velocity, and final position. The unit then controls the motor to meet these parameters. At any time during a move, you can change the maximum velocity, the target position, or both, and the motor will accelerate or decelerate accordingly—which permits the unit to change profile or filter parameters on the fly.

When the unit is in the velocity mode, the motor accelerates to the specified velocity at the specified acceleration rate and maintains this velocity until it receives a command to stop.

The analog control signal from the LM628 can feed either an 8- or 12-bit DAC. The 12-bit output is multiplexed on the eight parallel digital outputs. The amplified output of the DAC controls the motor.

Traditionally, the servo-system host must poll the controller; with the LM628, you have the option of using interrupts. The unit provides

index-pulse, absolute, or relative-position breakpoint interrupts, as well as wraparound, command-error, and end-of-profile interrupts. It also features an alarm register that you can set to cause an interrupt should the difference between the desired position and the actual position become greater than the programmable limit. This feature aids in the detection of rotor lock.


The LM629 is identical to the LM628 except that it provides a pulse-width-modulated output instead of a DAC-compatible output. Both motion-control processors come in 28-pin DIPs; operate over the -40 to $+85^{\circ}\text{C}$ range, and cost \$50 (100).—**David Shear**

National Semiconductor, 2900 Semiconductor Dr, Santa Clara, CA 95052. Phone (408) 721-4494.

Circle No 699

READERS' CHOICE


Of all the new products covered in EDN's **November 26, 1987**, issue, the ones reprinted here generated the most reader requests for additional information. If you missed them the first time, find out what makes them special: Just circle the appropriate numbers on the Information Retrieval Service card, or refer to the indicated pages in our **November 26, 1987**, issue.



▲ OPTICAL SWITCHES

Slotted optical switches are available with transistor (Series MOC70) and Darlington-type (Series MOC71) outputs (pg 267).


Motorola Inc.
Circle No 603



▲ VOICE MODULE

The low-bit-rate voice digitizer LBRV Codec Module produces voice-quality communications at 9600 bps. The pc board contains a μ -law codec that digitizes an analog voice input (pg 262).


Advanced Compression Technology.
Circle No 602



FILTER-DESIGN PROGRAM

The LCFIL stand-alone, menu-driven filter-design program runs on IBM PCs and compatibles or on the Apple Macintosh. You can design highpass, lowpass, and band-pass filters that have as many as 21 poles (pg 272).

BV Engineering.
Circle No 604



▲ DC/DC CONVERTER

The IR2100 dc/dc converter needs only three external components to form a complete 15V dc, 500-mA dc/dc converter power supply that works directly from 115/230V ac lines (pg 257).


International Rectifier.
Circle No 601

◀ SOLDERABILITY TESTERS

Mustmate-100 and -200 software packages provide PC-based solderability testing of electronic components (pg 288).

Multicore Solders Ltd.
Circle No 605
Multicore Solders Inc.
Circle No 606


Read At The
Speed Of Light.



It's the brightest thing going in optical drives. The Toshiba XM-3100. The fastest half-height 5.25" CD-ROM drive available on the market today. And it's lighting the way to a whole new realm of optical opportunities.

Because the XM-3100 is perfect for all sorts of applications. Like archives, catalogues and libraries. Any application that calls for a reference database with infinite capacity, complete portability, durability and high reliability.

Of course what makes the XM-3100 particularly well suited to the task is Toshiba engineering. With features like both digital and audio output to let your database speak its mind. 400ms average time-to-data to do the job fast. And a SCSI



interface to make system integration painless.

But then, taking pains to do it right is nothing new at Toshiba. After all, we shipped the first optical drive way back in 1981 and we've been in front ever since. With the products, the engineering and the support it takes to be the leader.

To see how the Toshiba XM-3100 can help put you in front, call us at 714-583-3150.

And before long you'll be light years ahead of the competition.

In Touch with Tomorrow
TOSHIBA
TOSHIBA AMERICA, INC.

Disk Products Division, 9740 Irvine Boulevard, Irvine, CA 92718

© 1987 Toshiba America, Inc.

LEADTIME INDEX

Percentage of respondents

ITEM	Off the shelf	1-5 weeks	6-10 weeks	11-20 weeks	21-30 weeks	Over 30 weeks	Last month's average (weeks)	Average (weeks)
TRANSFORMERS								
Toroidal	8	58	17	17	0	0	5.7	9.3
Pot-Core	0	50	25	17	8	0	8.2	9.4
Laminate (power)	6	39	33	17	5	0	7.8	8.7
CONNECTORS								
Military panel	0	0	67	17	16	0	12.2	11.5
Flat/Cable	17	44	28	11	0	0	5.3	6.6
Multi-pin circular	10	40	20	20	10	0	8.0	10.0
PC (2-piece)	0	33	45	22	0	0	8.0	7.3
RF/Coaxial	13	40	13	27	7	0	8.1	6.4
Socket	6	67	11	11	5	0	6.0	5.3
Terminal blocks	25	45	15	10	5	0	5.4	5.6
Edge card	19	44	19	12	6	0	6.3	6.3
D-Subminiature	13	40	33	7	7	0	6.6	6.2
Rack & panel	0	45	33	11	11	0	8.6	6.8
Power	0	29	29	28	14	0	11.2	7.2
PRINTED CIRCUIT BOARDS								
Single-sided	0	74	21	5	0	0	4.7	5.1
Double-sided	0	46	50	4	0	0	6.0	6.9
Multi-layer	0	23	69	8	0	0	7.4	7.9
Prototype	5	85	10	0	0	0	3.4	3.5
RESISTORS								
Carbon film	35	45	20	0	0	0	3.0	3.6
Carbon composition	28	43	19	10	0	0	4.3	3.1
Metal film	15	50	35	0	0	0	4.3	4.4
Metal oxide	11	56	22	11	0	0	5.2	4.8
Wirewound	4	46	32	14	4	0	7.2	7.2
Potentiometers	7	55	31	7	0	0	5.2	6.4
Networks	16	37	32	10	5	0	6.6	4.7
FUSES								
	54	38	8	0	0	0	1.8	3.8
SWITCHES								
Pushbutton	11	72	11	6	0	0	3.9	6.0
Rotary	5	67	11	17	0	0	5.5	7.3
Rocker	6	59	23	12	0	0	5.5	5.7
Thumbwheel	0	69	15	16	0	0	5.7	8.4
Snap action	0	64	29	7	0	0	5.3	5.6
Momentary	7	60	26	7	0	0	5.0	5.6
Dual in-line	0	50	20	30	0	0	7.8	6.4
WIRE AND CABLE								
Coaxial	23	68	9	0	0	0	2.8	3.3
Flat ribbon	26	42	32	0	0	0	3.8	4.0
Multiconductor	25	50	25	0	0	0	3.5	4.6
Hookup	23	65	12	0	0	0	2.9	3.1
Wire wrap	38	54	8	0	0	0	2.2	4.8
Power cords	28	56	12	4	0	0	10.8	4.5
POWER SUPPLIES								
Switcher	6	41	29	24	0	0	7.2	10.1
Linear	0	55	27	18	0	0	6.6	9.5
CIRCUIT BREAKERS								
	7	33	27	33	0	0	8.3	8.2
HEAT SINKS								
	17	46	33	4	0	0	4.7	6.2
RELAYS								
General purpose	13	67	12	8	0	0	4.3	6.9
PC board	0	79	0	21	0	0	5.7	8.5

ITEM	Off the shelf	1-5 weeks	6-10 weeks	11-20 weeks	21-30 weeks	Over 30 weeks	Last month's average (weeks)	Average (weeks)
RELAYS								
Dry reed	0	40	40	20	0	0	7.5	8.9
Mercury	20	40	40	20	0	0	4.4	8.8
Solid state	0	54	31	15	0	0	6.5	7.5
DISCRETE SEMICONDUCTORS								
Diode	32	42	19	7	0	0	3.8	7.8
Zener	35	35	15	15	0	0	4.7	8.8
Thyristor	8	38	31	23	0	0	7.2	9.5
Small signal transistor	37	32	21	10	0	0	4.3	8.8
MOSFET	6	44	28	22	0	0	7.0	8.0
Power, bipolar	15	31	39	15	0	0	6.4	7.5
INTEGRATED CIRCUITS, DIGITAL								
Advanced CMOS	0	50	33	17	0	0	6.8	9.3
CMOS	10	38	38	14	0	0	6.4	8.7
TTL	21	42	16	21	0	0	5.8	5.7
LS	19	48	19	14	0	0	5.2	5.9
INTEGRATED CIRCUITS, LINEAR								
Communication/Circuit	8	42	33	17	0	0	6.5	8.9
OP amplifier	17	33	22	28	0	0	7.1	7.8
Voltage regulator	11	42	26	21	0	0	6.6	6.8
MEMORY CIRCUITS								
RAM 16k	0	46	27	27	0	0	7.8	7.3
RAM 64k	0	47	27	26	0	0	7.7	7.7
RAM 256k	0	20	47	33	0	0	9.5	10.0
RAM 1M-bit	0	20	30	40	10	0	11.8	11.1
ROM/PROM	9	36	18	37	0	0	8.2	8.7
EPROM 64k	0	36	43	21	0	0	7.8	8.5
EPROM 256k	0	36	36	28	0	0	8.4	9.7
EPROM 1M-bit	0	22	45	33	0	0	9.4	13.5
EEPROM 16k	0	40	30	30	0	0	8.3	9.4
EEPROM 64k	0	36	37	27	0	0	8.3	9.6
DISPLAYS								
Panel meters	8	38	46	8	0	0	6.0	7.2
Fluorescent	0	12	38	50	0	0	11.1	13.0
Incandescent	0	33	34	33	0	0	8.8	8.9
LED	18	32	41	9	0	0	5.6	6.8
Liquid crystal	0	10	40	50	0	0	11.3	9.8
MICROPROCESSOR ICs								
8-bit	28	27	18	27	0	0	6.5	7.8
16-bit	8	50	17	25	0	0	6.7	9.1
32-bit	8	42	25	25	0	0	7.1	8.9
FUNCTION PACKAGES								
Amplifier	0	50	38	12	0	0	6.4	10.2
Converter, analog to digital	0	31	46	23	0	0	8.2	9.8
Converter, digital to analog	0	43	29	28	0	0	8.0	10.7
LINE FILTERS								
	0	63	12	25	0	0	6.8	7.6
CAPACITORS								
Ceramic monolithic	21	32	37	10	0	0	5.5	6.3
Ceramic disc	26	30	29	15	0	0	5.6	6.5
Film	9	45	32	14	0	0	6.0	7.5
Aluminum electrolytic	12	42	27	19	0	0	6.4	7.2
Tantalum	15	41	29	15	0	0	5.9	7.1
INDUCTORS								
	0	44	31	25	0	0	7.7	7.6

Source: Electronics Purchasing magazine's survey of buyers

JAN 38510/555
MEGA-RAD
SEAFAC Certified



Unclutter your 1553 data bus.

Now you can have a more reliable MIL-STD 1553 data bus system that uses less real estate. All on our monolithic, dual-redundant UT1553B RTI.

Fully proven in military and aerospace products of United Technologies Corporation, UTMC's RTI is ready for your system.

It features the low power consumption of CMOS technology and is the standard LAN used for military systems requiring a serial bus with low EMI/RFI susceptibility and high data

integrity. Of course, the UT1553B RTI is screened to selected tests in MIL-STD 883C.

This RTI reduces host overhead with an automatic DMA and address generation and can be used in a transparent dual-port RAM configuration. It interfaces with data bus transceivers, system memories, and 8- or 16-bit CPUs. Various 84-pin package options available.

If your 1553 data bus needs are getting lost in a maze of hybrids, call UTMC. We'll unclutter things.

Product Marketing
United Technologies
Microelectronics Center
1575 Garden of the Gods Road
Colorado Springs, Colorado 80907
1-800-MIL-UTMC



System, system how will I know it

Simulating and testing large, multi-technology systems utilizing ASIC's always involved lots of guesswork. And a little magic.


No more.

Now there's the AIDA Design System.

A comprehensive set of software design tools for capture, simulation and automatic generation of test patterns for systems of 5000 to 1 million gates. At all levels—chip, board, system.

Faster and more cost effective than ever before. Giving each designer 20 to 30 simulation turns a day. At one-tenth the cost of hardware accelerators.

The AIDA tool set is so powerful, it lets you do complete and automatic timing analysis of your design to identify all critical paths. And simulate its operation by running actual application programs and diagnostic software.



n, on the wall, you'll work at all?



Even better, it guarantees 100% test coverage for scanable designs by automatically generating all possible test vectors.

Installation and training are easy, too. Because the AIDA Design System runs on industry-standard workstations. And we have translators that let you use your existing databases with the AIDA design tools.


Skeptical? Call 408-980-5200 now to get a video tape* of what our customers are saying.

And see how we're helping them get systems off the wall and into production. Fast.

For more information, contact AIDA Corporation, 5155 Old Ironsides Drive, Santa Clara, CA 95054, 408-980-5200.

AIDA

*We reserve the right to qualify recipients.AIDA is the trademark of AIDA Corporation. © 1987.



You can reduce simulation time by adding a hardware accelerator, which implements simulation algorithms in hardware. The Cats accelerator from HHB Systems performs logic, timing, and fault simulation at around 300 times the speed of a VAX 11/780. The Cats accelerator starts at \$200,000; for a VAXstation II, the basic Cadat simulation package costs \$20,000.

ASIC simulators

Sophisticated digital simulators can help you develop your application-specific IC (ASIC) designs. Simulators can prevent chip-level design problems and can often come up with good test-vector sets, but they can't correct failures resulting from the old engineering bugaboo—inadequate design specifications.

Margery S Conner, *Regional Editor*

Design flaws in application-specific ICs (ASICs) can be costly: Most ASIC foundries report prototype chip yields of 95%, but many of their customers regularly throw away 40 to 60% of those chips because of flaws in the original designs. Digital-ASIC simulation packages can help you identify and correct some of those flaws before your design goes into production.


Manufacturers of these new logic and timing simulators boast, with some justification, that their products can solve your thorniest ASIC-design problems. (Fault simulation packages are also available; see **box**, "Fault simulators verify testability.") But no simulator in existence now, or likely to exist in the near future—barring a massive breakthrough in artificial intelligence—can make up for the failure to specify your designs rigorously at the chip level.

You can obtain an ASIC-simulation package from one of three sources: You can use your foundry's in-house package, you can develop and support your own custom simulation package, or you can purchase a simula-

tor from a third-party supplier. Each of these approaches has its advantages and disadvantages. The major advantage of using a foundry's in-house simulator, for example, is that the simulator is developed specifically for the foundry's processes and devices. When you use such a proprietary simulator, you are using a package that the foundry knows intimately and that is fine-tuned to model the foundry's proprietary process. What's more, if you encounter problems with your ASIC, you can get them solved promptly; you don't risk waiting around while the foundry and the simulation vendor argue about whose fault the problems are.

The second option—that of developing and supporting your own simulator—is impractical for most companies because it requires a large software effort. Developing a simulator is practical only for companies that already do a great deal of custom-IC work.

The big advantage of the third option, the third-party simulation package, is that it's portable: You can start with one foundry and later shift to another, as long as the simulator you choose supports both foundries' li-



Capable of performing logic, timing, and fault simulation, the Lasar simulator from Teradyne ranges in price from \$15,000 for the VAXstation 2000 version to \$280,000 for the VAX 8800 version.

Digital-ASIC simulation packages can help you identify and correct design flaws before your design goes into production.

braries of models. However, because of the huge number of foundries to choose from and the rapid advancements in model design, vendors of third-party simulators have not been quick enough to support new models.

Foundry supports third-party simulators

Until recently, many of the larger ASIC foundries have often refused to guarantee chips fabricated from designs simulated with third-party simulators. Now, however, some of the foundries show signs of bowing to their customers' demands for third-party-simulator support. VLSI Technology (San Jose, CA), for example, deals with many a potential customer that has already invested in a workstation package and doesn't want to purchase another one from a foundry. The company offers its Portable Library for the Daisy and Mentor workstations. The basic Portable Library interface is \$10,000; the timing-module libraries cost \$5000

each. (Each timing module is for a particular line width; ASICs with 1.2- μ m line widths, for example, have different timing characteristics than do those with 1.5- μ m line widths.) Because of the competition among foundries, third-party-simulator support will probably become the rule rather than the exception.

VLSI Technology chose Daisy's and Mentor's simulators because those two companies have large installed bases. That decision illustrates the Catch-22 situation that some of the younger simulator companies find themselves in: Designers are reluctant to commit to the newer simulator vendors, regardless of the quality or cleverness of their products, because newer companies' simulator libraries lack extensive foundry models. However, it's difficult for a younger company to develop a library of foundry models, because foundries usually choose only third-party simulators that are already in wide use.

When you're choosing a third-party simulator, it's

Fault simulators verify testability

The design engineer has traditionally been responsible for troubleshooting any logic and timing problems in an ASIC design. Now, however, the production problems associated with higher degrees of circuit integration—problems such as increasing circuit complexity and the lack of test points—are forcing design engineers to shoulder testability concerns as well. The reason that design engineers must consider testability is clear: The best point at which to determine whether a design is testable, and thus manufacturable, is the earliest one—the design stage.

To meet those needs, most vendors of ASIC-simulation packages currently offer fault-simulation packages in addition to their logic and timing simulators. Fault simulators help ensure that designs will be testa-

ble by inserting faults into a network model and running a network simulation for both the correct conditions (as an experimental control group) and the error conditions. For example, the most commonly used fault model, the "stuck-at" fault model, assumes that inputs and outputs of network primitives fail at either a high or a low state. The fault simulator looks for changes in the output for a stuck-at condition; if that output is different from the output exhibited in the fault-free state, then the input vector has detected a fault. The ultimate purpose of the fault simulator is to find out whether your fault-simulation vectors provide adequate fault coverage.

Note that these fault-simulation vectors are not test vectors. Rather, you use fault-simulation vectors to generate test vectors.

Test vectors are the stimulus and response patterns that the ASIC foundry uses to verify that its chip meets your design criteria and that the manufacturing process has not varied. Once the chip is in volume production, the foundry monitors the manufacturing process by running the test vectors through each ASIC.

Because of production-time and cost restraints, an ASIC house can usually run about 4000 to 10,000 test vectors through the ASIC—for more vectors, you must pay a premium. Although 10,000 test vectors are usually enough to verify that a chip has been produced correctly and that the manufacturing process is not varying, they are not sufficient to verify that the design is good. Fault-simulation vectors, however, *can* verify that a design meets its specifications.

useful to consider the experiences of companies that have developed their own simulators. Such companies understand how simulators work and have practical experience in applying them. Further, because they don't sell their simulators, these companies are relatively unbiased about what a simulator's capabilities should be, and they're under few illusions about what you can expect from a simulator.

One company's experience


For example, Zymos Corp (Sunnyvale, CA), which designs and manufactures customizable IBM PC- and PS/2-compatible chip sets, wrote its own logic and timing simulator. Initially, the company let customers use the simulator to simulate chips that varied from Zymos's basic ASIC design. The company then took those designs and turned them into silicon.

Zymos discovered, however, that the chips developed from those simulations often did not work in the customers' systems. The problem was not that the simulations were wrong, but that the specifications the customer used in the simulations were incorrect. Because Zymos had incurred unnecessary nonrecurring engineering costs to develop prototype chips that it never produced, the company elected to require that all new designs be proven first in its hardware emulator. In essence, the company required a breadboard of the new design. The lesson to be learned from Zymos's experiences is not that simulation doesn't work, but that ASIC design still requires a great degree of engineering-design skill.

Look for a complete library of models

The three most important features to consider when choosing a simulator are the simulator's library of models, its modeling capabilities, and its timing-verification capability. The library is the most important of these features. It should have enough of the models you need and should be compatible with your foundry's processes. Be sure to find out exactly what models the simulator supports before purchasing it; don't assume that the simulator will have the models you need just because it has a large number of models.

For example, a 7400, 74S00, and a 74ALS00 are all implementations of a NAND gate, yet the simulator manufacturer may count them as three separate models. Although it's true that the different families have different timing characteristics, the timing differences don't affect the device model; timing parameters are loaded in at simulator run-time.




With the 192M-byte expanded-memory option, the Compute Engine Model M can simulate designs having as many as 325,000 gates. The Model M typically allows Apollo workstations to perform logic simulations 24 times faster than they could without the accelerator. This acceleration allows you to perform mixed-mode ASIC simulation at the system level.

If, like most companies, your company designs products in one general field, it's more important for you to choose a simulator library that has most of the devices you design with than it is for the library to have a broad selection of models you won't use. Even so, your company will probably need to develop proprietary models for devices; using these proprietary models is one way to give your ASIC designs a competitive edge over products from companies that use all plain-vanilla parts. All digital-ASIC simulators let you define proprietary device models.

Paradise Systems (South San Francisco), for example, designs products and ASICs for the video-display market. Paradise has found that no simulator library covers all of the video-related devices that it designs with. Paradise chose the Mentor simulator package and added to it by writing many simulator models in house. An alternative to writing extra models yourself is to arrange for another company, such as Logic Automation (Beaverton, OR) or Quadtree (Bridgewater, NJ), to develop the library models for you under contract.

Next in importance to the simulator's library is its

Simulation can help solve some design problems, but no simulator can make up for poor chip-level specifications.



To perform behavioral modeling from the gate level through the system level, the Verilog simulator from Gateway Design Automation uses the Verilog-XL hardware-description language (HDL).

modeling capability. Simulators that offer a behavioral language make it easy for you to model complex devices. Further, because behavioral languages can model devices at various levels, they're well suited for use in hierarchical system design.

When you model a device, you face two challenges—you must describe how the device works, and you must be able to specify stimulus and response patterns. To make this process as painless as possible, you should use a simulator that supports a hardware description language (HDL) that is a behavioral language. Behavioral languages are C-like languages with control structures (constructs), such as If-Then-Else statements, that are tailored for defining the behavior of a device and its response to a stimulus.

Theoretically, the best way to design ASICs for a complex system is to start by specifying the system requirements. Next, you divide the system into subsystems and define each subsystem's requirements, repeating this process through the board level to the individual-ASIC level until the system is completely defined. This complete set of requirements for each building block allows you to simulate ASICs completely in their environment.

That's the theory, anyway. In reality, according to Pete Johnson, a product marketing manager at Gateway Design Automation Corp, it's very rare for a company to do a complete hierarchical system design.

Although more design engineers are seeing the benefits of specifying designs thoroughly from the system level to the chip level, Johnson notes, their managers don't always agree. The problem, he says, is that most engineering managers operating under a tight schedule feel more comfortable with hardware—even when it doesn't work and has to be rebuilt—than they do with the intangible results of a software simulation. They're not always willing to wait for a designer to completely specify and simulate a design before producing the actual part.

Cirrus Logic (Milpitas, CA), a designer of custom ICs for the peripheral-controller market, makes a good case for drawing up detailed design requirements. Because Cirrus's ASIC designs are specialized, the company can make the large software effort necessary to develop and support a custom simulator. However, George Alexy, the company's vice president of marketing, is quick to point out that no simulator is a panacea. More important than software tools are engineers who thoroughly understand what they're trying to design and can translate that understanding to good design specifications.

Cirrus, for example, committed itself to developing a fully custom IBM VGA-compatible chip for IBM PC- and PS/2-compatible machines in six months. Instead of jumping immediately into chip design, the company first developed a complete specification for the chip. After performing the design, Cirrus used a simulator that forced the designers to compare the simulated results with the initial requirements. This practice ensured two things: first, that the designers thoroughly understood how it expected the chip to perform in the system, and second, that the design would be completely documented.

No guarantee it's a duck

This detailed approach has obvious advantages over the traditional design technique that assumes, as the saying goes, that if it looks like a duck, walks like a duck, and quacks like a duck, it probably is a duck. Cirrus's results were impressive; it had delivered over 20,000 of the VGA-compatible chips before its competitors even started shipping. The project's success was largely due to the effort the company put into the initial design specifications.

Although they can emulate Cirrus by placing more emphasis on their designs' initial specifications, most small companies don't have the resources to develop their own simulators. Instead, they must rely on third-




Fig 1—To compare and contrast gate-level, functional, and algorithmic behavioral models, consider the 1-bit full adder shown in a. The gate-level behavioral model (b) of the adder demonstrates the detail needed at this level of modeling, even when you use a hardware description language (HDL). A functional model (c) of the same adder device is much less complex and requires a less-detailed knowledge of the device's gate composition—the code is basically just the Boolean equation for an adder. The algorithmic model (d) is the most abstract level of modeling. In this example it requires more lines of code than c does, but for more abstract devices it's the simpler of the two methods. Note that the first five lines of each model are the same; they are necessary to make the module appear to the simulator as a black box. These five lines describe the inputs and outputs and define an order in which the module can be accessed from another module. The language used in this example is Verilog-XL from Gateway Design Automation.

party simulators to support the design effort from the system level down to the chip level. If you choose a third-party simulator, be sure to choose one that uses an HDL, which is invaluable in supporting this range of simulation levels.

Behavioral-language models

Most HDLs being developed now are behavioral languages. You can use most behavioral languages to model devices from the transistor level up through the algorithmic level. Although early simulators could use

only transistor-level (or switch-level) device models, most currently available simulators can use a range of models, from the gate level to the algorithmic level. Devices are becoming so complex that even gate-level modeling is becoming impractical, however.

Developing a gate-level model of the 80386 could take a relatively long time—perhaps even a few years. In other words, it can take as long to model a device at the hardware level as it does to design it in the first place. At present, it's common to make behavioral-language models of complex chips at the more abstract bus level.

Some of the larger foundries now show signs of bowing to their customers' demands for third-party-simulator support.

Logic Automation developed such a model for the 80386 (which it offers for \$1850) over several months.

Behavioral-language modeling models a chip by describing, in a behavioral language, how the chip acts ("behaves") in the system. Although it takes about as long to create a behavioral-language model of a simple device—a flip-flop, for example—as it does to construct a Boolean model of the device, you can model complex devices much more rapidly by using behavioral-language modeling rather than hardware-level modeling. Hardware-level modeling describes the specific physical structure of a device. Because a behavioral-language model describes the behavior of a device independently of its physical structure, foundries can make extensive changes in the physical structure—as long as they don't change the device's behavior—without invalidating the simulation results obtained with the behavioral-language model.

Strictly speaking, you can make a behavioral model of a design at any level. Practically speaking, however, you'll probably use a behavioral-language model only when your ASIC's gate count exceeds about 25 gates. The programming overhead associated with behavioral-language modeling (setting up variables, for example) is too great to be worthwhile for less-complex devices.

ASIC simulators that offer behavioral languages let you model devices at any of three levels: the gate, functional, and algorithmic levels. A gate-level model defines a device in terms of its gate interconnections. A functional model defines a device's behavior as a set of Boolean equations. An algorithmic model defines the device's behavior in terms of algorithms by making full use of a behavioral language's constructs and higher-level capabilities. **Fig 1** gives examples of gate-level, functional, and algorithmic models written in an HDL that is also a behavioral language.

Hardware modelers

If your design includes a commercially available component for which no software model exists, you can still use that part in your simulation by plugging a hardware model of the part into a hardware modeler. A hardware modeler is a unit that interfaces with (or is built into) the simulator's workstation. A hardware model is usually a board that contains the commercially available device and any required support circuitry. Companies such as HHB Systems, Ikos, and Mentor offer hardware modelers and hardware models of various parts for use with their simulators. HHB Systems, for example, offers its hardware modeler for \$65,000

and sells hardware models for around \$5400 each.

A big advantage of hardware modeling is that, unlike a software model, a hardware model of a device always performs exactly as the commercially available part does. A disadvantage of the hardware model, however, is that although it always matches the commercially available part, it may not match the device the foundry eventually produces, because of design revisions. Software models can be changed more easily to accommodate any revisions. Further, you can't use a hardware model to run timing simulation, because you can't change the timing parameters of the hardware model.

Consider performing a timing simulation

To draw up a detailed specification for your ASIC, you need to specify timing parameters. It's one thing to write an ASIC specification that baldly states the relationship among the logic levels; it's much more difficult to write a spec that explains the minimum and maximum timing for each signal. These timing extremes are important because they verify that the ASIC will work over the range of timing conditions the manufacturing process allows.

Although min/max timing verification is time consuming because of the number of variables the simulator must consider, consider running a timing simulation anyway: Timing-simulation information is critical because it is information that a breadboard can't give. If your design has more than 5000 gates, your timing simulation will probably run very slowly. To speed the simulation of large designs, consider using a hardware accelerator.

Hardware accelerators are optional units that implement the simulation algorithms in hardware. Mentor's Compute Engine Model M accelerator, for example, lets a workstation perform a logic simulation of a 23,000-gate circuit 24 times faster than it could without the accelerator. The accelerator interfaces with the Apollo Model DN400, -500, -600, and -3000 workstations. Prices for the Compute Engine start at \$59,900.

However, accelerator prices cover a wide range. Zycad's line, for example, starts with the \$38,000 Magnum and ends with the \$2.5 million System Development Engine. Accelerators are also available for smaller budgets. One of the least expensive hardware accelerators is Aida's Persim, which performs 5 million evaluations/sec. The Persim Model 1 can model 64,000 gates; the Model II can model a maximum of 128,000 gates. The prices are \$7500 and \$20,000, respectively.

The reason the prices and simulation times quoted for

'REAL-TIME' SOLUTION TO ASIC VERIFICATION

**Tests Full Speed
At Up to 50 MHz
Across Entire Cycle.**



For the first time, you can test your VLSI prototype design at real world operating speeds. Thoroughly and easily. Across the entire cycle. Without compromise.

Topaz is a totally-integrated ASIC verification system that reduces prototype characterization and fault analysis time, while offering these exclusive advantages:

- **Full Data Formatting to 50 MHz**—for quick measurement of set-up times and propagation delays.
- **256 I/O Channels at Speed, Without Multiplexing**—for maximum performance and flexibility.
- **Programmable Pattern Generation to 50 MHz**—for initiation of loops, branching and data control.

ASIC design requires painstaking accuracy. Verifying that design has been neither fast nor easy. The time available to get today's increasingly-complex ASICs to market continues to contract, and the price of an undetected error can be incredibly costly.

With Topaz, you'll know your design is right, and you'll know it *faster*. CAE-LINK™ software permits easy translation of simulator vectors into ready-to-use test vectors. And, our exclusive Meta-Shmoo™ software allows you to quickly sweep voltages and times *at 500ps increments across an entire cycle*, without programming.

It acquires data with a minimum of effort; and its ability to do graphic error-bit mapping and multi-level triggering gives it unequalled performance in failure analysis.

Topaz is a cost-effective solution to today's high speed ASIC verification needs, and the even higher speeds you'll require tomorrow. Call for complete details or your personal demonstration.

HILEVEL
TECHNOLOGY, INC.

18902 Bardeen, Irvine, CA 92715
Phone: (714) 752-5215

DIAL TOLL FREE 1-800-HILEVEL
(In California 1-800-752-5215)

Circle 112 for Demonstration
Circle 151 for Literature Only

Third-party simulators are portable: You can start with one foundry and later switch to another, as long as your simulator supports both foundries' libraries.

the Persim models seem very low is that these simulators operate differently from the others. The Aida simulators perform levelized-compile-code simulation, which evaluates the output state of all logic gates in a design, in accordance with each change in the input pattern, and ignores timing delays. This type of simulation takes place much more quickly than do simulations that take gate delays into account. By ignoring any gate delays, the simulator can simply evaluate a Boolean equation. After you've performed the logic simulation and caught any obvious logic-design problems, you can then run the design through the timing-analyzer software, which determines the timing associated with all of the circuit's delay paths.

Because the Aida simulator doesn't take the gates' timing characteristics into account, this timing analysis only works for synchronous circuits; the simulator merely flags any asynchronous circuits. This scheme is generally adequate for most designs, however, because most large gate designs are synchronous.

Not all simulator manufacturers are fans of hardware accelerators. Prabhu Goel, president of Gateway Design Automation, claims that as engineering workstations gain more processing power, they'll no longer need separately accelerated simulation algorithms. For now, however, keep in mind that accelerators can commonly execute 500 MIPS, which is still far beyond the capability of a general-purpose workstation at pres-

Manufacturers of ASIC simulators

For more information on digital-ASIC simulation packages, contact the following manufacturers directly or circle the appropriate numbers on the Information Retrieval Service card.

Aida Corp

5155 Old Ironsides Dr
Santa Clara, CA 95054
(408) 748-8571
Circle No 650

Aptos Systems Corp

4113 Scotts Valley Dr
Scotts Valley, CA 95066
(408) 438-2199
Circle No 651

The CAD Group Inc

3911 Portola Dr
Santa Cruz, CA 95062
(408) 475-5800
Circle No 652

Cadnetix Corp

5757 Central Ave
Boulder, CO 80301
(303) 444-8075
Circle No 653

Calma Co

501 Sycamore Dr
Milpitas, CA 95035
(408) 434-4000
Circle No 654

Control Data Corp

8100 34th Ave S
Minneapolis, MN 55440
(612) 853-7460
Circle No 655

Daisy Systems Corp

700 Middlefield Rd
Mountain View, CA 94039
(415) 960-6593
Circle No 656

Data General Corp

6300 S Syracuse Way
Englewood, CO 80111
(303) 694-2900
Circle No 657

Endot Inc

11001 Cedar Ave
Cleveland, OH 44106
(216) 229-8900
Circle No 658

Gateway Design Automation

Box 573
Westford, MA 01886
(617) 692-9400
Circle No 659

GenRad Inc

510 Cottonwood Dr
Milpitas, CA 95035
(408) 946-6960
Circle No 660

HHB Systems

1000 Wyckoff Ave
Mahwah, NJ 07430
(201) 848-8000
Circle No 661

Ikos Systems Inc

145 N Wolfe Rd
Sunnyvale, CA 94086
(408) 245-1900
Circle No 662

Mentor Graphics Corp

8500 SW Creekside Pl
Beaverton, OR 97005
(503) 626-7000
Circle No 663

Personal CAD Systems Inc

1290 Parkmoor Ave
San Jose, CA 95126
(408) 971-1300
Circle No 664

Silicon Design Labs

645 Martinsville Rd
Liberty Corner, NJ 07938
(201) 580-0102
Circle No 665

Silvar-Lisco

1080 Marsh Rd
Menlo Park, CA 94025
(415) 324-0700
Circle No 666

SimuCad

1040 Marsh Rd
Suite 200
Menlo Park, CA 94025
(415) 321-2350
Circle No 667

Simulog Inc

2336H Walsh Ave
Bldg G
Santa Clara, CA 95051
(408) 727-8272
Circle No 668

Spectrum Software

1021 S Wolfe Rd
Sunnyvale, CA 94086
(408) 738-4387
Circle No 669

Teradyne Inc

321 Harrison Ave
Boston, MA 02118
(617) 482-2700
Circle No 670

Valid Logic Systems Inc

2820 Orchard Parkway
San Jose, CA 95134
(408) 945-9400
Circle No 671

Vamp Inc

6753 Selma Ave
Los Angeles, CA 90028
(213) 466-5533
Circle No 672

Viewlogic Systems Inc

275 Boston Post Rd W
Marlborough, MA 07152
(617) 480-0881
Circle No 673

XCAT

2855 Anthony Lane S
Minneapolis, MN 55418
(612) 789-2050
Circle No 674

Zycad Corp

3500 Zycad Dr
St Paul, MN 55109
(612) 631-5555
Circle No 675

ent. It's likely that accelerators will continue to increase in popularity for high-gate-count designs and for accelerating PC-based workstations, while unaided workstations will provide acceptable performance for medium-gate-count designs.

Unlike the manufacturers that offer hardware accelerators, Ikos has taken a different approach. The company designed its simulators to implement all of their simulation algorithms in hardware. The Ikos 1900, for example, is a desktop tower that interfaces to an IBM PC/AT, Apollo DN3000, or Sun 3. The 1900, which starts at \$46,500, simulates designs of as many as 16,000 gates. You can increase that number—to 245,000 gates—by adding as many as fourteen 16,000-gate evaluation boards at \$11,000 each.

EDN

References

1. Wiegand, Jim, "Gate Array Directory," *EDN*, June 25, 1987, pg 134.
2. "1987 Survey of Logic Simulators," *VLSI Systems Design*, February, 1987, pg 71.

Article Interest Quotient (Circle One)
High 470 Medium 471 Low 472

Low Cost EL Lamps. Fast.

Reliable, quality EL lamps. Any size. Any shape. With the fastest turnaround in the industry.

BKL's new soft touch EL lamps are made with KARD-O-LITE™, a revolutionary material that is quickly and easily die-cut to any configuration.

BKL's patented automated manufacturing process produces extremely thin (.012" to .018"), superior quality EL lamps at a drastically reduced cost. Ideal for LCDs, membrane switches, flat panel displays, emergency and safety lighting.

Call Dean Smith at (215) 277-2910.

BKL

Bonar KARD-O-LITE™ Inc.
421 Fehelley Drive, King of Prussia, PA 19406
(215) 277-2910

CIRCLE NO 14

**HOW TO
MAKE
THE
LIGHT
DECISION.**

FREE!!


IDI offers you the largest selection. LED's, Neon Glow Lamps, Relampable and Non-relampable indicator lights. They're all listed in our free catalog. Along with standard variations, money-saving packages, our customizing services and much, much more.

It's the industry's source... make it your source.




Industrial Devices, Inc., Hackensack, NJ 07601
Telephone: (201) 489-8989

It's yours FREE!! For more information,
circle 15 on the reader's card.



INTRODUCING THE IDEAL



A leader's work is never done.

No sooner do we invent the Programmable Gate™ Array and with it a whole new category of logic devices, than we're already outdoing ourselves.

By adding a brand new, more powerful family of Programmable Gate Arrays, the 3000 series.

What's new and different?

They're faster and denser,

with more gates than anybody ever thought a programmable logic device would ever have.

And, are you ready? Cheaper to use than conventional gate arrays.

Which makes them more ideal than ever.

Xilinx Programmable Gate Arrays have densities up to and including 9000 honest gates. How dense can you get? We aim to keep finding out.

THE PROGRAMMABLE GATE ARRAY, IMPROVED.

The 3000 series has a second generation Logic Cell™ Array architecture that turns a 40 MHz system clock rate.

That's enough speed to run with the highest performance microprocessors you can name.

Of course, our patented



Are the zebra's stripes white-on-black or black-on-white? Should you buy the Programmable Gate Array for its cost-effectiveness, short development cycle, off-the-shelf availability, or its 100% testability? Yes to both questions.

LOGIC DEVICE. AGAIN.

architecture is also responsible for gate counts that range from 1200 in the XC 2064 to 9000 in the XC 3090.

Enough density for just about any logic application you can name.

Plus more flexibility in routing and gate utilization than you'll know what to do with.

THE ONLY LOGIC DEVICE YOU MAY EVER NEED.

Like all Xilinx Programmable Gate Arrays, our 3000 series offers the same advantages you've come to know and love:

- Gate array density.
- User-programmability with unlimited reprogrammability.

- No NRE or inventory risk.

- 100% tested parts.
- Low cost gate array type design tools.


- And a development cycle that fits between paychecks.

Our Programmable Gate Arrays also make it simple to choose a logic device.

They simply make every other logic device obsolete.

With their new architecture, you'll have the speed you need, plus the density to get all your logic on one device.

A device with advantages no other technology can match.



Want to see how fast our new 3000 series is? Want to see it again?

Now stop and ask yourself, "Why should I use anything else?"

Good question, isn't it?

THE PRICE IS RIGHT, TOO.

We've told you about our improved speed.

And our increased density.

But we've saved the best news for last.

Using a Xilinx Programmable Gate Array costs less than using a conventional gate array.

So much less it isn't even funny. At least, not to them.

We can prove it, too.

We've prepared a study that lays out the cost comparison data in detail and, needless to say, we'd love to send you a copy. (There's also a nice thick data

book for those of you who are already true believers.)

Just call us toll-free at (800) 255-7778.

In California, (408) 559-7778. Or contact your local Xilinx sales representative or distributor.

The Programmable Gate Array from Xilinx. It's everything you've ever wanted. Again.




The Programmable Gate Array CompanySM

Xilinx, Logic Cell Array, XACT and Programmable Gate are trademarks and The Programmable Gate Array Company is a service mark of Xilinx, Inc.

© 1987 Xilinx, Inc., 2069 Hamilton Ave., San Jose, CA 95125, (408) 559-7778.

CIRCLE NO 81

Easy ASIC



Only from OKI:

- Most **complete** ASIC building blocks.
- Most **versatile** design/package options.
- Most **experienced** ASIC technology.

Nobody but nobody puts ASIC technology together like OKI Semiconductor can.

Ease into ASIC with OKI as your close working partner—and you instantly support your VLSI application with the most comprehensive ASIC capabilities on the world market today. Bar none.

From gate array, standard cell and full custom chips to standard components to integration to advanced board level products, OKI alone puts you on the leading edge of ASIC technology and its complete implementation.

OKI: the totally logical choice.

Opt for OKI ASIC, and you open up your options across the board. Only OKI now offers the system designer the unique security and entry ease that only a proven track record in CMOS ASIC problem-solving can provide. This history of performance built up since 1977 has produced the widest range of solid building blocks yet: advanced ASIC products and packaging including surface-mount, backed up with the most flexible cell libraries, CAD/CAE design tools and development aids.

As your working partner, OKI ASIC expertise is available to you at any stage of the development process. We'll help you define system requirements, determine the most cost-effective product solutions and supply complete design software—accessible at your own workstation or through our regional design centers. And then we take it from there: with high

volume fabrication, assembly and testing completed in one of the world's most highly robotized manufacturing facilities.

Compare Total ASIC Capabilities	OKI ASIC	Source "B"	Source "C"
Gate Arrays to 10K Gates	●	●	
Standard Cells to 30K Gates	●	●	
Full Customs – Lowest Cost	●		
1.5 Micron Cell Library	●	●	●
Macro Cells	●	●	
Bi CMOS	●		
High Density Surface Mount Packages	●		
Board Level Products	●		
Supporting Standard Products	●		
COB Technology (Chip on Board)	●		
CAD/CAE Design Support	●	●	●
Customer-Friendly Design Interface	●	●	●
Regional Design Centers	●	●	●
Robotic Manufacturing	●		

ASIC Solutions from **OKI:**
You can't beat the logic!

Check out OKI ASIC data:

EDN 020488

Please rush complete technical data/specs on OKI capabilities in:

- () Gate Arrays
 () Standard Cells
 () Full Customs
 () Please call: we have immediate requirements:


Name/Title _____

Company _____

Attach coupon to business card or letterhead and return to: ASIC Customer Service, **OKI Semiconductor**, 650 North Mary Avenue, Sunnyvale, CA 94086. Tel: (408) 720-1900.

CIRCLE NO 100






Team Performance

Gould 4070 Digital Oscilloscope
400 MS/s (sampling rate)

Gould K450B Logic Analyzer
80Ch. @ 100 MHz/40Ch @ 200MHz



Start solving your design problems today!

Gould offers two powerful tools to help the digital design engineer track down and eliminate intermittent failures. Used separately or teamed together with sophisticated triggering, they provide the power to resolve design problems.

The K450B Logic Analyzer, with 80 channels at 100MHz or 40 channels at 200MHz, gives you an overview of the whole system so that individual glitches or timing errors can be located.

Using the 4070 Digital Storage Oscilloscope, with 2 or 4 channels at 400 Megasamples per second, you can capture the analog details of the waveform and find noise transients or race conditions which can be the source of the failure.

Put Gould on your design team with our special combination offer on scopes and analyzers. Call **1-800-GOULD-10** or write to Gould Inc., Test & Measurement Group, 19050 Pruneridge Ave., Cupertino, CA 95014.

4070 DSO

2 or 4 channels @ 400MS/s
(400 Megasamples/sec.)

2.5ns resolution on
transient signals

Auto Setup™

Trigger delay by time/events

Built-in 4 color screen plotter

K450B LA

80 channels all @ 100MHz/
40 channels @ 200MHz

5ns glitch capture on
all channels

Auto Setup™

16 levels of Trace Control™

Built-in disk drive




GOULD
Electronics

You shouldn't buy
more board tester
than you need.

we never stop
asking

What if...



Or
less.

Now, you don't have to settle for too little or too much in a board tester. You can get one that's just right for you. From HP.

The HP 3065 family of board testers offers you flexibility. So you can get a system that fits your board mix, process, volume, and budget. Right now. And you can add capability or upgrade at any time to keep pace with your needs.

Our family begins with the HP 3065ST, our standard digital in-circuit tester starting under \$100,000. And goes all the way to the HP 3065AT, one of the most advanced combinational testers on the market. You can combine controllers, test stations, and options for the exact system you need.

And no matter which you choose, you get software and fixture compatibility up and down the line. Networking with CAE/CAD workstations and simulators. Built-in analog functional instruments.

A digital test library for 4,500 devices.

You get something else, too: HP experience in ATE dating back to 1975, with more than 85 service offices and 2,000 in-circuit testers installed worldwide. Plus, product reliability backed by our exclusive 99% Guaranteed Uptime Program.*

It all means better value for you. And, because our board test family offers systems at each level of price/performance, you buy just what you need... no more and no less.


Call HP today for a free videotape!

For a free videotape on the HP board test family, or more information, call 1-800-634-TEST (in Colorado, call collect: 303-669-9325.)



**HEWLETT
PACKARD**

CIRCLE NO 52



*Some restrictions apply.

©1987 Hewlett-Packard Company 0901702

Consider the tradeoffs when evaluating linear-semicustom ICs

System designers face special problems when creating analog circuits for semicustom IC fabrication. Unlike digital circuits, which you can readily subdivide into simple gates, analog circuits are highly irregular, require different design methods, and frequently need nonintegrable external components.

Bruce Moore, Raytheon Semiconductor, and Will Ritmanich, Consultant

The problem of designing analog (linear) circuits suitable for semicustom fabrication is complicated by the nature of the active and passive devices available for IC fabrication. Because the fabrication process imposes constraints, transistors, resistors, and capacitors in IC form display performance characteristics different from those of their discrete counterparts. To help minimize the cycle time, cost, and risk involved in your design effort, it is important to understand these performance characteristics and the design approaches necessary to implement a successful linear-semicustom circuit.

Start with a list

The first step in preparing your design for integration is to rank the circuit's key requirements and features in order of their relative importance. This ranking is essential because the process of creating a

semicustom-linear IC requires compromises involving a number of factors, including the following:

- available power-supply voltages
- desired power consumption
- required circuit speed
- desired accuracy
- operating environment
- I/O considerations
- time-to-market urgency
- volume vs device-cost tradeoffs.

To the extent that it is possible, you should assign objective specifications to each major functional block in your circuit. Successful monolithic designs are easy to manufacture and achieve good yields in volume production. If you impose parameter specifications tighter than those normally obtainable, you will limit production yields and substantially increase device costs. Don't make any specifications tighter than needed, even if you don't think that there's a chance of compromising manufacturability.

In reviewing your circuit for feasibility of integration, you should be aware of four generalized aspects of monolithic-IC circuit designs that distinguish them from discrete or hybrid designs:

1. **Matching.** Semicustom IC designs generally rely on the matching and tracking of component *ratios* rather than on absolute values. If possible, you should avoid circuits that depend on tight-tolerance absolute values, or change the circuits to rely on component matching. If the circuit needs precision components—timing resistors, for example—you'll usually have to leave them off chip.

2. **Component choice.** You can best accomplish semi-

Transistors, resistors, and capacitors in integrated-circuit form do not display characteristics identical to those of their discrete counterparts.

custom designs through proper partitioning, which entails leaving the difficult-to-integrate components outside the package. For instance, you must handle large-value capacitors in this manner because it is difficult and expensive to integrate more than 50 picofarads of capacitance on chip. Power transistors create similar problems; they commonly require special processing to achieve their rated performance, and the large die sizes and high power dissipation of high-current (>200 mA) power transistors usually preclude their use on chip. Medium-power transistors, however, are generally available on chip.

3. I/O limitations. Successful semicustom designs generally minimize the number of bonding-pad (I/O) connections and maximize the interconnection of internal elements. The number of I/O and power-supply connections is a major determinant of an IC's chip size, packaging yields, test costs, and reliability. Try to keep the IC pin count lower than 44 to take advantage of low-cost packaging, though any work to minimize the bonding-pad count will prove rewarding. In particular, for circuits that use many capacitors, you can often reconfigure the circuit to reduce the device pin count while providing performance equal to or better than that of the original design. If your circuit contains both analog and digital elements, you'll sometimes find it cost effective to split the design into two chips. Large semicustom chips using analog elements to provide digital functions are generally more difficult to design, manufacture, and test—and are much more expensive—than purely digital circuits with comparable logic performance.

4. Infinite redesign. Although a discrete design that




Fig 1—The workhorse of the linear bipolar IC, this small-signal npn transistor is similar to the 2N3904 discrete type in construction and basic performance. Its saturation voltage, stray capacitance, and current-handling capability are inferior to those of the discrete device.




Fig 2—Having no practical discrete equivalent, lateral pnp transistors operate laterally in the plane of the die surface. Their gain and frequency characteristics are poor in comparison with those of vertical devices.

is already in production can be modified, tweaks and fixes in an IC are expensive and difficult, and thus you should give some thought to the lifetime of the end product. Consider including options or adjustability features in your design before committing it to production. (For more information on this subject, see **box**, "Achieving first-pass design success.") If there's a great likelihood that your initial design may change before attaining substantial volume, then an array-based approach is probably your best choice. If circuit accuracy or volume requirements are a high priority, you may want to choose a standard-cell design or a full-custom design. An approach that many engineers have adopted is to use arrays for prototyping and low-volume production, and then to phase in full-custom designs later. This approach offers the best of both worlds—low initial design costs, low risk, a reduced time factor, and the provision for producing low-cost devices in large volume when you need them.

Bipolar workhorse is like the 2N3904

Fig 1 shows the structure of a small-signal npn transistor, the workhorse of the linear bipolar IC. Similar to the discrete 2N3904 in construction and basic performance, it has one outstanding difference. In a discrete transistor, ohmic contact is made directly underneath the base-emitter junction to minimize bulk collector resistance and $V_{CE(sat)}$. Because this interconnection technique isn't possible in a junction-isolated IC, manufacturers add a heavily doped, buried layer instead. This buried layer causes higher saturation voltages, a higher collector capacitance (about 3 pF), and a lower current-handling capacity (about 10 mA).

Frequency response of the integrated transistor is very good—the small npn transistors in Raytheon's

A general problem that most system designers face is that they don't have the time to redesign malfunctioning circuits. Because most linear ICs start with a paper design followed by a discrete breadboard, you should avoid the possibility of a redesign by selecting the most suitable technology and methodology early in your design cycle. Reducing the risks by eliminating the unknowns is always a good idea.

Raytheon's RLA series of tile-based, linear macrocell arrays includes a variety of thin-film resistors ranging in value from 1.25 k Ω to 150 k Ω . Further, the configurable, tile-based differential gain blocks have high gain and provide performance approaching that of many off-the-shelf op amps and comparators. In addition, a proprietary 2-layer-metal process allows ease of routing and provides maximum array utilization and low NRE costs. Such features permit the creation of array-based circuits that rival the performance of standard-product ICs.

Fig A—This 1.23V bandgap regulator rivals discrete designs. It has an initial circuit accuracy of $\pm 2\%$, a typical TC of ± 20 ppm/ $^{\circ}\text{C}$, and a load regulation of ± 2 mV at currents to 20 mA.

V_{BE} has a negative temperature coefficient; the R_2 voltage has a positive temperature coefficient, which the voltage across R_1 determines. These voltages sum to produce a nearly zero TC at the V_{BG} terminal. The output, V_{PAT} , is the actual bandgap voltage, which is proportional to the actual temperature. You can scale this output to any convenient value by using a buffer amplifier having suitable gain.

Fig 2 depicts the geometry of the pnp transistors normally encountered in a monolithic IC. These transis-

High-value capacitors and precision resistors are difficult and costly to fabricate; they're often best left off the chip.

tors, for which no practical discrete equivalent exists, operate laterally in the plane of the die surface. Their construction results in a base-emitter area that is much smaller than that of an npn device having an equal emitter size. Because of their method of operation, as well as processing limitations, lateral pnp transistors exhibit a falloff in beta at collector currents below 100 μ A. The frequency response also suffers; the typical f_T is about 4 MHz unless exotic processing is used. By employing dielectric isolation and a special complementary-bipolar process, manufacturers can create vertical pnp devices with greatly improved performance, but production costs and manufacturing complexity escalate rapidly. Conventional lateral pnp transistors find use as current sources, level shifters, and input stages.

MOS pros and cons

Manufacturers of linear ICs have used bipolar technology for a much longer time than they've used CMOS. However, many of today's applications employ CMOS to great advantage. The use of CMOS is especially valid for designs that must implement a sampled-data system. CMOS is very useful when a high degree of interconnection exists between analog and digital func-




Fig 3—This layout of a typical n-channel, silicon-gate MOS transistor shows the coding for the mask layers and the scale in microns.




Fig 4—This characteristic of an NMOS transistor plots conduction from the linear region to the switched region as a function of V_{GS} .

tions, such as in data-acquisition systems. Whereas linear bipolar devices are best suited for use in a current-steering mode, CMOS circuits work best in switching-type applications. This mode (always-on) eliminates the problems that storage-time delays create when the devices switch.

MOS devices, which use voltage rather than current to control their conduction characteristics, have both advantages and disadvantages. Their advantages include low input currents, high input impedance, and excellent logic compatibility. Their disadvantages involve higher noise, poorer matching (caused by processing and environmental variables), and a lower effective transconductance than that of bipolar devices of the same die size.

Fig 3 shows the layout of a typical n-channel MOS device. As the gate-to-source voltage (V_{GS}) varies (Fig 4), the lateral conduction through the channel varies from the linear region to the switched region. This action illustrates a principal challenge in linear MOS designs—that of keeping the device properly biased. Unlike the base input of a bipolar transistor, the isolated gate of an MOS transistor exhibits a high input impedance and only a small diode-leakage current. This characteristic allows MOS devices to have low leakage currents at low temperatures and to function well as analog switches.

As current sources, MOS devices provide high output impedance; as switches, they allow bidirectional current flow and exhibit much lower impedance than that of bipolar devices. Voltage-noise performance is worse than that of bipolar devices, however, because running higher current through the MOSFET doesn't lower the noise nearly as much as in a bipolar transistor. Because

TABLE 1—BIPOLAR/CMOS PERFORMANCE COMPARISON

PARAMETER	JUNCTION-ISOLATED BIPOLAR		SILICON-GATE CMOS	
	NPN	LATERAL PNP	N-CHANNEL MOSFET	P-CHANNEL MOSFET
GAIN	VERY GOOD	GOOD	GOOD	FAIR
MATCHING	VERY GOOD	GOOD	POOR	FAIR
INPUT IMPEDANCE	LOW	LOW	HIGH	HIGH
OUTPUT IMPEDANCE	MODERATE	MODERATE	MODERATE	MODERATE
SPEED	VERY HIGH	LOW	HIGH	MODERATE
NOISE	VERY LOW	LOW	HIGH	HIGH
RADIATION RESISTANCE	GOOD	FAIR	POOR	FAIR
CONTROL ELEMENT	CURRENT	CURRENT	VOLTAGE	VOLTAGE
CONDUCTION PATH	VERTICAL	SURFACE	SURFACE	SOURCE

the current flow is lateral, rather than vertical, the transconductance of an n-channel MOSFET is less than $\frac{1}{10}$ that of an npn bipolar transistor of the same size. As a result, achieving high-gain-bandwidth op amps is much more difficult with MOS than it is with bipolar devices.

P-channel MOSFETs are similar to n-channel devices in operation and construction, but have reversed polarities. Because they conduct by the movement of holes rather than electrons, p-channel devices operate at much lower speeds than n-channel types. However, PMOS devices are more stable than their NMOS counterparts; designers often use them as input stages for op amps and comparators. For both n- and p-channel devices, manufacturers can control the linear characteristics, such as power and speed, by scaling the width-to-length (W/L) ratio of the channel geometries. Logic transistors have a short channel of about 3 μm . Transistors suitable for use as linear elements generally have device channel lengths greater than 10 μm .

A common practice among manufacturers of CMOS ICs is to use ion implantation to selectively control the devices' operating characteristics. Because radiation affects the threshold voltage of MOSFETs, the devices are often not as well suited for aerospace applications as are bipolar devices. Also, operating at low (3V) supply voltages is generally more difficult with MOS devices than it is with bipolar types.

Table 1 shows a performance comparison between bipolar and CMOS circuits for a number of important parameters, and **Table 2** provides a comparison between bipolar and CMOS circuits in various applications.

Manufacturers of ICs create resistors in several

ways. The most common approach is via diffusion or pinch diffusion of reverse-biased active devices. Ion implantation is another method that both bipolar and MOS technologies employ, and some fabrication processes also use sputtered, thin-film resistors.

Several factors determine the characteristics of an IC resistor. Of major importance is the sheet resistivity of the material used to create the resistor—a high value is generally desirable. Sheet resistivity determines the die area required for a given resistor value and tolerance, and the die area determines the cost of the resistor. Another factor to consider is the material from which the resistor is made. A drawback to using silicon for resistors is the nonlinearity of their resistance-vs-voltage characteristic.

The junction isolation separating the resistor from its surrounding material introduces stray capacitance that varies with the applied voltage. Further, a reverse-

TABLE 2—BIPOLAR/CMOS COMPARISON

APPLICATION	BIPOLAR	CMOS
OP AMP	VERY GOOD	FAIR
ANALOG SWITCH	POOR	VERY GOOD
COMPARATOR	VERY GOOD	FAIR
D/A CONVERTER	FAIR	FAIR
REFERENCE	VERY GOOD	POOR
REGULATOR	VERY GOOD	POOR
ACTIVE FILTER	GOOD	VERY GOOD
LOGIC COMPATIBILITY	FAIR	VERY GOOD
<3V OPERATION	VERY GOOD	POOR
RADIATION RESISTANCE	GOOD	POOR

The workhorses of a linear bipolar IC are the small-signal npn and the medium-power npn—roughly equivalent to the discrete 2N3904 and 2N2222.

biased diode associated with each resistor exhibits increased leakage-current flow when subjected to radiation. This radiation susceptibility is a possible contributor to major circuit errors.

It is a simple matter to create resistors from either MOS or bipolar active devices. As an example, Fig 5 shows a diffused base resistor formed by the transistor's base-diffusion step. Because of the difficulty in controlling the depth and density of the impurity concentration, the resistance value can vary as much as $\pm 30\%$. The low sheet resistivity, along with a distributed capacitance that is directly proportional to the resistor's value, as well as the need to reverse-bias the parasitic diode, limits the usefulness of this type of resistor.

The temperature coefficient of a base resistor's value varies nonlinearly from -600 ppm/ $^{\circ}\text{C}$ at -55°C to 1200 ppm/ $^{\circ}\text{C}$ at 125°C . Moreover, the difference in potential between the epi (epitaxial) island and the resistor terminals modulates the value of the base resistor. Although they're the most commonly used resistors in bipolar technology, base resistors require a highly experienced linear-IC designer and skillful layout techniques to avoid serious accuracy problems. An optimal base-resistor layout isn't possible in configurable linear-semicustom arrays.




Fig 5—Because of the difficulty in controlling the depth and density of the impurity concentration, the resistance value of this diffused base resistor will vary as much as $\pm 30\%$.

Fig 6 shows a base pinch resistor. An extra diffusion (the n+, which ordinarily forms the transistor's emitter) pinches the resistor channel, increasing the effective sheet resistance, but worsening all other characteristics. One disadvantage of the pinch resistor is that its value is directly related to the beta of the npn transistor. Another is that the fabrication process creates a parasitic zener diode that limits the maximum permissible voltage across the resistor.

An epi resistor offers a high sheet resistivity, but otherwise it has poor electrical characteristics. A pinched version (Fig 7) of the epi resistor has an even




Fig 6—In this equivalent circuit (a) and cross-section (b) of a base pinch resistor, an extra n+ diffusion pinches the resistor channel, increasing the effective sheet resistance, but worsening all other characteristics.




Fig 7—An epi resistor (in this case a pinched version) is formed by an epitaxial layer and offers high sheet resistivity but poor electrical characteristics.

**INTEL'S FIRST CMOS
16-BIT DATA CONTROLLER
AVAILABLE THROUGH 58 LOCATIONS**

Intel makes faster designs and consolidation in a cinch with a new standard of performance in microprocessors: The 80C186 data controller.

The most highly-integrated, highest-performance 16-bit microprocessor they created, with a CPU running at 12.5 MHz, optimized for data-intensive applications such as printers, ISDN and LAN. The 80C186, fabricated in CHMOS, is compatible with Intel's industry-standard NMOS 80186. But it provides 1.5 times the throughput. So now you can choose higher clock speeds with one-chip power consumption.

The best part is Intel's condensed a lot of functions onto this one chip — 15 to 20 of the most common microcontroller components, including two DMA channels, four operational modes and a DRAM control unit.

And if you think the 80C186 is fast, you see how quickly Hamilton/Avnet responds to your order, with immediate or next-day delivery.

To order Intel's new high-performance 80C186 data controller, call your local Hamilton/Avnet representative. To find the location nearest you, call toll free: 1-800-442-6458 (1-800-387-6879 in Canada; 1-800-387-6849 in Ontario and Quebec).

See how simple innovation can be.

INTEL from HAMILTON/AVNET



The Highest Integrated 16-Bit Controller is now

The FASTEST

**FREE INTEL 80C186
SAMPLER DISK FROM
HAMILTON/AVNET**

See for yourself how easily you can speed-up your designs with a 80C186 sampler disk from Intel.

It's free, and all you have to do is fill out the coupon below and send it to your #1 source for Intel components, Hamilton/Avnet.

Yes, I would like a complimentary 80C186 floppy disk sent to me today.

NAME

TITLE

COMPANY

ADDRESS

CITY

STATE ZIP

PHONE

MSTOP

APPLICATION

Mail to:

M. Burnett
Advertising Department
Hamilton/Avnet
10950 Washington Blvd.
Culver City, CA 90230

Hamilton Avnet
ELECTRONICS  AN AVNET COMPANY



CMOS circuits are best suited to switching applications, or to designs having a high degree of interconnection between analog and digital functions.

TABLE 3—IC RESISTOR-TYPE COMPARISON

RESISTOR TYPE	SHEET ρ (Ω/\square)	ABSOLUTE TOLERANCE (%)	MATCHING TOLERANCE (%)	TEMPERATURE COEFFICIENT (ppm/ $^{\circ}$ C)	VOLTAGE COEFFICIENT	RADIATION RESISTANCE
BASE DIFFUSION	100 TO 200	± 20	± 2 (10 μ m WIDE) ± 0.2 (50 μ m WIDE)	-600 TO +1200	LOW	POOR
BASE PINCH	2k TO 10k	± 50	± 10	+2500	VERY HIGH	POOR
EPITAXIAL	2k TO 5k	± 30	± 5	+3000	HIGH	POOR
EPITAXIAL PINCH	4k TO 10k	± 50	± 7	+3000	VERY HIGH	POOR
ION IMPLANTED	100 TO 1000	± 20	± 2 (10 μ m WIDE)	+1000	MODERATE	MODERATE
THIN FILM	2k TO 5k	± 10	± 1	± 100	NIL	VERY GOOD

higher sheet resistivity and even poorer electrical characteristics. Fabricators can also create well-type resistors from MOS devices; these resistors offer similarly poor performance.

In CMOS circuits, manufacturers often form resistors by performing ion implantation of polysilicon material. Having oxide isolation, these resistors will tolerate voltages beyond the value of the supplies. Unfortunately, besides harboring a parasitic capacitance, they exhibit a low sheet resistivity (from 100 Ω /square to a maximum of 1000 Ω /square) that limits their usefulness in many applications, especially those requiring moderate resistor values. Processing tolerances in the polysilicon deposition, photolithography, and implant dosages limit the absolute tolerances of ion-implanted resistors to about $\pm 20\%$.

Your best choice for precision designs is thin-film resistors. Their performance is equal to or better than that of most discrete equivalents, and is much better than that of the silicon resistors previously described. Thin-film resistors have no junction capacitance, are almost perfectly linear, and can tolerate voltages well beyond those of the power supplies. This voltage tolerance is often a major consideration in analog systems, many of which require an overvoltage capability. If you use junction-isolated resistors, the ac performance of the final circuit will often differ from that of the breadboard. Thin-film resistors, however, don't degrade the ac performance relative to that of the breadboard. **Table 3** summarizes the performance available for the various resistor types.

Capacitors are difficult

Because the dielectrics used in the manufacture of an IC are very inefficient (compared with those found in discrete devices), the fabrication of high-value capacitors in an IC is very difficult. Nitride capacitors (such as

those provided in the RLA arrays, as well as in some other manufacturers' ICs) provide higher capacitance and better reliability than do the thin-oxide capacitors that most manufacturers use. However, if your design calls for capacitor values greater than 50 pF, or requires absolute tolerances tighter than $\pm 10\%$, then your best policy is to keep these capacitors off chip.

Some applications are naturally amenable to the use of on-chip capacitors. For example, active filters operating at frequencies to 50 kHz often lend themselves to the use of switched-capacitor techniques, which you can readily implement in CMOS. In these filters, capacitor values need not be large and the capacitors are easy to integrate. In another example, CMOS sample/hold circuits often include the (small) hold capacitor on chip.

EDN

Authors' biographies

Bruce Moore is a linear applications engineer at Raytheon (Mountain View, CA), where he is presently involved in ASIC design. Bruce has an EET degree from Heald Engineering College and holds two patents. His hobbies include motorcycle road racing, skiing, and chess.

Will Ritmanich is an IC-design consultant living in Detroit, MI. His previous employment includes Precision Monolithics and Analog Devices. Will has a BSEE from San Jose State and has applied for two patents. His spare-time activities include camping and skiing.

Article Interest Quotient (Circle One)
High 497 Medium 498 Low 499

**NOW!
DIGITAL
STORAGE
ANSWERS
STARTING AT
\$2995.**



The new 60 MHz Tek 2221 (above) offers such features as CRT readout and measurement cursors for just \$3995.

Now you have three low-cost choices in Tek digital storage oscilloscopes. All featuring powerful 20 MS/s digitizing along with familiar, full-bandwidth analog operation. It's the best of both worlds in one easy-to-use, portable package.

Discover the potential!

With digital storage you can freeze waveforms. Capture events invisible to non-storage scopes. Find signals buried in noise. And build a library of reference waveforms.

CRT readout and cursors distinguish the new 2221. For even higher performance, there's the 100 MHz, dual time base 2230 with optional battery-backed

Features	2230	NEW! 2221	2220
Analog/Digital Storage BW	100 MHz	60 MHz	60 MHz
Maximum Sampling Speed	20 MS/s	20 MS/s	20 MS/s
Record Length	4K/1K (selectable)	4K	4K
Peak Detect	100 ns	100 ns	100 ns
Save Reference Memory	One, 4K Three, 1K	One, 4K	One, 4K
Vertical Resolution	8 bits 10 bits (AVG mode) 12 bits (AVG mode over the bus)	8 bits 10 bits (AVG mode)	8 bits
CRT Readout/Cursors	Yes	Yes	No
GPIB/RS-232-C Options	Yes (\$750)	Yes (\$500)	Yes (\$500)
Battery-Backed Memory (save 26 waveform sets)	Yes (inc with GPIB/RS-232-C)	No	No
Warranty	3 year on labor and parts, including the CRT		
Price	\$4995	\$3995	\$2995

Prices subject to change without notice.

memory for saving up to 26 waveform sets. And if it's economy you want, choose the 60 MHz 2220 with many of the same features at an even lower cost.


With each scope you can automate measurements with interface options. And output direct to a printer or plotter. Tek software is available for systems.

**Call Tek direct:
1-800-426-2200**

for free video brochure for orders/assistance.



Tektronix®
COMMITTED TO EXCELLENCE



*Digital and analog functions
in standard packages*



*Similar functions in a standard cell
available for packaging*

We've mixed analog with digital to help you make it small in ASIC.

NATIONAL INTRODUCES OP AMP, COMPARATOR, ANALOG SWITCH, AND BAND GAP REFERENCE CELLS DESIGNED TO CUT YOUR ANALOG REAL ESTATE DOWN TO SIZE

Now you can bring the finest in analog performance right into the heart of your digital cell-based design.

Because now, the people who wrote the book on linear offer you industry-standard functions in analog cells.

With all the quality and reliability you've come to expect from National. Plus all the design and high-yield manufacturing expertise it takes to ensure you get the cells you need when you need them.

EIGHT CELLS YOU CAN BUILD ON

Our cell library now includes three general-purpose op amp cells, based on our popular LM324, with gain bandwidths ranging from .75 MHz to 3 MHz.

We've also developed the A021 and A022 Comparators, which feature two different input common mode ranges. Both cells are similar in performance to our industry-standard LM339.

Our A241 Analog Switch is designed to handle signal voltages equal to, or less than, VDD while exhibiting a lower on-resistance than

NATIONAL'S CELL LIBRARY INCLUDES:

Op Amps

- Wide input common mode (0.3V to VDD - 1.5V)
- Up to 3 MHz gain bandwidth product

Analog Comparators

- High input common mode range (1.5V to VDD - 0.5V)
- Low input common mode range (0.3V to VDD - 1.5V)
- Less than 70nS response time

Voltage Reference

- 2.5V Band Gap Reference
- Tempco under 100 ppm/°C

Analog Switch

- Analog signal range 0V to VDD
- Low on-resistance 100 ohms

All are available in military, commercial, and industrial temperature ranges and in a variety of high-density surface-mount packages.

most switches in our AH50XX, LM, or LF families.

As you'd expect, we've also added a 2.5V Voltage Reference, plus resistors. And all our analog cells operate at the standard 5V.

PROVEN CELLS YOU CAN WORK WITH

We're already working with digital ASIC designers who need basic analog functions without making basic analog trade-offs in size, weight and performance.

One major automotive subsystem manufacturer, for example, is currently testing our op amp and comparator cells in a revolutionary anti-skid braking system under severe environmental conditions.

Wherever there's a need for mixed digital and analog solutions that improve efficiency and reliability by eliminating bulky, power-hungry multi-chip configurations, there's a need for analog cells from National.

FUTURE CELLS YOU CAN COUNT ON

All our analog cells are fabricated in our proprietary M²CMOS process. Which guarantees you three important competitive advantages: outstanding low-power performance, noncopyable functional implementation, *and* a steady stream of other proven National analog products into our cell library.

The result? Your decision to go with National's analog solutions will continue to pay off long after the decision is made.

CELL EXPERTS YOU CAN TALK TO

We can show you how a little analog functionality can make a big difference in your digital ASIC design. For details, call our Applications Hotline at (408) 721-6247, or write:

National Semiconductor
ASIC Solutions
M/S 23-200
P.O. Box 58090
Santa Clara, CA 95052-8090



**National
Semiconductor**

High-resolution conversion



in the blink of an eye.

Get video speed, low power consumption, high resolution and superior price/performance with our new CMOS data converters.



We've expanded our line to include more CMOS flash ADC's, a charge balancing ADC, an SPI ADC and a DAC. All featuring single 5V supply operation.

We also offer a new high-speed op amp especially well-suited to driving ADC's or video cables.

4, 6 and 8-bit CMOS flash ADC's.

Choose from 4, 6 and 8-bit ADC's. All operate at video speeds, with clocking speed and input bandwidth specified at 5V. What makes these flash ADC's special is silicon-on-sapphire construction, resulting in low cost, high speed, very low input capacitance, low power consumption and inherent latch-up resistance.

10-bit CMOS charge balancing ADC.

This 10-bit successive approximation ADC captures fast moving signals, providing excellent resolution.

It features a built-in fast track and hold, with conversion rates of 150 KHz and an input bandwidth of 1.5 MHz. Even at the maximum rate, power consumption is less than 20 mW.

10-bit CMOS serial ADC.

The CDP68HC68A2 is selectable for either 8- or 10-bit resolution and has an 8-channel multiplexer allowing up to 8 channels of inputs. The device can be used directly with our CDP68HC05C4, C8 or D2 microprocessors or other similar SPI (Serial Peripheral Interface) buses.

8-bit CMOS R-2R video-speed DAC's.

These CMOS/SOS digital-to-analog converters operate

from a single 5V supply at video speeds and can produce "rail-to-rail" output swings. Typical update rate is 50 MHz. Settling is fast (20 ns typical) to 1/2 LSB. "Glitch" energy is minimized by segmenting and bar graph decoding of upper 3 bits.

High-speed op amp.

Specially designed for use with data converters, the CA3450 op amp has excellent speed and transmission line driving capabilities.

For 10-bit accuracy, it settles to within 1/2 LSB in 40 ns with a 2V input signal. And it can drive up to four 50 ohm transmission lines.

ADC's	Res. Bits	Conv. Rate Hz	Power Diss. (mW)	Pkg. Leads	1K Price
CA3304E	4	20M	30	16	2.95
CA3304AE	4	25M	35	16	4.50
CA3306CE	6	10M	65	18	5.50
CA3306E/3306AE	6	15M	70	18	6.25/11.25
CA3318E/3318CE	8	15M	150	24	38.50/24.00
CA3310E/3310AE	10	150K	15	24	6.00/8.00
CDP68HC68A2E	10	10K	15	16	3.75
DAC's					
CA3338E/3338AE	8	50M	100	16	6.00/8.40
OP AMP	UGBW Hz	Slew Rate (X10)	I _{out} MA	Pkg Leads	1K Price
CA3450E	200M	300V/μSec	±75	16	2.70

Data in a flash.

For data sheets of these new products, call toll-free 800-443-7364, extension 19. Or contact your local GE Solid State sales office or distributor.

In Europe, call: Brussels, (2) 246-21-11; Paris, (1) 39-46-57-99; London, 0276-685911; Milano, (2) 82-291; Munich, (89) 63813-0.



GE Solid State

GE/RCA/Intersil Semiconductors


These three leading brands are now one leading-edge company. Together, we have the resources—and the commitment—to help you conquer new worlds.

WREN FIVE

**THE BEST 5¼ INCH DISK DRIVE AVAILABLE
UNTIL WE BUILD WREN VI.**

INTRODUCING WREN V

The fastest, most reliable 5¼" disk drives are now better than ever. The new Wren V with bigger capacity has up to 574 Mbytes formatted with the SCSI interface, or 442 Mbytes of unformatted capacity using the ESDI.



PERFORMANCE SECOND TO NONE

Wren V is high performance. Average seek is a blistering 14.5 ms. A patented, balanced straight-arm actuator, employing less mass than other designs, results in precision positioning and faster seek times.

DESIGNED-IN RELIABILITY

New Wren disk drives are better than ever thanks in part to lower power consumption, special shock mounts, advanced electronics packaging, and synchronized spindle capability for high performance subsystem applications. You can count on years of trouble-free use.

A COMMITMENT TO QUALITY

Manufacturing quality products and backing them with top-notch service and customer support is our commitment to

you. We're with you every step of the way; from system's design to post-sales service in a true customer manufacturer partnership.

Get the high performance edge—Wren disk drives from Control Data. For more information, call 1-800-828-8001, ext. 82.


Model	Capacity (Mbytes)	Avg. Seek (ms)	Interface	Transfer Rate (MHz)
Wren V	574	16	SCSI	10-15
Wren V	442	16	ESDI	10
Wren V	383	14.5	ESDI	10
Wren V	344	16.5	SCSI	10-15
Wren V H.H.	190	18	SCSI	10-15
Wren IV	307	16.5	SCSI	10-15
Wren III	182	16.5	ESDI	10
Wren III	160	16.5	SCSI	10
Wren III H.H.	106	18	ESDI	10
Wren III H.H.	91	18	SCSI	10
Wren II	96	28	ST506, ESDI	5
Wren II H.H.	51	28	ST506	5

H.H. = Half High Models

SCSI models list usable capacity formatted in 1024 Byte sectors. Wren III, IV, V-344 Mb SCSI models have 40,000 Hr. MTBF (others: 30,000 Hr. MTBF).

GD CONTROL DATA





Now, high performance vacuum/pressure blowers that operate from 120 VAC

Compact units feature brushless dc motors with integral controller and variable speed capability

These new Windjammer® blowers combine electronics, motor, and fan system in a compact, cost-effective package that operates from a standard 120 VAC input. An exclusive Lamb Electric design, they were developed for demanding, limited space applications such as business machines, medical equipment and



materials handling applications.

Just 5.7" in diameter, the blowers have 1-, 2-, or 3-stage fans for performance from 50" H₂O vacuum at 0 CFM to 110 CFM at 0" H₂O. With one version, a 0 to

10 VDC signal from a sensor or other device will control motor speed and adjust air performance from 0 to 100%. Or, a second model provides manual speed control by means of a potentiometer located in the blower housing.

These blowers also feature low noise performance and are UL/CSA component recognized. Get complete details by contacting AMETEK, Lamb Electric Division, 627 Lake Street, Kent, OH 44240. (216) 673-3451. Telex: 433-2140. Cable: LAMETEK.

AMETEK
LAMB ELECTRIC DIVISION

S/H amp-ADC matrimony provides accurate sampling

When using an A/D converter to capture samples of moving signals, you usually need a sample-and-hold amplifier to hold the voltage steady at the converter's input. If you don't choose the right S/H amplifier for the application, signal degradation in the form of distortion and reduced dynamic range invariably results.

Al Little and Bob Burnett, *Harris Corp*

Choosing the optimum sample-and-hold amplifier for a particular A/D converter in a given application is often not an easy matter. The choice depends on the speed and resolution of the converter, the system's sampling rate, and several other variables. A less-than-ideal S/H amplifier-ADC match can result in reduced system efficiency or in degradation of the sampled signals. The discussion that follows uses three available monolithic S/H amplifiers and several industry-standard A/D converters as examples of how to arrange a harmonious S/H amplifier-ADC marriage for your application. The principles detailed here are universal; thus, they're equally applicable to other available S/H amplifiers and A/D converters.

The principal parameters of an S/H amplifier that come to bear on the accuracy you can obtain in a given A/D-conversion application are acquisition time, hold-mode settling time, aperture time, aperture jitter,

pedestal, hold-mode feedthrough, and droop rate. The first four of these parameters set an upper limit on the allowable input frequency and the achievable sampling rate. The input-voltage-dependent pedestal can introduce nonlinearities into an S/H amplifier's transfer function. Finally, feedthrough introduces accuracy errors, and droop imposes a limit on the length of the A/D-conversion period. Before studying the effect of these parameters on A/D conversions, it's useful to review the parameters in some detail.

S/H terms are esoteric

Data sheets for S/H amplifiers use many terms that are peculiar to these devices. Sometimes they use several different terms for the same spec. The waveforms in **Fig 1** illustrate the parameters that are of principal interest in arranging a good match between an S/H amplifier and an A/D converter. First, consider the acquisition time. This quantity is the time the S/H amplifier requires to sample (more accurately, to track) the input signal to within a given error band after it receives a Sample command.

S/H-amplifier manufacturers usually specify the slew rate for the hold-to-sample transition. Note, however, that the acquisition-time spec takes into account both slew rate and settling from any overshoot and ringing. (If you want to calculate the specific effects of input slew rate on the S/H amplifier's overall performance, see **box**, "Take finite S/H-switch time into account.") Many data sheets specify acquisition time for two error bands: $\pm 0.1\%$ and $\pm 0.01\%$. The $\pm 0.01\%$ figure equates roughly to $\pm \frac{1}{2}$ LSB for a 12-bit conversion.

After acquiring the input signal, the S/H amplifier

An inappropriate match between an S/H amplifier and an A/D converter can result in degradation of the sampled signal.

tracks the signal until it receives a Hold command. Their internal connections commit many S/H amplifiers to unity-gain operation; the HA-2420, -5320, and -5330 families, however, contain uncommitted input amplifiers that allow feedback-determined gain in inverting or noninverting configurations. The two intervals immediately following the Hold command are aperture time and hold-mode settling time.

Aperture time is the interval required before the S/H switch can open; hold-mode settling time is the interval, after the receipt of a Hold command, in which the output settles within a given error band about its final settled value. The hold-mode settling time, which includes the aperture time, is the parameter of interest here, because the settled, held voltage is presented to the S/H amplifier's mating A/D converter during the conversion cycle. Aperture jitter (or uncertainty) is also of particular interest; it imposes a limit on the allowable input frequency.

When the S/H amplifier's output settles after the reception of a Hold command, it doesn't exactly settle to the value of the previously tracked input voltage imposed on the hold capacitor. Because of unavoidable

stray capacitance between the S/H-command input and the hold capacitor, the sample-to-hold transition causes charge to transfer to the hold capacitor. According to $V=Q/C$, this charge produces a voltage step in the capacitor. This step is variously called pedestal (as in Fig 1), charge injection, offset step, hold step, or sample-to-hold offset.

To complicate matters, the pedestal is not always a constant quantity. It can be a function of the amplitude and the transition time of the S/H command, for example, and sometimes it can vary as a function of the analog input voltage. This latter dependency is itself a function of the S/H amplifier's architecture. Fig 2 shows how a device's architecture can have a bearing on the relationship between pedestal and input voltage.

Two basic S/H-amplifier architectures are evident in Fig 2. In Fig 2a, the input amplifier, upon closure of the Sample/Hold switch, charges the hold capacitor to the voltage level to be held. After the switch opens, the hold capacitor has no discharge mechanism except the input-bias current of the output amplifier and the leakage resistance of the open switch, so it holds the sampled voltage. In Fig 2b, the input transconductance




Fig 1—S/H amplifiers need their own dictionary, as witness the esoteric terms in this timing waveform. What's more, many of the parameters can have several alternate names. For example, aperture time is sometimes called aperture delay, aperture jitter is also called aperture uncertainty, and pedestal is also referred to as charge injection, hold step, offset step, and sample-to-hold offset. The important parameters for timing considerations are acquisition time, hold-mode settling time, and aperture jitter.

amplifier, upon closure of the switch, charges a hold capacitor connected in the feedback loop of the output amplifier. The amplifier provides a charging current proportional to the differential input voltage.

In **Fig 2a**, the voltage at the junction of the hold capacitor and the input of the output amplifier varies

directly as a function of the input voltage. On the other hand, in the integrating configuration of **Fig 2b**, this junction is a virtual ground, held at 0V by negative feedback. The problem is that the amount of charge transferred to the hold capacitor in **Fig 2a**'s circuit is a function of the voltage on the hold capacitor. This

Take finite S/H-switch time into account

Some of the specifications commonly given in S/H-amplifier data sheets can be misleading or confusing. For example, a data sheet might specify acquisition time for a 10V static signal, but not for a rapidly moving input signal.

Similarly, aperture time indicates the time it takes for the Sample/Hold switch to open from 10 to 90%. It's useful to study the effects this finite switch-opening time has on overall performance. In analyzing the effects, it's convenient to think in terms of a simplified equivalent circuit for an S/H de-

vice such as the one in **Fig Aa**. **Fig Ab** shows such a simplified circuit for the very fast, transconductance-input types of S/H amplifiers, such as the HA-5320 and -5330.

In this simplified form, the circuit is easily recognizable as a simple lowpass configuration. The characteristics of the low-pass circuit lead directly to the analysis of the S/H circuit. For example, high-frequency signal components will suffer from phase lag through the RC circuit. This simple circuit makes it possible to estimate the quantitative capacitor error voltage

during the acquisition phase for any given signal.

Similarly, it's also possible to estimate sampling errors arising from aperture time. For example, suppose you're digitizing a 2V p-p, 20-kHz signal. The maximum rate of change, occurring at the signal's zero-crossing point, is given by

$$\frac{dV}{dt}(\text{MAX}) = \frac{d}{dt} [\sin 2\pi (20 \text{ kHz})t]_{t=0} \\ = 1.257 \times 10^6 \text{ V/SEC.}$$

As the switch opens (**Fig Ac**), the resistance increases exponentially. To make a worst-case estimate, you can assume that for, say, a 10-nsec aperture time, the switch remains closed for an additional 5 nsec. What error voltage results from this prolonged closure? The capacitor continues to be charged at the rate of 125,700V/sec. For 5 nsec, the error is 628 μV , which is approximately a 1/4-LSB error for a 12-bit, 10V FSR A/D conversion.

Modeling the S/H amplifier in this way gives you some insight into how the different S/H-amplifier specifications figure into the overall accuracy of the device for any particular application.




Fig A—Modeling a sample-and-hold amplifier such as the HA-5320 or HA-5330 (a) with a simplified equivalent circuit (b) enables you to understand the effects of finite aperture time. In the sample mode (switch closed) the R and C components introduce increasing error because of phase lag vs frequency. Then, following the switch-open command, the switch causes additional error by allowing the capacitor to continue charging for several nanoseconds (c).

To avoid harmonic surprises in sampled signals, be aware of how an S/H amplifier's pedestal varies as a function of the amplitude of the voltage to be sampled.

problem is compounded by the fact that the Sample/Hold switch often displays nonideal characteristics. For example, if the switch is a MOSFET, the gate-to-source (that is, S/H-logic-to-hold-capacitor) capacitance can vary as a function of the gate-to-source voltage, and hence as a function of the input voltage.

The scope photos in Fig 3 illustrate the dependence (or independence) of the pedestal on input voltage. For all three photos, traces A, B, and C show the pedestals that occur for input voltages of +10V, 0, and -10V, respectively. For Fig 3a, the S/H amplifier is an HA-2420 using a 1-nF hold capacitor. This IC is a nonintegrating device that uses the architecture shown in Fig 2a. The S/H units for Figs 3b and 3c, the HA-5320 and -5330 (respectively), use the integrating structure shown in Fig 2b. You can see that both the pedestal and its variation are much smaller—in fact, negligible—for the integrating types.

Fig 4 shows the typical dependence of the pedestal on the input voltage for the HA-2420. The coordinates for the 1-nF curve come from the scope photo in Fig 3a; those for the 100-pF curve are from typical curves in the data sheet. As you can see, the pedestal with the 1-nF hold capacitor varies linearly with the input voltage. It's a simple matter to derive the equation for pedestal vs input, then to prove that this linearly






Fig 2—The architecture of an S/H amplifier has a profound influence on the device's pedestal. In circuit configuration a, the voltage at the output amplifier's input terminal varies with the input voltage. This variation causes changes in the value of the stray capacitance C_S , and thus causes variations in the pedestal as a function of the input level. In b's circuit, the voltage at the summing junction is invariant with input voltage; therefore, the value of C_S remains constant. The result is a constant pedestal voltage, which only adds a fixed offset to the S/H amplifier's output.



TRACE	INPUT	VERTICAL	HORIZONTAL
A	+10V	10 mV/DIV	50 μSEC/DIV
B	0V	10 mV/DIV	50 μSEC/DIV
C	-10V	10 mV/DIV	50 μSEC/DIV

(a)



TRACE	INPUT	VERTICAL	HORIZONTAL
A	+10V	2 mV/DIV	50 μSEC/DIV
B	0V	2 mV/DIV	50 μSEC/DIV
C	-10V	2 mV/DIV	50 μSEC/DIV

(b)

Fig 3—Nonintegrating S/H amplifiers display a variable pedestal, as seen in a. The pedestal for the HA-2420 under test varies from -6 mV for a -10V input to -11 mV for a +10V input. The HA-5320 and HA-5330 are integrating S/H devices; therefore, their pedestal is not a function of the input level, as seen in b and c. A linearly variable pedestal adds an offset to the S/H amplifier's output; a nonlinearly variable pedestal contributes nonlinearity in the form of harmonics.




Fig 4—Based on measurements made at 95°C on a nonintegrating S/H amplifier (the HA-2420), these curves show that the pedestal is a strong function of the input voltage. In the curve measured with a 1-nF hold capacitor, the pedestal varies linearly with input. For a configuration using a 100-pF hold capacitor, the pedestal-input relationship is a second-order one, and the result is harmonic distortion.

varying pedestal does not introduce nonlinearities in the S/H amplifier's transfer function:

$$\begin{aligned}
 P &= -0.0025V_{IN} - 0.009 \\
 V_{OUT} &= V_{IN} + P \\
 &= V_{IN} - 0.0025V_{IN} - 0.009 \\
 &= 0.9975V_{IN} - 0.009 \\
 V_{IN} &= 10\sin\omega t \\
 V_{OUT} &= 9.975\sin\omega t - 0.009,
 \end{aligned}$$


where P is the pedestal in volts. These expressions reflect a $\pm 10V$ sinusoidal input signal. The result shows that the linearly varying pedestal introduces a 0.025% gain error and a constant 9-mV negative offset voltage in the transfer function. You can easily compensate for these errors by simply adjusting the gain and offset of the S/H amplifier. The effects of a nonlinearly varying pedestal, however, are more insidious. The following expressions are based on a second-order (quadratic) pedestal-input relationship, derived from the coordinates of the 100-pF curve in Fig 4.

$$\begin{aligned}
 P &= -0.000045V_{IN}^2 - 0.00105V_{IN} - 0.015 \\
 V_{OUT} &= V_{IN} + P = 0.99895V_{IN} - 0.000045V_{IN}^2 - 0.015 \\
 V_{IN} &= 10\sin\omega t \\
 V_{OUT} &= 9.9895\sin\omega t - 0.0045\sin^2\omega t - 0.015 \\
 \sin^2\omega t &= \frac{1 - \cos 2\omega t}{2} \\
 V_{OUT} &= 9.9895\sin\omega t + 0.00225\cos 2\omega t - 0.01725.
 \end{aligned}$$

The obvious result of the nonlinear pedestal-input relationship is harmonic distortion. The $0.00225\cos 2\omega t$ term indicates that the output voltage will contain a 4.5-mV p-p second-harmonic term; this amplitude represents almost 1 LSB for the $\pm 10V$ input range under discussion. A good way to minimize pedestal-induced nonlinearity in an S/H amplifier is to reduce the input excursions. For example, when using the HA-2420 with an industry-standard 574 A/D converter, you'd do well to use the lowest input range available: $\pm 5V$ or 0 to $+10V$. A curve-fitting and equation-solving exercise for the -5 to $+5V$ portion of the 100-pF curve in Fig 4 reveals that the resulting second harmonic measures about 0.75 mV p-p, or only about $\frac{1}{3}$ LSB for the 10V full-scale range.

Don't neglect droop

After the output of the S/H amplifier settles to within the specified error band following the sample-to-hold transition, two more error-producing phenomena arise



TRACE	INPUT	VERTICAL	HORIZONTAL
A	+10V	1 mV/DIV	50 μ SEC/DIV
B	0V	1 mV/DIV	50 μ SEC/DIV
C	-10V	1 mV/DIV	50 μ SEC/DIV

Acquisition time and hold-mode settling time impose an upper limit on the sampling frequency for an S/H amplifier; droop limits the ADC's conversion time.




Fig 5—An S/H amplifier's held voltage sags linearly with time, as seen in these scope photos. In **a**, the HA-2420's voltage droops (actually, it rises—droop can be positive or negative, depending on the direction of the hold capacitor's discharge current) at 0.4V/sec. For the HA-5320 and -5330 of **b** and **c**, the respective droop values are 4.4 and 12V/sec. These droop characteristics were measured at a 95°C operating temperature.





Fig 6—The maximum rate of change for a sine wave occurs at zero crossing; this fact is both intuitively obvious and easily proven mathematically. For the small angular displacements shown in the expanded view, $A \sin \omega t = A \omega t$, and the maximum rate of change is $A \omega$ (10ω for the $\pm 10V$ sine wave depicted). The $\pm 0.012\%$ ordinates shown correspond to $\pm \frac{1}{2}$ LSB for a 12-bit A/D converter.

for consideration: feedthrough and droop. Feedthrough is what its name implies: the transmission of input-voltage variations to the output while the S/H amplifier is in hold mode. For the S/H devices discussed here, this parameter is not a cause for alarm; the feedthrough specs for the HA-2420, -5320, and -5330 are -76 dB, 2 mV, and -88 dB, respectively. In all cases, these figures represent feedthrough that's considerably lower than 1 LSB. Note, however, that you must take measurement conditions (voltage and frequency) into account when interpreting feedthrough specs; these conditions vary in the data sheets for the various available S/H amplifiers.

A parameter more worthy of attention is droop. This phenomenon is the change in output voltage that accrues from the inevitable discharge of the hold capacitor. The discharge paths are the bias current of the output amplifier and the leakage current of the Sample/Hold switch, as well as any leakage paths that may exist in external circuitry (in the case of S/H amplifiers using an external hold capacitor).

As is usually the case with semiconductor devices, these currents double with each 10°C rise in junction temperature. Fig 5 shows the droop characteristics at 95°C for the HA-2420 (**a**), the HA-5320 (**b**), and the HA-5330 (**c**). For this test, the HA-2420 used an



TRACE	HELD VOLTAGE	VERTICAL	HORIZONTAL
A	+10V	200 mV/DIV	100 mSEC/DIV
B	0V	200 mV/DIV	100 mSEC/DIV
C	-10V	200 mV/DIV	100 mSEC/DIV

(c)

external 1-nF hold capacitor; the other two devices used their internal hold capacitors. Take note that the leakage currents (also called drift currents) for some S/H amplifiers can be extremely difficult to measure. The 5-pA typ spec at 25°C for the HA-2420, for example, equates to about $3 \times 10^{12} \Omega$ impedance. This high impedance level also points up the need to exercise extreme care in laying out a pc board for an S/H amplifier that uses an external hold capacitor. Guarding techniques and moisture-avoidance measures are often necessary for these devices.

According to Fig 5a, the highest droop value at 95°C for the HA-2420 occurs with +10V input; at this level, the output voltage droops (or sags) at the rate of 0.4V/sec. For the HA-5320 and HA-5330, the droop figures are 4.4 and 12V/sec, respectively. Again, when you apply the $\pm \frac{1}{2}$ -LSB max criterion for output change, the longest times you can keep these devices in hold mode are 3, 0.27, and 0.1 msec, respectively. Based on the fact that the acquisition and hold-mode settling times are negligible in comparison with these figures, the lowest allowable conversion rates (assuming a 50% duty cycle for the sampling-conversion period) for $\pm \frac{1}{2}$ -LSB max error are 330 Hz, 3.7 kHz, and 10 kHz, respectively.

Slew limits ADC speed

To see why A/D converters usually need the assistance of S/H amplifiers, assume you've just procured a fast, 12-bit A/D converter—for example, the 12- μ sec

HI-674A. The 12- μ sec conversion time tells you the device is capable of an 83-kHz conversion rate. If you were unaware of the idiosyncrasies of successive-approximation A/D converters, you might intuitively jump to the conclusion that the unassisted converter could digitize signals having frequency components as high as 41 kHz. Unfortunately, the allowable input-signal speed is far below this figure. The problem is that for a successive-approximation A/D converter to achieve rated accuracy, the input signal must remain constant (within $\pm \frac{1}{2}$ LSB) during the conversion cycle.

To understand the implications of this constant-input rule on allowable input frequencies, refer to Fig 6. The sine wave represents a ± 10 V input signal presented to an HI-674 A/D converter, for example. The highest rate of change for the sine wave occurs at the zero-crossing point. The expanded view represents a $\pm \frac{1}{2}$ -LSB excursion around the zero-crossing point. The slope, or rate of change, of the curve at this point is $A\omega$, where A is 10V. If the conversion time, T, is 12 μ sec, the maximum permissible rate of change is 200V/sec. When you solve for ω and divide by 2π , you find that the maximum allowable input frequency presented to the A/D converter is 3.2 Hz—a far cry from 41 kHz.

It's thus clear that, in most cases, A/D converters need the assistance of S/H amplifiers. The ADC-S/H mating having taken place, it's natural to assume that the only limitation on the input frequency would be Nyquist's criterion: a maximum of half the sampling frequency. Not so. Referring again to Fig 1, you can see that a parameter called aperture jitter or aperture uncertainty imposes a limit on the input's rate of change, and thus on the input frequency. This parameter is the uncertainty concerning the exact time the Sample/Hold switch opens; that is, variations in aperture time from one sample-to-hold transition to another.

Fig 6 shows a ± 10 V sinusoidal input signal, along with an expanded view of the zero-crossing point (again, the point of maximum rate of change for a sine wave). This time, the positive and negative T values on the time axis correspond to the aperture-jitter spec of an S/H amplifier. Again, the assumption is that $\pm \frac{1}{2}$ LSB is the maximum variation permitted in the input voltage presented to an A/D converter. For a 12-bit converter, the maximum variation is thus $\pm 0.012\%$. For the small excursions depicted in Fig 5, $A \sin \omega t = A \omega t$. From the aperture-jitter specs ($\pm T$) in the S/H amplifiers' data sheets, it's then a simple mathematical exercise to solve for ω , then for f. For the

Aperture jitter—in essence a random modulation of the time the Sample/Hold switch takes to open—imposes a limit on the input signal's slewing rate.




Fig 7—Sample-and-hold cycles and A/D-conversion times are additive, as this timing diagram shows. Before the A/D conversion can begin, the S/H amplifier must acquire the input signal to within a $\pm\frac{1}{2}$ -LSB error band, and then settle in hold mode to within the same error allowance. This diagram applies to an HA-5330 S/H amplifier working with an MN5245 1- μ sec A/D converter. The total acquisition, hold-settling, and conversion period for the S/H-amplifier/ADC combination is 1560 nsec.




Fig 8—If one S/H amplifier won't do the job, try two. In this configuration, one S/H unit is holding the sampled signal constant for the A/D conversion while the other S/H amplifier is acquiring the next sample. The result is a nearly 50% increase in sampling rate. If you used this circuit, you might be able to save money by using a slower A/D converter than you could use in a single-S/H-amplifier circuit.

HA-2420, -5320, and -5330, the input frequencies that produce $\pm\frac{1}{2}$ -LSB max jitter-induced error are 7.6, 127, and 382 kHz, respectively.

Before leaving the topic of aperture jitter, note that this parameter is a relative (sample-to-sample) one, whereas aperture time is an absolute quantity. Because it remains constant from sample to sample, the aperture time has no detrimental effect on the accuracy of sampling for repetitive signals. However, if you must obtain accurate phase-related data for the signal you're sampling, you can simply advance the Hold command by an interval equal to the aperture time.

When using a fast S/H amplifier with a high-speed A/D converter, you must consider your timing budget carefully. The factors that come into play are the S/H amplifier's acquisition time and hold-mode settling time, as well as the A/D converter's conversion time and necessary timing overhead. For example, consider an HA-5330 S/H amplifier operating in tandem with Micro Networks' (and others') MN5245 A/D converter. The S/H unit has a 500-nsec acquisition time; the A/D converter specs 900-nsec conversion time. It might seem natural to jump to the conclusion that the combination can work with a 1400-nsec sampling period, but the conclusion would be wrong. Fig 7 shows the timing considerations for the pair.

First, the S/H amplifier must acquire the input signal to within a $\pm 0.012\%$ error band; this operation takes 500 nsec. Next, the held signal takes 100 nsec to settle within this error band before the falling edge of the start pulse commands the A/D unit to start converting. A 60-nsec interval ensues between the start command and the conversion interval of the status line. Finally, the conversion consumes 900 nsec, during which the S/H amplifier must hold the acquired signal constant. The entire cycle takes 1560 nsec, not the 1400 nsec you might expect; the maximum sampling rate is thus 641 kHz, rather than 714 kHz.

The speed-limiting factor in this marriage is the fact that the S/H amplifier must hold the acquired signal during the entire conversion period and must not start acquiring a new signal until the conversion is complete. If it were possible for the S/H device to acquire while

the A/D converter is converting, the cycle time would be considerably shorter. Fortunately, there is a way to shorten the cycle. If you use two S/H amplifiers and switch between their outputs by using an analog

switch, one S/H amplifier can acquire while its companion unit is holding, and vice versa.

Fig 8 gives the schematic diagram of a circuit that embodies the dual-S/H-amplifier scheme. Each S/H




Fig 9—Two holds are better than one, as you can see from this timing diagram for two HA-5330 S/H amplifiers driving an MN5245 A/D converter. Each S/H amplifier operates at half the 943-kHz sampling rate. While one S/H unit is holding the acquired input signal constant for the A/D converter, the other S/H amplifier is acquiring the next sample. The result is an almost 50% increase in sampling rate over that of the configuration that uses only one S/H device.




Fig 10—Signal acquisition follows a linear ramp. These photos show the slew-limited nature of the acquisition transition. In order of increasing acquisition time, the three waveforms in **a** are for the HA-5330, -5320, and -2420 S/H amplifiers. The photo in **b** shows the effect of using external hold capacitors having different values with the HA-2420. Quite simply, higher-value hold capacitors take longer to charge.

By using two S/H amplifiers instead of one to drive a high-speed A/D converter, you can increase the achievable sampling rate by a significant amount.




Fig 11—You can use these curves to choose the optimum S/H amplifier for your application. The curves in a give the maximum achievable sampling rates for the three S/H amplifiers under discussion, as a function of the speed of the ADC the S/H amplifier must drive. The curves in b show the contribution of the S/H amplifier to the total sampling time. For example, when working with a 10-μsec converter, the fast HA-5330 contributes only about 6.5% of the sampling period at the highest achievable sampling rate; the slower HA-2420 contributes about 38% of the sampling time.

TABLE 1—S/H AMPLIFIER-ADC COMBINATIONS VS THROUGHPUT

THROUGHPUT (kHz)	S/H AMPLIFIER	A/D CONVERTER
30	HA-2420	HI-574A
40	HA-2420	HI-674A
50	HA-5320 HA-2420	HI-674A HI-774
75	HA-5320	HI-774
100	HA-5330	HI-774A
200	HA-5320	ADC-817
300	HA-5320 HA-5330	MN5245 ADC-817
500	HA-5330	MN5245

unit operates at half the sampling frequency. A side benefit of this method is that it lets you use lower-speed S/H devices than you could use in a single-S/H-amplifier scheme. Fig 9's timing diagram is similar to that of Fig 7; you can see that the sample and hold intervals for the two S/H amplifiers overlap. The circuit operates at very nearly the maximum repetition rate possible for the MN5245; the only additional timing overhead is the 100 nsec allowed for the analog switch to settle completely. As shown, the sampling period is 1060 nsec, for a sampling rate of 943 kHz.

Acquisition time is the determining factor

As you've seen, acquisition time is the preponderant term in an S/H amplifier's sample-and-hold cycle. Its value is a measure of the speed of the input amplifier and of the amplifier's ability to charge the hold capacitor rapidly to the value of the input signal. The scope photos in Fig 10 show some typical acquisition-time measurements. Fig 10a shows comparative acquisition times for a +10 to -10V input step for the HA-5330, -5320, and -2420, in order of decreasing speed.

It's evident from Fig 10a that the naked eye is not a very effective measurement tool when it comes to $\pm 0.01\%$ settling. The 500-nsec (typ) HA-5330 appears to settle in an interval well under 500 nsec, and the 1-μsec (typ) -5320 seems to settle in about 500 nsec. Remember, though, that the $\pm 0.01\%$ represents only a ± 2 -mV excursion around the final -10V value. Another fact that's evident from the trace for the -2420 in Fig 10a is that the acquisition speed is slew limited, as borne out by the linear nature of the trace.

Fig 10b gives more proof of the slew-limited behavior of the acquisition process. Here, you see the effects of

"EDN MAGAZINE GREATLY ENHANCES OUR INTERNATIONAL IMAGE."

Phil F. Walters
Marketing Director
Hunting Hivolt Ltd.


Based in England, Hunting Hivolt is a leader in high-voltage technology. Yet the company wanted to further enhance its international image and gain an even greater awareness with engineers and engineering managers worldwide.

What was the answer?

First, set up a facility in the United States. Then support it with an advertising program in EDN magazine. Says marketing director Phil Walters, "The result has been an utter success. The quality of response has helped strengthen our position in

the United States and throughout the many countries where EDN magazine is circulated."

Phil Walters sees EDN magazine as a key element in his worldwide advertising campaign. "With EDN magazine and the solid foundation of Cahners Publishing behind it, we will continue to make strides in the international marketplace."



Advertising in EDN magazine works for
Hunting Hivolt. It can work for you.

EDN

Where Advertising Works

The choice of the right S/H amplifier and ADC for a particular application often entails tradeoffs involving price, speed, and application-related features.




Fig 12—A fault-tolerant A/D converter can save time, as this timing diagram shows. Because the HI-774A A/D converter can tolerate errors as high as +32, -31 LSB during much of its conversion cycle, it lets you initiate a sample-hold cycle much later than you could with less-forgiving converters. By taking advantage of the A/D converter's error-correction mechanism, you can increase the achievable sampling rate by about 30%.

increasing the value of the external hold capacitor used with the HA-2420. The traces depict acquisition time for a 0 to 10V input step. In order of decreasing speed, the hold-capacitor values are 1, 68, and 100 nF. Again, it's evident from the linear traces that the input amplifier charges the hold capacitor with a constant current.

Timing and budget determine S/H-amplifier choice

Just as it's wasteful to use a cannon to kill a fly, it's unwise to splurge on an S/H amplifier that's overly specified for the application at hand. The prices of both S/H amplifiers and A/D converters, of course, are proportional to the devices' speed. Depending on the required throughput rate in your application, you often have a tradeoff decision to make. The tradeoff involves speed, cost, and application-mandated features in the S/H and A/D units.

Fig 11a can help you select the optimum S/H ampli-

er and A/D converter for a particular application. For the HA-2420, -5320, and -5330 S/H amplifiers, the curves give the maximum achievable throughput as a function of A/D-converter speed. The A/D-conversion times reflect the total conversion cycle—that is, the specified conversion time plus any timing overhead. For example, the timing overhead for the HI-X74 Series of A/D converters is 200 nsec. Fig 11b gives the three S/H amplifiers' percent contribution to total throughput time as a function of A/D-converter speed.

The data presented in Table 1 comes from the graphs in Fig 11a. For each throughput rate, Table 1 gives appropriate S/H-amplifier/ADC combinations. In each case, the cited S/H amplifier is the minimum (that is, the slowest and least expensive) one that will do the job. You'll note that, for 50-kHz throughput, a tradeoff is possible: the HA-2420 with the HI-774, or the HA-5320 with the HI-674A. Incidentally, in 100-piece quantities,

NOW YOU CAN DRIVE OUR SUBCOMPACTS.

Seagate's family of 3½" hard disc drives.



As computers grow smaller, the demand for high-quality drives grows larger. But if you're looking for 3½" drives for your small computer systems, you don't have a lot to choose from.

Except at Seagate.

We offer six 3½" drives with 21, 32 and 48 MB formatted capacities. You also have a choice of interfaces: SCSI or ST412 with RLL or MFM encoding. All with 28 msec access time.

Our 3½" drives use Seagate's field-proven, proprietary stepper motors to achieve fast access times normally found only with more expensive voice coil actuators.

Seagate's 3½" drives are not only fast—they're power savers, using as little as 8 watts. And for added data integrity, the drives feature autopark with a balanced positioner.

All of Seagate's 3½" drives are built with the precision and quality that have made us the world's leading independent manufacturer of 5¼" full-height and half-height hard disc drives.

Only Seagate has the worldwide, high-volume manufacturing efficiency to meet the growing demand for 3½" drives.

When you're ready to go for a little drive, give us a call. 800-468-DISC.



 **Seagate**

The first name in disc drives.

It's unwise to splurge on an S/H amplifier that's overspecified for the application at hand.

the first combination is about \$5.50 less costly. For throughput rates higher than 200 kHz, the HI-X74 Series has insufficient speed. The high-speed A/D converters chosen for this example are Datel's 2- μ sec ADC-817 and Micro Networks' 1- μ sec MN5245.

Forgiving ADC saves time

Most successive-approximation A/D converters are of an unforgiving nature. That is, they require that the input voltage be within a $\pm\frac{1}{2}$ -LSB error band of its final value from the beginning to the end of the conversion period. Again, this error band is $\pm 0.012\%$ for a 12-bit converter. However, a slight timing leeway is possible: The input signal doesn't have to reach its final value until the first (MSB) successive-approximation bit decision is made. This decision time varies from converter to converter. The leeway is very slight, however.

You can see, then, that to calculate throughput you must add the S/H amplifier's full acquisition time plus its hold-mode settling time to the ADC's conversion time. A more forgiving A/D converter, the HI-774A, uses error correction to reduce the timing demands on the analog input voltage. Fig 12 shows that the analog input merely has to settle to within a -31 - to $+32$ -LSB envelope for much of the conversion cycle. This leeway lets you effectively advance the beginning of an A/D-conversion cycle in relation to the beginning of a sample-and-hold operation, and thus shorten the total acquisition-hold-conversion time.

Fig 12 illustrates the timing requirements for an HA-2420 S/H amplifier working in tandem with an HI-774A A/D converter. Curve A gives the timing considerations for the S/H unit operating with a conventional 12-bit A/D converter, one that demands that the input signal be fully settled at the beginning of the conversion. Curve B shows how you can take advantage of the HI-774A's forgiving nature. For curve A, you must take into account the S/H device's full 12-bit acquisition and hold-mode settling times in starting the sample-hold cycle. For the HA-2420, this time is 6 μ sec max.

For the situation represented by curve B, you can delay the initiation of the sample-hold cycle such that settling to a lesser accuracy occurs within a safe period at some time well into the conversion cycle. In Fig 12, the S/H amplifier settles to within $\pm 0.1\%$ in a 1- μ sec interval after the start of the conversion. The HA-2420's spec for acquisition and settling to within $\pm 0.1\%$ is 4 μ sec max. You can see that the initiation of the sample-hold cycle for situations A and B must take

place no earlier than 6 and 3 μ sec before the start of conversion, respectively. The total respective conversion times are thus 13 and 10 μ sec, yielding maximum sampling rates of 77 and 100 kHz.

By taking advantage of the HI-774A's input-settling envelope, you can thus increase the conversion rate by about 30%. Note that the throughput rates determined in this example are based on the HI-774A's 7- μ sec typical conversion time; the converter's maximum conversion time is specified at 8 μ sec.

EDN

Authors' biographies

Al Little is technical marketing manager for the data/comm product line at Harris Semiconductor. A 7-year employee at Harris, he obtained math and physics degrees from the University of the South at Sewanee, TN; a BSEE from Georgia Tech; and a master's degree in psychology from Nova University in Fort Lauderdale, FL. He holds a patent for an ECG-monitoring amplifier. Al's spare-time activities include playing the piano and electronic music synthesizers.



Bob Burnett is an applications engineer for data-acquisition products at Harris Semiconductor. He holds a bachelor's degree in psychology from the State University of New York at Oneonta, and a BS in electronic technology from the University of Central Florida. His hobbies include bicycling and motorcycling.



Article Interest Quotient (Circle One)
High 494 Medium 495 Low 496

**WITH AVIS
ROVING RAPID RETURN,
YOU GET YOUR RECEIPT
1-2-3.**

**(WITH HERTZ, IT'S
1-2-3-4-5-6-7-8-9-10-11
12-13-14-15-16-17.)**

Now, during peak periods at major U.S. airports and selected downtown locations, an Avis Roving Rapid Return representative will meet you right at your car. Just three rapid entries into the Avis Carside Computer,SM and Wizard[®] calculates your rental charges and your printed receipt is ready in seconds.*

The Avis Carside Computer talks directly to our Wizard III computer system, so all your contract information is available instantaneously. And your receipt will be complete and accurate.

Hertz also offers a carside service. However, their machine is a stand-alone computing

device—not a terminal linked to your rental information. So all your car rental information has to be manually entered—up to 17 separate entries (and extra chances for errors), before your transaction can be completed and a receipt issued.

Avis invented Rapid Return. And now, with Avis Roving Rapid Return, you can be on your way in mere seconds.

Avis is always trying harder, with super services and low SuperValue Rates. So next time, rent Avis. It's as easy as 1-2-3!



Red hotSM

CIRCLE NO 42



Avis features GM cars.
Buick Regal

The Ultimate Complement



EDN magazine for technology in depth.
EDN News for news of products,
technology, and careers.

Together, they provide complete coverage
of electronics for engineers and
engineering managers worldwide.

EDN MAGAZINE/EDN NEWS
Cahners Publishing Company • 275 Washington Street • Newton, MA 02158-1630 • (617) 964-3030

The Fastest Growing Electronics Newspaper



Now Reaches The Fastest Growing Electronics Market!



The newspaper is EDN NEWS.
The market, the Pacific Rim.

Starting with the December 1987 issue, EDN NEWS increases its circulation by 7,500 engineers and engineering managers in the key Pacific Rim markets of Japan, Taiwan, South Korea, Hong Kong, Singapore, and Malaysia.


This increase of 7,500 gives EDN NEWS the largest controlled circulation in the Pacific Rim of *any* electronics industry newspaper or magazine. EDN NEWS also reaches EDN magazine's U.S. circulation of 121,500...now for a total of 129,000 readers worldwide!

For details, contact Warren Dickson, Publisher, or Peter Coley, Advertising Sales Director, at (617) 964-3030 or your local EDN NEWS sales representative.


EDN NEWS

News of Products,
Technology, and
Careers for
Engineers and
Engineering
Managers

Cahners Publishing Company • 275 Washington Street
Newton, MA 02158-1630 • (617) 964-3030



**Easy loaders.
Faster test and burn-in
with AMP sockets.
Faster delivery from AMP.**



AMP is a trademark of AMP Incorporated.

Our LIF burn-in sockets for PLCCs, for instance. Rated to 200°C, they offer J lead-down loading—and they can be used in automated processes.

For PGA burn-in sockets, our ZIF styles feature normally-closed contacts for long life, and curved-handle design to make life easier. Use them for test and they're rated to a phenomenal 25,000 cycles. Loading and

unloading leadless ceramic packages is a breeze, too, thanks to a press-to-release cover on our Low Height test/burn-in versions: no tools necessary, no loose parts.

No matter what technology you work with, AMP sockets can make your work easier. Popular styles are available off-the-shelf.


And they all come with the name that spells affordable dependability: AMP.

Call (717) 780-4400. Ask for the Test/Burn-In Sockets Desk. AMP Incorporated, Harrisburg, PA 17105-3608.


CIRCLE NO 44

AMP Interconnecting ideas

Broad range of inexpensive test sockets, and sockets for high-cycle and 150°C environments.



Press-to-release hinged cover on low height burn-in socket eliminates tools, eliminates loose parts. Low profile gets more on the board.



Low-cost DIP sockets for burn-in and test applications feature fast and simple below-package sword slot unloading.



Your next destination:



The ACL Computer Age.

The future belongs to computers and peripherals built with RCA Advanced CMOS Logic (ACL).

The pressure is on to make your systems smaller, faster, cheaper.

Some of your competitors are doing just that by incorporating ACL into their new designs. If you want to stay on the fast track, you can't afford not to consider ACL for your new designs.

The computer of the future.

Imagine a computer with power dissipation so low you could eliminate all cooling systems. Or design a sealed system to prevent dust problems.

And get dramatically improved reliability, thanks to the far lower heat generated. As well as far smaller system size.

You'd also be able to use it in a far wider operating temperature range (-55°C to $+125^{\circ}\text{C}$). Even in high-noise environments.

FAST* speed, CMOS benefits.

Advanced CMOS Logic gives you high speed (less than 3ns propagation delay with our AC00 NAND gate) and 24 mA output drive current.

But unlike FAST, it gives you a whole new world of design opportunity for computers, peripherals, telecommunications and other speed-intensive applications.

ACL dissipates less than 1/8 Watt while switching, compared to 1/2 Watt for a FAST IC (octal transceiver operating at 5 MHz). And quiescent power savings are even more dramatic: ACL idles at a small fraction of the power of a FAST IC.

In addition, ACL offers balanced propagation delay, superior input characteristics, improved output source current, low ground bounce and a wider operating supply voltage range.

Latch-up and ESD protection, too.

Latch-up concern is virtually eliminated, because ACL uses a thin epitaxial layer which effectively shorts the parasitic PNP transistor responsible for SCR latch-up.

And a dual diode input/output circuit provides ESD protection in excess of 2KV.

A broad and growing product line.

Our line already includes over 100 of the most popular types (SSI, MSI and LSI). More are coming soon. And many are available in High-Rel versions.

All this at FAST prices.

Our ACL line is priced comparably to FAST. So you get better performance at no extra cost. Why wait, when your competition is very likely designing its first generation of ACL products right now?

Get into the passing lane, with RCA ACL from the CMOS leader: GE Solid State. Free test evaluation kits are available for qualified users. Kits must be requested on your company letterhead. Write: GE Solid State, Box 2900, Somerville, NJ 08876.

For more information, call toll-free 800-443-7364, extension 24. Or contact your local GE Solid State sales office or distributor.

*FAST is a trademark of Fairchild Semiconductor Corp.

In Europe, call: Brussels, (02) 246-21-11; Paris, (1) 39-46-57-99; London, (276) 68-59-11; Milano, (2) 82-291; Munich, (089) 63813-0; Stockholm (08) 793-9500.



GE Solid State

GE/RCA/Intersil Semiconductors

These three leading brands are now one leading-edge company. Together, we have the resources—and the commitment—to help you conquer new worlds.

THE NEW POWER IN RECHARGEABLE BATTERY TECHNOLOGY.



Gates Energy Products has purchased GE's Battery Business Department, making us the world's largest source of sealed rechargeable batteries.

What does this mean to you?

That Gates is dedicated to providing you with the best rechargeable batteries in the world.

Gates now has the technology and resources to offer the largest selection of rechargeable batteries including nickel cadmium, nickel hydrogen and sealed lead batteries—from .065Ah to 300Ah.

Leading the technological advancements at Gates is our new GEMAX™ Series of nickel cadmium cells. These cells are providing more run time and maximizing power delivery in all product applications by incorporating higher capacities and lower internal resistance.

As a result of GEMAX technology, Gates now offers the world's highest capacity, production-volume Sub C cell at 1.4Ah (1-hour rate). And more advancements are on the way.

Our commitment to supply batteries tailored to your specific applications is

yet another aspect of our determination to make sure that Gates batteries are superior.

No other rechargeable battery company in the world is taking such dramatic steps to perfect and expand their rechargeable battery products as the new Gates. It's time you discovered the difference.

For more information worldwide, contact one of the Gates Regional Sales Offices listed below.

Gates Energy Products

WESTERN U.S.
4063 Birch St. #130
Newport Beach,
CA 92660
(714) 852-9033

CENTRAL U.S.
2860 S. River Rd.
Suite 401
Des Plaines, IL 60018
(312) 827-9130

EASTERN U.S.
1 Prestige Dr.
Meriden, CT 06450
(203) 238-6840

SOUTHERN U.S.
1835 Savoy Dr.
Suite 200
Atlanta, GA 30341
(404) 458-8755

PACIFIC AND ASIAN
3706 A, Shun Tak Centre
200 Connaught Rd. Central
Hong Kong
011-852-5-403073

EUROPE
Units 12/13
Loomer Rd. Industrial Estate
Chesteron
Newcastle-under-Lyme
Staffs. ST5 7LB, Great Britain
011-44-782-566525

©1987 Gates Energy Products, Inc.

Heed local norms when designing telecomm interfaces

In designing customer-premises telecomm equipment for foreign markets, you must account for the respective countries' national telecommunications standards. These norms often differ in significant ways from the FCC Rules Part 68, which governs telecomm equipment in the US.

Glen Dash, *Dash, Straus & Goodhue Inc*

Although most of the world's market for installed telecommunications apparatus remains closed to US suppliers, three major markets are open: Canada, the United Kingdom, and Japan. To gain approval for US-built customer-premises equipment (CPE) in these countries, however, you must demonstrate that the apparatus meets the national standards relevant to several aspects of the equipment's interface to the telecomm network (see **box**, "If you need standards information"). By using the test methods described here, you can prove that an installation complies with the key national norms governing safety, electrical performance, and other aspects of a CPE's operation. The tests cover voltage stress, hazardous voltages and currents, pulse and DTMF (dual-tone multifrequency) characteristics, signal power, impedances and line balance, and billing protection.

Many of the criteria for overseas telecomm interfaces differ significantly from the requirements delineated in FCC Rules Part 68, and you must be aware of these criteria during the telecomm equipment's design and testing stage. (**Ref 1** discusses corresponding test methods for Part 68.) Before going into the electrical performance of an export-destined CPE, it's helpful to see how the different countries recommend feeding dc power to the CPE.

In perusing the various standards and their test methods and circuits, note that many of the specs call for specific loop-current settings in the CPEs during testing. Indeed, several of the spec-limit graphs use the CPE's loop current as their abscissa. To impose the necessary dc-feed conditions, the standards offer what are in essence network power-supply schematics. **Fig 1** shows the recommended dc-feed circuitry (also called a loop simulator) for Canada, the UK, and Japan.

The feed circuit for Canada is the most elaborate, as it provides a ringing circuit for bringing the CPE to an off-hook condition. The 0 to 105V adjustable supply (nominally 48V) feeds a variable resistor that allows you to trim the loop current to the value specified for a given measurement. For any test, the + and - terminals connect to the CPE's tip and ring terminals, respectively. (The term "ring" in tip and ring is a carryover from the phone plugs that switchboard operators used in the days of yore.)

In the British telecomm documentation, the dc-feed circuit recommended for most tests makes no provision for ringing the CPE. Instead, the UK specs stipulate a

To gain approval for telephone equipment in foreign markets, you must prove that the apparatus conforms with national norms, according to mandated test methods.

separate circuit for testing the ringer. This configuration, like the Canadian circuit, allows you to adjust the loop current (I). Many of the British standards specify the loop current, and they also offer an alternative: "Compliance shall be checked by the test of (spec No) with an apparatus current of (spec) mA, or the current obtained when the apparatus is connected to a 50V dc source in series with a 400 Ω resistor, whichever is the less."

The Japanese seem singularly unconcerned about testing various parameters under varying loop currents; their fixed-value dc-feed circuit for most tests is an inductively blocked 48V dc supply in series with a 440 Ω resistor.

First, stresses and surges

National telecomm standards impose various requirements for dielectric strength and for excessive voltages and currents. The purpose of these requirements is twofold. First, the CPE must not subject the telecomm network to excessive voltages. Second, the CPE must protect the user from contact with any hazardous voltages that might originate in the network.

Consider the Canadian test for CPE resistance to voltage surges (lightning, for example). Fig 2a gives the Canadian test circuit for surge voltage. As is the case with most of the Canadian standards, it uses the dc-feed circuit of Fig 1a. The surge generator in Fig 2b provides the controlled-characteristic voltage surge shown in Fig 2c. The timing specs for this waveform are complicated and use some very idiosyncratic terms. For example, the waveform is defined as 1000V, 10 μ sec max \times 1000 μ sec min. The 10 μ sec, an index of the wave front, is the "virtual duration" of the front. This quantity is 1.67 times the interval for the voltage to rise from 30 to 90% of its crest value. The 1000 μ sec, an index of the wave tail, is the interval from the tail's 50% point to "virtual zero," the point of intersection of the 0V abscissa with a line drawn through the tail's 90 and 30% points.

Esoteric terms notwithstanding, the way to perform surge-voltage testing on a Canada-destined CPE is to place S_1 and S_2 in position A and S_3 in position B, and then to fire the surge generator three times. This action applies the surge to the tip terminal; the ring is grounded. Next, place S_2 in position B (thereby reversing tip and ring) and fire the surge generator three more times. Now, adjust the surge generator to produce 1000V, 100 μ sec max \times 1000 μ sec min and repeat the two preceding steps. Next, place S_1 in position B

and operate the ring-up circuit to bring the CPE off hook. You then repeat the firings for both connections of tip and ring and for both surge-generator waveforms. Finally, you place S_3 in position A and repeat all the tests. The criterion for passing the surge-voltage test is




Fig 1—Generate the loop current for your CPE by using one of these dc power-supply circuits. The Canadian dc-feed circuit (a) has a ringing circuit for bringing the terminal equipment off hook; the British (b) and the Japanese (c) dc-excitation circuits are simpler. All three provide essential capacitive dc blocking to the measurement terminals and inductive ac blocking to the driving-voltage source.




Fig 2—In this Canadian surge-voltage testing scheme, (a), the surge generator (b) supplies impulses to the tip, ring, and other connections of the terminal equipment. The impulse's wave front and tail must have very particular timing characteristics (c).

as follows: The test sample, after testing, is fully operational in accordance with the manufacturer's instruction manual, or it must fail in a mode that will not cause harm to the network—for example, permanently on hook.

The UK standards, too, mandate a surge-voltage test to protect users from excessive voltages originating in the telecomm network. A simple RC network provides the surges (Fig 3). To perform the test, you charge the 20- μ F capacitor to 1.5 kV. Closing S_1 delivers the impulse to the CPE. The standards require 10 impulses each of both polarities, applied at 1-minute intervals. The terminals of the impulse generator are connected between all network-interface connections and all exposed conducting surfaces on the CPE. After applying the impulses, perform a 500V insulation-resistance test. The measured insulation resistance must exceed 2 M Ω .

Another UK stress test involves measuring insulation resistance. The way you perform the test depends on whether your CPE's insulation barriers must serve as the entire insulation system between the network and any eventual hazardous voltages, or whether it will serve as supplementary insulation.

Consider the example of a modem. It connects to the telecomm network via its DCE port, to a computer via its DTE (RS-232C) port and, perhaps, to an auxiliary telephone handset. If the computer's insulation system




Fig 3—British impulses are easy to generate, with the help of this simple network. You simply charge the 20- μ F capacitor to 1.5 kV, then close S_1 . This impulse test is actually a conditioning measure; you perform an insulation-resistance test after applying 10 impulses for each polarity of the terminal equipment.

complies with British safety standard BS6204, then you can consider the modem's barrier to be supplementary insulation. Satisfying BS6204 in this context means that the DCE-to-DTE interface in the computer is a "class 2" circuit. That is, the supply feeding the interface uses an approved transformer and supplies less than 42.4V at 8A. In this case, you would perform insulation-resistance tests according to curve A in Fig 4. If, however, the modem's insulation must be the primary barrier (for example, in the event of insulation

In performing tests to national standards, you must set up a dc supply that simulates conditions in the actual phone network.

failure in the computer), then you must perform insulation-resistance tests according to the more severe curve B in Fig 4.

To perform these tests, you must determine the maximum working voltage—that is, the voltage that the telecomm network could encounter in the event of insulation failure (which would impose the primary-supply voltage on the modem). You then apply this voltage to the insulation barrier as follows: Increase the applied voltage from 0V to the test voltage gradually (over 5 to 10 sec), then maintain this voltage for 60 sec. The criterion for failure is insulation breakdown.

The Japanese standards for stress and breakdown are simple. If the highest working voltage in the CPE is 300V dc or lower, the power-circuit-to-housing insulation resistance must be at least 200 k Ω . If the voltage exceeds 300V dc or ac, the insulation resistance must be at least 400 k Ω . You must test dielectric strength only if the working voltage exceeds 750V dc or 600V ac. To perform the test for dielectric breakdown, apply 1.5 times the working voltage for 10 minutes.

Take your pulse carefully

If you plan to design customer-premises equipment for installation in Canada, the UK, or Japan, you must accommodate the national standards governing the characteristics of dial pulses and DTMF tones. To create dial pulses, of course, the CPE simply connects

(the “make” interval) and disconnects (the “break” interval) itself to and from the network. Curiously, the US standards do not regulate the characteristics of dial pulses. In the three countries under discussion here, however, the respective national norms rigidly govern these characteristics.

Table 1 gives the countries’ salient specs for dial pulses. In Canada, to obtain an adequate loop current for measuring dial-pulse characteristics, you adjust the variable resistor in the dc-feed circuit of Fig 1a. The Canadian spec for spurious breaks applies to the total spurious breaks that occur during any make interval. The spec for maximum interdigital pauses applies, of course, only to automatic dialers. The tip-to-ring resistance during break intervals must equal or exceed 20 k Ω .

For CPEs destined for the UK, you can test for compliance with dial-pulse requirements by using a dc-feed circuit consisting of a 50V dc source in series with a 400 Ω resistor. The British standards mandate that the loop current during break intervals must not exceed 500 μ A. In contrast with most of the very carefully stipulated UK specs, the British spec for dial-pulse distortion is somewhat hazy: “The pulsing performance of the apparatus shall be adequate for




Fig 4—Insulation resistance is of prime concern in the UK, and the measurement of it depends on your CPE and its application. Use curve A if the insulation barriers in the other equipment connected to the CPE satisfy British standards. If, however, the insulation barrier in the CPE must serve as the primary barrier in the case of a breakdown, you must test according to the more stringent curve B.

TABLE 1—DIAL-PULSE CHARACTERISTICS

PARAMETER	CANADA	UK	JAPAN
DIALING RATE (PULSES/SEC)	8 TO 11	9 TO 11	9.21 TO 10.8 OR 18.4 TO 21.6
MAKE/BREAK RATIO	36 TO 42%	28 TO 37%	30 TO 36%
INTERDIGITAL PAUSE	700 mSEC TO 3 SEC	AUTOMATIC: 720 TO 920 mSEC; MANUAL: 240 mSEC MIN	10-PPS MODE: 600 mSEC MIN; 20-PPS MODE: 450 mSEC MIN
SPURIOUS BREAKS	3 mSEC MAX TOTAL	NO SPEC	NO SPEC

TABLE 2—DTMF SIGNAL TONES

	HIGH (Hz)			
LOW (Hz)	1209	1336	1477	1633
697	1	2	3	A
770	4	5	6	B
852	7	8	9	C
941	*	0	#	D

normal operation under extremes of conditions and configurations."

The UK standards explain the difference in automatic and manual (rotary-dial) interdigital-pause specs as follows: "Rotary dials normally have a lost-motion period of not less than 240 msec inherent in the design. In addition, it may be assumed that rotary dials have a wind-up time of not less than 180 msec for digit 1, and that the wind-up time increases for other digits. Together with user-selection time, this may be expected to give an average interdigital pause of about 800 msec."

The Japanese standards allow for two dial-pulse-speed classes of CPEs: 10 and 20 pps (pulses/sec). As Table 1 shows, the $\pm 8\%$ dialing-rate spec is the most rigid of the three countries. The spec for interdigital pauses in Japan is the same for automatic or manual systems. Note that, neither the UK nor Japan, unlike Canada, specify spurious breaks during make intervals. Note also that the Japanese standards do not delineate the dc-feed conditions that must prevail during dial-pulse measurements.

DTMF tests set the tone

One thing the three countries agree upon is the set of DTMF frequency pairs that define the numbers 0 to 9, the asterisk (*), and the pound sign (#). In addition to these characters (found on a standard telephone handset), the tone pairs can define the four letters A, B, C, and D. Table 2 gives the universally agreed-upon frequencies. Note that Canada, the UK, and Japan also agree upon a $\pm 1.5\%$ max frequency tolerance. Where the countries diverge is in the waveform characteristics and the signal-power levels of the DTMF tones.

Table 3 lists the Canadian, British, and Japanese telecomm standards for DTMF waveform characteris-

tics. You can see that the three sets of specs are widely disparate, and you'll have to take account of these disparities if you're designing equipment for different markets. Consider the rise time of a DTMF waveform, for example. (The rise-time parameter applies to the composite-tone envelope.) In Canada, the rise time is the time it takes the envelope to reach 90% of its final value, starting from the -55-dBm level. The UK defines it as the time it takes the envelope to reach the specified tone-power limits. Japan has no spec at all for rise time.

Disparities in standards become really pronounced regarding DTMF-tone signal levels. In Canada, for example, DTMF network-control signals transmitted by the CPE to the network interface must meet the following requirements:

- The maximum power difference between the high- and low-group components shall not exceed 4 dB
- The power level of the high-group component shall equal or exceed that of the low-group component
- Loop-powered DTMF-signal power levels shall conform to the limits shown in Fig 5
- The total power of all extraneous frequencies transmitted by the CPE shall be at least 20 dB lower than the DTMF-signal power.




Fig 5—For loop-powered terminal equipment destined for Canada, the power levels of DTMF dial tones must fall within the limits indicated by these curves. As you can see, the tone power is a function of loop current. To test the tones, you can vary the loop current by using the dc-feed circuit of Fig 1a.

TABLE 3—DTMF WAVEFORM CHARACTERISTICS

PARAMETER	CANADA	UK	JAPAN
RISE TIME	STARTING FROM -55 dBm, ≤ 5 mSEC TO 90% OF FINAL VALUE	≤ 15 mSEC TO LIMITS IN FIGURE	NO SPEC
ON TIME	≥ 50 mSEC	≥ 68 mSEC	≥ 50 mSEC
INTERDIGITAL PAUSE	≥ 45 mSEC	≥ 68 mSEC	≥ 30 mSEC
CYCLE TIME	≥ 100 mSEC	≥ 136 mSEC	≥ 120 mSEC

Virtually all national telecomm standards view tests for hazardous voltages and dangerous leakage paths as of paramount concern.

For fixed-level, locally powered generators, DTMF-signal power levels have the following requirements:

- nominal power per frequency: -6 to -4 dBm
- maximum power per frequency pair: 2 dBm
- minimum power, high group: -10 dBm
- minimum power, low group: -12 dBm.

In Canada, for data equipment designed to have the DTMF level track the data signal level, the power levels of the high- and low-group DTMF signals shall not exceed that of the data by 2 and 0 dB, respectively. Finally, for autodialers, DTMF-tone average power levels shall not exceed 0 dBm, over any 3-sec interval and at any loop current.

Fig 6 gives the power-level limits for individual DTMF tones for CPEs destined for installation in the UK. Additional stipulations accompany these limits:

- The high-group tone amplitude shall be 2 ± 1 dB higher than the low-group tone amplitude
- The transient peak voltage (associated with rise and fall intervals) for a DTMF tone shall not exceed 5V
- During DTMF signaling, the power level for a single unwanted frequency component shall not exceed -33 dBm, and the total power of unwanted frequency components shall be at least 20 dB lower than the lowest power level of any one signaling tone of a digit tone burst.

Unlike those in Canada and the UK, the standards in Japan require that measurements be made at the central office, rather than at the CPE site. You must, therefore, take line loss into account. The Japanese standard for DTMF-signal power levels specifies the




Fig 6—DTMF tone-burst power must meet British norms by remaining within this envelope. As they are in Canada, the DTMF power limits are a function of the loop current. You can vary the loop current by using the dc-excitation circuit of Fig 1b.

low- and high-group limits as a function of the line loss. The low-group minimum and maximum power limits are $(-16.5 + 0.8L)$ and $(-6.5 + 0.8L)$ dBm, respectively; L is the line loss in dBm measured at 1500 Hz. The absolute maximum power level for the low group is -3.5 dBm. For the high group, the limits are $(-16 + L)$ and $(-6.5 + L)$ dBm, not to exceed -2.5 dBm.

Scrutinize signal power

In the three countries under consideration here, no other parameter is so closely regulated as the signal power that the CPE delivers to the telecomm network. Also, no other parameter displays such a disparity in specs. Consider the Canadian standards, for instance. Fig 7 shows the permissible limits for transmitted signal power. Again, you'll find esoteric nomenclature. The term "metallic" applies to differential signals, and "longitudinal" refers to single-ended, ground-referenced signals.

Fig 7's limit curves reflect power levels measured over a 3-sec interval. The written specs allow short-term power levels beyond the curves' limits. For example, the spec limits metallic voice and data signals to -9 dBm; however, during a 250-msec interval, the power can attain 3 dBm max. The Canadian standards also regulate the maximum dc signals that the CPE may impose on the network. On hook, the metallic and longitudinal dc voltage may not exceed ± 25 mV. Off hook, the longitudinal signals may not exceed 0V, nor be more negative than -0.5V. Note that, though Fig 7 doesn't show it, the frequency range of 3995 to 4005 Hz




Fig 7—Signal power is a crucial parameter in Canada. The curves reflect measurements averaged over a 3-sec interval; shorter bursts (250 msec) have higher limits. "Metallic" signals are differential, tip-to-ring signals; "longitudinal" signals are single-ended signals, measured from tip to ground and ring to ground.

is restricted: Metallic voice and data levels may not exceed -29 and -20 dBV, respectively. The telecomm system uses this frequency band for network control.

In the UK, signal-power limits are more complex than in Canada (or anywhere else). **Table 4** gives the limits for in-band frequencies. The tabular figures represent instantaneous power measured in a 10-Hz bandwidth. Besides these limits, the British standards mandate a 1-minute mean power level of -9 dBm max for fixed-level CPEs, and -13 dBm max for apparatus having adjustable power levels. For the adjustable CPEs, the installer must set the level at the time of installation, according to procedures prescribed by British telecomm authorities.

You should interpret **Table 4** in the following way: When a signal occurs in area A, it shall be accompanied by a signal or signals in area B, whose power level is not more than 12 dB lower than that of the signal in area A. Similarly, when a signal occurs in area C, it shall be accompanied by a signal or signals in area B, whose power level is not more than 12 dB lower than that of the signal in area C. When no signal exists in area B, the total power in the frequency range of 2220 to 2340 Hz shall not exceed -33 dBm. **Table 5** lists the limits for out-of-band signal power in the UK. These limits reflect 1-minute mean power measured in any 3-kHz bandwidth above 3.4 kHz.

As mentioned, the Japanese telecomm standards take account of transmission-line losses between the CPE and the central exchange, as borne out by the signal-power limits in **Table 6**. As you can see, the specs impose a maximum mean power level of (L-15) dBm, where L is the line loss. Assuming losses between 0 and 7 dB, the CPE should be able to transmit maximum mean power levels between -15 and -7 dBm.

You can consider the lines coming from the telecomm network to your CPE to be long, open-wire transmission lines. To be able to reject noise and hum (principally 50 and 60 Hz) and to minimize coupling to other telephone lines, these lines must remain in balance. Therefore, it's important that your CPE present balanced longitudinal impedances to the network. ANSI/IEEE-455 is the standard test procedure that Canada has adopted for terminal-equipment balance tests. **Fig 8** shows the proposed circuit for performing these tests; the accompanying table gives the Canadian limits for longitudinal-impedance balance. For data-terminal equipment, the minimum balance is 45 dB over the range of 200 to 4000 Hz.

To perform the balance test, you place S_2 in position B

TABLE 4—UK SIGNAL-POWER LIMITS

FREQUENCY (Hz)	POWER LEVEL IN A 10-Hz BANDWIDTH (dBm)	NOTES
0	-33	
100	-33	
100	-23	
200	-23	
200	-6	
450	-6	
575	-43	
775	-43	
865	-33	AREA C
900	-6	
900	-6	
1000	-23	
1000	-45	
2000	-45	AREA B
2000	-23	
2130	-6	
2130	-6	
2220	-33	
2340	-33	AREA A
2430	-6	
3200	-6	
3200	-23	
3400	-23	
3400	-33	

TABLE 5—UK POWER SPECTRAL-DENSITY LIMITS

FREQUENCY (kHz)	POWER SPECTRAL DENSITY (dBm)
3.4	-33
5.1	-40
8.9	-40
50	-70
10,000	-70

TABLE 6—SIGNAL-POWER LIMITS IN JAPAN

PARAMETER	FREQUENCIES	SIGNAL-POWER LIMITS
IN-BAND SIGNALS	4 kHz MAX	L-15 dBm MAX MEAN LEVEL 0 dBm MAX LEVEL
OUT-OF-BAND SIGNALS	4 TO 8 kHz 8 TO 12 kHz > 12 kHz	P-20 dB MAX P-40 dB MAX P-60 dB MAX

NOTES:

1. L IS THE LINE-TRANSMISSION LOSS BETWEEN THE SWITCHING FACILITIES OF A TELECOMMUNICATIONS CARRIER AND THE INTERFACE WITH THE TERMINAL EQUIPMENT, MEASURED AT 1.5 kHz.
2. THE MEAN LEVEL IS THE AVERAGE SIGNAL POWER MEASURED AT THE TERMINAL EQUIPMENT. THE MAX LEVEL IS THE MAXIMUM PERMISSIBLE POWER LEVEL TO BE SET AT THE TIME OF ADJUSTING THE TERMINAL-EQUIPMENT OUTPUT.
3. P IS THE IN-BAND SIGNAL-POWER LEVEL.
4. THE DENOTED SIGNAL-POWER LEVELS APPLY TO SYSTEMS HAVING 600Ω BALANCED IMPEDANCE.

Thankfully, all three countries use the same DTMF frequencies, but the permissible power levels for the dial tones vary considerably from country to country.

and close S_3 to produce an on-hook condition. You then apply a 10V rms signal and measure the voltage from tip to ring at all the stipulated frequencies. The 250-k Ω potentiometer compensates for any mismatch between the 368 Ω resistors; when these impedances are balanced, flipping S_1 shouldn't produce any differences in

the tip-to-ring voltages. The balance figure is 20 times the base-10 log of the ratio of the oscillator voltage to the tip-to-ring voltage. You must test the CPE in an off-hook condition, too. For this condition, you open S_3 and adjust the loop current to obtain the lowest balance indication, and then repeat the balance tests.




Fig 8—Balanced impedance to ground is of prime concern in Canada. Longitudinal-impedance imbalance can cause noise and hum pickup, as well as interference with other phone lines. The table gives the minimum acceptable balance figures for various frequencies; the test circuit shown comes from ANSI/IEEE-455.




Fig 9—A concern for balance prevails in the UK, as well as in Canada. Somewhat simpler than Fig 8's circuit for measuring longitudinal-impedance balance, this circuit depends on precise matching of components for its accuracy. The principle of operation and the test method are identical to those for Canadian CPEs.









Fig 10—You must pay your phone bills in Canada, thanks to these off-hook voltage-current limits set by Canadian standards. The CPE's off-hook impedance properties allow the phone company to detect off-hook conditions for billing purposes.

Your Connectors Specialist



We supply a wide range of products to boost your sales in 1987, including PS/II signal cable Round Cable & Flat Cable Assemblies, D-Subconnectors, 57 Series Connectors, Modular Jacks, Gender Changers, Switching Power Supplies, Pin Headers, Terminal Strips, etc. Contact us right away for further information.

OEM WANTED!



Manufacturer & Exporter



GREATLINK ELECTRONICS TAIWAN LTD.

3/F., No. 16, Lane 54, Chung Cheng Rd. Hsin-Tien City, Taipei, Taiwan, R.O.C.

Tel: 886-2-917-9261

Tlx: 34559 GTLINK

Fax: 886-2-917-8064

CIRCLE NO 115


Turn Good Ideas Into Good Articles

With EDN's FREE Writer's Guide!

Would you like to get paid for sharing your clever engineering ideas and methods with your professional colleagues? If so, then send for EDN's new FREE writer's guide and learn how.

You don't need the skills and experience of a professional writer. And you don't need to know publishing jargon. All you *do* need are a little perseverance, your engineering skills, and the ability to communicate your ideas clearly.

Our new writer's guide takes the mystery and intimidation out of writing for a publication. It shows you how to write for EDN using



skills you already have. Plus, it takes you step-by-step through the editorial procedures necessary to turn your ideas into polished, professional articles.

Get your FREE copy of EDN's writer's guide by circling number 800 on the Information Retrieval Service Card or by calling Sharon Gildea at (617) 964-3030.

Signal power is the most closely regulated parameter in all telecomm markets. Specs for the various countries vary widely.




Fig 11—Off-hook impedance is important in the UK, as is evident from this limit curve. The off-hook voltage-current status of a terminal allows the phone company to ascertain an off-hook condition for billing.

The circuit prescribed by the UK standards for measuring longitudinal-impedance balance (called “impedance balance about earth” in the UK) is shown in Fig 9. The British specs simply stipulate that the balance, calculated in the same way as the Canadian standards, must exceed 46 dB over the range of 300 to 3400 Hz. Curiously, the Japanese telecomm standards do not specify longitudinal-impedance balance.

In order to be able to bill a caller, a telephone company must be able to detect that the caller’s CPE is indeed off hook. One way to do this is to assign limits to

the CPE’s off-hook voltage-current relationship. An example of such a billing-protection spec is the Canadian standard off-hook V-I-limit diagram (Fig 10). The tip-to-ring voltage-current characteristic must satisfy the limits in the diagram for a minimum of 5 sec following the on- to off-hook transition.

In addition to the voltage-current limits shown in the diagram, Canada also stipulates that the measured current shall not decrease by more than 25% from the maximum value attained during the 5-sec interval following the transition. This last requirement does not apply if the current is greater than the current that would flow through a 200 Ω resistor connected from tip to ring. As in the US, another Canadian billing-protection provision mandates that energy in the 800- to 2450-Hz band exceeds that in the 2450- to 2750-Hz band.

Although not labeled as a billing-protection measure as such, an off-hook V-I limit diagram forms part of the British telecomm standards, too. Fig 11 shows the upper limits on the tip-to-ring voltage measured for currents ranging from 0 to 125 mA. The Japanese standards have no explicit billing-protection provisions. The only Japanese spec that corresponds to the Canadian and the British standards is the requirement that the CPE exhibit dc off-hook resistance between 50 and 300 Ω .

EDN

If you need standards information

The following companies provide standards information, testing services, and instrumentation necessary for testing telecommunications apparatus to the various national standards discussed in the accompanying article.

Standards information

Compliance Engineering

593 Massachusetts Ave
Boxborough, MA 01719
(617) 264-4208

ANSI

1430 Broadway
New York, NY 10011
(212) 642-4900

Testing services

Dash, Straus & Goodhue Inc
593 Massachusetts Ave
Boxborough, MA 01719
(617) 263-2662

Underwriters Laboratory

1655 Scott Blvd
Santa Clara, CA 95050
(415) 782-6900

Instrumentation

Hewlett-Packard

1820 Embarcadero Rd
Palo Alto, CA 94303
(415) 857-8000

Compliance Design Inc

629 Massachusetts Ave
Boxborough, MA 01719
(617) 264-4668

References

1. Dash, Glen, “Understand FCC rules when designing telecomm equipment,” *EDN*, May 16, 1985, pg 193.

Author’s biography

Glen Dash is the founder of Dash, Straus & Goodhue Inc, a Boxborough, MA-based R&D organization that deals with FCC and VDE consulting and testing and with telephone-interconnect analysis for US- and foreign-standards compliance. Glen holds a BS in Electrical Engineering and an MBA, both from MIT, and has a law degree from Harvard University. He holds four patents and enjoys playing softball in his leisure hours.

Article Interest Quotient (Circle One)
High 491 Medium 492 Low 493

XILINX PROGRAMMABLE GATE ARRAYS from HAMILTON/AVNET PERFECT DESIGNS ALL THE WAY DOWN THE LINE



FIRST USER-PROGRAMMABLE GATE ARRAYS AVAILABLE THROUGH 57 LOCATIONS

Create complex logic designs with the Xilinx family of Logic Cell* Arrays, the only user-programmable gate arrays. You get the performance and densities you expect from a conventional gate array with none of the risk. That could add-up to substantial savings in time and money.

Hamilton/Avnet's experienced team of field application engineers are available to demonstrate the versatility and convenience of using Xilinx LCA's. And if you want help with your design, our design center engineers are always on hand.

Xilinx's patented architecture is responsible for gate counts that range from 1200 gates in our XC2064 to 1800 in the XC2018. While the 3000 series, with enhanced architecture, features the 2000 gate XC3020.

But this is only the beginning. The 9000 gate XC3090 is soon to come, offering enough density for just about any logic application.


With speeds that run with the fastest performance microprocessors available, VLSI densities and 100% tested parts, the Xilinx Programmable Gate Array is the ideal logic device. And it's available now from Hamilton/Avnet.

So, if you want the very best in high performance, high density programmable logic, and the strongest technical support group around, get on the line with your local Hamilton/Avnet representative today.

For more information or to find the location nearest you, call toll free: 1-800-HAM-ASIC. (In Canada, 1-800-387-6879; 1-800-387-6849 in Ontario and Quebec.)


*Logic Cell and LCA are trademarks of XILINX, INC.

Hamilton Avnet
ELECTRONICS  AN AVNET COMPANY



CIRCLE NO 54

Supports application interfaces for 3270/3299 & 5250 connectivity



** DP8344 BCP*

"Soft" device = adapts completely to industry system evolution. Can standardize hardware & use common control code for years!

Now anyone can draw on the power of the mainframe with a single chip.

INTRODUCING THE DP8344 – THE EASY, AFFORDABLE WAY TO IBM CONNECTIVITY


At last there's a one-chip solution to processing IBM 3270, 3299 and 5250 communication protocols – the programmable DP8344 Biphasic Communications Processor.

The BCP™ is easily integrated into cluster controllers, PCs, terminals and printers, so now anyone can design a plug-compatible interface for IBM mainframe and departmental processors.

You can also use the DP8344 in a PBX or to build a gateway to various local- and wide-area networks.

You can use it in a protocol converter to give inexpensive peripherals access to the power of the mainframe. Or in a PC or IBM PS/2 to provide 3270 or 5250 terminal emulation.

In fact, providing IBM connectivity is now so simple and inexpensive that a host of new applications are being developed. The BCP has been designed in by more than 100 companies – including Hewlett-Packard, Local Data, Pathway Designs, Lee Data, Centronics, and Memorex.



IT GIVES YOU A LOT OF POWER IN A VERY SMALL SPACE

A full system, supporting all three IBM protocols can be implemented in an area not much larger than a credit card.

The BCP integrates an intelligent transceiver and a high-performance CPU on the same low-power CMOS chip.

Powerful enough to operate as the sole system processor, the BCP also incorporates a flexible bus interface with on-chip arbitration logic, enabling communication with other processors.

With a 20-MHz, 50-nanosecond T-state processor, 30 instruction types, full-function ALU, and an instruction-cycle time ranging from 100 to 200 nanoseconds, the DP8344 supports the 3270 protocol using only 20 percent of the CPU bandwidth.

Fast and flexible interrupt and subroutine capabilities, with on-chip stacks, make the remaining bandwidth readily available for other system tasks. In fact, enough power is available to eliminate other system processors entirely.

IT COULDN'T BE MORE FLEXIBLE

The BCP features a software-configurable transceiver that supports not only IBM 3270, 3299 and 5250 protocols but also general eight-bit protocols.

A simple line interface connects the BCP to the communications line. The receiver includes an on-chip analog comparator and provides a TTL-level input for added flexibility.

WE'LL GIVE YOU ALL THE SUPPORT YOU NEED

The DP8344 is backed by a development package that includes a demo/evaluation board with a monitor/debugger program, in-system emulation features, and demonstration software for complete 3270 terminal emulation on an IBM PC.

On the system level, we offer both 3270 and 5250 controller emulators and analysis tools.

Application support is available through a worldwide network of technical support centers.

For more information on the DP8344 BCP – the easy, inexpensive way for you to provide IBM connectivity – please contact your National Sales Engineer.

Or write National Semiconductor, MS 23/200, P.O. Box 58090, Santa Clara, CA 95052-8090.

 **National
Semiconductor**

Advanced
Peripherals

© 1988 National Semiconductor Corporation
BCP is a trademark of National Semiconductor Corporation.
IBM and PS/2 are registered trademarks of
International Business Machines Corporation.

Cut your losses



High current, low dropout regulators reduce power loss

Stop wasting power, space and weight. With our LT1083/84/85 positive adjustable regulator family, you'll easily achieve high current at low dropout voltage with precision performance. Low dropout voltage allows dramatic reductions in power dissipation, or increases headroom and operating flexibility. Cut heat sink sizes by 50% and enjoy lower system costs with our TO-247 and TO-220 packages.

All three regulators are pin-compatible with existing three-terminal adjustable devices. They are rated 7.5A, 5A and 3A, with a guaranteed dropout voltage of 1.5V at maximum output current. This makes them the lowest dropout regulators in their class.


Short-circuit and safe area protection are included on the chips, and these regulators don't need protection diodes. Unlike most PNP low dropout regulators where 10% or more of input current flows to ground and is wasted, our regulators

are efficient with all quiescent current flowing into the load.

This regulator trio delivers a strong array of specifications. On-chip trimming adjusts reference voltage error to less than $\pm 1\%$. Line and load regulation are 0.015% and 0.1%, respectively. Current limit trimming minimizes stress on the power source, since maximum current is well controlled. For greater reliability, all units are subjected to 100% thermal limit burn-in.

Typical applications include high efficiency voltage regulators, constant current regulators, and post regulators for switching power supplies.

Cut your losses with our triple-threat power regulator family. LT1083/84 devices are packaged in TO-3 metal cans and TO-247 plastic. The LT1085 is in TO-3 and TO-220 plastic, and all are offered in MIL-STD-883 versions. Pricing begins at \$3.70 each, in quantities of 100. For literature contact: LINEAR TECHNOLOGY CORPORATION, 1630 McCarthy Blvd., Milpitas, CA 95035. 800-637-5545.



LINEAR
TECHNOLOGY

TOUGH PRODUCTS
FOR TOUGH APPLICATIONS.

CIRCLE NO 88

DESIGN IDEAS

EDITED BY TARLTON FLEMING

Soft-start and delay protects power supply

William Andreycaak

Unitrode IC Corp, Merrimack, NH

The Fig 1 circuit governs the manner in which a switch-mode power supply returns to normal operation following a short-circuited output. (If the short remains, successive retries can produce excessive power dissipation in the supply.)

Delays inherent in a typical switcher's PWM IC, drive circuit, MOSFETs, and current-sense filter contribute to power dissipation by delaying a short-circuit shutdown. Therefore, the small propagation delay of a high-speed PWM chip such as IC₁ helps to reduce the on-time following a short. Without protection circuitry, however, the supply will continue to deliver a finite-width current pulse during each period of IC₁'s oscillator signal.

To further reduce power dissipation during retry attempts, you must minimize the pulse widths and pulse rate. You can control the pulse widths by incorporating a soft-start sequence in the control circuit. The soft-start delivers a narrow pulse to the load followed by successively wider pulses until the supply is back in operation or the short triggers another shutdown. You control the pulse rate by adjusting the R₅/C₄ time constant, thereby reducing IC₁'s power dissipation as required.

The soft-start alone may produce an unacceptably slow buildup of supply voltage, however. The Fig 1 circuit therefore introduces a restart delay of several tens or hundreds of milliseconds, which lowers the average rate of retry pulses while allowing supply voltages to rise at the turn-on rate required.




Fig 2—These waveforms show how the circuit of Fig 1 responds to repeated fault conditions.

During normal operation, the pin-8 voltage (IC₂) is high, and both transistors are off. A fault (shorted output) then shuts down the supply and produces a low level at pin 8 (Fig 2). Q₁ and Q₂ turn on in quick succession, discharging the restart-delay capacitor C₂ and the soft-start capacitor C₄. When the fault is removed pin 8 returns high and Q₁ turns off, producing the restart delay by allowing a slow recharge of C₄.

The restart delay ends and the soft-start sequence begins when Q₁'s collector voltage reaches Q₂'s turn-on threshold, about 0.5V. Q₂ turns off, which allows C₄ to charge and unclamp the error amplifier's input voltage (IC₁, pin 2). R₅ and C₄ form the soft-start time constant. The circuit can respond accurately to fault conditions lasting longer than 25 nsec.

EDN

To Vote For This Design, Circle No 748




Fig 1—Following shutdown of a PWM switching supply caused by a fault condition, this circuit eases the restart by introducing a delay followed by a soft-start sequence, in case the fault is still present.

Pulse-burst generator is programmable

David Tutlo

General Electric, Philadelphia, PA

The programmable pulse generator of **Fig 1a** loads data and produces a programmable pulse burst, time delay, or pulse width on receipt of a negative trigger edge. When the circuit is not busy (that is, when the last output event is complete and the trigger signal has returned high), it loads itself with data. It ignores data while the output is active (commencing with the first positive clock edge following a trigger edge). The alphabetically labeled waveforms in **Fig 1b** illustrate the generator's operation.

By automatically latching the received trigger edges, the circuit accepts asynchronous triggers without producing fractional pulses. The generator also adjusts to the trigger waveform's duty cycle, with the proviso that new digital data enter the counter (IC₂) only when the trigger waveform is high. IC₂ is a 4-bit binary counter; by cascading one or more of these (or the BCD-equivalent 74192 counters) you can implement any desired binary or decade modulo.




Fig 2—One application for the circuit in **Fig 1a** is to generate a programmable time interval, denoted by two negative edges.

For binary inputs representing the decimal number *N*, the output exhibits an *N*-pulse burst (replicating the clock waveform) for each negative trigger edge received. Or, you can use waveform *H* (IC₂, pin 13) as an output, obtaining a programmed interval of *N* clock periods denoted by an end-of-cycle pulse (**Fig 2**). And





Fig 1—This 2-IC circuit (a) provides a pulse burst, pulse width, or time interval that you can program with a resolution of $\pm \frac{1}{2}$ clock period. Waveforms (b) illustrate the circuit's operation.

tiny SPDT switches

absorptive... reflective



dc to 4.6 GHz from \$32⁹⁵ (1-24)

Tough enough to pass stringent MIL-STD-202 tests, useable from dc to 6GHz and smaller than most RF switches, Mini-Circuits' hermetically-sealed (reflective) KSW-2-46 and (absorptive) KSWA-2-46 offer a new, unexplored horizon of applications. Unlike pin diode switches that become ineffective below 1MHz, these GaAs switches can operate down to dc with control voltage as low as -5V, at a blinding 2ns switching speed.

Despite its extremely tiny size, only 0.185 by 0.185 by 0.06 in., these switches provide 50dB isolation (considerably higher than many larger units) and insertion loss of only 1dB. The absorptive model KSWA-2-46 exhibits a typical VSWR of 1.5 in its "OFF" state over the entire frequency range. These surface-mount units can be soldered to pc boards using conventional assembly techniques. The KSW-2-46, priced at only \$32.95, and the KSWA-2-46, at \$48.95, are the latest examples of components from Mini-Circuits with unbeatable price/performance.

Connector versions, packaged in a 1.25 x 1.25 x 0.75 in. metal case, contain five SMA connectors, including one at each control port to maintain 3n sec switching speed.

Switch fast... to Mini-Circuits' GaAs switches.

SPECIFICATIONS

	KSW-2-46 ZFSW-2-46		KSWA-2-46 ZFSA-2-46	
FREQ. RANGE	dc-4.6 GHz		dc-4.6 GHz	
INSERT. LOSS (db)	typ	max	typ	max
dc-200MHz	0.9	1.1	0.8	1.1
200-1000MHz	1.0	1.3	0.9	1.3
1-4.6GHz	1.3	1.7	1.5	2.6
ISOLATION (dB)	typ	min	typ	min
dc-200MHz	60	50	60	50
200-1000MHz	45	40	50	40
1-4.6GHz	30	23	30	25
VSWR (typ)	ON	1.3:1	1.3	
	OFF	—	1.4	
SW. SPEED (nsec)				
rise or fall time	2(typ)		3(typ)	
MAX RF INPUT (bBm)				
up to 500MHz	+17		+17	
above 500MHz	+27		+27	
CONTROL VOLT.	-5V on, OV off		-5V on, OV off	
OPER/STOR TEMP.	-55° to +125°C		-55° to +125°C	
PRICE (1-24)	\$32.95 \$72.95		\$48.95 \$88.95	

finding new ways ...
setting higher standards

Mini-Circuits

A Division of Scientific Components Corporation
P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500
Fax (718) 332-4661 Domestic and International Telexes: 6852844 or 620156

C 117 REV.B

DESIGN IDEAS

by using waveform A (IC₁, pin 4) as the output (Fig 3) you get a one-shot multivibrator, whose output is a pulse whose width is programmable. These circuits synchronize the trigger and clock signals by introducing as much as one clock period of delay, in addition to the programmed interval.

Finally, you can use the burst generator in a binary-to-BCD code converter (Fig 4). Each positive trigger pulse clears the BCD counters IC₁ and IC₂. The pulse's trailing edge causes the generator to load the 4-bit binary data and then issue a corresponding burst of N pulses, which increments the counters to the desired BCD code for N. The generator's end-of-burst pulse can flag a host processor. Again, you can expand the counters to handle larger numbers.

EDN

To Vote For This Design, Circle No 747




Fig 3—In this application, the circuit of Fig 1a serves as the digital analog of a one-shot multivibrator.




Fig 4—Connecting the Fig 1 pulse-burst generator as shown here forms a binary-to-BCD converter.

Power circuit has constant full scale

James Bryant
Analog Devices, Newbury, UK

An analog computational chip such as AD538 can easily generate the relationship

$$V_{OUT} = V_{IN}^M$$

The full-scale output V_{FS} varies considerably with M , however, for a given range of V_{IN} . You can produce a constant-full-scale output by adding a second IC (Fig 1). This circuit inserts a factor into the above equation:

$$V_{OUT} = V_{FS}^{(1-M)} V_{IN}^M$$

Note that the two equations above are numerically accurate but dimensionally incorrect. You must first normalize a voltage to a dimensionless quantity before raising it to a power—like this, for example:

$$V_{OUT} = \left(\frac{V_{IN}}{2V} \right)^M (2V)$$

(The circuit, in fact, does perform this normalization.)

Z I L O G



The highest performance and highest integration, ever. Together on a single 16-bit chip.

The Z280™ gives you a more powerful CPU and higher performance peripherals than you've ever seen on a 16-bit chip. Think of it as a complete microsystem on a chip.

Unmatched performance...

Start with the most powerful 16-bit engine available, add on-board Cache, MMU and Burst Mode memory support — and you'll begin to understand the Z280's power and potential.

...powerful on-board peripherals...

Imagine the savings in cost and board size when you have peripherals like 4 DMA channels that'll give you transfers at 6.6 Mbytes/sec, and a full-duplex UART.

...and the glue to tie it all together.

With a DRAM Controller to support up to 1 MBit DRAMs and Programmable Wait State Logic — on board — you're really looking at significant glue reduction.

	Z280™	80186	68070
Package	68-pin PLCC/CMOS	68-pin LCC/NMOS	84-pin PLCC/CHMOS
Typical Power	375 mW	2 W	800 mW (est)
Speed	10-25 MHz	8-12.5 MHz	10 MHz
Memory Support	16 Mb Physical Paged	1 Mb Physical Segmented	16 Mb Physical 8 or 128 Segments
16-bit Registers	12 General	8 General	15 Dedicated
Instruction Pre-fetch	256-Byte Assoc. Cache; Burst Mode	6-Byte Queue	None
Multiprocessor Support	Local or Global	Local only	Local only
Wait Logic	Programmable	Programmable	Hardwire
DMA	4 Channels, 6.6 Mb/s @ 10 MHz	2 Channels 2 Mb/s @ 8 MHz	2 Channels, 3.2 Mb/s @ 10 MHz
Counter/Timers	3 16-bit	3 16-bit	2 16-bit
Serial I/O	1 Full-Duplex UART	None	1 Full-Duplex UART
DRAM Controller	10-bit Refresh	None	None
Price (100)	\$33	\$43	\$50

Z280: Truly a microsystem.

The Z280 gives you a lot more performance. In a lot less board space. All off the shelf and backed by Zilog's proven quality and reliability. Plus, it's binary code-compatible with the Z80®, and priced to rival 8-bit chips. And all the development support tools you need are available from industry leaders. Contact your local Zilog sales office or your authorized distributor today. Seeing is believing. Zilog, Inc., 210 Hacienda Ave., Campbell, CA 95008 (408) 370-8000.

The choice is clear.

Right product. Right price. Right away.

ZILOG SALES OFFICES: CA (408) 370-8120, (714) 432-9971, (818) 707-2160, CO (303) 494-2905, FL (813) 585-2533, GA (404) 923-8500, IL (312) 885-8080, MA (617) 273-4222, MN (612) 831-7611, NJ (201) 288-3737, (609) 778-8070, OH (216) 447-1480, TX (214) 231-9090, **CANADA** Toronto (416) 673-0634, **ENGLAND** Maidenhead (44) (628) 781227, **W. GERMANY** Munich (49) (89) 612-6046, **JAPAN** Tokyo (81) (3) 587-0528, **HONG KONG** Kowloon (852) (3) 723-8979, **R.O.C.:** Taiwan (886) (2) 731-2420, **U.S. AND CANADA DISTRIBUTORS:** Anthem Electric, Bell Indus., Graham Elec., Hall-Mark Elec., JAN Devices Inc., Lionex Corp., Schweber Elec., Western Microtech., **CANADA** Future Elec., SEMAD.

Zilog
an affiliate of
EXXON Corporation

DESIGN IDEAS

Each IC has the transfer function $V_{OUT}=Y(Z/X)^M$, where X, Y, and Z are inputs (pins 15, 10, and 2). IC₂ applies $V_{FS}(2V/V_{FS})^M$ to the Y input (pin 10) of IC₁, which completes the desired expression by adding the factor $(V_{IN}/2V)^M$. Potentiometer R₃ lets you set V_{FS} in the range 2 to 10V. (You can obtain V_{FS}=10V by simply opening the connection to pin 5; R₃ and R₄ are unnecessary in that case.)

The ganged potentiometers R_{5A} and R_{5B} let you set the power M . The maximum value for M depends on the common value chosen for R_3 and R_4 :

$$M_{MAX} = \frac{R_3 + 200}{R_3}.$$

$$M_{\text{MIN}} = \frac{100M_{\text{MAX}}}{R_5 + 100}.$$

For a given circuit, you get the maximum M value by turning R_5 to zero resistance. You get the minimum M ($M_{\text{MAX}} \div 21$) by turning R_5 to its maximum value of 2 k Ω . The accuracy of your chosen V_{FS} value depends on the matching between R_5 sections A and B. For many applications, 1%-tolerance sections are satisfactory. The circuit can handle signal frequencies as high as several tens of kilohertz, provided that V_{IN} remains positive.

EDN

EDN

M_{MIN} depends on M_{MAX} and the common value of the R_5 potentiometer sections:

To Vote For This Design, Circle No 746




Fig 1—This circuit raises V_{IN} to a power M set by the potentiometer R_5 . You set V_{OUT} 's full-scale value by adjusting R_1 .

DSP Development Cut through the clutter.



INMOS and IMS are trademarks of the INMOS Group of Companies.

You've seen the advantages offered by the A100 Digital Signal Processor. The single-chip DSP solution that features 32 multiply-accumulators, executes up to 320 MOPs, and easily attaches to microprocessors.

Now INMOS speeds A100 system development with the new D704, the complete DSP Development System. The D704 overcomes the clutter normally encountered in developing DSP systems such as hand-crafted assemblers, interleaved busses and power-hungry glue. And since it is tailored for the A100, your end product is first to market and second-to-none in performance.

The D704 combines a comprehensive set of software tools, PC plug-in card and extensive documentation, providing a powerful yet easy-to-use DSP environment. You can experiment with the technology, simulate DSP algorithms in software and run them in real time on the A100's provided on the board.

The A100 is quickly becoming the number one choice in everything from avionics to ultrasonics. And with MIL-STD 883C devices available soon, it will be a natural for military DSP programs of all types. With the D704 Development System, creating DSP solutions has never been easier.

So if you'd like to cut through the clutter, start by clipping the coupon.

THE A100 DSP FAMILY

IMS A100	Single-Chip 32-Stage Cascadable Transversal Filter—16-Bit Data, 16-Bit Coefficients, 320 MOPs
IMS B009	PC Plug-In Card Including Four A100's
IMS D704	IMS B009 + Interactive Software Simulator/ DSP Development Suite



I'd like to cut through the clutter. Please send me full details of the IMS D704 DSP development system.

Name _____ Title _____

Company _____

Address _____

Telephone _____

EDN 020488

INMOS Corporation, PO Box 16000, Colorado Springs, Colorado 80935.
Tel (303) 630-4000.

INMOS Limited, PO Box 424, Bristol BS99 7DD. Tel (0454) 616616.

Switched signal powers analog switch

Jack Armijos
Siliconix Inc, Santa Clara, CA

The analog switch IC_1 in **Fig 1** can derive power from its input signal during power outages, provided the input signal amplitude exceeds 4V and its frequency exceeds 1 kHz. For normal operation, the supply voltage (V^+) is 12V, and you apply 5V at V_L for TTL compatibility. With these voltages present, a logic low at IN_2 closes the switch and produces a 45 Ω on-resistance.

If V_L and V^+ are lost, the switch becomes a guest of the signal source and draws power from it. Typical CMOS switches can be destroyed under these conditions, but blocking diodes D_1 and D_2 prevent the chip from drawing excessive current from the source.

A positive input pulse turns on the clamping diode D_3 and charges C_1 . Charge on C_1 powers the chip; opera-




Fig 1—If this analog-switch circuit loses V_L and V^+ voltage, it will draw power from the signal source instead.




Fig 2—These waveforms show that the **Fig 1** circuit passes TTL waveforms even when the power is removed. The data input must have at least a 4V amplitude and a 1-kHz repetition rate.

tion is satisfactory because the chip requires less than 1 μ A of supply current. Loading of the signal source is imperceptible (**Fig 2**). Switch resistance is a respectable 100 Ω for this mode of operation.

Pullup resistor R_2 restores the output level for TTL data. If TTL control is lost, the pulldown resistor R_3 ensures that the switch will remain closed. IC_1 contains two normally closed switches and two normally open switches, so you can also configure a switch that opens when the control is lost. Either circuit requires inverted logic and handles data rates from 1 kHz to 1 MHz.

EDN

To Vote For This Design, Circle No 749


Zero-current sensor protects relay contacts

B Erik Valeur
Electronic Instrument & Specialty Corp,
Stoneham, MA

The **Fig 1** circuit extends the life of a reed relay by allowing the relay's contacts to open only at moments of

zero current. (Destructive arcing can cause rapid contact wear if the contacts open repeatedly while conducting current.) Unlike zero-crossing circuits that predict the zero-current moment, this circuit senses that condition and responds immediately, using a fast relay (K_1 , 100 μ sec).

WE'LL SHOW YOU WHAT NO ONE HAS EVER SEEN BEFORE



AND WE'LL COLOR IT, TOO!

With A 3 Hz Filter That Provides A New Industry Standard Of Resolution For Close-In Performance...

The user friendly Marconi Model 2383, 100 Hz to 4.2 GHz Spectrum Analyzer with built-in tracking generator establishes a new standard of high accuracy, resolution and stability of measurements. The automatic self calibration routine provides exceptional RF level accuracy of ± 1.5 dB at 4.2 GHz from

+ 27 dBm to - 130 dBm. Close-in performance is unmatched with a 3 Hz filter and 1 Hz frequency resolution.



4.2 GHz Spectrum Analyzer-Model 2383

With numerous high performance display functions, dynamic trace, limits memory, RGB drive, GPIB, plus limits masking. The 2383 is at your command for demanding spectral analysis requirements.

For a demonstration or details contact: Marconi Instruments, 3 Pearl Ct., Allendale, NJ 07401.
• (800) 233-2955 • (201) 934-9050
• In Canada (514) 341-7630

Marconi
Instruments



Design Entry Blank

\$75 Cash Award for all entries selected by editors. An additional **\$100 Cash Award** for the winning design of each issue, determined by vote of readers. Additional **\$1500 Cash Award** for annual Grand Prize Design, selected among biweekly winners by vote of editors.

To: Design Ideas Editor, EDN Magazine
Cahners Publishing Co
275 Washington St, Newton, MA 02158

I hereby submit my Design Ideas entry.

Name _____

Title _____ Phone _____

Company _____

Division (if any) _____

Street _____

City _____ State _____ Zip _____

Design Title _____

Home Address _____

Social Security Number _____
(Must accompany all Design Ideas submitted by US authors)

Entry blank must accompany all entries. Design entered must be submitted exclusively to EDN, must be original with author(s), must not have been previously published (limited-distribution house organs excepted), and must have been constructed and tested.

Exclusive publishing rights remain with Cahners Publishing Co unless entry is returned to author or editor gives written permission for publication elsewhere.

In submitting my entry, I agree to abide by the rules of the Design Ideas Program.

Signed _____

Date _____

Your vote determines this issue's winner. All designs published win \$75 cash. All issue winners receive an additional \$100 and become eligible for the annual \$1500 Grand Prize. **Vote now**, by circling the appropriate number on the reader inquiry card.

ISSUE WINNER

The winning Design Idea for the October 29, 1987, issue is entitled "Debouncer for spdt switches uses few parts," submitted by Mounir Boukadoum of the University of Quebec at Montreal (Quebec, Canada).




Fig 1—You control this power circuit by operating the S_1 switch; the diodes and the optoisolator prevent a response in the relay except when the relay contacts' current is near zero.

The on/off switch S_1 controls the application of V_{SUPPLY} to the load by controlling K_1 . Load current biases one of the diode pairs on, which in turn activates one of two LEDs in the optocoupler. This action turns on the phototransistor, ensuring that the relay remains closed while load current is flowing regardless of the state of S_1 .

Conventional 60-Hz ac current, however, goes through zero twice per cycle, about every 8 msec. At that time the phototransistor turns off, and (if you have opened S_1) K_1 opens, at or near the moment of zero current. Resistor R_1 limits the LED current if necessary. (No limit is required in this circuit, which can handle one or two amperes.) Similarly, the zener diode D_1 protects the opto device by clamping the relay's flyback voltage (the zener's breakdown should be about $4\times$ the coil voltage). D_1 isn't required with the components shown.

This type of circuit can extend a relay's life by several orders of magnitude while handling contact currents at least $2\times$ that rated for the relay. The circuit shown, for example, ran for 40 or 50 million operations with little evidence of wear and no signs of contact breakdown.


EDN

To Vote For This Design, Circle No 750



FLASH OF BRILLIANCE

Tri-Color Excellence in a T1 size from the World Leader in High-Efficiency LEDs.



Actual size

For performance superiority, space saving design and packaging selection, Data Display's tri-color LEDs are your brilliant choice. As high-intensity red, green and amber light indicators, their quality and reliability clearly shine through in a T1 package.

The tri-color LED light output is a good 21 MCD with wavelengths of 635 for red and 565 green. A milky diffused package provides an extra wide viewing angle. Also, you're designing in the dependability and competitive pricing you can expect from a world leader in LEDs.

Save Space. Two LEDs in One Package.

All of our tri-color LEDs use a bright idea to improve your high density packing. The T1 size has 2 LED chips in the same small package. Two-terminal operation gives red (DC +), green (DC -), and amber (AC) with current of 20mA.

Also having the same two-terminal operation features is a larger T1 $\frac{3}{4}$ size. It's ideal for lens illumination. Another T1 $\frac{3}{4}$ size has three-terminal operation with a common cathode.

Choice of Packages. Shining Support.

Data Display has a network of sales representatives and distributors to get you the quantities you want. Our complete line of LEDs includes a variety of packaging options—from PCB mounts including our new variable array to panel lights available with or without lenses. And we also provide engineering support.

Make the brilliant choice. Call Data Display, TOLL FREE (800) 421-6815. Within California, call (213) 640-0442. Free catalog.



**DATA
DISPLAY
PRODUCTS**

Your Brilliant Choice

P.O. Box 91072, Los Angeles, CA 90009
(213) 640-0442, TELEX 664-690, FAX 213-640-7639

INTERNATIONAL REPS: Argentina YEL SRL, PH: 541 46 2211, TLX: 390 18605 - Australia Ampec, PH: 6893522, TLX: 790 127136 AMPEC, FAX: 612 6335448 - Belgium/Holland Klaasing Eic, PH: 01620 81600, TLX: 844 54598 KLBDNL, FAX: 0162056500 - Denmark Radio Parts, PH: 01 333311, TLX: 855 19613 RPARTDK - France A Jahnichen, PH: 387 59 09, TLX: 842290714, FAX: 011311-4387-3319 - Israel R.C.M. Computers, PH: 03 476225, TLX: 922 341390 IL, FAX: 011-972-491942 - Italy Microdata, PH: 0187 988182, TLX: 8432 72070 - South Africa Liberty Elec., PH: 52 7637/8/9, TLX: 960 867325A SA - Spain Betatron, PH: 6942511, TLX: 831 23911 PCOE - United Kingdom Marl Int'l, PH: 0229 52430, TLX: 851 65100 MARLG, FAX: 0229-55155 - West Germany/Austria Kuhn GmbH, PH: 06235 5662, TLX: 841 464766 KUHN, FAX: 0623581955

*Cosette Trautman-Scheiber
Marketing Manager
SMT Plus, Inc.
San Jose, CA*

"In the Product Mart sections of EDN magazine and EDN NEWS."

"I recommend EDN magazine and EDN NEWS. They are the right vehicles for getting our message to the market."

g?
magazine
product
we get the
our bucks!
azine and
reach our
with out-
results and
money.
uct Mart
generated
me, high-
les leads.
mend EDN
and EDN
they are the
cles for
ur message
rket."



"EDN MAGAZINE HAS BEEN A CONSISTENT WINNER FOR THE SGS BRIGHTER POWER CAMPAIGN."

Daniel Queyssac
President
SGS Semiconductor Corporation

As president of SGS Semiconductor Corporation, Daniel Queyssac set a goal of establishing SGS as a leader in power MOS and an innovator in smart power devices. The Brighter Power campaign was created to help get the job done.

To insure that the right audience — design engineers — would get the message, SGS needed the right vehicle. For Queyssac, EDN was the logical choice. "It had performed very well for SGS in the past," says Queyssac, "so, naturally, we expected good results."

"EDN's pulling power exceeded our expectations. In fact, our Brighter Power ads drew inquiries in record numbers."

"EDN will remain at the top of the SGS media list simply because it works."



Advertising in EDN magazine works for
SGS Corporation. It can work for you.

EDN

Where Advertising Works

Switch with Liton

20-1,000W-Meets FCC, UL, CSA, TUV and VDE standards



Taiwan Liton Electronic Co., Ltd. produces a greater range of high-performance switching power supplies than most any other manufacturer anywhere: 20-1,000W. By customizing cost-saving standard models with an alternative component or two, available SPS configurations run into the thousands. Design and production fully meets FCC class "B", UL, CSA TUV and VDE standards. Applications include PCs and workstations, telecommunications equipment, as well as OA equipment like facsimile machines, copiers and printers. PC models are electrically as



well as physically IBM PC/AT PC/XT compatible and are full power rated and wired for hard-disk or tape drives, as well as other peripherals. We've built our reputation with top-quality components. With gigantic facilities and modern equipment, we design and manufacture computer and communications products which meet the highest international quality control and performance standards. Our R&D customizes a standard model or generates a 100% original design in a lead time worth switching for!

Taiwan Liton Electronic Co., Ltd.

12th Fl., 25 Tunhwa S. Rd., Taipei, Taiwan, ROC

Tel: (02) 771-4321/8 Fax: 886-2-751-1962 Tlx: 24514/20211 TWLITON

*IBM PC/AT and PC/XT are trademarks of the International Business Machines Corp.
CIRCLE NO 67

NEW PRODUCTS

COMPONENTS & POWER SUPPLIES

CLOCK BATTERIES

- Maintain power to clock chip when computer is turned off
- 2- to 4-year lifetime

The Model 843 and 844 batteries utilize a 4.5V, 1-Ahr alkaline system and replace the lithium battery that comes with all IBM PC/AT computers. These clock batteries maintain power to the clock chip when the computer is turned off. The batteries also maintain the memory of the chip to prevent loss of the computer's system-configuration information. The 844 features a 4-pin termination that lets it directly replace the original lithium battery in most 80286- and 80386-based systems. The 843 comes in a 3-pin configuration. Unlike the 6.0V OEM lithium batteries, the 843 and 844 employ no internal voltage-dropping resistors.




Thus, they have a lifetime spec of two to four years. \$11.

Rayovac Corp, 601 Rayovac Dr,

Madison, WI 53711. Phone (608) 275-3340. TLX 190428.

Circle No 351



SENSOR


- Designed to measure heat losses from any solid surface
- Temperature-independent operation

Essentially a metabolic rate indicator for inanimate systems, the Model MS-175 thermoelectric sensor is a flat-plate transducer that measures heat losses from any solid surface. When mounted on a motor housing, it can intercept a small fraction of the heat flow and thereby generate an electrical signal that's proportional to the local heat flux. Under normal load conditions, the transducer can deliver a steady-state signal that's independent of

either the ambient or the operating temperature. High steady-state signals indicate inefficiency or incipient failure. You can read out sensor output signals on any millivolt recorder, potentiometer, or data logger. \$125.

ITI Co, Box 309, Del Mar, CA 92014. Phone (619) 755-4436.

Circle No 352



POWER SUPPLIES

- Have wide-range input capability
- Feature 300,000-hour MTBF


PY Series single-output, open-frame switching power supplies feature a 300,000-hour MTBF rating. The supplies have an 85 to 132V ac input range and are available with 5, 12, 15, and 24V outputs. The family includes models with power outputs of 15 to 50W. Each model features inrush current limiting and overvoltage protection. All but the

15W models come with overcurrent protection as a standard feature. Each supply has a 70% min efficiency rating, a 16- μ sec min holdup time, and $\pm 3\%$ regulation. The supplies' internal noise filters meet FCC B-Class requirements, and they provide full-load ratings at temperatures as high as 50°C. \$28 to \$46 (100). Delivery, four to six weeks ARO.

Shindengen America, 2649 Townsgate Rd, #200, Westlake Village, CA 91361. Phone (805) 373-1130.

Circle No 353

CADDOCK's Precision and Ultra-Precision Resistor Networks provide a designer's choice of performance that will optimize solutions in precision analog circuit designs.




Precision and Ultra-Precision Resistor 'Pairs' and 'Quads' deliver a selection of Ratio Tolerance to as tight as $\pm 0.01\%$ and Ratio Temperature Coefficient to 2 PPM/ $^{\circ}\text{C}$ combined with exceptional long-term stability.

Standard Type T912 and T914 Precision and Ultra-Precision Resistor Networks.

Standard models of the Type T912/T914 Precision and Ultra-Precision Resistor Networks combine all of these performance characteristics:

- **Absolute Tolerance:** 0.1% for all resistors.
- **Ratio Tolerances:** 0.1%, 0.05%, 0.02% and 0.01%
- **Ratio Temperature Coefficients:** from 10 PPM/ $^{\circ}\text{C}$ to 2 PPM/ $^{\circ}\text{C}$.
- **Absolute Temperature Coefficient:** 25 PPM/ $^{\circ}\text{C}$ from 0°C to $+70^{\circ}\text{C}$.
- **Ratio Stability of Resistance at Full Load for 2000 Hours:** within 0.01%.
- **Shelf Life Stability of Ratio for Six Months:** within 0.005%.

The standard part number below provides a selection of over 500 in-production models of Type T912/T914 precision and ultra-precision 'pairs' and 'quads':





Custom Type T912 and T914 Precision and Ultra-Precision Resistor Networks.

Custom models of these precision 'pairs' and 'quads' can include these special performance features:

- **Resistance Values:** from 1K to 2 Megohms with maximum ratios of 250-to-1.
- **Absolute TC:** as low as 15 PPM/ $^{\circ}\text{C}$.
- **Ratio TC:** as low as 2 PPM/ $^{\circ}\text{C}$.

• For Type T912/T914 data, circle Number 201.



Precision Decade Resistor Voltage Dividers and Current Shunt Resistor Networks deliver many optimum combinations of precision and temperature coefficient performance for high accuracy range-switching circuitry.



Standard Type 1776 Precision Decade Resistor Voltage Divider Networks.

The Type 1776 Precision Decade Resistor Voltage Dividers provide a family of networks that includes 3, 4 and 5-decade voltage dividers with ratios from 10:1 to 10,000:1. Standard performance includes a wide range of specifications in particular combinations that meet the most often requested requirements.

- **Absolute Tolerances:** from 0.25% to 0.1%.
- **Ratio Tolerances:** 0.25%, 0.1% or 0.05%.
- **Absolute TC:** from 50 PPM/ $^{\circ}\text{C}$ to 25 PPM/ $^{\circ}\text{C}$.
- **Ratio TC:** from 50 PPM/ $^{\circ}\text{C}$ to 5 PPM/ $^{\circ}\text{C}$.
- **Voltage Coefficient:** As low as 0.02 PPM/Volt.

With 36 standard models to choose from, each circuit designer can specify the exact levels of performance required by each application.

- For Type 1776 data, circle Number 202.




Standard Type 1787 Precision Current Shunt Resistor Networks.

The Type 1787 Current Shunt Resistor Networks achieve the combination of performance requirements necessary to meet the demands of precision current measurement circuits, including laboratory and bench-type instrumentation:

- **Resistance Values:** 1 ohm, 10 ohms, 100 ohms and 1000 ohms.
- **Absolute Tolerances:** 0.25%, 0.1% or 0.05%.
- **Absolute TCs:** 100 PPM/ $^{\circ}\text{C}$, 80 PPM/ $^{\circ}\text{C}$ or 50 PPM/ $^{\circ}\text{C}$.

There are now 12 standard models of the Type 1787 Current Shunt Resistor Networks available for 3 and 4-decade applications, and prototype quantities of many models are normally available from factory stock.

- For Type 1787 data, circle Number 203.



Caddock's new 28-page General Catalog describes over 200 models of both standard and custom precision and ultra-precision resistors and resistor networks. For your personal copy, call or write our main offices at - Caddock Electronics, Inc., 1717 Chicago Avenue, Riverside, California 92507 • Phone (714) 788-1700 • TWX: 910-332-6108

CADDOCK

HIGH PERFORMANCE FILM RESISTORS

COMPONENTS & POWER SUPPLIES


COUPLER

- Requires no external power
- Converts current to isolated output voltage

The TLP590/591 photovoltaic coupler converts the current output from a TTL device to electrically isolated output voltage. It converts electrical signals to light by using a GaAs infrared LED. A series-connected photodiode array receives this light and generates a photovoltage. Because the driving circuit is completely isolated from the control-signal circuits, you can use this photovoltage to drive power MOSFETs. The photovoltaic coupler provides enough voltage for direct MOSFET gate drive and thus requires no external power supply. \$2 (1000). Delivery, 12 weeks ARO.

Toshiba America Inc., Semiconductor Products Div, 2692 Dow Ave, Tustin, CA 92680. Phone (714) 832-6300.

Circle No 354



POWER SUPPLIES

- $\pm 0.05\%$ line regulation
- 120,000- to 460,000-hour MTBF

The Olympian Series linear power supplies feature calculated MTBF ratings of 120,000 to 460,000 hours. These international units are rated from 6 to 115W and conform to UL, IEC, CSA, and VDE requirements. With jumpers, they can accommodate ac inputs ranging from 100 to 240V. Standard features include line regulation of $\pm 0.05\%$ for a 10% line change, load regulation of $\pm 0.05\%$ for a 50% load change, short-circuit and overload protec-

tion, and remote sensing. \$29.50 to \$108 (25).

Tamura Corp of America, 1150 Dominguez St, Carson, CA 90746. Phone (213) 638-1790. TLX 664759.

Circle No 355



DC/DC CONVERTERS

- Provide 15W single, dual, or triple outputs
- Have 0.33-in. mounting height

PKC-Series In-Card pc-board mounting, 15W dc/dc converters come in single-, dual-, or triple-output versions, and have 500V dc input to output isolation. The converters provide outputs of 5, 12, or 15V and are available for operation from 18 to 36V, or 36 to 72V inputs. Output voltage accuracy on triple-output versions is $\pm 2.5\%$ on all outputs. Their operating temperature range is -45 to $+85^\circ\text{C}$, and their MTBF is in excess of 200 years. Each converter comes in a $3.15 \times 2.17 \times 0.42$ -in. package; however, its pins let you mount the package in a cutout in the pc board, thus reducing the mounting height to 0.33 in. This mounting height lets you position adjacent pc boards on a 0.6-in. (3TE) spacing. The supplies are pin compatible with the vendor's PKA Series converters. 5V, single-output version, approximately £40 (100).

Rifa AB, Power Products Div, 16381 Stockholm, Sweden. Phone (8) 757-5000. TLX 10948.


Circle No 356

Rifa Inc., Greenwich Office Park 3, Greenwich, CT 06836. Phone (203) 625-7300.

Circle No 357

Your Custom Precision and Ultra-Precision Resistor Networks from Caddock:

- Can be delivered in only 6 weeks ARO
- With total NRE charges typically under \$950⁰⁰
- Includes 10 prototype networks for your in-circuit evaluation.
- Thin-Profile, Single-In-Line package design.




Type T1794 Custom Low TC Precision and Ultra-Precision SIP Resistor Networks.

Caddock's Tetrinox® resistance films provide a wide choice of Absolute TCs, Ratio TCs and precision tolerance specifications. Select the performance of your custom network from the following:

- Resistance Values: from 500 ohms to 50 Megs.
- Absolute Tolerances: 1.0%, 0.50%, 0.25%, 0.20%, 0.10%, 0.05% and 0.025%.
- Ratio Tolerances: 1.0%, 0.50%, 0.25%, 0.20%, 0.10%, 0.05% and 0.025%.
- Absolute Temperature Coefficients: 50 PPM/ $^\circ\text{C}$, 25 PPM/ $^\circ\text{C}$ and 15 PPM/ $^\circ\text{C}$ from 0°C to $+70^\circ\text{C}$.
- Ratio Temperature Coefficients: 50 PPM/ $^\circ\text{C}$, 25 PPM/ $^\circ\text{C}$, 10 PPM/ $^\circ\text{C}$ and 5 PPM/ $^\circ\text{C}$ from 0°C to $+70^\circ\text{C}$.
- For Type T1794 information, circle Number 204.

Type 1789 Custom Low Resistance Value Precision SIP Resistor Networks.



Using Caddock's Micronox® resistance films, your low resistance custom networks can now include:


- Resistance Values: from 0.5 ohms to 10,000 ohms.
- Absolute Tolerances: 1.0%, 0.50%, 0.25%, 0.20%, 0.10% and 0.05%.
- Ratio Tolerances: 1.0%, 0.50%, 0.25%, 0.20%, 0.10% and 0.05%.
- Absolute Temperature Coefficients: 100 PPM/ $^\circ\text{C}$, 80 PPM/ $^\circ\text{C}$ and 50 PPM/ $^\circ\text{C}$ from 0°C to $+70^\circ\text{C}$.
- Ratio Temperature Coefficients: 80 PPM/ $^\circ\text{C}$, 50 PPM/ $^\circ\text{C}$, 25 PPM/ $^\circ\text{C}$ and 15 PPM/ $^\circ\text{C}$ from 0°C to $+70^\circ\text{C}$.
- For Type 1789 information, circle Number 205.

Caddock's high thru-put manufacturing capabilities provide cost-effective, on-time delivery of your custom resistor network requirements. Custom network designs are now in-production in quantities from 500 networks per year to as high as 500,000 networks per year.

For fast solutions to your custom resistor network needs, call our Applications Engineers at Telephone No. (714) 788-1700.

CADDOCK
HIGH PERFORMANCE FILM RESISTORS

High-Performance IEEE-488 Solutions



for your
IBM PS/2

COMPARE THESE BENEFITS

- Runs on Personal System/2 models 50, 60, and 80 (Micro Channel™)
- Most extensive software library – program in the language of your choice
- Highest performance available – up to 1M bytes/sec data transfer rate using NI Turbo488™ gate array
- ON SRQ interrupt response
- Applications Monitor – real-time error checking and program tracing with pop-up windows
- Best price/performance
- **FREE** technical support with toll free telephone service
- 30-day money back guarantee
- 2-year warranty




**NATIONAL
INSTRUMENTS™**

The Leader in IEEE-488

12109 Technology Blvd.
Austin, Texas • 78727-6204

CALL FOR FREE CATALOG
800/531-4742 • 512/250-9119

COMPONENTS & POWER SUPPLIES



POWER SUPPLY

- *Designed to power disk drives*
- *Rated for 400W*

The QX-11 switching power supply is meant for applications that include several 500M-byte disk drives. The fan-cooled power supply is housed in a 5×3.4×13.5-in. chassis and provides three fully regulated outputs. The supply is rated at 400W and sustains 575W peak for 10 sec. The supply features a 0 to 50°C ambient-temperature operating range; an input surge-current limit; brownout protection; jumpers for 115/230V ac operation; and complete overload, overvoltage, and reverse-voltage protection. The supply has a typical efficiency of 75% and a holdup time of 20 msec. You can obtain remote on/off control and thermal shutdown as options. \$349 (100).

Cherokee International Inc., 2841 Dow Ave, Tustin, CA 92680. Phone (714) 544-6665. TWX 510-101-0493.

Circle No 358

DIODE RECTIFIERS


- *Feature high efficiency*
- *Deliver 44A outputs*

The 40CPQ050 and 40CPQ060 dual-die, center-tapped, Schottky-diode rectifiers have repetitive peak reverse-voltage ratings of 50 and 60V, respectively. Housed in TO-3P packages, the devices handle 44A and are highly efficient—their forward drop/junction measures only 0.63V at 25°C. The units come configured with two anode input pins and have one cathode center-tapped

output pin integrated with the base plate. Each device has a nonrepetitive surge-current rating of 525A, a peak reverse-current rating of 25A (at $T_J=25^\circ\text{C}$), a junction-to-case thermal resistance of 0.6°C/W, and an operating junction-temperature range of -40 to $+125^\circ\text{C}$. 40CPQ050, \$6.41 (100); 40CPQ060, \$6.58. Delivery, eight weeks ARO.

International Rectifier Corp., 233 Kansas St, El Segundo, CA 90245. Phone (213) 607-8837.

Circle No 359




DATA LINKS

- *Feature pin-selectable inputs and outputs*
- *Single-supply operation*

The Series 5660 analog fiber-optic data links consist of a transmitter, a receiver, and a 50m cable. The transmitter and receiver are housed in 24-pin dual-in-line packages. Pertinent specs include a 10-kHz bandwidth, $\pm 0.025\%$ FS linearity, an 80-dB signal-to-noise ratio, and a 100-ppm/°C temperature coefficient. Transmitter and receiver full-scale input and output voltages are pin-selectable for 0 to 1, 0 to 2, ± 5 , and $\pm 1\text{V}$. The transmitter and receiver modules operate from a single supply of 11.5 to 20V. The receiver includes a 3-pole, active lowpass filter, which you can bypass to suit your application. \$200. Delivery, six to eight weeks ARO.

Dymec Inc., 8 Lowell Ave, Winchester, MA 01890. Phone (800) 225-1151; in MA, (617) 729-7870. TWX 710-348-6596.

Circle No 360



4 REASONS TO SPECIFY BELDEN FOR YOUR GOVERNMENT AND MILITARY APPLICATIONS

Selection. We offer a broad line of electronic wire and cable designed to meet military specifications such as MIL C 17, MIL C 49055, MIL W 16878, MIL W 22759 and others. Many are QPL listed.

From fiber optic cable to multi-conductor and high

temperature cables, choose the cable best suited to your specific application. Or work with our Product Engineering Group to design specialty cable to your exact requirements.

Belden Innovation.

We're a leading innovator in shielding technology and patented testing methods. Our shielding is designed to meet the highest performance standards in the industry—including military TEMPEST requirements. To make your cable decision easier, we provide you with all the test data necessary to choose the proper and most cost-efficient shield for your application. We also offer a variety of insulations and jacketing materials designed to provide superior performance under hostile environmental conditions. Critical application requirements are not a problem

when you
work with
Belden.



Quality and Reliability.

After working with governmental and military applications for over 30 years, we understand the interrelationship of quality components and critical requirements. We believe quality is the responsibility of leadership. That's why our Quality Assurance Department has full authority to maintain high quality standards for our

products. And we use patented testing methods to guarantee our product reliability. Choosing Belden means choosing high quality, reliable products.



The Belden Government

Department. Since we understand how the government and prime contractors work, we provide you with full support services—from sales and engineering support to contract administration. We're ready to help with your design decisions where and when you need us.

To make your design project easier, call us for technical assistance. Because when you specify Belden, *There is no equal.*

Contact the Belden Wire and Cable Government Department today. P.O. Box 1980, Richmond, IN 47375.

Phone: 1-800-BELDEN-4

(In Indiana, call 317/983-5200)

There is no equal.™

CIRCLE NO 46

SEE OUR CATALOG IN EEM


Copyright © 1986, 1987 Cooper Industries, Inc.



BELDEN

THE PROVEN PERFORMERS FOR 40 YEARS!


JANCO ROTARY SWITCHES




MINIATURE

**MIL SPEC
QPL**


MIL-S-3786
and
MIL-S-22710




MICRO-
MINIATURE



PUSHBUTTON
ROTARY



POWER




PRINTED CIRCUIT

Janco
AN ESOP CORP.

3111 Winona Avenue, Burbank, CA 91504
(818) 846-1800 • TWX: 910 4982701

COMPONENTS & POWER SUPPLIES



PROTOTYPE PANEL

- Features 4-layer construction
- Includes area for PGA devices

The 8136-VME940-03D is a 9U×400-mm wire-wrappable panel for use in VME Bus applications. It features 4-layer construction—two full ground planes and two full V_{CC} planes—that maximizes power distribution. Integral surface-mounted decoupling capacitors increase distributed capacitance and decrease overall impedance, making the panel compatible with high-speed logic devices. The panel accommodates as many as 595 16-pin DIPs when you also use the PGA (pin-grid array) areas for the ICs. The PGA areas withstand the high power dissipation that is typical of devices in PGA packages. \$1583.

Augat Inc, Box 1037, Attleboro, MA 02703. Phone (617) 222-2202. TWX 710-391-0644.

Circle No 361

VF DISPLAY MODULE

- For harsh environments
- Features single-supply operation

The 31098-99 is a shock-mounted, ruggedized 6-line×40-character vacuum fluorescent (VF) display module for use in applications that require high tolerance to shock and vibration. The display operates over a -40 to +85°C temperature range and features 5.05-mm-high, 5×7-dot-matrix, blue-green characters. The module operates from a 5V supply. Its internal μP controls all display functions and easily in-

terfaces to an 8-bit parallel TTL-compatible ASCII data bus. The module displays the complete 96-character ASCII font set, as well as ECMA (European Computer Manufacturers Association) characters and scientific symbols. It can also display user-defined fonts, which you can download with software. \$4256 (10). Delivery, six to eight weeks ARO.

IEE Inc, Industrial Products Div, 7740 Lemona Ave, Van Nuys, CA 91409. Phone (818) 787-0311, ext. 418. TLX 4720556.

Circle No 362



DC/DC CONVERTERS

- Are compatible with 0.5-in. board-spacing applications
- Feature 0.02% line and load regulation

The 4.5W Model 5D12.185 and Model 5D15.150 converters operate from 5V inputs and deliver $\pm 12V$ at ± 185 mA and $\pm 15V$ at ± 150 mA, respectively. Measuring only 2×2×0.375-in., they are compatible with applications involving boards separated by 0.5 in. The converters' key specifications include 0.02% line and load regulation; 10-mV p-p output noise; 0.3%/1000-hour long-term output stability; 500V dc isolation; 60% min efficiency; and 8-hour min short-circuit protection. The converters also furnish a 6-side shielded case and an LC filter that minimizes the amount of current noise that feeds back into the power bus. Their operating range spans -25 to +80°C. \$105.

Calex Mfg Co Inc, 3355 Vincent Rd, Pleasant Hill, CA 94523. Phone (415) 932-3911. TLX 269888.

Circle No 363




Off-The-Shelf Rocker Switches To Fit Your Design Parameters

Oak rocker switches are available in an assortment of designs, colors, sizes and styles to retrofit most existing design parameters. These attractive and highly-reliable switches are available in single or double pole, lighted, non-lighted or LED varieties. Choose from 6 standard colors and 9 profiles. Quick Connect terminations are standard, with other terminations available.

Oak rocker switches' off-the-shelf capability ensures prompt delivery. UL and CSA approved. Most have VDE, BEAB and SECV approval.

Contact: Oak Switch Systems Inc.
P.O. Box 517
Crystal Lake, IL 60014
Phone: 815/459-5000

Circle 110 for Literature Circle 149 for Sales Call



Lighted Pushbutton Switches Meet Military, Commercial Specifications

Oak's Optolite lighted pushbutton switches and indicators are available in a wide variety of sizes to meet most design requirements. They feature nine custom colors, eleven pushbutton styles, custom legends including dual lamp/split legends, and choice of mounting options.

A wide range of electrical ratings (dry circuit to 15 amps) and contact configurations are available in both alternate and momentary operation with up to 10 million duty cycles. The switches are UL, CSA listed and many are available with international approvals.

Contact: Oak Switch Systems Inc.
P.O. Box 517
Crystal Lake, IL 60014
Phone: 815/459-5000

Circle 111 for Literature Circle 150 for Sales Call

Standard and Custom Solenoids For Almost All Circuit Designs

Oak Switch System's extensive line of rotary and linear solenoids include box frame, tubular, flat pack, and rotary selector. All are engineered and manufactured to meet stringent quality standards.

Oak has standard solenoids for virtually any force/stroke requirement. Oak engineers will also custom design rotary or linear solenoids to meet client specifications.

Contact: Oak Switch Systems Inc.
P.O. Box 517
Crystal Lake, IL 60014
Phone: 815/459-5000

Circle 113 for Literature Circle 152 for Sales Call



What you can't see is the experience.

Go ahead, look closely. Oak Micromotion membrane switch panels invite your rigorous inspection. From every angle, the quality is apparent. Colors are crisp, clean, and to your specifications. Graphics are exact. Options such as texture, LED's and tactile feel are just as you require.

And while you can feel the quality, you can't see Oak's more than 50 years of switch manufacturing experience. But you can sense it from the moment you call. You immediately know you're talking with professionals, people who know the demands of industrial and commercial environments.

Take a good look at Oak Micromotion membrane switch panels. You'll see high reliability, unlimited graphic design options, competitive prices and fast delivery. You might not see the experience, but the quality tells you it's there.




OAK Switch Systems Inc.
P.O. Box 517
Crystal Lake, IL
Phone: 815/459-5000

OAK
*Your Partner
in Excellence*

Circle 114 for Literature

Circle 153 for Sales Call



RC NETWORK KIT

- For prototyping surface-mount designs
- Includes assembly procedures

The 9000 kit is for assembling prototype resistor-capacitor circuits that employ surface-mount components. Each kit contains metallized ceramic substrates as well as instructions and examples of typical circuits. Five substrates are provided for

each of three circuit patterns to allow maximum flexibility in possible circuit configurations. Surface-mount components come assembled on a 10-pin SIP (single-in-line package) substrate to minimize the size of the finished device. The instructions include a discussion of surface-mount assembly procedures. \$395.

Debttek Inc., 503E Vandell Way, Campbell, CA 95008. Phone (408) 866-7286.

Circle No 364

OPTOCOUPERS

- Accept ac or dc inputs
- Feature 1000V/ μ sec min CMR

HCPL-576X Series 8-pin, hermetically sealed optocouplers accept either ac or dc inputs, which lets them serve in either voltage- or current-sensing applications. Typical applications include monitoring a limit- or proximity-switch, a relay-con-

tact, or a power-supply protection circuit. HCPL-5760, the standard product, is a single-channel, ac/dc-to-logic interface optocoupler; HCPL-5761 is the version tested to MIL-STD-883 Class B requirements for use in military and high-reliability systems. Each unit has a guaranteed operating range of -55 to $+125^{\circ}\text{C}$. Their CMR equals 1000V/ μ sec min at a withstand-test voltage of 500V. HCPL-5760, \$61.90; HCPL-5761, \$109.85.

Hewlett-Packard Co., 1820 Embarcadero Rd, Palo Alto, CA 94303. Call local office.


Circle No 365

SOCKET SYSTEM

- Handles 1 to 3A current levels
- Available with tin-lead or gold-plated contacts

The CHG wire-mount socket system is designed for signal-transmis-

Series CV Compact Economy Switchers



Compare to LH Series TMF !


More power! Better specs! Better prices!

- | | |
|-------------------------|------------------|
| ■ Safety & EMI | ■ 42 models |
| ■ Form & function equal | ■ 1-5 outputs |
| ■ 2 year warranty | ■ 5-48V, to 120A |
| ■ Direct from stock | |

Now for a limited time – purchase small quantities @ 100 piece price!

Call Toll Free 1-800-523-2332


Deltron inc. P.O. BOX 1369 ■ WISSAHICKON AVENUE, NORTH WALES, PA 19454
PHONE: 215/699-9261 TWX: 510/661-8061



Brushless DC fans use advanced IC technology for greatly improved reliability and control.

A single chip incorporating "Hall" sensing and power electronics performs all commutation functions, replacing the printed circuit board assembly. Starting inrush current requirements are reduced for power supply savings—and various speed control methodologies can be accommodated to tailor output to thermal and acoustic variables. In fans from 2" to 4½". Only from Nidec-Torin. For additional information, please call (203) 482-4422, ext 502. Or write: The Nidec Corporation, 100 Franklin Drive, Torrington, Connecticut 06790.


Nidec
The Nidec Corporation



sion and logic-power applications requiring current ratings between 1 and 3A. Two contact options accommodate 22/24 or 26/28 AWG discrete-wire or prenotched ribbon cable on a 0.1-in. grid spacing. You can select 1- and 2-row sockets containing from 2 to 40 or 4 to 80 contacts without polarization or with center-bump polarization. The 2-row military and DIN versions contain from 10 to 80 contacts and are available with or without the center bump. The contact plating includes a choice of 0.1- μ m. tin-lead (entire contact) or 10 or 30 μ m. of gold over 50 μ m. of nickel. \$0.96 (1000) for a 1-row, 10-position socket with 30 μ m. of gold plating and no center bump.

3M, Dept EP7-99, Box 2963, Austin, TX 78769. Phone (512) 834-1800.

Circle No 366



SOCKET

- Has perforated construction that simplifies board cleaning
- Features insulator with 94V-0 UL rating

The PLCC-068 socket accepts 68-pin plastic leaded chip carrier (PLCC) devices. The socket is JEDEC-qualified for type-A carri-

ers and it has an 8x8-position contact array that places contacts on 0.050-in. centers. Its glass-filled polyphenylene sulfide insulator has a 94V-0 UL rating, and its preloaded, stamped-and-formed, copper-alloy contacts have a tin-lead plating. The socket features a compact low-profile design and perforated construction to ease board

cleaning. The socket's design lets you probe the chip-carrier pins in the circuit. The socket operates over a temperature range that spans -65 to +125°C. \$3 (100). Delivery, stock to eight weeks ARO.

Precicontact Inc, Box 798, Langhorne, PA 19047. Phone (215) 757-1202.

Circle No 367



When your specs call for emission control, call for Emcor's EMI/RFI series



Emcor offers a choice of shielding solutions, all of which are tested to MIL STD 285. These enclosures combine high strength with modular options and attractive esthetics. Emcor's commercial EMI/RFI enclosures are fabricated from 14-gauge cold-rolled steel and are fully zinc-plated. Our Tempest-style enclosures provide even higher levels of attenuation. They are fabricated from 12-gauge cold-rolled steel, nickel-plated and feature a unique latching system and door design (patent pending).

Contact Emcor to discuss your EMI/RFI needs. Our engineering staff has the knowledge and experience to help solve shielding problems. We can also design modified and custom products.



Crenlo, Inc.

1600 - 4th Ave. N.W.
Rochester, MN 55901
Phone 507-289-3371
FAX #507-287-3405

EMCOR

CIRCLE NO 20

NEW PRODUCTS

COMPUTERS & PERIPHERALS



IMAGE SCANNER

- Provides 300-dot/in. image scanning
- Scans at 16-sec/page rate

The desktop IX-12F image scanner can scan documents for text, graphs, drawings, maps, and pictures and can enter them into a computer. It can scan images at a speed of 16 sec/page and can provide a resolution of 300 dots/in. It offers 32 levels of halftones, a useful feature for photo reproduction. The scanner has a CCD sensor and a

halogen light source. An optional automatic document feeder can handle as many as 20 letter- or legal-size sheets of paper. The unit measures $14\frac{1}{2} \times 21\frac{1}{2} \times 3\frac{1}{2}$ in. You can use an interface board to connect it to one of the vendor's personal computers or to an IBM PC, PC/AT, or compatible computer. Scanner, \$1495; document feeder, \$595.


Canon USA Inc., System Div, 1 Canon Plaza, Lake Success, NY 11042. Phone (212) 688-1200.

Circle No 368

backed clock calendar. You can use the board's Debug firmware to link it to an RS-232C device or to an IBM PC or compatible computer. You can download Intel Hex-formatted code from your IBM PC or compatible and execute it in RAM with a breakpoint. The board's power requirements are 5V at 90 mA, 12V at 1 mA, and -12V at 4 mA. \$395; with A/D converter, \$445.

CμBit, 190 S Whisman Rd, Mountain View, CA 94041. Phone (415) 962-8237. TLX 797377.

Circle No 369



DISK COPIERS


- Make duplicate floppy disks from hard disks or floppy disks
- Provide as many as 300 copies/hour

MST Replica! Series diskette duplicators let high-volume software publishers make as many as 300 copies/hour of 3½-, 5¼-, and 8-in. double-sided media at each of their copy stations. The copiers can handle disks compatible with MS-DOS-based computers and with Commodore Amiga, Apple Macintosh, Atari, DEC, and Wang computers. A user-programmable batch mode permits the automatic duplication of several masters from either a hard- or floppy-disk original. The units can operate unattended after their initial setup. They can record serial numbers. You can order copiers whose options let you copy between various 5¼- and 3½-in. floppy

STD BUS BOARD

- Uses a 4.6-MHz 64180 μ C
- Features an 8-channel A/D converter for data acquisition

The Model 8020 all-CMOS CPU board for the STD Bus uses a 64180 4.6-MHz μ controller chip. The board features three memory sockets, two of which have 32k bytes of battery-backed RAM. The remaining socket contains Debug software. You can also use this socket to hold a 27C256 EPROM (CMOS) or, if all-CMOS operation isn't required, a 27512 EPROM. The board's 64180 μ C has two RS-232C ports with programmable baud rates. The board also has a synchronous, half-duplex serial I/O channel and a Z80



PIO IC that provides two 8-bit channels. An 8-channel, 8-bit A/D converter furnishes data acquisition through 0 to 5V inputs. Other features of the board include two 16-bit and four 8-bit cascadable counter timers, one watchdog timer, two DMA channels, and a battery-

CHINON: Scanning the future.



Chinon's design engineers have a serious commitment to produce the most technologically advanced products that the mind of man can imagine.

That commitment has created subsystems, peripherals and components that could change the way we think about computers—and change the way computers are used.

The Scanner and the CD-ROM units pictured here are the types of products that continually move the leading edge forward. The Scanner could change the way business works by making true OCR technology more affordable and easier to use than ever before. The unique scanning head design means that the document to be scanned remains fixed, unlike other scanners that


can only accept a single sheet fed through the unit. It is also extremely compact and lightweight, and is designed to set new standards of cost-effectiveness.

CD-ROMS can provide users with access to databases that, only a few years ago, were possible only with a mainframe system.

Technology is still moving as fast as the best minds can advance it. At Chinon, our commitment to that progress keeps our products at the very forefront of the leading edge. We're bringing the future of computing to the needs of today.

CHINON

Chinon America, Inc., 6374 Arizona Circle
Los Angeles, CA 90045 (213) 216-7611 FAX: (213) 216-7646



we never
stop
asking

What if...

The new HP PaintJet color graphics printer.
Great color is only 1/2 the story.



© 1987 Hewlett-Packard Co.

COMPUTERS & PERIPHERALS

disks or allow you to use an IBM PC, PC/XT, or compatible to copy disks intended for the IBM PC/AT and PS/2 or Apple II. From \$5500.

Media System Technology Inc., 16812 Hale Ave, Irvine, CA 92714. Phone (800) 443-8515; in CA, (714) 863-1201. TLX 4992344.

Circle No 370

PRINTER ADAPTER

- Lets IBM PCs or compatibles drive high-speed laser printers
- Provides access to laser-printer formatting features

The USA/PC enables IBM PCs or compatibles and IBM PS/2 computers to drive high-speed laser printers and Xerox ion-deposition printers. It drives high-speed laser printers by Datagraphics, Hewlett-Packard, IBM, Kodak, NCR, Siemens, and Storage Technology. Computers such as the PS/2 Model



80 and the Compaq 386, which employ 80386 μ Ps, or machines such as the PS/2 models 30 and 60, which employ the 80286 μ Ps, can drive the Xerox 8700 and 9700 and the IBM 3800 at full speed. IBM PCs or compatibles and the PS/2 models 25 and 30 can drive the Xerox 4050 and 4060 ion-deposition printers, which feature maximum operating speeds of 50 and 60 pages/minute respectively. The unit also grants access to such printer features as an unlimited selection of type fonts, type

sizes ranging from four to 24 points, variable-line and -character spacing, variable-page width, and the capacity to print on both sides of a sheet of paper. \$9000.

Spur Products Corp., 13469 Beach Ave, Marina Del Rey, CA 90292. Phone (213) 822-7100.

Circle No 371

SMART MODEM

- Hayes AT-compatible 212A/103 modem
- Autoanswer and autodialing for DTMF and pulse

The MCM-MODEM is a self-contained Bell 212A/102 and CCITT V.22 and V.21 compatible modem on an STD Bus card. It supports the full Hayes AT command set with additional features: autoanswer and autodialing for both DTMF and pulse dialing, and call-progress monitoring. The modem has an

HP PAINTJET PRINTER

Description

Desktop color graphics printer for engineering use

Color

6 colors plus black at 180 dpi; 330 colors at 90 dpi

Text-Speed

NLQ at 167 cps (average page printed in 30-40 seconds)

Software

Works with CAD and other popular software

Compatibility

HP Vectra PC, IBM PC and compatibles

Media

A-size paper or transparency film

Price

\$1,395 US list

For a PaintJet-Pack, call 1 800 367-4772 EXT. 904A

we never
stop
asking

What if...

It can also print a page of text
in 30 seconds flat.




HEWLETT
PACKARD

© 1987 Hewlett-Packard Co.

CIRCLE NO 21

COMPUTERS & PERIPHERALS



FCC-registered data-access arrangement (DAA) for connection to the telephone line and a 8250B UART-type interface to the STD bus. It's configured for 8- and 10-bit addressing and requires a total of eight consecutive I/O addresses. The board generates an interrupt whenever the following prioritized levels are active: received data available, transmitter holding register empty, receiver-line status, and modem status. The card is I/O mapped and processor independent—it can work with the 80186, 8088, 68008, HD64180, Z80, or 8085A. It

comes with an audible telephone-line monitor and an auxiliary RJ-11 jack for a separate telephone handset. The unit requires 5V at 250 mA and -12V at 40 mA; it operates over 0 to 65°C. \$395.


WinSystems Inc., Box 121361, Arlington, TX 76012. Phone (817) 274-7553.

Circle No 372

LAN SERVER

- Implements the ISO Open System Interconnection protocol
- Connects as many as 64 peripheral devices to a LAN

The CS/1-OSI LAN communications server implements the full 7-layer Open System Interconnection (OSI) protocol as defined by the International Standards Organization (ISO). It can connect as many as 64 computing and peripheral devices to a LAN. These devices can include




asynchronous, bit- and character-synchronous, and IBM-3270 Category A devices. The server is also compatible with the Technical and Office Protocols (TOP) 3.0, a specification of the OSI protocols layered over Ethernet (IEEE 802.3). In addition to Ethernet, the server is available in versions for token-ring LANs (IEEE 802.5) and for the vendor's 5M-bps CSMA/CD broadband LANs. The server's architecture uses a 16-MHz 68020 main μ P and several 68000 μ Ps to offload communication-processing tasks from the host. A network-user

log-in feature permits the independent configuration of each port in order to restrict access. The server also has a built-in packet generator, which lets you perform network diagnostics while the network is operational. Eight-port version, \$9900; 64-port version, \$16,000. OSI software, \$250. Delivery, 90 days ARO.

Bridge Communications Inc., 2081 Stierlin Rd, Mountain View, CA 94043. Phone (415) 969-4400. TLX 176544.

Circle No 373



μC BOARD

- Uses a CMOS 64180 microcontroller chip
- Has floating-point Basic interpreter resident in ROM

The Vitrax IX is a microcontroller board for digital control and data acquisition. It uses a CMOS 64180 μC that's compatible with the Z80 in-

struction set. The board contains a floating-point Basic-language interpreter in ROM, as many as 16k bytes of EPROM-based user code, and 16k bytes of CMOS static RAM that you can expand to 32k bytes. In addition, the device has an onboard EPROM programmer for code generation. It provides 24 bidirectional I/O lines; two full-duplex asynchronous RS-232C channels with data-transfer rates as high as 18,200

baud; a Centronics printer port; an optional 8-channel, 10-bit CMOS A/D converter; and an optional real-time clock/calendar. The unit operates on a 5V power supply with a current drain of less than 150 mA. It is supplied as a 4½×6½-in. pc board in kit and assembled forms. Basic kit and manual, \$139.50; 8-channel, 10-bit CMOS A/D converter, \$39.50; CMOS real-time clock/calendar, \$34.50.

Sintec Co., 28 8th St, Frenchtown, NJ 08825. Phone (800) 526-5960; in NJ, (201) 996-4093.

Circle No 374

ANALOG I/O CARDS

- Provide 12-bit, 64-channel analog input
- Available with software drivers for OS-9/68000

The VME-68320-ADC and -68330-DAC are VME Bus-compatible ana-



The First


When you're looking for input on raster plotters, take a look at some major CalComp output. Twenty-four different versions from the fastest growing raster family in the world. (With more family members arriving soon.)

Every raster plotter incorporates more industry firsts, more choices. From simple, colorful business graphics to the complexity of super-dense integrated circuit design, mapping, etc.

The 5800 and 5700, our color and black-and-white electrostatic plotters, deliver speed, superior resolution, multiple configurations and A to E size plots.

For CAD graphics, PlotMaster™ produces quick-check "A" size presentation-quality color. Or plug ColorMaster® into your PC and through CalCompatibility, you can run the most popular business presentation graphics software.

ColorMaster is a registered trademark of CalComp. © 1987 CALCOMP



log input and analog output cards, respectively. The VME-68320-ADC provides 64 single-ended or 32 differential input channels, which are digitized to 12-bit resolution at a conversion rate of 50k readings/sec. The input ranges for the A/D converter are 10V for a unipolar input, or ± 10 or ± 5 V for a bipolar input. A programmable gain amplifier on the front end allows you to introduce gain of $\times 1$, $\times 2$, $\times 4$, or $\times 8$, or a user-defined gain factor. A patch panel is provided next to each input connector so that you can add your own signal-conditioning circuitry. The VME-68330-DAC provides

eight 12-bit analog outputs. You can select bipolar output ranges of ± 2.5 , ± 5 , or ± 10 V or unipolar output ranges of 5 or 10V. Both boards have onboard dc/dc converters that allow them to operate from the VME Bus 5V supply. Software drivers for the OS-9/68000 operating system are available for the boards. VME-68320-ADC, DM 2480; VME-68330-DAC, DM 1750.


EKF Elektronik Messtechnik GmbH, Weidekampstrasse 1A, 4700 Hamm 1, West Germany. Phone (02381) 12630. TLX 828621.

Circle No 375


DISK CONTROLLER

- Board for Sun 3 workstations supports four SMD/SME drives
- Is the same size as Sun's triple-high, triple-wide cards

An enhancement of the Rimfire 3200, the Rimfire 3220 is a VME



Bus disk-controller board for Sun 3 workstations. The board has the same dimensions as do Sun's triple-high and -wide cards, and it can support four SMD/SME drives via faceplate connections. It uses an 80186 μ P to manage a 512k-byte segmented cache memory; the cache eliminates unnecessary seek and rotational delays by prereading disk files that span track boundaries. The board can handle SMD E-drive data rates to 24 MHz and can burst data across the VME Bus at rates in



Family.

The first family? You bet. First in high-resolution 400 DPI color. First in pin-point accuracy with electronic registration. First in embedded controllers to save space. First with convenient ROM pack firmware. First with flexibility of over 2,000 line and area fill colors. And too many more firsts to talk about here.

There's also a national 800 helpline, 425 trained service persons, 46 service centers nationwide, 32 international field offices, and on-site service. And a single supply source.

Don't be the last to learn about the first family. Call 1-800-CALCOMP or write CALCOMP, P.O. Box 3250, Anaheim, CA 92803. In Canada, call (416) 635-9010.

We draw on
your imagination.™



A Lockheed Company

excess of 30M bytes/sec. Software support includes device drivers for Unix BSD 4.2 and SunOS. You can also obtain software that boots a Sun 3 workstation directly from the controller. \$3495.

Ciprico Inc, 2955 Xenium Lane, Plymouth, MN 55441. Phone (612) 559-2034.

Circle No 376

DISK CONTROLLER

- *Incorporates a disk cache to speed data transfers*
- *Handles four mixed-format floppy-disk drives*

To achieve disk access at data rates as high as 500k bytes/sec, the FCM1 floppy-disk-drive controller card for G64 Bus systems incorporates 8k

bytes of onboard disk-caching memory and a DMA controller that regulates data transfer between the cache memory and floppy disk-drive controller. The Eurocard board interfaces with as many as four 3.5-, 5.25-, or 8-in. floppy-disk drives and handles any combination of single- or double-sided, single- or double-density drives. The device operates from a 5V supply and consumes 600 mA. You can obtain a driver for the OS9 operating system. £318.

Syntel MicroSystems, Queens Mill Rd, Huddersfield, Yorkshire HD1 3PG, UK. Phone (0484) 535101. TLX 51194.

Circle No 377

PHOTOPLOTTER

- *Achieves a resolution of 2540 dots/in.*
- *Accommodates film sizes to 18×24 in.*

Suitable for use with pc-board CAD systems, the L1 drum photoplotter uses a raster-scan technique and a 5-mW focused-beam argon-ion laser to provide a resolution of 2540 dots/in. The blue light emitted by the laser exposes low-cost orthochromatic film. The imaging area is 25×25 in. and supports standard film sizes as large as 18×24 in. The largest film sizes are exposed in less than five minutes. A vacuum holds the film against the inside of the drum during operation. The photoplotter links to a host computer via an RS-232C serial interface and accepts RS-274 (Gerber) photoplot data. It works with the company's S44 artwork editor and CAM workstation software. From 300,000 to 400,000 Sw Fr.

EIE Electronic Industrial Equipment SA, 15 rue Marziano, 1211 Geneva, Switzerland. Phone (022) 423260. TLX 429484.

Circle No 378



10 MILLION STRONG ...AND GAINING

Over 10 million Canon EN35 DC Micro Motors are working in computers, printers, VCRs, video disk and tape drives, and business and medical equipment of major OEM manufacturers worldwide.

Canon EN35s owe their enduring popularity to their exceptionally long life (up to 10,000 hours) ... compact size and light weight ... high power ... low mechanical and electrical noise (optional filter network lowers electrical noise even further) ... low vibration. Especially suited for capstan, ribbon and carriage drives; fans; paper transport drives for banking machines and other applications. Modifications available in OEM quantities.

Canon U.S.A., INC.
COMPONENTS DIVISION.

One Canon Plaza, Lake Success, NY 11042
Tel: (516) 488-6700 • FAX (516) 354-1114


NEW PRODUCTS

INTEGRATED CIRCUITS

12-BIT QUAD MDAC

- Four 12-bit CMOS DACs on a single monolithic chip
- Each DAC provides two outputs

The CMOS HS-7584 contains four multiplying DACs, each having two current outputs and a separate reference input and feedback resistor. The double-buffered input structure accepts 12-bit parallel data or 8-bit/4-bit data, and interfaces with a μ P. The use of thin-film resistors ensures 12-bit accuracy, and each DAC is laser trimmed for linearity and gain matching. The device's current-output settling time is 3 μ sec max. The converter operates from a single 5V supply and draws 1 to 10 mA of current, depending on the input logic levels. The device comes




in a hermetic 40-pin ceramic DIP or a 40-pin ceramic LCC. HS7584C, \$62; HS7584B, \$120 (100). Delivery, six to eight weeks ARO.

Hybrid Systems, 22 Linnell Cir-

cle, Suburban Industrial Park, Billerica, MA 01821. Phone (617) 667-8700. TWX 710-347-1575.

Circle No 379



TV TUNER CONTROL

- Supports multiple tuning functions
- For use in either frequency- or voltage-synthesized tuners

The CA3263 provides interface control for TV/CATV tuning systems and can drive either frequency- or voltage-synthesizer tuners. Two logic-level inputs (0 or 5V) operate the IC's bandswitch controller, whose outputs drive the supply voltages of the VHF, UHF, and Superband bands in the tuner. At a supply voltage of 12V, the bandswitch controller's output voltages are 11.3V min at a current of 30 mA. You can use its inverting and noninverting op amps to amplify error signals or serve as active-filter

elements with tuners using phase-locked loops. The IC comes in a 14-pin DIP and costs \$1.00 (100).


GE Solid State, Route 202, Somerville, NJ 08876. Phone (201) 685-6994.

INQUIRE DIRECT

VOLTAGE DETECTORS

- 2 to 16.5V operation
- Three temperature ranges available


The MAX8211 and MAX8212 are programmable voltage detectors for use in power-supply monitoring applications. They contain a comparator, a 1.15V (± 40 mV) bandgap reference, and an open-drain N-channel output driver. The devices operate from a 2 to 16.5V supply and draw a maximum supply current of 15 μ A. The 8211 provides a 7-mA current-limited output sink when the threshold pin is below the reference voltage. On the 8212, inputs above the reference voltage activate the output, which is not cur-



rent limited and can typically sink 35 mA. The hysteresis-type output can typically source 10 mA, allowing you to apply positive feedback for noise-free output switching. The applications include undervoltage and overvoltage detection, battery-backup switching, and power-supply fault monitoring. MAX8211MTY and MAX8212MTY in hermetic TO-99 metal cans for military applications, \$5.75; MAX8211EPA and MAX8212EPA in 8-pin plastic DIPs for industrial and commercial applications, \$2.14 (100).

Maxim Integrated Products, 510 N Pastoria Ave, Sunnyvale, CA 94086. Phone (408) 737-7600.

Circle No 381



DC/DC CONVERTER

- Provides eight isolated supply voltages
- ± 7 to $\pm 20V$ dc outputs

The modular PWS740 dc/dc converter consists of three components: PWS740-1, housed in a TO-3 package, is a 400-kHz oscillator/driver that drives as many as eight separate power outputs; PWS740-2 is a trifilar-wound isolation transformer in a plastic package; PWS740-3 is a high-speed rectifier bridge in a plastic, 8-pin miniature DIP. By sharing a common power driver among several channels and using board-mounted transformers and rectifi-

ers, you can generate bipolar isolated power to ± 30 mA for about \$6 to \$8/channel. PWS740-1, \$12.75; PWS740-2, \$2.50; PWS740-3, \$1.25 (100).


Burr-Brown Corp., Box 11400, Tucson, AZ 85734. Phone (602) 746-1111. TLX 666491.

Circle No 382

A/D CONVERTER

- 4-bit output
- 200M samples/sec

The AD9688 ADC guarantees no missing codes while performing 4-bit conversions at rates typically greater than 200M samples/sec. The device uses a flash-converter architecture to provide 7-bit linearity, which equates to 0.0625 LSB for a 4-bit device, and you can stack multiple units to obtain 6-bit resolution via the overrange output terminal. The converter accepts analog input



signals between -2.7 and $3.0V$; all digital inputs and outputs are ECL compatible. The device is pin compatible with the AMD AM6688. A small-signal bandwidth of 200 MHz (-3 dB) and low input capacitance of 13 pF eases the device's application in high-speed designs. The applications include ECM (electronic countermeasure), digital radio systems, and low-resolution radar guidance for smart munitions. Available in either an 18-pin ceramic DIP or a 20-pin ceramic LCC, the converter


Color by

Quadram's new Quad HPG™ graphics adapter delivers unbeatable PC graphic capabilities. Brooktree makes it possible with an unbeatable triple 8-bit RAMDAC that provides 256 colors from a 16 million palette.

typically consumes <700 mW of power from 5V and -5.2V power supplies. From \$20 (100).

Analog Devices, Literature Center, 70 Shawmut Rd, Canton, MA 02021. Phone (617) 329-4700. TWX 710-394-6577.

Circle No 383



before the circuit completes the existing conversion. The ADC-508 has three pin-programmable input ranges: 0 to 10V, 0 to 20V, and $\pm 10V$. For commercial temperature range, \$330; for military temperature range, \$399.

GE Datel Inc, 11 Cabot Blvd, Mansfield, MA 02048. Phone (617) 339-3000. TWX 710-346-1953.

Circle No 384

12-BIT ADC

- 800-nsec conversion time
- Pin-programmable inputs

Performing a 12-bit conversion in a maximum of 800 nsec and dissipating a maximum power of 1.9W, the ADC-508 offers the best speed/power ratio available in this type of product, according to the manufacturer. The converter's performance is a result of the digitally corrected, subranging architecture, which is enhanced by the use of a custom chip and laser-trimming techniques. The device's features include low

initial errors of 3 LSB for both offset and gain, CMOS/TTL compatibility, and 3-state outputs. Other features not usually available in 12-bit, high-speed converters are pins that provide different coding selections, an indication of signals that are above or below the full-scale range, and a means of improving throughput by putting the S/H function back into the sample mode

ADDRESS GENERATOR

- Provides programmable address sequences
- Cascadable for greater addressing range

Suitable for use in DMA, database addressing, and waveform-synthesis applications, the PDSP1640A address generator allows you to generate complex 8-bit address sequences at speeds as high as 40 MHz. You can cascade devices to increase the

Brooktree®




Brooktree Bt453. Triple 8-bit 40 MHz RAMDAC with 256 color lookup table. Monolithic CMOS.

Quadram Quad HPG. 640 x 480 x 8 high performance graphics adapter board for IBM PC family, IBM Personal System/2™ Model 30, and compatibles.

Brooktree Corporation, 9950 Barnes Canyon Road, San Diego, California 92121. 1-800-VIDEO IC or 1-800-422-9040, in California.

© Copyright Brooktree Corporation 1988.
Quadram is a registered trademark of Quadram Corp. Quad HPG is a trademark of Quadram Corp. IBM Personal System/2 is a trademark of International Business Machines Corporation.

CUSTOM X-Y MONITORS OFF-THE-SHELF



X-Y monitors for simulation, training, ATE, CAE/CAD/CAM or radar repeating. XKD can provide high performance XM-300 series monochrome stroke writers in a broad range of sizes, shapes, and phosphors without the usual long delivery times required for custom projects.

So if your application requires an X-Y monitor with high writing speed, fast settling time and excellent edge focus, and if you require special configurations promptly without extra charges, call Skip McLaughlin now at (408) 395-3700.



© XKD 1987

CIRCLE NO 25

INTEGRATED CIRCUITS


addressing range. Two devices can generate 16-bit addresses at speeds as high as 20 MHz, and four devices can generate 32-bit addresses at 15 MHz. Five internal registers allow you to perform variable increment counting and conditional jumps to two internally stored branch addresses or to an externally generated address. A masking facility allows you to jam selected address bits. PDSP1640A, in a 28-pin DIP, £35; PDSP1640, a 20-MHz version, £10 (1000).

Plessey Semiconductors Ltd, Cheney Manor, Swindon, Wiltshire SN2 2QW, UK. Phone (0793) 36251. TLX 449637.

Circle No 385

Plessey Semiconductors, 9 Parker, Irvine, CA 92718. Phone (714) 472-0303.

Circle No 386



POWER OPTOCOUPLER


- High-speed capability
- Can drive power transistors having ratings as high as 20A

Packaged in an 8-pin DIP, the TLP557 contains a GaAlAs LED and a high-gain, high-speed integrated photodetector. The device's output current is suitable for driving power transistors that have ratings to 20A. An external resistor between pins 6 and 7 of the device creates a constant-current output that provides a stable base drive for power transistors or modules. The optocoupler has an input threshold current of 5 mA and a switching speed of 1 μ sec, and operates from a 15V supply. \$2 (1000). Delivery, 12 weeks ARO.

Toshiba America Inc, ECBS,

Semiconductor Products Div, 2692 Dow Ave, Tustin, CA 92680. Phone (714) 832-6300.

Circle No 387



150-MHz COMPARATOR

- Complementary ECL output
- 9.5-nsec propagation delay

The 150-MHz CMP-08 comparator responds in 6.5 nsec to a 5-mV overdrive. The maximum response time over temperature is 9.5 nsec for the industrial-grade device and 12 nsec for the military device. The device offers improved stability in the transition region; the resulting oscillation-free performance eliminates the need for a minimum slew-rate requirement for its inputs. The analog input range is -3 to 2.7V when connected to a 5V supply. It comes in an 8-pin miniature DIP. Industrial grade, \$3.35; military grade, \$7.10 (100).

Precision Monolithics Inc, Box 58020, Santa Clara, CA 95052. Phone (408) 727-9222. TWX 310-371-9541.


Circle No 388

ANALOG/DIGITAL ASICs

- Provide as many as 2500 analog and digital components
- Include on-chip power Darlingtons

This family of five bipolar analog/digital arrays ranges in complexity from 400 to 2500 components that you can customize with 2-level metal. The arrays contain customizable tiles of I²L and ECL logic elements, npn and pnp transistors,

Give your system the benefit of NO doubt.




Add the advantages of voice verification to your product.

What if your system could make its own fool-proof decisions about who uses it—and enable hands-free operation as well? Now, it can. With VoicePac™ speech verification technology, your system can be secured and controlled by the human voice. Integrating VoicePac into your product lets only authorized users start, stop, modify or control operation.

VoicePac is the economical, easy-to-use, biometric technology that permits the use of speaker verification in a variety of applications. A proven method of identifying and verifying users based on speech patterns that are unique to each individual, it opens up new opportunities for system integrators.

Already in development for such diverse applications as keyless/hands-free door locks, home arrest monitoring systems, ATM's and voice-secured computer workstations, VoicePac is the imaginative stroke that will give your product a competitive edge.

VoicePac is designed for OEM use and includes this compact speech verification board with a variety of options to meet custom requirements.



ECCO Industries, Inc. 130 Centre Street Danvers, MA 01923 617-777-7750/FAX: 617-774-7347

Please send details on VoicePac to:

Name

Title

Company

Address

City

State

Zip

Phone

EDN 020488

MODUTEC'STM BIG-LITTLE GETS BOLDER & BRITER



THE WORLD'S ONLY LCD DPM WITH SUPER-BRITE LED BACKLIGHTING.

A cost-saving breakthrough! By using LED's...with 100K hours of life...for backlighting, Modutec's new LCD Big-Little DPM's now provide high visibility in daylight, nightlight, any light. You have a choice of red or green economical backlighting plus plug-in compatibility with Modutec standard LCD Big-Little DPM's. Backlighting power is 5, 12, 24 VDC or 115 VAC. Displays are -20°C to $+65^{\circ}\text{C}$ operating and storage with $3\frac{1}{2}$ digits, $\frac{1}{2}$ " high, full scale of 1999. Actual size: 2.36" L. x .95" H. x .51" D. Enjoy the benefits of low power consumption with Modutec's LCD DPM featuring an LED look.

Additional features:

- * ± 200 mV or $\pm 2\text{V}$ input * 3 power options: 9V battery, $\pm 5\text{VDC}$ or $\pm 5\text{VDC}$
- * Window or bezel mount
- * Accuracy: $\pm (0.1\% + 1 \text{ count})$

For a day/night demonstration, contact your local Modutec sales representative, distributor or MOD Center, nationwide.

MODUTEC

BORN IN
AMERICA

MODUTEC, INCORPORATED
P.O. BOX 778, 18 MARSHALL ST.,
NORWALK, CT 06856-203/853-3636.
1-800/METERS-1 TWX 710-468-2039
Wescon Booth #1826

CIRCLE NO 26



INTEGRATED CIRCUITS

and power Darlington. They also have standard analog functional blocks, including an RC- or crystal-controlled oscillator, a bandgap reference, a 6-bit D/A converter, a high-frequency op amp, a voltage reference, and an ECL reference. The npn transistors have an F_T of 3 GHz. The on-chip npn power Darlington can switch 200 mA, and you can configure them to create a 200-mA bridge output stage. Alternatively, you can use 30-mA pnp transistors to produce complementary output stages. The ECL elements have multiple emitters that allow you to produce stacked logic configurations that contribute to a high packing density and high-speed operation. You can configure inputs and outputs for TTL compatibility or as ECL-compatible inputs and outputs suitable for operation at frequencies as high as 200 MHz. The I^2L logic elements operate at speeds as high as 2 MHz. The arrays have a 15V operating voltage range. The company provides VAX-based CAD software with schematic entry, SPICE simulation, and autolayout facilities, and an IBM-PC based system that uses PCAD software.

SGS-Thomson Microelectronics, 101 Blvd Murat, 75016 Paris, France. Phone (1) 45241716. TLX 611220.

Circle No 389


SGS-Thomson Microelectronics, 1310 Electronics Dr, Carrollton, TX 75006. Phone (214) 466-6000.

Circle No 390

GaAs MMIC

- 1- to 20-GHz bandwidth
- 7-dB gain at 18 GHz


The UPG102 is the first in a series of new GaAs wide-band MMICs (monolithic microwave ICs) from NEC (Mountain View, CA). The device operates over an ultrawide frequency range from 1 GHz to 20 GHz and has a typical gain of 7 dB. The cascaded device has both its input



and output matched to 50Ω and has a power output of 10 dBm at 1 dB of compression. Typical applications are as a driver amplifier in commercial, military, and high-reliability applications requiring extreme bandwidths. The MMIC is available in chip form as the UPG102P and in a hermetic, ceramic package as the UPG102B. From \$280 (100).

California Eastern Laboratories Inc, 3260 Jay St, Santa Clara, CA 95054. Phone (408) 988-3500.

Circle No 391



HIGH-SPEED RAMDAC

- Operates to 175 MHz
- Offers 1024 colors plus a 256-color window

The Bt461 second-generation high-speed RAMDAC incorporates a 1024×8 -bit color look-up table, a 256×8 -bit alternate palette, and a 32-word overlay palette. Constructed in CMOS, the RAMDAC includes an 8-bit DAC, a μP interface, and multiplexers. Originally designed to operate at 135 MHz, the final characterization of the $1.5\text{-}\mu\text{m}$ process shows a typical operating speed of 170 MHz. Applications for the RAMDAC are those requiring the display of large numbers of colors, such as true-color imaging and multiwindow environments. The de-

Control Point

Test and Control Systems Product News from Ziatech

Winter 1988

Ziatech Corporation

Inside Control Point

PAGE TWO New Single Board Computers


The ZT 8808 and ZT 8809 are Ziatech's most IBM-compatible single board computers. The new computers feature a number of PC/XT peripherals, large on-board memory, and they support PC DOS, VRTX operating systems and user-developed ROM-based software.

PAGE THREE First Extended Memory System on STD Bus

Ziatech's new byte-wide STD Bus memory board extends the 8088/8086 family of processors' address space beyond 1 Mbyte via a memory-mapping technique called EMS. This memory board is supported in Ziatech's STD DOS systems for main memory expansion and as a RAM/ROM disk.

PAGE FOUR Free GPIB, STD Bus Literature

Ziatech's STD Bus and IEEE 488 product lines are described in four separate catalogues. The Technical Data Book features the entire product line with separate technical guides also available on IEEE 488 products, STD DOS systems, and the Z-NET Local Industrial Network.



This new NEC V20-based Single Board STD Bus Computer, the ZT 8808, is the latest addition to Ziatech's family of single board computers (SBCs) for industrial control applications. The V20 microprocessor on the ZT 8808 is available in 5 or 8 MHz versions, giving the new SBC enhanced STD-8088 compatibility.

In addition to an on-board memory capacity of 512 Kbytes, the ZT 8808 contains several IBM PC/XT peripherals. These include three 16-bit counter/timers, two serial ports, a Centronics interface, and an interrupt controller. This new SBC features support for both operating systems and ROM-based systems, and will be available in a CMOS version later this year. (See story, page 2, and/or check box A on the return card.)

ZIATECH
CORPORATION

New IBM PC/XT-compatible STD Bus Computers

Ziatech's new ZT 8808 provides a high level of functionality on a single board STD Bus computer at a reasonable cost. Based on the NEC V20 processor, a superset of the 8088, this single board computer (SBC) was designed to support both PC DOS and PROM-based industrial control applications.

PC/XT Peripherals

Available in 5 MHz (ZT 8808) and 8 MHz (ZT 8809) versions, these SBCs contain IBM PC/XT peripheral devices such as three 16-bit counter/timers, an interrupt controller, two serial ports, and a Centronics printer interface. 512 Kbyte on-board memory capacity and a wait state generator are also provided.

Software Development


The ZT 8808 and ZT 8809 are supported by STD DOS, Ziatech's implementation of PC DOS on the STD Bus. The PC compatibility of STD DOS allows

developers to run sophisticated development tools on the STD target system to prepare for use with PC DOS or a PROM-based application. The new SBCs are also supported by Ziatech's STD Prototype Development System, which aids in the development of applications that don't need operating system support.

CMOS Version

The ZT 8808 and ZT 8809 will soon be available in CMOS versions for applications where low power consumption and extended temperature operation are required.

For more information on the ZT 8808/8809, check box A on the return card.



ZT 8808/8809
Functional Diagram



Ziatech's STD DOS Stand-Alone (SA) development system lets users develop STD Bus systems utilizing PC DOS or PROM-based operating software. The SA system is equipped with a monitor, keyboard and disk drives to enable it to function like a PC. Ziatech also offers a PC-assisted development system, which utilizes a user-supplied PC for its console and mass storage requirements.

About Control Point

Control Point is a bi-monthly newsletter published by Ziatech Corporation for OEMs and system integrators designing industrial automation and instrumentation applications.

Control Point examines the new products, applications, and issues in today's test and control industries.

Ziatech Corporation, established in 1976, manufactures STD Bus-based computers, development and operating systems for the STD Bus, and IEEE 488 interfaces for MULTI-BUS, STD Bus, and personal computer systems.

For more information on Ziatech STD Bus and IEEE 488 products, return the Control Point postcard, or call Ziatech at 805-541-0488.

Ziatech Brings Extended Memory System to Industrial Busses

The new ZT 8825 Extended Memory System from Ziatech is the first industrial bus memory board to use a unique memory-mapping technique which extends the amount of memory available to STD Bus systems. The ZT 8825 serves Ziatech's STD DOS systems in two different ways. It can function as a high speed, solid state disk, providing Ziatech's STD DOS systems with a 2 Mbyte PROM/RAM/BRAM disk capability. One RAMdisk can be configured (using multiple ZT 8825s) to contain many MBytes of data.


Expands Memory for STD DOS Systems

The ZT 8825 also can be used as an expanded address main memory. In this role it expands the logical address space while occupying only 16K of the base 1 Mbyte address space. The extended memory is mapped in the logical address space via map registers, which determine when and where the extended memory will be accessed. Lotus, Intel, and Microsoft jointly developed this technique, called the Expanded Memory System (EMS). EMS is becoming popular on PCs and is implemented in a growing number of PC software packages. The ZT 8825 also follows the "Enhanced Expanded Memory System," E²MS, which is a superset of EMS.

Eight 32-pin JEDEC sockets

Eight 32-pin JEDEC sockets accept either EPROMs or RAMs in each grouping of four sockets. Battery backup is provided as an option.

For more information on the ZT 8825, check box B on the return card.



The ZT 8825 Extended Memory System is the first industrial bus memory board to use the Expanded Memory Specification (EMS).

ZT 8825 Extended Memory System Features


- Direct 20- and 24-bit addressing (STD-8088 compatible)
- Two sets (4 sockets each) of independently configured 32-pin JEDEC sockets
- Optional 1 Amp-hour lithium battery for RAMs (BRAM)
- No wait states required at 5 or 8 MHz for fast memory device types
- Supports various combinations of RAM (32K, 128K, 512K chip size) and EPROM (16K to 1 Mbyte chip size)
- Supports PROM & RAM disk configurations in STD DOS
- Supports EMS and E²MS paging specifications
- 2 Mbyte maximum on-board storage, mappable in 16K pages



Free STD Bus, GPIB Product Literature from Ziatech

Technical Data Book Features Entire Ziatech Product Line

Ziatech's 200-page Technical Data Book provides product descriptions, photos, functional considerations and technical specifications of Ziatech's entire STD Bus and IEEE 488 product line.



The Technical Data Book also contains a New Product Section featuring Ziatech's most recently introduced products. It additionally features a comprehensive STD-8088 system designer's guide and the STD-8088 Bus specification.


For a copy of the Technical Data Book, check box C on the return card.

IEEE 488 Products

A new 16-page brochure details Ziatech's line of IEEE 488 interfaces and driver software.

IEEE 488 interfaces for the IBM Personal System/2, the IBM PC, MULTIBUS systems and STD Bus systems are featured.

Complete descriptions and examples of Ziatech software support packages are also featured, including the new EZ.488, Ziatech's simplest driver software for integrating PC-based instrument systems.




STD DOS Systems

A 24-page brochure describes Ziatech's line of PC DOS-based STD Bus systems, STD DOS.

Ziatech's STD DOS industrial computers execute PC-compatible software packages, both for system development and target operation. This brochure describes STD DOS architecture, performance, system configurations, options, software development, device driver software, and ordering information.

For a copy of the STD DOS brochure, check box F on the return card.




For a copy of the IEEE 488 brochure, check box D on the return card.

Z-NET Network Technical Guide

A new guide to Z-NET, Ziatech's Local Industrial Network for STD Bus and PC systems, is now available. Z-NET, based on the ARCNET protocol and ViaNet software, is a simple-to-use network that extends the capability of Ziatech's STD DOS systems for industrial applications.

The Z-NET Technical Information and Configuration Guide provides a comprehensive introduction to this STD Bus and PC network, and includes ordering information.



For a copy of the Z-NET guide, check box E on the return card.

ARCNET is a registered trademark of Datapoint Corporation. ViaNet is a registered trademark of Western Digital Corporation. VRTX is a trademark of Ready Systems, Inc. IBM PC/XT and PC DOS are registered trademarks of International Business Machines Corporation.

MEMBER
STDMG
STD MANUFACTURER'S GROUP

ZIATECH
CORPORATION

3433 Roberto Court
San Luis Obispo, CA 93401 USA
ITT Telex 4992316
FAX (805) 541-5088
Telephone (805) 541-0488

INTEGRATED CIRCUITS

vice provides the large palettes needed for superior graphics, and the 32x8-bit overlay palette gives the designer great flexibility in deciding what should run through the overlays, independent of the main graphics image. The device comes in a 132-pin pin-grid-array package and in three speed grades: 135-MHz, \$245; 110-MHz, \$204; 80-MHz, \$176.

Brooktree Corp., 9950 Barnes Canyon Rd, San Diego, CA 92121. Phone (619) 452-7580. TLX 383596.

Circle No 392

CMOS STATIC RAM

- 8kx8 bits
- Three speed versions

Pin-compatible with the 2764 EPROM family, the MCM6064 requires no clocking for the chip-enable pins when operating in a fully static mode. The device has both active-high and active-low enable pins. The device goes into its low-power standby mode when either pin is not enabled. In standby mode, the device requires from 100 μ A max to 3 μ A min, at 5.5 to 2.0V, under typical operating conditions (a 0.6- to 1.0- μ A version is available). Inputs and outputs are TTL compatible, and the outputs can assume a 3-state condition. The available speeds are 100, 120, and 150 nsec. Depending on speed selection, from \$3.36 to \$4.64 (500).


Motorola Inc., Technical Info Ctr, Box 52073, Phoenix, AZ 85074. Phone (512) 928-6705.

Circle No 393

CMOS DUAL DAC

- Two 8-bit multiplying DACs
- Interfaces directly to DSP chips


Designed with a high-speed control interface, the TLC7528 encompasses two, 4-quadrant 8-bit multiplying D/A converters on a single monolithic chip. Its control signals can interface directly with the TMS320 family of DSP chips. The



device's DACs use a common 8-bit input port. Each DAC consists of an inverted R/2R ladder, analog switches, and input data latches. Commercial grade, \$5.54; industrial grade, \$8.15 (100).

Texas Instruments Inc., Semiconductor Group (SC-775), Box 809066, Dallas, TX 75380. Phone (800) 232-3200, ext 700.

Circle No 394



PS/2 CHIPS

- Interface to IBM Micro Channel
- Provide memory, I/O functions, and peripheral control

These chips provide a 100%-compatible interface to the IBM PS/2 Micro Channel architecture. The 82C611 furnishes memory and I/O functions, and the 82C612 provides control of peripherals. The products target manufacturers of add-in-board adapters. The 82C611 replaces 10 to 15 TTL devices, and the 82C612 replaces 25 to 30 TTL devices. The MicroChips are available in 68-pin PLCC and 80-pin PFP (plastic flatpack) packages. 82C611, \$8.65; 82C612, 11.10 (1000).

Chips and Technologies Inc., 3050 Zanker Rd, San Jose, CA 95134. Phone (408) 434-0600.

Circle No 395

SUN 3/60 Compatible Memory



Available Now Only from Clearpoint 1-800-CLEARPT

Let your Sun 3/60 reach for the stars. Upgrade your system to the system maximum of 24 MB with high reliability Clearpoint memory. Each one megabyte SIMM is packed with eight 1 megabit DRAM DIPs, plus a megabit DRAM to support parity. Buy a set of four SIMMs and meet the basic Sun 3/60's 32-bit performance. Add five SNX60 SIMM sets to your system—your Sun 3/60 can rival its higher-end family products at much less cost but with Clearpoint's uncompromising quality.

All Clearpoint products come with a Lifetime Warranty, full Product Support, trade-ups credits when you upgrade... and competitive pricing that's out of this world.

Write or call for
Clearpoint's
SUN family
literature, our
1987/88
Catalog and the
New Designer's
Guide to Add-in
Memory.



Sun is a trademark of Sun Microsystems.
Clearpoint is the registered trademark of
Clearpoint Research Corporation.



CLEARPOINT

99 South Street • Hopkinton, MA 01748-2202
U.S.A. 1-800-CLEARPT Telex: 298281 CLEARPOINT UR
Massachusetts 617-435-5395/435-2301
Europe: Clearpoint Europe b.v.
Tel: 31-23-273744 Telex: 71080 CLPT NL
Canada: Clearpoint Canada Tel: 416-620-7242
Japan: Clearpoint Asia
Tel: 03-221-9726 Telex: 32384

CIRCLE NO 27

NEW PRODUCTS

TEST & MEASUREMENT INSTRUMENTS



SIGNAL GENERATOR

- Covers 100 kHz to 1 GHz
- Has phase noise of -130 dBc at 100 MHz with 20-kHz offset

The SMX signal generator covers the frequency range from 100 kHz to 1 GHz, providing output levels from -137 to $+13$ dBm in 0.1-dB steps at better than 1.5-dB accuracy. At 100 MHz, 20 kHz from the carrier, the phase noise is down at least 130 dB from carrier level. The generator provides both AM and FM at four fixed frequencies. An optional internal source modulates

the carrier at a frequency that you can vary continuously over a range of 10 Hz to 100 kHz. If you use an external source, you can obtain pulse-modulated output with 2- μ sec rise and fall times. You can store 40 complete instrument setups and recall them from the nonvolatile memory in an instant, or you can fully control the generator via its standard IEEE-488 interface. \$5990. Delivery, eight weeks ARO.


Rohde and Schwarz, 4425 Nicole Dr, Lanham, MD 20706. Phone (301) 459-8800.

Circle No 396

CONVERTERS

- Connect RS-232C and RS-422 devices to IEEE-488 bus
- Have μ P with 64k- or 256k-byte buffer

The GPIB-232CV and GPIB-422CV allow you to connect RS-232C and RS-422 devices to the IEEE-488 bus. They can interface to IEEE-488 instruments and controllers and provide transparent data conversion in either direction. Each converter is based on a 64180 μ P (which features an integral DMA controller) and either a 64k- or 256k-byte buffer. This hardware permits data transferral from bus to buffer at 900k bytes/sec. When connected to




a converter's serial port, the unit controls the rate at which the buffer empties. Each converter's μ P automatically interleaves inbound and outbound data transfers. An SROEMPTY feature allows multiple users to share a single RS-232C or RS-422 device. With 64k-byte buffer, \$495; with 256k-byte buffer, \$695.

National Instruments Corp.

12109 Technology Blvd, Austin, TX 78727. Phone (800) 531-4742; in TX, (512) 250-9119. TLX 756737.

Circle No 397



PS/2 CONTROLLER

- Connects data-acquisition modules to PS/2 Bus
- Uses one Micro Channel slot to connect 10 modules

The PS/2 interface card, which occupies a single Micro Channel bus slot, connects the vendor's Series 500 data-acquisition system to the IBM PS/2 Model 50 and to higher models. The Series 500 chassis accommodates 10 data-acquisition modules from the vendor's catalog of 30 types, which include A/D and D/A converters; strain-gauge, thermocouple, and LVDT (linear variable differential transformer) signal conditioners; and digital I/O modules. The vendor supplies its software on 3½-in. disks for systems based on PS/2s. The latest software revision permits the transfer of data to applications software such as Lotus 1-2-3 and Asyst. \$770.

Keithley Instruments Inc., 28775 Aurora Rd, Cleveland, OH 44139. Phone (800) 552-1115; in OH, (216) 248-0400. TLX 985469.


Circle No 398

LEADER

LBO-516

NOW 100-MHz OSCILLOSCOPE

✓ \$1495 Manufacturer's
Suggested
List Price



✓ 8-Trace Capability

✓ Alternate Triggering

✓ 2 Time Bases

✓ 3-Channel Input

✓ Clear, Bright Trace

✓ 0.5 mV Sensitivity

✓ 2-Year Warranty

✓ Coast-to-Coast Service

Circle 156 for Product Information

For immediate delivery or more information call toll-free

✓ 800-645-5104

In New York State
516-231-6900

For professionals who know the difference.

LEADER
Instruments Corporation

380 Oser Ave., Hauppauge, NY 11788

Circle 117 for Product Demonstration

TEST GENERATOR


- *Runs on MicroVAX 2000 and VAXstation 2000*
- *Produces in-circuit and functional test programs*

VAXstation 2000 and MicroVAX 2000 can now run ATG-32 automatic test-generation software for the vendor's 227X family of midrange combinational test systems. ATG-32 runs four to eight times faster on the VAX hardware than it does on the PDP-11 series. After you simulate your pc board with the company's HiLo-3 simulator, the Hipost.DTS intelligent postprocessor converts the results into tester-specific functional test models. The test-generation software then uses these models to produce a combinational test program with functional and in-circuit tests. GRnet, the vendor's networking system, includes a test-procedure-management application that automatically uses

Ethernet to transfer programs produced by ATG-32 from the VAXstation or MicroVAX to the tester. ATG-32 for VAXstation 2000, \$15,000; for MicroVAX 2000, \$20,000.

GenRad Inc., 300 Baker Ave, Concord, MA 01742. Phone (617) 369-4400.

Circle No 399



ETHERNET ANALYZER

- *Monitors network performance and isolates faults*
- *Includes lap computer acting as terminal emulator*

The LAN Specialist is a portable system that allows you to monitor the performance of an Ethernet network and diagnose network faults. It consists of a briefcase-sized unit and an IBM PC-compatible lap computer running software that makes it emulate a DEC VT-220 terminal.

You can use the analyzer separately from a network in order to verify the proper operation of units you plan to interconnect. You can also connect the analyzer to an operating network to obtain an indication of which units are producing errors (for example, transmitting messages that frequently collide). The analyzer can make quantitative measurements of network performance; for example, it can calculate network utilization, total errors, errors by station, and errors by type. It can also generate traffic to simulate the effect of expanding the net-

Thermography enters

With the advent of the Hughes Aircraft Company Probeye® 7300 Thermal Video System, thermal imaging has entered a new age—the Age of Information.


In a single package, the Hughes Probeye 7300 Thermal Video System gives you a powerful, intelligent laboratory system with instant field diagnostic capability. Immediately select, store, quantify and analyze. And, most importantly, *understand* the information—with more speed and accuracy than ever before! Hughes has leapfrogged the competition with state-of-the-art features that can't be matched by any other system.

Start with superior resolution—240 infrared lines. Not just on the monitor, but also in the eyepiece of


the portable imager. Which means you can perform on-the-spot detection and analysis in up to 128 distinct levels.

All-electric operation does away with liquid nitrogen or argon gas. The imager uses ac or battery power for full field portability—it goes wherever the information originates.

Fully automatic operation allows you to concentrate on detection and analysis. Precise comparisons are facilitated by built-in features. There's no exhaustive training process. No delays. Just point and read. And, the design is extremely functional—in addition to the portable imager and attached CRT viewfinder, the system includes a processor with built-in, full-function keyboard and a high resolution RGB color monitor.



Circle No 400



- *Let beginners develop micro-programming languages*
- *Work on IBM PC/AT*

The QuickLearn microprogram Starter Kit consists of a group of microprogram development tools: the MicroStep Personal Development Station, a plug-in board for the IBM PC/AT; the MetaStep Microprogram Language System; the EZStep Target System, a microprogrammable system on a board, and a tutorial; and the MetaStep Pro-

programmer's Environment. The Programmer's Environment software uses a menu-driven interface to help you define a custom microprogram language specific to your system's architecture. It also guides you through the processes involved in language development: definition, assembly, linking, and formatting.

Step Engineering, 661 E Arques Ave, Sunnyvale, CA 94088. Phone (800) 538-1750; in CA, (408) 733-7837. TWX 910-339-9506.

Circle No 401

- *Uses 80386 with 16-MHz clock and zero-wait-state static RAM*
- *Compensates for light-intensity variations*

The Intellevue 386 vision computer is based on an 80386 μ P with 1M bytes of zero-wait-state static RAM and an 80287 math coprocessor. A pattern-transform function provides gray-scale pattern matching independent of linear and nonlinear changes in light intensity and pattern contrast. A camera-calibration feature allows the system to compensate for nonorthogonal cameras, perspective distortion, and skewing. The system's windowing function allows you to treat six image buffers as a single spreadsheet and to define source and target windows across the boundaries of individual buffers. The system has four camera ports with standard RS-170 camera interfaces. For program develop-

For details, specifications, and a hands-on demonstration, call or write today. We'll show you how a single system solution can put you into, and on top of, the Age of Information. Hughes Aircraft Company, Probeye Marketing, 6155 El Camino Real, Carlsbad, CA 92009, (619) 931-3617.



HUGHES
AIRCRAFT COMPANY



Precision performance even in limited space. Designed with a right angle lead exit, this ultra compact

gaging head is ideal for measurement in miniature fixturings and of small inside diameters. AC-powered, it features excellent linearity and a gaging range of ± 0.010 ".

Measuring DISPLACEMENT, PRESSURE, ACCELERATION, FORCE/WEIGHT, SLOPE/TILT, or VELOCITY? For nearly half a century, we've demonstrated our commitment to sensor technology with products for a variety of measurement applications.

For complete information on the ultra compact gaging head, write Schaevitz, U.S. Route 130 & Union Avenue, Pennsauken, NJ 08110 or call our **Hot Line: 609/662-8008.**

Grid Scale: 3/8" x 3/8"

Miniature Gage Head (.75" long) Measures Precisely in Tight Places



schaevitz

The Name in Sensor Technology

CIRCLE NO 29


TEST & MEASUREMENT INSTRUMENTS



ment, the vendor supplies a version of the Basic language containing extensions for machine vision. You can also develop programs for the system using the Microsoft C compiler on an IBM PC-compatible computer. \$11,900 without camera; \$14,900 with camera. Delivery, 60 days ARO.

Intelledex, 4750 SW Research Way, Corvallis, OR 97333. Phone (503) 758-4700. TLX 752441.

Circle No 402



SMD ADAPTER


- Works with Data I/O 120/121A programmers
- Gang programs 10 PLCC EPROMs

The Surface Mount Adapter works with Data I/O's 120/121A programmers and uses standard programmer instructions and readouts. It can gang program 10 PLCC (plastic leaded chip carrier) EPROMs on the programmer's 10 upper or lower sockets; you can employ two adapters simultaneously to program 20 devices. To use the adapter, you drop it into the programmer and lock it in place, then you place the master device containing the data to be copied in the first socket of the upper bank of 10. The PLCC sockets are vertically oriented; after programming, you actuate an ejection

tor to pop the devices out of the adapter. \$2000. Delivery, four to six weeks ARO.

Program Automation Inc, 22706 Aspan St, Suite 308, El Toro, CA 92630. Phone (714) 859-8200.

Circle No 403



HANDHELD DMM

- Displays 4½ digits
- Provides 0.05% basic dc accuracy

The 380451 4½-digit handheld multimeter's LCD readout provides dc accuracy of $\pm(0.05\%$ of reading + two digits). The unit provides visual continuity and low-battery indicators, and a data-hold feature that lets you observe readings after you've disconnected the probes from the circuit under test. You select functions and ranges via a 24-position rotary switch. The meter's ranges cover 200 mV to 1 kV ac and dc; 2 mA to 10A ac or dc; and 200 Ω to 20 M Ω . A 0 Ω adjustment applies to the lowest resistance range only; the other ranges require no adjustment. The meter has a built-in tilt stand for benchtop use. \$129.

ExTech Instruments Corp, 150 Bear Hill Rd, Waltham, MA 02154. Phone (617) 890-7440. TLX 940913.

Circle No 404

INSTRUMENTS

CONTINUITY TESTER

- Uses IBM PC or compatible as host
- Learns continuity from known-good unit

You can buy the PC-CAT continuity/discontinuity tester configured for either 128- or 256-point measurements and can expand it to handle as many as 64,000 points. You can choose a desktop, roll-around, or rack-mount model. The tester uses your IBM PC or compatible computer as a controller. Its PC-bus-compatible interface card also works in IBM's PS/2 Model 25 and PS/2 Model 30. Unlike some continuity testers, which merely determine whether the resistance is higher or lower than a fixed threshold value, the PC-CAT actually measures the value of resistance between selected points. This resistance-measuring capability lets you use the unit as a static in-circuit tester for loaded pc boards. To conduct high-volume testing, you mate the PC-CAT to bed-of-nails fixtures, which are available from other vendors. 128-point unit, \$2395; 256-point unit, \$2995.

CEI of Florida Enterprises Inc.
2050 2nd Ave S, St Petersburg, FL 33712. Phone (813) 822-3001.

Circle No 405

FUNCTION GENERATOR

- Provides function-generator outputs for bench or ATE systems
- Has an optional, pulse-generator output

The Model-4434 function generator provides sine, triangular, square, and pulse waveforms from 5 to 50 MHz. It features normal, gate, triggered, and synthesized modes. It can vary the duty cycle and can generate signal trains that have variable initial phases. If you obtain the B-channel option, the instrument will also provide pulse-generator functions such as adjust-

NEW SONY/TEK CURVE TRACERS

BUS PROGRAMMABLE. SYSTEM BASE.

New 370 and 371 curve tracers are like a programmable 576. Get full IEEE-488 bus compatibility, plus the front-panel familiarity that's so important for manual measurements. Use either to produce measurement setups and comparison curves, then store as many as you like on your PC, or up to sixteen of each in onboard memory.

The heart of a measurement system.

Join your 370 or 371 with your PC, or the new Tek PEP 301

RANGE	370	371
Max Peak Voltage	2000V	3000V
Peak Current Pulsed	20A	400A
Max Peak Power	220W	3000W
Price	\$17325	\$19950

(shown), and Tekware™ utilities, and enjoy the speed and accuracy of automatic device-testing software. Do it all easily with a menu-driven interface. Other PC software makes it easy to archive and analyze test results.

Instant hardcopy. To complete the system, connect the Tek HC-100 plotter, for hardcopy with no waiting and no need for a camera. To find out more, contact your local Tek representative or call 1-800-835-9433, ext. 170.



Tekware is a trademark of Tektronix, Inc.
Copyright © 1987, Tektronix, Inc. All rights reserved. SCA-834



able pulse width, single or double pulses, and adjustable rise and fall times. Each channel has a maximum output amplitude of 30V p-p. You can drive the B channel directly from the function generator, or you can connect it to an external generator via the instrument's clock input. You can obtain more complex waveforms by summing two signals. The instrument's modulation modes include external FM and internal or external variable-rate AM. Its non-volatile memory lets you store as many as 25 instrument setups. The instrument has an IEEE-488 interface. Single-channel version Fr fr

62,000; with B-channel option, Fr fr 80,000.

Schlumberger Instruments-Enertec, 5 rue Daguerre, 42030 Saint-Etienne Cedex 2, France. Phone 77252264. TLX 300796.

Circle No 406

Solartron Instruments, 2 Westchester Plaza, Elmsford, NY 10523. Phone (914) 592-9168.

Circle No 407



EMULATOR

- Supports 68030 at 20 MHz
- Dequeues data to provide intelligible trace display

The 68030 Probe/3 in-circuit emulator supports real-time emulation of Motorola's 68030 μ P at clock rates to 20 MHz. To make the trace display intelligible, the unit's post-processing program weeds out pre-fetched, but unexecuted, instructions and data. Though the

unit requires an IBM PC/AT or compatible computer for control, it provides both symbolic and source-level debugging support for code compiled on other machines, such as the Sun 4.2 BSD C compiler, Unix System V compilers that run on a DEC VAX or workstation, and Greenhills and Microtec Research compilers that run on a variety of computers. 16-MHz version, \$16,450; 20-MHz version, \$18,450.

Atron, 20665 Fourth St, Saratoga, CA 95070. Phone (408) 741-5900. TLX 989939. FAX (408) 741-1293.

Circle No 408

Ultra-Speed Memory:

CAPTURE 640 MB IN 3.2 SECONDS

Cluster units to 80 GB


From Dataram: high-speed data acquisition and management for signal/image processing, logic analysis, AI, other advanced applications.

- FAST: 200 MB/sec bidirectional
- FLEXIBLE: up to 8 I/O ports
- ADAPTABLE: interfaces for VAX, MicroVAX, Gould, Star, Numerix, VME, and others
- EXPANDABLE: 8-640 MB/unit

FOR BROCHURE:
Circle the Reader Response Number, or contact us directly for fastest response.


DATARAM

Dataram Corporation
P.O. Box 7528
Princeton, NJ 08543-7528
609-799-0071 • 800-822-0071



CIRCLE NO 31

LIXI® MICROFOCUS — over 100X magnification on CCTV.



Detecting solder voids and solder balls under leadless carrier in a surface mount device.


Find even the smallest defects before they find you.

Lixi's real-time X-ray and portability mean instant inspection on line. You can adjust your processes before bad products fill the pipeline. More than a quality control tool, LIXI MICROFOCUS is your competitive edge in a tough market.

Send us a defective sample - we'll return a picture of the defect.



©1987 Lixi, Inc.
LIXI is a trademark of Lixi, Inc.



Better than a fixed cabinet type X-ray system - better image, greater magnification and lower cost. (Model shown LX-85-708 with optional accessories.)

Lixi, Inc.
1438 Brook Drive
Downers Grove, IL 60515, USA
(312) 620-4646
Telex: 6871077 DKROB
Telefax: (312) 620-7776

CIRCLE NO 32 EDN February 4, 1988

NEW PRODUCTS

CAE & SOFTWARE DEVELOPMENT TOOLS

FUNCTION LIBRARY

- Provides image-compression and -decompression functions
- Conforms to CCITT Group 3 and Group 4 image standards

The CCITT Function Library lets the vendor's TMS34010 graphics processor IC act as an embedded controller for facsimile, CD-ROM, image-scanner, and magnetic-storage systems, all of which have adopted the CCITT Group 3 and Group 4 standards in order to reduce a monochrome image's required storage space by a factor of 20 or more. The library consists of a compression function and a decompression function; both are written in TMS34010 assembly language. The routines come in source-code form (on a 5¼-in. disk or on 1600-bpi tape) and generate 38k bytes of object code. You can call either routine from a C applications program. Payment of the \$3000 license fee entitles you to make unlimited executable copies.



ment of the \$3000 license fee entitles you to make unlimited executable copies.

Texas Instruments, Semiconduc-

tor Group (SC-772), Box 809066, Dallas, TX 75380. Phone (800) 232-3200, ext 700.

Circle No 420

FILTER DESIGNER

- Lets you design FIR and IIR digital filters
- Provides on-screen frequency-response plots

The DFD program lets you design FIR (finite-impulse response) and IIR (infinite-impulse response) digital filters, and runs on the IBM PC and compatible computers. You specify the desired characteristics, such as filter type, sampling rate, cutoff frequency, and passband and stopband ripple; the program then computes the configuration and component values that will most closely approximate the filter characteristics that you want. The FIR-filter types include multiband pass or stop types, differentiators, and Hilbert transformers. The program can design lowpass, highpass, bandpass, and bandstop filters of Butterworth, Chebyshev, or elliptic types.

\$169.

Microcraft Corp, Box 513, Thiensville, WI 53092. Phone (414) 241-8144.

Circle No 421

IC DESIGN TOOL

- Handles design from schematic entry to layout
- Includes analog and digital device libraries

Solo-1200 runs on a variety of desktop workstations—including the IBM PC/AT, Sun, Apollo, and DEC units—and allows you to design mixed analog/digital ASICs. The package provides circuit description via schematic capture or use of the Model hardware description language; switch-level simulation; fully automatic placement and routing; and test-vector generation. To ensure design integrity throughout

the design process, the package also contains a design manager that forces you to adopt good design practice. The system comes with a set of device libraries that include analog functions, gate-level and MSI-level components, 74LS family components, parameterized macros, and functional equivalents of the company's SystemCell standard cell library. Analog functions include 8-bit A/D and D/A converters, multiplexers, op amps and comparators, oscillators, and voltage references. Digital functions include compacted high-complexity RAM blocks; ROM and PLA blocks are being added to the library. Price for a system that runs on an Apollo or Sun workstation, £29,000.

European Silicon Structures Ltd, Mount Lane, Bracknell, Berkshire RG12 3DY, UK. Phone (0344) 525252. TLX 847724.

Circle No 422

PL/M-TO-C TRANSLATOR

- Translates existing PL/M programs to C
- Flags PL/M syntax errors in the list file

The PLC86, PLC51, and PLC80 are translators that convert programs written in PL/M-86, PL/M-51, and PL/M-80 to equivalent programs in C, with comments. The translator checks the syntax of the PL/M-86 source file designated as input, flags any errors that it detects, and generates an output file in a tertiary language that is common to all three translators. The second phase translates the tertiary-language file into logically equivalent, compilable C source code. PL/M comments are transferred to the output file without changes. Any built-in functions for string manipulation and I/O that exist in the input file are converted to calls to external procedures. The C source code conforms to the Kernighan and Ritchie standard, with the addition of the *enum* data type. To run any of the three translators, you need an IBM PC, PC/AT, or a compatible computer that has at least 256k bytes of RAM and runs under MS-DOS 2.1 or a later version. \$475 each.


Micro-Processor Services Inc., 92 Stone Hurst Lane, Dix Hills, NY 11746. Phone (516) 499-4461.

Circle No 423

C DEBUGGER FOR VAX

- Provides source-level debugging facilities for C programs
- Debugs code for 68000-family μ Ps

Validate/XEL is a source-level debugger for C programs that runs on 68000-family μ Ps. This version of the debugger runs on VAX and MicroVAX workstations and consists of two portions: a source-level debugger and a C crosscompiler from Microtec Research (Santa Clara, CA). Two versions of the debugger are available: One is an inte-



grated tool that works with the vendor's ES 1800 in-circuit emulator and the target hardware; the other is a simulator that lets you debug your software before the target hardware is available. Both versions are window oriented, and both give you simultaneous views of the source code and the corresponding machine code, together with the contents of registers, variables, and stacks. The MCC68K crosscompiler creates compact code that is optimized for fast execution. From \$12,500 for the MicroVAX version.

Applied Microsystems Corp., Box 97002, Redmond, WA 98073. Phone (800) 426-3925; in WA, (206) 882-2000. TLX 185196.

Circle No 424

SIMULATOR

- Provides high-frequency, nonlinear-analysis capability
- Helps you design large-signal circuits such as limiters and mixers

The Libra harmonic-balance simulation program combines linear analysis in the frequency domain with time-domain analysis of nonlinear elements. The package includes the vendor's Touchstone frequency-domain simulator for linear simulation. By extending the file to include appropriate models, you can add nonlinear-analysis capabilities. The

simulator will show you time-dependent voltage waveforms at any node; time-dependent current into any nonlinear device; power density and total power; frequency-selective power; and frequency-selective voltage and current, including phase response. You can transfer all of the data from a simulation to a disk file. If you need steady-state response to sinusoidal waveforms, the package lets you obtain solutions based on the vendor's library of microwave components. A new large-signal and small-signal model for GaAs FETs improves the precision of nonlinear simulations of microwave active networks. The program currently runs on VAX/VMS workstations, Apollo Domain-IX workstations, and HP 9000, Series 300 computers under the HP-UX operating system. Prices start at \$20,000 and depend on the system configuration.


EEsof Inc., 5795 Lindero Canyon Rd., Westlake Village, CA 91362. Phone (818) 991-7530. TLX 384809.

Circle No 425

GaAs LOGIC LIBRARY

- Has simulation models for gate arrays and standard cells
- Lets you create schematic net lists and test vectors

The ASIC Designer's WorkSystem has been augmented by a simulation model of TriQuint's (Beaverton, OR) TQ3000 GaAs gate array and simulation models for TriQuint's Q-Logic family of GaAs standard cells. These libraries let you use the vendor's Designer's WorkSystem to create schematic net lists and test vectors in the form that TriQuint requires for physical layout and manufacture of your design. The TQ3000 is an array of 3000 equivalent GaAs gates for applications that operate at frequencies as high as 1 GHz. The Q-Logic standard cells feature 100-psec gate delays, 2-GHz clock speeds, and integration levels as high as 1500 equivalent gates. TQ3000 design manual and



*"CASE and DEC
combine... to offer
CAE solutions
that work!"*

digital

CASE Technology's new Vanguard CAE Design System, in combination with Digital's VAX-based engineering workstations, provides one of the most complete computer-aided engineering solutions available. The system includes schematic capture for PCB and ASIC design, digital logic simulation, circuit simulation and PCB design capabilities.

The strength of the Vanguard CAE design solution is its flexibility. With DECNet and DECNet/DOS, using VAX minicomputers and workstations linked with standard personal computers, an entire engineering facility can be networked, creating a completely integrated design automation environment.

The Vanguard system can also be utilized as a front-end CAE design tool for users that need to integrate existing

tools or as a facility solution for those interested in a single source for their CAE needs.

With more than 3000 installed systems worldwide, CASE Technology has developed a solid reputation as a premier supplier of professional CAE design tools. If you haven't seen what CASE has to offer, then now is the time.

CASE Technology Inc., 2141 Landings Drive,
Mountain View, California 94043
Phone (415) 962-1440; Telex 506513;
Fax (415) 962-1466


**CASE
TECHNOLOGY**

"CAE Solutions Planned *Right* from the Start"

software libraries, \$3000; Q-Logic design manual and software libraries, \$495.

Tektronix Inc., CAE Systems Div, Box 4600, Beaverton, OR 97076. Phone (800) 547-1512; in OR, (503) 645-6464.

Circle No 426



DATABASE ANALYZER

- Combines AI techniques with statistical techniques
- Can perform complex predictions on very large databases

IXL: The Machine Learning System combines statistical methods, symbolic data analysis, induction, and deduction to explore and reveal previously unknown data interdependencies and relationships in very large databases. You can specify the level of error you are willing to accept, the kind of rules that the program should use, and the con-

cepts (both exact and inexact) that the program should use in constructing the rules. The program presents its results in the form of the percentages of data elements that conform to each rule, with a confidence factor based on the variations in the database contents. The user interface is menu driven; it prompts you for all the information it needs, so you don't need any programming experience to use the program. To run the program, you'll need an IBM PC/XT, PC/AT, or a compatible computer that's equipped with at least 512k bytes of

RAM and a hard disk. \$490.

IntelligenceWare Inc., 9800 S Sepulveda Blvd, Suite 730, Los Angeles, CA 90045. Phone (213) 417-8896.

Circle No 427


MATH SOFTWARE

- Runs on 80386-based machines with 80387 or Weitek 1167
- Includes numeric analysis and matrix computation

The 386-Matlab is a new version of the well-known Matlab (matrix laboratory) interactive mathematical software package for scientists and engineers. This version runs on 80386-based computers that are equipped with an 80387 numeric coprocessor. A second version, 386/Weitek-Matlab, runs on 80386-based machines that are equipped with the Weitek 1167 high-speed math coprocessor. Both versions run in

EDN INFO CARDS

The Fastest,
Most Cost-Effective Way
to Generate Sales Leads!



For further information, contact Lauren Fox, EDN Info Cards Manager, at (203) 328-2580.

* Numbers represent actual responses

EDN NEWS




HOT NEWS OF
PRODUCTS, TECHNOLOGY,
AND CAREERS

the protected mode of the 80386 and can thus use all the memory in the system. The program accepts commands in standard mathematical notation, and its basic data object is a matrix that does not require dimensioning and that allows you to solve numeric problems in much less time than you'd need to write an equivalent program in Fortran, Basic, or C. The amount of physical memory in the system is the only limit on matrix or vector sizes, and on the number of variables that you can use. To run the program, you need an 80386-based computer equipped with an 80287 or 80387 numeric coprocessor or the Weitek 1167 coprocessor; at least 1M bytes of RAM; and an IBM CGA or compatible board, an IBM EGA or compatible, or a Hercules monochrome graphics card. 386-MATLAB, \$1495. 386/Weitek-MATLAB, \$1995.

The Math Works Inc., 20 N Main St, Suite 250, Sherborn, MA 01770. Phone (617) 653-1415. TWX 910-240-5521.

Circle No 428



ENHANCED CAD

- Lets you create artwork for complex microwave/RF circuits
- Can activate as many as 35 drawing files simultaneously

MiCAD II is an enhanced version of the vendor's earlier CAD program for designing microwave/RF circuits and subassemblies and for generating the corresponding artwork.

Added features in the user interface include the ability to create user-defined shapes, a rubberbanding capability, better prompts and help screens, and the ability to use single or dual monitors. The database can now handle large and complex designs such as stripline layouts and microstrip; in addition, you can now activate as many as 35 drawing files

simultaneously. A utility program lets you create a preliminary mask file, which you can later convert to another format (such as GDS II or Gerber) for use by your IC manufacturing service. You can run the program on an IBM PC, PC/XT, PC/AT, or compatible computer equipped with the Intel Above-Board (or equivalent expanded

CHOMERICS HELPS YOU CONFORM TO WORLD STANDARDS

WITH FCC/VDE TESTING AND CERTIFICATION SERVICES

For manufacturers of digital devices selling into world markets, meeting applicable EMI emission and susceptibility standards is an unavoidable reality.

Chomerics Radiation Test Services can locate and measure radiated or conducted EMI, develop a cost-effective fix if necessary, and certify your unit to meet FCC, VDE, CISPR, Part 68, MIL, and TEMPEST standards.


Shielding effectiveness of enclosures can be measured from 150 kHz to 18 GHz with 120 dB dynamic range. Cable, line surge and ESD problems also are solved by our experienced engineers utilizing the latest EMI test equipment in our shielded rooms.

So, if you have an existing product, or are just in the design phase, call Chomerics at (617) 935-4850 ext. 355 and let us help you take on the world.

CHOMERICS
a GRACE company

**THE LEADER IN SHIELDING
INNOVATION, DESIGN, AND
TESTING TECHNOLOGY.**

Chomerics Radiation Test Services
77 Dragon Court
Woburn, Massachusetts 01888
TEL: (617) 935-4850
TWX: 710-393-0173



CIRCLE NO 35

memory), or on a workstation such as the Apollo Domain, HP 300 Series, or Digital Equipment's VAX-station. For the IBM PC version, prices start at \$8400, depending on options.

EESof Inc., 5795 Lindero Canyon Rd, Westlake Village, CA 91362. Phone (818) 991-7530. TLX 384809.

Circle No 429

RECTIFIER ANALYSIS

- Predicts dc and ripple output in rectifier circuits
- Accommodates a wide variety of load types

RectSim is a simulator program that runs on the IBM PC, PC/XT, PC/AT, and compatible computers and provides fast and accurate performance predictions for capacitor-input rectifier circuits. The program can simulate single-phase, half-wave circuits, full-wave bridge

circuits, and symmetrical doubler circuits; it predicts dc and ripple output voltages, dc and rms currents, and power dissipation. The program can automatically run a series of simulations that sweep any specified parameters over any desired range of values. To run the program, your PC must have at least 128k bytes of RAM and MS-DOS version 2.1 or higher. \$99.


Design Automation Inc., 809 Massachusetts Ave, Lexington, MA 02173. Phone (617) 862-8998.

Circle No 430

CASE ANALYSIS TOOL

- New features provide 33 types of analysis reports
- Lets you incorporate output in documents

Excelerator is a CASE tool that runs on the IBM PC, PC/XT, PC/AT, and compatibles and the



IBM PS/2 Model 50 and Model 60. Version 1.8 contains substantial enhancements, particularly a new extended-analysis facility. This facility provides 33 types of analysis reports and 25 matrices, which help you evaluate the accuracy, completeness, consistency, and efficiency of system and database designs. The affinity-analysis feature identifies empty, incomplete, or redundant records, as well as screens and reports that have similar or equivalent contents. The data-modeling-analy-

THE CY360 INTELLIGENT WAVEFORM SYNTHESIZER

offers the most powerful and flexible source of audio and low frequency waveforms. Stored program generation of both standard and user defined outputs.



40 pin,
+5 volt,
simple TTL
interface to any
microcomputer I/O port.
ASCII and Binary programmable.
24 Instructions. \$125 ea (\$30/1000)




Cybernetic Micro Systems

P.O. Box 3000, San Gregorio, CA 94074
(415) 726-3000 Telex: 171-135 attn: Cybernetic

CIRCLE NO 36

DATA ACQUISITION PROCESSOR™



ONBOARD INTELLIGENCE FOR IBM PC/XT/AT

- analog and digital I/O to 150,000 samples/second
- 80186 coprocessor—realtime processing
- onboard software, including FFT
- run applications without programming
- direct access to Lotus 1-2-3
- full documentation with sample applications and tutorial—\$20
- digital I/O from \$995
- analog I/O from \$1595

**MICROSTAR
LABORATORIES**

(206) 881-4286
2863 152nd Ave N.E.
Redmond, WA 98052
TLX 5106013473

CIRCLE NO 37

VF Technology... The Bright Decision

Futaba, a world leading manufacturer of vacuum fluorescent displays, offers a wide assortment of *display tubes* in many sizes and formats. Also, Futaba offers *display modules* with all the electronics required to refresh the display and easily interface with the host system.

GRAPHIC DISPLAY

Both front glass phosphor, which provides maximum viewing angle and uniform surface appearance, and conventional back glass phosphor, with optimum brightness and software dimming capabilities, are available. All Futaba graphics modules offer complete drive electronics, bit mapped control with a DC/DC converter. All active components are surface mounted onto a single board.

DOT MATRIX MODULES

Utilizing Futaba's dot matrix displays, a completely intelligent line of "dot modules" is available. Each includes all drive, power supply and microprocessor components surface mounted onto a single board. Surface mounted technology results in higher reliability and allows for a smaller overall package and lower cost. All dot modules require only a 5V DC power source and can accept parallel or 8 possible serial baud rates.

GRAPHIC DISPLAYS/MODULES

Futaba Display	Futaba Module	Pixels (Row X Char.)	Brightness (FT-L)	Module Dimensions (in.)
GP1005B	GP1005B03	128X64	400	7.28X3.35X1.77
GP1006B	GP1006B04	256X64	200	9.84X3.35X1.77
GP1009B	GP1009B03	240X64	200	6.2X2.76X1.57
GP1010B	GP1010B01	176X16	200	7.32X2.16X1.70
GP1002C	GP1002C02	320X240	100*	7.10X6.30X1.60
GP1004B	GP1004B03	640X400	30	9.65X7.28X1.85

*Different Versions Available

DOT MATRIX DISPLAYS/MODULES

Futaba Display	Futaba Module	Char. X Row	Dot Format	Char. Ht. (in.)	Module Dimensions (in.)
20SD01Z	M20SD01	20X1	5X7	0.200	6.3X1.97X.75
20SD42Z	M20SD42	20X1	5X12	0.344	7.1X2.16X.88
40SD02Z	M40SD02	40X1	5X7	0.200	9.45X2.16X.88
40SD42Z	M40SD42	40X1	5X12	0.344	9.45X2.16X.88
202SD03Z	M202SD03	20X2	5X7	0.200	6.7X2.56X.90
402SD04Z	M402SD04	40X2	5X7	0.200	10.43X2.56X.90

MANY OTHER
DISPLAYS




NEW MODULES
AVAILABLE SOON



FUTABA
Corporation of America
Electronic Components Division

711 E. State Parkway
Schaumburg, IL 60173


Telephone: (312) 884-1612
or (312) 884-1444



Compact, flat panel graphic displays and modules present clean, sharp images, whether for text or full graphics application.



2 x 40 character (display)



2 x 40 character (module)

Pattern flexibility and pleasing appearance are offered by Futaba in dot displays and modules.




Futaba also offers a complete catalog of alphanumeric, segmented displays.

Futaba supports its products with design engineering and system integration assistance. Call or write today.

sis feature locates records with missing, mislabeled, or multiple keys; compares connections on data-model diagrams with data relationships described in the data dictionary; and checks data-modeling normalization. The extended structure-analysis feature tracks the use of data at its lowest level to ensure that all data can be processed according to the design. Version 1.8 also lets you integrate Excelerator output with documents generated by Ventura's Desktop Publisher or printed on any laser printer that works with Adobe's PostScript command language. If you have an Excelerator and are covered by the warranty or the product-maintenance plan, you can change to version 1.8 at no charge; otherwise, the upgrade costs \$500.

Index Technology Corp., 1 Main St., Cambridge, MA 02142. Phone (617) 494-8200. TWX 910-380-7014.

Circle No 431



DSP SOFTWARE

- *Acquires, displays, and analyzes complex signals*
- *Lets you design FIR and IIR digital filters*

Hypersignal and Hypersignal Plus are DSP (digital-signal processing) programs that run on IBM PC/XT, PC/AT, PS/2, and compatible computers. They allow you to acquire and display data from files, A/D converters, DSP-chip-emulator or -simulator programs, or serial communications links. You can display this data in single- or dual-waveform time-domain format, and em-

ploy zoom, pan, or random-frame access. You can generate a 3-dimensional spectrogram or can plot the poles and zeros of an IIR (infinite-impulse response) filter. The programs' signal-processing capabilities include FFT and inverse-FFT, convolution, recursive filtering, autocorrelation, and various waveform functions. Hypersignal Plus has all of the above features and further lets you design FIR (finite-impulse response) and IIR digital filters, using the Kaiser Window method or other methods. Once your design is complete, the program can generate assembly-language source-code files representing the filter, for use by Texas Instruments 32000-family DSP chips. Hypersignal, \$349; Hypersignal Plus, \$489.

Hyperception, 9550 Skillman, LB 125, Dallas, TX 75243. Phone (214) 828-3508.

Circle No 432

Turn Good Ideas Into Good Articles

With EDN's FREE Writer's Guide!


Would you like to get paid for sharing your clever engineering ideas and methods with your professional colleagues? If so, then send for EDN's new FREE writer's guide and learn how.

You don't need the skills and experience of a professional writer. And you don't need to know publishing jargon. All you *do* need are a little perseverance, your engineering skills, and the ability to communicate your ideas clearly.

Our new writer's guide takes the mystery and intimidation out of writing for a publication. It shows you how to write for EDN using

skills you already have. Plus, it takes you step-by-step through the editorial procedures necessary to turn your ideas into polished, professional articles.

Get your FREE copy of EDN's writer's guide by circling number 800 on the Information Retrieval Service Card or by calling Sharon Gildea at (617) 964-3030.




EDN PRODUCT MART

This advertising is for new and current products.

Please circle Reader Service number
for additional information from manufacturers.

WAVEFORM SYNTHESIZER



- For IBM-PC/XT/AT and compatibles
- Generates user-definable signal
- Up to 2000 points per envelope



\$795.00

478 E. Exchange St. Akron OH 44304
(216) 434-3154 TLX: 5101012726
1-800-553-1170

CIRCLE NO 325

PAL®/EPLD PROGRAMMER

From
\$689.00



Stand Alone/RS-232 Programs and Verifies
20/24 pin PLDs from MMI, TI, National
Cypress, Lattice, AMD, Altera
PAL is a registered trademark of MMI.

From A Name You Can Trust

LOGICAL DEVICES INC.

1201 N.W. 65th Place
Ft. Lauderdale, FL 33309

1-800-331-7766 (305) 974-0967
Telex 383142 Fax (305) 974-8531

CIRCLE NO 326

WE PROVIDE SOLUTIONS TO
MANY INTERCONNECT PROBLEMS...



- Test Adapters (Socketed LCC/PLCC/PGA)
- Test Clips (Surface Mounted SOIC/PLCC)
- 150 Types of Prototyping Board Adapters
- 125 Types of Programming Socket Converters
- Many Types of Emulator Pod Converters
- PGA/PLCC Extraction/Insertion Tools
- And Much, Much More...



Emulation Technology, inc.

STATE OF THE ART VLSI and SURFACE MOUNT ACCESSORIES

2368-B Walsh Ave. • Bldg. D • Santa Clara, CA 95051
TEL: (408) 982-0660 • FAX: (408) 982-0664

CIRCLE NO 327



CROSS-16 META ASSEMBLER

- Table based 8/16 bit cross-assembler.
 - Uses manufacturer's assembly mnemonics.
 - Tables & Example Source files are included for ALL of the following processor families:
- | | | | |
|--------|--------|-------|------|
| 1802 | 3870 | 64180 | 6502 |
| 65816 | 6801 | 6805 | 6809 |
| 6811 | 68000 | 7000 | 8048 |
| 8051 | 8085 | 8086 | 8096 |
| COP800 | SUPER8 | Z8 | Z80 |
- Users may modify or create new tables for additional processors.
 - Produces listing, symbol table, and 8/16 bit binary. Intel and Motorola hexcode.
 - 5" DSDD for PC/MS-DOS 2.0 or greater.
\$99.95 US \$139.95 CDN
 - Portable C sourcecode is available.

Worldwide shipping (AIRMAIL) & handling included. Credit Card orders (\$139.95 CDN) please specify: Card number, name on card and expiry date.



Universal Cross-Assemblers
P.O. Box 384, Bedford, N.S.
Canada B4A 2X3

CIRCLE NO 328

SMART CARD EXTENDER EASY ON \$165⁰⁰ — PC/XT \$195⁰⁰ — AT

A smart card extender for
PC/XT/AT and compatibles

- Allows card insertion and extraction without power on/off cycles
- Saves time by eliminating DOS re-boots
- Reduces wear and tear on hard disk drives
- Extends host interface for hardware and software development and test
- A single switch controls the connection of all signals to and from the computer bus
- Patent pending



30 DAY NO RISK EVALUATION
APPLIED DATA SYSTEMS
9811 Mallard Dr. Suite 203
Laurel, MD 20708

For more information call **800-541-2003**

CIRCLE NO 329

MINI-PBX SIMULATOR To Save Your Telephone Lines!



Use our MINI-PBX SIMULATORS instead of regular telephone lines or PBX for testing or demonstrating your telecommunication equipment. Because our low-cost instruments simulate telephone lines, you no longer pay high monthly telephone bills or invest in your PBX line increase. Our MINI-PBX SIMULATORS not only simulate PBX, but also simulate the worst telephone lines via a satellite! Some of our features include:

- Simulates 2 to 8 lines PBX
- Accepts pulse or DTMF dialing
- Tones and Ring Signal
- Low Cost
- Line Impairment and Satellite Delay Options
- 20 HZ Ring Signal Option
- Portable (ideal for your next show)


• The Programmable Interface Option provides IEEE-488 and RS232C controls of line impairment conditions and telephone numbers in MINI-PBX SIMULATOR from any computer.

Micro Seven, inc.

P.O. Box 5597
Beaverton, OR
97006
(503) 629-5935
(503) 626-7428

CIRCLE NO 330

To advertise in Product Mart, call Joanne Dorian, 212/463-6415




SOLVE DECOUPLING PROBLEMS

MICRO/Q capacitors with special pinout configurations give superior noise suppression, design ease. Solve special decoupling, routing problems for 8-, 16-, or 32-bit microprocessors, ECL devices, and many other devices where power and ground are not at conventional positions. **Rogers Corp.**, 2400 S. Roosevelt St., Tempe, AZ 85282. 602/967-0624

CIRCLE NO 331

(E) PROM/(E) PLD MULTIPROGRAMMER™ OFFERS 18/12 PROTECTION PLAN



BYTEK's new 135 is a SET EPROM Programmer, a GANG EPROM Duplicator, & a UNIVERSAL Device Programmer. Complete stand alone operation via 25 keys, or PC hookup with RS232. With standard 256Kx8 RAM, the 135 supports more devices than any other production programmer, including 32 pin EPROMs. Can be easily expanded to support 40 pin EPROMs, 40 pin Micros, Bipolar PROMs & Logic Array Devices. 18 MONTH WARRANTY & 12 Month FREE Device Updates.

Model 135-E just \$11195.00

Call today: 1-800-523-1565

In Florida: (305) 994-3520


BYTEK Corporation

1021 S. Rogers Cir., Boca Raton, FL 33487

FAX: (305) 994-3615 TELEX: 4998369 BYTEK

CIRCLE NO 332

THE BETTER RAM TESTER



WITH BETTER COST/PERFORMANCE

IST Model 6400 ADVANTAGES:

- Tests most Static RAMs or DRAMs up to 1Mbit.
- Automatically rejects any out-of-tolerance device (in power consumption or speed) by testing operating current and access time.
- A software controlled edge deskew procedure generates the most precise timing waveforms for DRAMs testing.
- Tests function with a group of specialized test patterns to detect all possible faults.
- Interface to automatic IC handlers with front panel control sorting capability.
- Stand alone or slave to a terminal or computer (via RS-232C) for detailed test result display or failure analysis.
- Modular architecture eliminates set-up time when changing over from one device to another.
- Low cost/high performance with one-year warranty. Price: \$2,500.



487 Gianni Street
Santa Clara, CA 95054
FAX: (408) 980-1794
TELEX: 372 4348 INFO SCAN

FOR LOW COST/
HIGH PERFORMANCE, call:
(408) 988-1908


CIRCLE NO 333

AXELEN 24100

**FOR IBM® PC/XT/AT
PC-BASED LOGIC
ANALYSIS SYSTEM**

- 24 CHANNELS: 100MHz
- A NEW STANDARD AND CONCEPT OF L.A. OPERATION
- EASY-TO-USE WITH ONLINE HELP MENU

- 8CH at 100MHz 8176 bits/CH
- 24CH at 25MHz 2044 bits/CH
- FOUR LEVELS SEQUENTIAL TRIGGER
- MORE THAN 4,000 COMBINATIONS OF TRIGGER CONDITIONS
- DATA QUALIFICATION TO RECORD ONLY EVENTS OF INTEREST
- FAST SCROLLING AND PAGING
- QUICK SEARCH AND LOCATE FEATURE
- BIN/OCT/HEX/ASCII DISPLAY BASE
- HARD COPY




AGENT WANTED! AGENT WANTED! AGENT WANTED!



AXELEN INDUSTRIAL INC.
P.O. BOX 24-650 Taipei Taiwan R.O.C.
FAX: 886-2-7529768 • Tlx: 10305 AXELEN
Tel: 886-2-7529819/7714867

CIRCLE NO 334

EPROM PROGRAMMER \$349



THE EP-1's A GREAT VALUE & HERE'S WHY:

- READS, PROGRAMS, COPIES OVER 300 EPROMS AND EEPROMS FROM 29 MANUFACTURERS INCLUDING 2716-27513, 2804-28256, 27011
- READS & WRITES INTEL, MOTOROLA, STRAIGHT HEX AND BINARY
- OPTIONAL HEADS PROGRAM INTEL 874X, 8751, 87C51, 8755
- MENU-DRIVEN CHIP SELECTION BY MFG & PIN; NO MODULES
- FAST, SLOW, QUICK PULSE PROGRAMMING ALGORITHMS
- SPLITS FILES BY BASE ADDRESS AND ODD/EVEN (16/32 BIT)
- ALL INTELLIGENCE IN UNIT: Z80 MICROPROCESSOR BASED
- 5, 12, 5, 21, 25 VOLT PROGRAMMING FOR CMOS AND -A SUFFIX PARTS
- FREE PC-DOS SOFTWARE
- GOLD TEXT/TOOL ZIF SOCKET
- SAME DAY SHIPMENT
- ONE YEAR WARRANTY
- MONEY-BACK GUARANTEE
- RS232 TO ANY COMPUTER
- 8 BAUD RATES TO 38,400
- GENERATES, CHECKS CHECKSUMS
- TWO FREE FIRMWARE UPDATES
- UV ERASERS FROM \$34.95

CALL TODAY FOR MORE INFORMATION

BP MICROSYSTEMS

800/225-2102 713/461-9430 TELEX 1561477
10681 HADDINGTON #190 HOUSTON, TX 77043

CIRCLE NO 335

New Low Price

DC/DESIGN™ Complete PCB Design Package \$695

Includes Draftsman-EE™ and DC/Check+™, each sold separately for \$395. Low-cost options include:

DC/Autorouter™ \$795
DC/Convert™ (Format Converter) \$195

DC/Design for IBM PCs and compatibles features easy-to-use menus for Schematic Capture; Net List, BOM, and Rat's Nest generation; interactive parts placement and routing; design rule checking; and complete, professional documentation.

Save even more. Our DC/810™ Package includes DC/Autorouter (our low-cost 1-mil diagonal autorouter), Draftsman-EE and DC/Check+ for only \$1,390.

Limited Time Offer:

Order by March 31, 1988 to receive a Free Upgrade worth up to \$1,255, featuring Surface Mount, 64 layers, and Hi-Res support. Call for details.

Call to order with our 30-day money back guarantee. Demo Package also available at \$50.

DESIGN COMPUTATION

Route 33 Sherman Square, Farmingdale, NJ 07727
(201) 938-6661

CIRCLE NO 336


SYNCHRONOUS/ASYNCHRONOUS RS-422, RS-485, RS-232, CURRENT LOOP

SYNCHRONOUS COMMUNICATION

- 1 Mbaud data transfer rate
- DMA facility
- Byte sync, SDLC, HDLC
- RS-422, RS-485, RS-232

ASYNCHRONOUS COMMUNICATION

- Single/dual port option
- Selectable interrupt
- Address selectable
- Current Loop, RS-422, RS-485, RS-232



Leaders in Communication Technology

TOLL FREE: 1-800-553-1170
478 E. Exchange St. Akron, Ohio 44304
(216) 434-3154 TLX: 5101012726 FAX: (216) 434-1409

CIRCLE NO 338

DEVELOP ROMABLE SOFTWARE IN "C" WITHOUT AN EMULATOR

ROM C86™ is a software package that works in conjunction with the Aztec C86.c™ compiler. ROM C86 provides a cost effective means of developing efficient, ROMable software for 8088, 8086, 80188, 80186, and 80286 based microcomputers. The only hardware required is an XT/AT and a functional target system with a serial port.

WITH ROM-C86 YOU CAN:

- Use "C" library functions including PRINTF, FPRINTF, SCAN, FSCAN, MALLOC, and CALLOC.
- Specify the size and location of the stack and heap.
- Download programs from an XT/AT to target RAM via a serial link using the DBR86 loader/debugger program and the DM86 target system monitor.
- Debug programs in target RAM using the powerful symbolic debugging capabilities provided by the DBR86 loader/debugger working in conjunction with the DM86 target system monitor.
- Use the HEXCON conversion program to convert relocatable .EXE files to extended hex format for down loading to an EPROM programmer.

ROM C86 Price — \$499

Call TOLL FREE 1-800-521-0714 Ext. 229


M.K. HANSEN COMPANY

634 Industry Drive, Seattle, WA 98188

Aztec C86.c is a trademark of Manx Software Systems.

CIRCLE NO 339

To advertise in Product Mart, call Joanne Dorian, 212/463-6415



PC488 \$145

LOW COST PC/XT/AT INTERFACE
FOR IEEE-488 (GPIB/HPIB)

- SHORT CARD FOR PC/XT/AT & COMPATIBLES
- 1 OF 6 INTERRUPT LEVELS
- 1 OF 2 DMA CHANNELS
- UP TO 4 BOARDS PER COMPUTER
- CONTROLLER / TALKER / LISTENER
- INCLUDES SOFTWARE DRIVERS
- CUSTOM SOFTWARE SUPPORT AVAILABLE
- COMPATIBLE WITH MOST IEEE488 SOFTWARE PACKAGES FOR THE IBM PC
- QUANTITY DISCOUNTS

Call today for datasheet!!

B&C MICROSYSTEMS

355 West Olive Ave., Sunnyvale, CA 94086
PH: (408)730-5511 FAX: (408)730-5521 TELEX: 984185
VISA & MC accepted.

CIRCLE NO 340

PCB DESIGNED WITH 300+ IC'S IN TWO WEEKS!

In today's highly competitive electronics market, companies with the shortest development cycle will lead the market. At CDI-West we provide a development process shorting design time, increasing quality and saving money.

CDI-West is the largest CAD/CAM facility in California providing full E/M design and tooling. Our specialty is to provide fast turn-around of digital circuits with our CBDS PCB design system. We will take your Daisy, FutureNet etc. CAE netlist into our large IBM mainframe. Sizeable, high-density PCB's are placed, routed automatically, correct to your input specifications. We design to IPC and MIL-P-55110P standards and provide full documentation. We also provide Hybrid and SMT circuit design.


For More Information Contact

CDI CORPORATION: west
DIVISION OF CDI CORPORATION

911 Bern Court, San Jose, CA 95112
(408) 287-9140

CIRCLE NO 341

NEW CONTROL COMPUTER




Our Multitasking Industrial Basic runs as fast as BASICA on the IBM PC/AT. It can also handle interrupts, frequency inputs, bit manipulation, datalogging and more. The hardware includes 4 channels of Analog with 12-bit resolution, 32 digital I/O lines, battery-backed calendar clock, keypad and display ports. 2 RS-232C serial ports, 96K RAM, EPROM and EEPROM programmers, autorun mode, low power CMOS circuitry, 8 MHz Z80 CPU. Only 4.5" x 8". Stand-alone or expandable. Low cost optional software turns your IBM PC into a program development workstation. FREE CATALOG describes other models and accessories. Call 303-428-8540 for same day response.

OCTAGON SYSTEMS CORPORATION 6510 W. 91st Ave.
Westminster, CO 30030

CIRCLE NO 342

SBX MODULES



We've upgraded our SBSxSCSI module to support Block-Mode Pseudo-DMA transfers. That means CPUs without DMA can increase transfer speeds by not polling for READY on every byte. We've also added an optional Centronics-compatible printer port (SBSxSCSI/CEN). If you only need the printer port, save money with our low-cost SBSxCEN module. We also offer a Floppy-Disk Controller module (SBSxFDC) that handles 3 1/2", 5 1/4", and 8" drives with SD, DD and HD formats.

Call or write for more information.

Single Board Solutions, Inc.

20045 Stevens Creek Blvd.
Cupertino, CA 95014
(408) 253-0250

CIRCLE NO 343

ZIPPY SWITCHES

NO: E91274

*FULL DETAILS AND SAMPLES
ON REQUEST


*OEM ARE WELCOME



ZIPPY SHIN JIUH CORP.

P.O. Box 10184 SHIN TIEN TAIPEI HSIEN, TAIWAN, R.O.C.
TEL: (02) 9188512-5 TLX: 33418 ZIPPY FAX: 886-2-9155765

CIRCLE NO 344




LEADLESS CHIP TO WIRE WRAP ADAPTERS

Save prototyping time, these LCC, PCC and PGA socket adapters provide the designer with a labeled test point for each pin and are available for 44, 52, 68 and 84 pin chips. WW pins are on .3" centers. Unit pricing for the 68 pin version is \$49.00 delivered from stock.

Antona Corporation

2100 S. Sawtelle Blvd., L.A., CA 90025
(213) 473-8995

CIRCLE NO 345



ALPHACOM 42®

The ideal printer for **MEDICAL, SCIENTIFIC** and **INDUSTRIAL INSTRUMENTATION**.

- Fast - 2 lines/sec.
- Quiet - Thermal Dot Matrix Printing
- Low Cost - Less than \$125 in OEM quantity
- Plug-In Interface for Serial or Parallel

Alphacom® is a Trade Name of
BROWN KELLOGG, INC.

2108-C Bering Drive
San Jose, CA 95131
(408) 436-0801

CIRCLE NO 346

"D" SIZE PLOTTER

\$2295⁰⁰
RETAIL

\$1695⁰⁰
INTRODUCTORY
OFFER



- Model PC 3600
- Repeatability .001"
- Speed at 7" Per Second
- Vacuum Paper Hold Down
- High Resolution Circles: Suitable for PCB Artwork

(415) 490-8380 **ZERICON**

STEVENSON BUSINESS PARK
BOX 1669 • FREMONT, CA 94538

CIRCLE NO 347

FREE CATALOG OF ELECTRONIC INSTRUMENTS FOR RENT



1987-88 Rental Catalog is available from **Genstar Rental Electronics, Inc.** New equipment from major manufacturers includes analyzers, meters, generators, oscilloscopes, recorders, and

more. Rental terms and conditions are included as well as toll free numbers of the U.S. inventory centers.

RENTAL ELECTRONICS, INC.

6307 De Soto Avenue, Ste. J
Woodland Hills, CA 91367
(800) 227-8409
(800) 331-3440 (in CA)

CIRCLE NO 348

To advertise in Product Mart, call Joanne Dorian, 212/463-6415

E & H Field Probes

\$495



EDN "Readers Choice" (6/25/87)

Makes finding E & H Field emissions easy!


Use with any o-scope or spectrum analyzer. Set includes three H and two E field probes, extension handle, case, documentation, two year warranty. Pre-amp with battery charger, optional. Call, write to order or for brochure.

1-800-253-3761
PO Box 1546 Austin, TX 78767



CIRCLE NO 349

6800/6809 Micro Modules




OEM 6800/6809 MICROCOMPUTER MODULES for dedicated control and monitoring. Interfaces for sensors, transducers, analog signals, solenoids, relays, lamps, pumps, motors, keyboards, displays, IEEE-488, serial I/O, floppy disks.



Wintek Corp.
1801 South Street
Columbia, IN 47504
317-742-5428
800-742-6809

CIRCLE NO 350

RS232



28/24 pin connector **\$150⁰⁰**

DPROM

RS232 Downloadable PROM (32K x 8)

- Eprom emulator for 2716's — 27512's
- Supports 8, 16, or 32 bit wide busses
- Non-Volatile memory standard
- Up to 19200 Baud
- Accepts Intel Hex formats
- 150 ns access time standard


30 DAY NO RISK EVALUATION

APPLIED DATA SYSTEMS
9811 Mallard Dr. Suite 203
Laurel, MD 20708

For more information call **800-541-2003**

CIRCLE NO 751

Analog Circuit Simulation



**NEW
SPICE_NET
\$295.00**

Make SPICE input files from schematic drawings using pull down menus and a mouse to draw and connect parts. Use an IBM PC with any UC Berkeley compatible SPICE program.

Simulation Programs

for

- **IS_SPICE, \$95.00.** Performs AC, DC and Transient analysis.

- **PRE_SPICE \$200.00:** Adds Monte Carlo Analysis, Sweeps, Optimization, libraries and algebraic parameter evaluation.

- **Intu_Scope \$250:** A graphics post processor works like a digital oscilloscope. Easy to use with all the waveform operations you will ever need.


**IBM
PC's
from
intusoft**

(213) 833-0710

P.O. Box 6607
San Pedro, CA
90734-6607

CIRCLE NO 752

SCHEMA II Schematic Capture



FREE Demo Disk: 1-800-553-9119

SCHEMA's success is the talk of the CAE industry and thousands of satisfied SCHEMA owners know why. Incredible speed, ease of use, and power have made SCHEMA a best-selling schematic capture program for engineering professionals the world over.




Now, SCHEMA II is available. SCHEMA II sells for \$495 and supports most common IBM PC/XT/AT configurations. Please call today for a free SCHEMA II demo disk.

OMATION

In Texas Call (214) 231-3167

CIRCLE NO 753



HSC-9160 Graphic CRT Terminal Card


Variable resolution to 640 by 300 dots, multiple and downloadable character fonts. Two serial ports programmable to 38.4K baud, RS-232 and TTL/CMOS levels. Enhanced ANSI X3.64 control sequences. Configurable from host, on card switches or from keyboard. Composite or separate video and an IBM PC compatible keyboard input. The 100 by 160mm card requires 5V only. \$235/ea, quantity discounts and cable assemblies available.

Heritage Systems Corp.

P.O. Box 10588
Greensboro, NC 27404
(919) 274-4818. Telex via WUI 6503057397

CIRCLE NO 754

ELIMINATE DECOUPLING CAPACITORS




CAP-BUS® CAPACITOR/BUS BAR

Eliminate the decoupling capacitors and the power and ground traces from your PCB for more reliability. CAP-BUS® has a distributed capacitance of .05 micro-farads per lin. in., at 50 VDC with low inductance and low impedance. The capacitor and the bus bar have been joined together for CAP-BUS®; a more efficient capacitive decoupled power distribution system, increasing IC density on a two sided board.

ELDRE COMPONENTS, INC. 1500 Jefferson Rd.
Rochester, NY 14623
(716) 427-7280

CIRCLE NO 755



E(E)PROM PROGRAMMER \$495

- Built in Timer Eraser option (\$50); Foam pad;
- **No personality modules;** Menu selection of devices;
- User friendly software; Complete help menu;
- Direct technical support; **Full 1 year warranty;**
- Stand alone duplication & verify (24/28 pins);
- **Quick pulse algorithm** (27256 under 60 sec);
- All 24/28 pin parts to 1 Mbit; CMOS, **EEPROMs;**
- 8741, -2, -4, -8, -9H, -9H, -51, -52, -55, 9761 & more
- **IBM-PC, Apple, CPM or Unix driver; Autobaud RS232;**
- Offset/split Hex, Binary, Intel & Motorola 8, 16, 32 bit;
- **Kits from \$95. Manual with complete schematics.**

Call today for datasheets!!

B&C MICROSYSTEMS

355 WEST OLIVE AVE., SUNNYVALE, CA 94086
Ph: (408) 730-5511 VISA & MC


CIRCLE NO 756

68HC11 EMULATOR

The Micro-AID/11A and an IBM PC/AT provide complete development support for the Motorola 68HC11 microcontroller.

- **In-Circuit Emulator** - Real-time emulation of the 68HC11 in both single chip and expanded modes.
- **Real-Time Trace** - 2Kx32 memory captures up to 2048 cycles of bus activity.
- **Symbolic Debugger** - Allows symbolic reference to parameters in emulator commands.
- **EEPROM Programmer** - Programs the 68HC11 on-chip EEPROM.
- **Micro-AID/05A** available for the 6805 family.

Micro-AID/11A: \$2395.00 Micro-AID/05A: \$1200.00



THORSON ENGINEERING COMPANY

6225 76th St. S.E., Snohomish, WA 98290
(206) 334-4214

CIRCLE NO 757

To advertise in Product Mart, call Joanne Dorian, 212/463-6415




smARTWORK® PCB Software. In a fraction of the time hand taping requires, you can create double-sided printed-circuit boards with smARTWORK and your IBM PC. The program's features include continual design-rule checking, automatic pad shaving, a silkscreen, and text for all three layers. smARTWORK with autorouting is \$895 (without, \$495) and comes with a 30-day money-back guarantee. Credit cards accepted. Write or call

Wintek Corporation

1801 South Street, Lafayette, IN 47904
(800) 742-6809 or (317) 742-8428

CIRCLE NO 758



UNIVERSAL E(E)PROM PROGRAMMER KITS FROM \$ 95

- On board power supply (110/220V AC).
- No personality modules; Device selection by menu.
- Direct technical support; Full 1 year warranty.
- User friendly software; Complete help menu.
- Quick pulse algorithm (27256 under 60 sec).
- All 24/28 pin parts to 1 Mbit; CMOS; EEPROMS.
- Micros: 8741, 8742, 8748, 8748H, 8749, 8749H & more.
- IBM-PC, Apple, CPM or Unix driver; Autobaud RS232.
- Offset/split Hex, Binary, Intel & Motorola 8,16,32 bit.
- Manual with complete schematics.

VISA & MC Call today for datasheets !!


B&C MICROSYSTEMS

355 WEST OLIVE AVE. SUNNYVALE, CA 94086
PH: (408) 730-5511 FAX: (408) 730-5521 TELEX: 984185
EPROM PROGRAMMER

CIRCLE NO 759

ACTIVE FILTERS To 1MHz.

Tiny: 2x1x1/2. 10 days.




Butterworth/Chebyshev • Bandpass/band reject/highpass/lowpass • Ruggedized • NO MINIMUM • Price example: 6-pole Butterworth approx \$87 ea. • Free catalog • For instant information, call our Engineering Hotline: (213) 473-0584.



TTE, Inc.
2233 S. Barry Ave.
West Los Angeles, CA 90064
(213) 478-8224, Telex 3725291.

CIRCLE NO 760



MICRO/Q II

FOR A DECOUPLING CAPACITOR THAT SAVES SPACE, DEFEATS NOISE, IS SUITABLE FOR MILITARY APPLICATIONS AND BEATS HUMIDITY, HEAT AND COLD:

ROGERS MICRO/Q® II

Rogers Corp., 2400 S. Roosevelt,
Tempe, AZ 85282. 602/967-0624

CIRCLE NO 761



Great Designs Start With Tango-Schematic.™ Just \$495.

Designs quickly come to life with Tango-Schematic's easy-to-use drawing editor and extensive component libraries. Features four line types, four text sizes, repeat and block functions, unique built-in word processor. Includes DRC, BOM, Wire List, Net List outputs and crisp plots, prints, or laserprints. The perfect front end to our popular Tango-PCB and Tango-Route board design systems.

For IBM PC/XT/AT/PS2. Just \$495. Full-function Demo Package: \$10. Order toll-free 800 433-7801. VISA/MC. Thirty-day money back guarantee.

ACCEL Technologies, 7358 Trade St., San Diego, CA 92121
Outside N. S. America contact HST Technology (Australia)
Phone: 61-02-34-8499 FAX: 61-02-23-8771

CIRCLE NO 762



Glide Through PCB Design.

TangoPCB™ Create the toughest board designs with powerful layout software that's a snap to use. Function-rich Tango-PCB supports eight layers, 1 mil grid, OrCAD™ or Schema™ netlist input, print/plot/photoplot output, and more.

TangoRoute™ Get impressive completion rates and remarkable speed with Tango-Route, a four layer, eleven pass autorouter.


Just \$495 each.

For IBM PC/XT/AT/PS2. Compare features and you'll buy Tango. Or try full-function Demo Package, just \$10. Order toll-free: 800 433-7801. VISA/MC. Thirty-day money back guarantee.

ACCEL Technologies, 7358 Trade St., San Diego, CA 92121

CIRCLE NO 762

FREE 1988/89 EQUIPMENT GUIDE



U.S. Instrument Rentals has just published its New 1988/89 Product Guide. This free 400 page guide to instrumentation provides information on most of the 5000 different models (from all major manufacturers) of electronic test and measurement and data processing equipment that USIR has in its inventory. The new Product Guide is a comprehensive, single-source reference book containing descriptions, photos, and technical data. Rent, lease, or purchase with immediate delivery. Call today for your free copy!

UNITED STATES INSTRUMENT RENTALS, INC.

2988 Campus Drive
San Mateo, CA 94403 (800) 824-2873

CIRCLE NO 764



Flow Charting II+ The New Plus for Fast Flowcharting

FLOW CHARTING is new! It's now

Flow Charting II+, with more speed + more functions + more printing options;

- 10 text fonts; 26 shapes; • Line mode can stop at a shape; • Backspace key can erase a line to its origin; • Free text entry anywhere, or select auto-centering; • Vertical or horizontal printing; one chart or multiple charts.

Used by Fairchild, Bechtel and more than 500 other major corporations. Edit quickly and accurately — even major edits — with Flow Charting II+, the Specialist.


See your retail store or call:

PATTON & PATTON

Software Corporation
800/672-3470, ext. 897 California
800/538-8157, ext. 897 National
408/629-5044 International

CIRCLE NO 765

IEEE-488



IEEE-488, PARALLEL, and SERIAL PORTS PLUS 4M BYTES of MEMORY

- Control any instrument. RS232 or '488.
- 4Mbytes of extended/expanded memory.
- Software library and memory manager.
- High speed DMA. Risk free guarantee.



Capital Equipment Corp.
99 South Bedford St.
Burlington, MA. 01803

FREE demo disk. Call (617) 273-1818

CIRCLE NO 766


To advertise in Product Mart, call Joanne Dorian, 212/463-6415

Measuring noise figure made easier

Product Note 8970B/S-2, *Applications and Operation of the HP 8970B Noise Figure Meter and HP 8970S Microwave Noise Figure Measurement System*, describes how to measure noise figure from 10 to 18,000 MHz. The publication examines the features and functions of the instruments and gives step-by-step instructions on different methods of measuring. It also serves as a general reference guide for the instruments.

Hewlett-Packard, 1820 Embarcadero Rd, Palo Alto, CA 94303.

Circle No 409




Computer-integrated manufacturing ideas

The 12-pg publication, *The Role of Automated Information in Computer-Integrated Manufacturing*, presents the company's philosophy toward computer-integrated manufacturing: to unify all production, administration, and engineering functions into one computer system. The vendor's goals include improved productivity and higher quality. The brochure also presents major concepts involved in integrating management information and plant-floor information.

Allen-Bradley Response Ctr, Dept 5234, Box 92846, Rochester, NY 14692.

Circle No 410



Guide to memory requirements

The 1988 Designer's Guide to Add-In Memory describes a broad range of memory products from the very technical to the management-oriented. The 80-pg catalog contains information about buses currently in use; DEC's latest offerings; where to find the best price and performance for memory products; and a survey of performance and memory options available from IBM. Also included are the features for the HP-9000 and the MIPS and number of megabytes that are available for the Sun 4/2XX and Apollo DN 4000.

Clearpoint Inc, 99 South St, Hopkinton, MA 01748.

Circle No 411

Linear/digital ASICs characterized

The 182-pg Exar/Exel Military Databook presents product specifications for military-compliant linear/digital ASICs and high-performance electrically erasable devices. It describes fabrication processes and procedures that are used to meet MIL-STD-883C. The fabrication descriptions appear in the sections on product assurance, documentation, military screening and qualification, and quality conformance inspection. Product data

sheets include device features, performance characteristics, materials, drawings, and schematics. Special sections deal with custom and semi-custom linear, as well as digital and linear/digital ICs.

Exel Microelectronics Inc, Box 49007, San Jose, CA 95161.

Circle No 412



How to select the right plotting software

The booklet *Versatec Graphics Software—the complete software plotting solution* helps you choose the right software for your particular needs. It covers four types of software: Versaplot, Versaplot Random, Versaplot Random Enhanced, and a variety of plotting utility packages. The publication differentiates between each type of software and contains a listing of all available packages.

Versatec, 2710 Walsh Ave, Santa Clara, CA 95051.

Circle No 413


App note explains frequency synthesizer

Application note AN969 discusses the MC145159 phase-locked-loop frequency synthesizer, or more specifically, S/H phase detector. It explains that this phase detector is used as a fine-error signal and that the synthesizer also contains sepa-

rate power-supply pins for the analog phase detector, a lock-detect output, and on-chip logic for control of the dual-modulus prescaler.

Motorola Literature Distribution Center, Box 20912, Phoenix, AZ 85036.

Circle No 414



Catalog of lubricants

Lubricants for Electric Contacts and Connectors is the vendor's catalog of specialty oils and greases. It covers four application areas: greases for sliding electric contacts, as in electric switches; oils for sliding contacts and potentiometers; potentiometer greases; and lubricants for stationary separable electric connectors. It describes lubricant properties and operating-temperature ranges and discusses lubricants you can use to help suppress arcing conditions.

William F Nye Inc, Box G-927, New Bedford, MA 02742.

Circle No 415

Software package presented

This 2-pg data sheet focuses on the functions of the Com 2 software driver that provides control of the vendor's logic programmers. It features sections on auto-recall of pre-set parameters, color-enhanced displays, the main menu's device program sequence, and error statis-

tics. It also explains the system requirements and provides a list of devices that the vendor's logic-programmer family supports. Color illustrations and a diagram of the package complete the publication.

Stag Microsystems Inc, 1600 Wyatt Dr, Santa Clara, CA 95054.


Circle No 416

DSP products categorized

The vendor's *1987 DSP Products Databook* includes four categories of DSP products: DSP μ Ps, micro-coded support components, floating-point components, and fixed-point components. It also contains package information, application notes, and an appendix, which includes an ordering guide and a worldwide service directory. A guide to finding product data is provided inside the front cover. Numerous diagrams, tables, schematics, and listings complete the volume.

Analog Devices, Literature Center, 70 Shawmut Rd, Canton, MA 02021.

Circle No 417




Test instruments described

The *TTC Telecommunications Test Instruments* catalog provides information about the vendor's products, their applications, accessories, key features, mainframe options, and specifications. The featured product lines include Fireberd and Data

Sentry 10 data-communication analyzers, Model 124 drop and insert for T networks, and T-Berd T-carrier instruments, which analyze and monitor digital data-communication links, digital-communications simulators, and breakout boxes. Photographs and charts highlight the text.

Telecommunications Techniques Corp, 444 N Frederick Ave, Gaithersburg, MD 20877.

Circle No 418



Discussion of composite amplifiers

The 12-pg application note *AN21: Composite Amplifiers* discusses the compromises you must make in order to achieve optimal speed, drift, bias current, and noise and power output from an amplifier. It provides schematics and descriptions of composite amplifiers, which are suggested as alternatives to simple amplifiers. It describes several applications including a wideband FET input-stabilized buffer; a gain-trimmable wideband FET amplifier; a fast, stabilized noninverting amplifier; and a stabilized, ultra-wideband amplifier with a slew rate exceeding 3000V/ μ sec.

Linear Technology Corp, 1630 McCarthy Blvd, Milpitas, CA 95035.

Circle No 419

EDN's CHARTER

EDN is written for professionals in the electronics industry who design, or manage the design of, products ranging from circuits to systems.

EDN provides accurate, detailed, and useful information about new technologies, products, and design techniques.

EDN covers new and developing technologies to inform its readers of practical design matters that will be of concern to them at once or in the near future.

EDN covers new products

- that are immediately or imminently available for purchase
- that have technical data specified in enough detail to permit practical application
- for which accurate price information is available.

EDN provides specific "how to" design information that our readers can use immediately. From time to time, **EDN's** technical editors undertake special "hands-on" projects that demonstrate our commitment to readers' needs for useful information.

EDN is written by engineers for engineers.

EDN

275 Washington St
Newton, MA 02158
(617) 964-3030

BUSINESS/CORPORATE STAFF

F Warren Dickson
Vice President/Publisher
Newton, MA 02158
(617) 964-3030
Telex 940573
Diann Siegel, Assistant

Peter D Coley
VP/Associate Publisher/
Advertising Sales Director
Newton, MA 02158
(617) 964-3030
Ora Dunbar, Assistant/Sales Coordinator

NEW ENGLAND
John Bartlett, Regional Manager
Chris Platt, Regional Manager
199 Wells Ave
Newton, MA 02159
(617) 964-3730

STAMFORD 06904
George Isbell, Regional Manager
8 Stamford Forum, Box 10277
(203) 328-2580

NEW YORK, NY 10011
Daniel J Rowland, Regional Manager
249 West 17th St
New York, NY 10011
(212) 463-6419

PHILADELPHIA AREA
Steve Farkas, Regional Manager
487 Devon Park Dr
Suite 206
Wayne, PA 19087
(215) 293-1212

CHICAGO AREA
Clayton Ryder, Regional Manager
Randolph D King, Regional Manager
Cahners Plaza
1350 E Touhy Ave, Box 5080
Des Plaines, IL 60017
(312) 635-8800

DENVER 80206
John Huff, Regional Manager
44 Cook St
(303) 388-4511

DALLAS 75243
Don Ward, Regional Manager
9330 LBJ Freeway
Suite 1060
(214) 644-3683

SAN JOSE 95128
Walt Patstone, Regional Manager
Bill Klank, Regional Manager
Philip J Branon, Regional Manager
James W Graham, Regional Manager
3031 Tisch Way, Suite 100
(408) 243-8838

LOS ANGELES 90064
Charles J Stillman, Jr
Regional Manager
12233 W Olympic Blvd
(213) 826-5818

**ORANGE COUNTY/
SAN DIEGO 92715**
Jim McErlean, Regional Manager
18818 Teller Ave, Suite 170
Irvine, CA
(714) 851-9422

PORTLAND, OREGON 97221
Pat Dakin, Regional Manager
Walt Patstone, Regional Manager
1750 SW Skyline Blvd, Box 6
(503) 297-3382

UNITED KINGDOM/BENELUX
Jan Dawson, Regional Manager
27 Paul St
London EC2A 4JU UK
44 01-628 7030
Telex: 914911; FAX: 01-628 5984

SCANDINAVIA
Stuart Smith
27 Paul St
London EC2A 4JU UK
01-628 7030
Telex: 914911; FAX: 01-628 5984

FRANCE/ITALY/SPAIN
Alasdair Melville
27 Paul St
London EC2A 4JU UK
01-628 7030
Telex: 914911; FAX: 01-628 5984

WEST GERMANY/SWITZERLAND/AUSTRIA
Wolfgang Richter
Sudring 53
7240 Horb/Neckar
West Germany
49-7451-7828; TX: 765450

ISRAEL
Igal Elan
Elan Marketing Group
13 Haifa St, Box 33439
Tel-Aviv, Israel
Tel: 972-3-268020
TX: 341667

EASTERN BLOC
Uwe Kretzschmar
27 Paul St
London EC2A 4JU UK
01-628 7030
Telex: 914911; FAX: 01-628 5984

FAR EAST
Ed Schrader, General Manager
18818 Teller Ave, Suite 170
Irvine, CA 92715
(714) 851-9422; Telex: 183653

TOKYO 160
Kaoru Hara
Dynaco International Inc
Suite 1003, Sun-Palace Shinjuku
8-12-1 Nishishinjuku, Shinjuku-ku
Tokyo 160, Japan
Tel: (03) 366-8301
Telex: J2322609 DYNACO

TAIWAN
Acetam International
Marketing Corp
6F, No 43, Lane 13
Kwang Fu South Rd
Mailing Box 18-91
Taipei, Taiwan ROC
760-6209 or 760-6210
Telex: 29809
FAX: (02) 7604784

KOREA
BK International
Won Chang Bldg, 3rd Floor 26-3
Yoido-dong, Youngdongpo-ku
Seoul 150, Korea
Tel: 785-6665
Fax: 784-1915
Telex: K32487 BIZKOR

PRODUCT MART
Joanne Dorian, Manager
249 West 17th St
New York, NY 10011
(212) 463-6415

**CAREER OPPORTUNITIES/
CAREER NEWS**
Roberta Renard
National Sales Manager
103 Eisenhower Parkway
Roseland, NJ 07068
(201) 228-8602

Janet O Penn
Eastern Sales Manager
103 Eisenhower Parkway
Roseland, NJ 07068
(201) 228-8610

Dan Brink
Western Sales Manager
18818 Teller Ave
Suite 170
Irvine, CA 92715
(714) 851-9422

Maria Cubas
Production Assistant
(201) 228-8608

**William Platt, Sr, Vice President, Reed Publishing USA
Cahners Magazine Division**
Terry McDermott, President, Cahners Publishing Co
Frank Sibley, Group Vice President, Electronics/Computers
Tom Dellamaria, VP/Production & Manufacturing

Circulation
Denver, CO: (303) 388-4511
Sherri Gronli, Group Manager
Eric Schmierer, Manager

Reprints of **EDN** articles are available on a custom printing basis at reasonable prices in quantities of 500 or more. For an exact quote, contact Joanne R Westphal, Cahners Reprint Service, Cahners Plaza, 1350 E Touhy Ave, Box 5080, Des Plaines, IL 60018. Phone (312) 635-8800.

IF YOU'RE WASTING TIME LOOKING FOR THE BROADEST LINE OF SMD[®] PASSIVES,

CUT IT OUT!

**Mail to: Mepco/Centralab, Inc., Attn: Corp. Advertising
2001 W. Blue Heron Blvd., Riviera Beach, FL 33404.**

Mail this coupon today to request your personal copy of the new Mepco/Centralab Surface-Mount Device Catalog, containing important design, performance and specifying data on America's broadest line of SMD[®] passive components:

- Tantalum and monolithic ceramic chip capacitors
- Aluminum electrolytic capacitors
- Thick-film and precision metal-film resistors
- Power resistors
- High-performance trimmers

Or ask for our valuable data book on leaded resistors and capacitors.

Please send me these specification guides:

- ☐ 1987 Surface-Mount Device Catalog
☐ Resistor/Capacitor Data Book

Name _____
Title _____
Company _____
Dept. / Div. _____
Address / MS _____
City _____
State / Zip _____

EDN 2/4

MEPCO/CENTRALAB
A NORTH AMERICAN PHILIPS COMPANY

THE ACTIVE LEADER IN PASSIVE COMPONENTS

*SMD is a service mark of North American Philips Corporation.






Illustration of Benjamin Franklin first exhibited in the Great Exhibition of 1851, now permanently on display in the Cafe Royal, Edinburgh.

Independent, idealistic, visionary – his own man. All descriptions which could be applied to both the creative genius and entrepreneur in their pursuit of an ideal.

Such a man was Benjamin Franklin, American statesman and distinguished scientist.

His first attempt to go it alone as a printer – an honest artisan – failed, and it was only his reserves of inner strength and single-mindedness which sustained him.

It's a great pity he couldn't have set up here in Glenrothes. He would have found no shortage of help and

encouragement from well-established companies in the town – Benjamin could even have bought all his paper supplies right here in Glenrothes.

Here, in the heart of Scotland, he would have had the most breathtaking scenery in Europe to allay any homesickness and he could have played golf at St Andrews – before the folks back home in Massachusetts discovered the game.

If like Benjamin, you too are in pursuit of excellence, everything you need is here.


We'd like your company.



GLENROTHES
DEVELOPMENT CORPORATION

FOR FURTHER INFORMATION PLEASE CONTACT: JOHN McCOMBIE, DIRECTOR OF DEVELOPMENT, GLENROTHES DEVELOPMENT CORPORATION, BALBIRNIE HOUSE, GLENROTHES, FIFE, SCOTLAND KY7 6NR. TELEPHONE: 0592-754343. TELEX: 727125.

Placement Agencies:



Let The Job Hunter BEWARE

Deborah Asbrand, *Associate Editor*

Placement agencies' opportunities always sound so attractive. Their large recruiting advertisements in the Sunday editions of most newspapers list dozens of high-salaried jobs in many industries. Some recruiters, using more personalized tactics, place phone calls or write letters to individuals to inform them of job openings that might interest them. And, best of all, the only thing you have to do in order to plug into this network of job opportunities is send in a resume.

The system seems almost too good to be true, and, in most cases, it is. Recruiters do indeed have access to unadvertised job openings, and an individual represented by a reputable agency can benefit from inside contacts. Job counselors,

though, advise that recruiters handle only a small portion of available positions, and that anyone considering working with an agency should be aware that association with a disreputable firm could harm his or her career.

The two most common forms of placement service are search firms and employment agencies. Their methods of operation are different, but both types of business receive their commissions from the hiring company—which means that their primary allegiance is to the company, not to the job seeker.

Placement's elite

Search firms constitute the upper crust of the placement industry. Companies generally hire search

firms to fill jobs that command salaries of \$50,000 or more. Searchers are the true "headhunters": On receiving an assignment, they research their client's industry to identify the leading companies and then target talented employees who might be interested in the client company's job opening.

Search firms say that in their business, discretion is the name of the game. Their clients hire them to conduct judicious, thorough searches. To preserve their industry's sense of propriety, most search firms maintain low profiles and rarely advertise their services. Most politely decline to accept unsolicited resumes. As Jennifer Munro, president of a Greenville, SC, search firm, explains, "Search firms

PROFESSIONAL ISSUES

are not for people who are looking for jobs."


The search-industry's particular etiquette is reflected in its trade jargon. Searchers don't "place" people, they "complete searches." And the searchers themselves aren't recruiters, they're "consultants."

Searchers, who get a fee equal to 30% or more of the open position's salary, roll out the red carpet for clients. Munro's business, Consultants for Corporate Management, includes a researcher, recruiter, and reference checker on its five-member staff. The company spends seven to 10 days researching a job opening, gathering information on the industry involved, and compiling the names of at least 350 candidates before it begins placing phone calls. After reducing the number of candidates to five or six front-runners, Munro meets with each, sometimes traveling cross-country to do so; she then presents her client with the finalists.

Electronics companies typically hire search firms to fill managerial positions such as director of engineering, director of research and development, or vice president of engineering. But they also carry out searches for hard-to-fill engineering specialties. Munro, for example, recently filled a \$60,000 slot for a supervisor of ruby- and sapphire-crystal growing.

Search firms take great pains to

distinguish themselves from their distant relative, the employment agency. Most employment agencies work on a contingency basis—that



is, they don't receive their commission unless the company hires a candidate they've submitted.

Mercurial and competitive

In contrast to the refined, low-key search industry, the contingency-agency business is mercurial and competitive. It's also booming, having grown 30% between 1982 and 1984. As a result, an estimated 18,000 agencies now elbow for the attention of both job seekers and employers.

Most states require agencies to be licensed or registered, but do not

otherwise regulate or supervise them. The low overhead required to set up an agency—and the appeal of commissions that average 20% of a position's annual salary—attracts many newcomers to the field each year. "There are a lot of guys working out of the trunks of their cars," says Carl Tomforde, a recruiter with the Littleton Group, a Littleton, MA, contingency firm. Tomforde adds that a one-person shop doesn't necessarily imply a fly-by-night business. "Some [recruiters] work out of their homes, and they probably do a fine job. They can hand-pick their candidates and can really give them the attention that they're looking for."

Unlike search firms, most contingency agencies are volume businesses. Because an agency doesn't receive a commission unless it comes up with a winning candidate, it's in the agency's best interest to forward as many resumes as possible, increasing the odds that one of the resumes will interest a company and result in a hire.

A tarnished reputation

Not surprisingly, the cutthroat business practices that stem from employment agencies' constant vying for attention have accorded the placement industry a reputation on a par with used-car sales. Two professional associations that seek to promote a positive image are the

Guidelines for choosing an employment agency

- Check out an agency's reputation just as you would evaluate any other business whose services you engage. Ask your friends about agencies they've used or with which they're familiar.
- Most states require employment agencies to be licensed or registered. Call your state's labor office and ask whether any complaints have been filed against any agencies that you're considering approaching.
- Ask about the agency's professional affiliations. Is it a member of the NAPC? Have any of its recruiters been designated Certified Placement Counselors by the NAPC? The NAPC lists its members geographically and by specialty in the *Career Guide Handbook* (\$19.95). For more information, write to the NAPC at 1432 Duke St, Alexandria, VA 22314 or phone (703) 684-0180.

PROFESSIONAL ISSUES


National Association of Personnel Consultants (NAPC) and National Personnel Associates (NPA), both of which require members to adhere to ethical standards. NPA's occasional expulsion of a member, however, indicates the skewed nature of industry morality: The organization most often banishes members not for substandard behavior toward a client company or job hunter, but for infractions against another agency.

Despite the bad will created by unethical agents, contingency agencies can serve job hunters as yet another avenue to new employment. The NAPC estimates that its 2000 members place 50,000 individuals in jobs each year.

A bad rap

Career counselors attribute some of employment agencies' image problems to job hunters' misperceptions. "In all fairness to the agencies, lots of people go to their offices thinking 'here's a person who'll find me a job'—an erroneous expectation," says Libby Pannwitt, vice president at Mulford Moreland &

Associates, a Cupertino, CA, outplacement firm. "The agency's main job is to fill job openings, not to help the job seeker."



Other counselors advise people not to rely on agencies when looking for a job. "Agencies handle 10 to 15% of available jobs, and that's about the percentage of job-hunting time that the job hunter should devote to them," says Ron Wade, a career-management counselor for

Career Directions (Needham, MA.)

Failure to thoroughly check out an agency can ultimately hurt a job hunter's reputation. Some agencies, for example, engage in mass mailing, sending out as many as 200 copies of an individual's resume. Such an inundation of the market makes it nearly impossible for a job hunter to keep track of his resume's whereabouts. It also makes it that much easier for word of a job-hunter's search to enter the rumor mill and find its way back to his or her employer.

Recruiter Carl Tomforde also counsels job hunters to keep a tight rein on an agency's activities and to avoid viewing an agency as a job-hunt panacea. "My advice to candidates who call is to continue doing their own legwork and their own networking."

EDN

Article Interest Quotient
(Circle One)

High 500 Medium 501 Low 502

What to look for in the agency you choose

- Visit the agency to meet with one of its recruiters and to see its operations. Be suspicious of agencies that don't ask you to come in for an interview.
- Find out how your resume will be presented to prospective employers.

Find out whether the agency sends out copies of the resume you submit, or whether it formats your resume in a distinct agency style. Some agencies redo your resume, whereas others merely label your resume with a sticker that lists their name and contact information. Know whether your resume reflects you or the agency that you've sent it to.

- Ask to examine any documentation about you that the company plans to send out.

Know how the agency presents you—and

itself—to potential employers. Does it include a cover letter with the resumes it sends? Will your resume be mailed individually, or will the agency merely include your resume in a stack of others destined for the same company?

- Ask for the names of the companies to which your resume is being sent.

When looking for a job, discretion is the watchword. Many agencies conduct mass mailings, sometimes sending an applicant's resume to as many as 200 companies. They claim that mass mailings offer job candidates broad exposure. Ask the company how it decides which companies it will send your resume to. Exercise quality control and ask to see those companies' names.

Envision the future.

At KLA, the success and growth we've experienced for over a decade has been extraordinary. As a result, we've cemented our position as a leader in automated optical inspection systems. In fact, we've captured and maintained over 70% of the market share in both our two major product lines. And our sales have risen from \$42MM to approximately \$90MM in just the last four fiscal years.

This kind of dramatic growth is fostered by our vision and our commitment to new technology. KLA has a highly charged, goal-oriented environment — one that provides the best mix of variety, stability, and the challenge of our cutting-edge image processing technology. The following are just a few of the over 80 open requisitions (mostly new positions) that we have:

- Software Engineers (14 openings)
 - Systems
 - Image Processing
 - Real-Time
 - Applications
 - Management and lead openings available
- Hardware Design Engineers (lead position also available)
- Mechanical Engineers
- Manufacturing Engineers
- Applications Engineers
- Test Engineers

For more information, send your resume, indicating position of interest, to KLA Instruments Corporation, P.O. Box 58016, M/S 5000, Santa Clara, CA 95052. We are an equal opportunity employer. Principals only, please.



CAREER OPPORTUNITIES

1988 Editorial Calendar and Planning Guide

Issue Date	Recruitment Deadline	EDN	
		Editorial Emphasis	EDN News
Jan. 7	Dec. 14	Computers & Software, Communications ICs	Closing: Dec. 21 Mailing: Jan. 14
Jan. 21	Dec. 30	Microprocessors, Software, Components	
Feb. 4	Jan. 14	Semicustom ICs, Computers & Peripherals	Closing: Jan. 21 Mailing: Feb. 11
Feb. 18	Jan. 28	Materials & Hardware, CAE, Power Sources	
Mar. 3	Feb. 11	Communications, CAE, High-Speed Logic	
Mar. 17	Feb. 25	Graphics, Filters, Software/CAE	Closing: Mar. 3 Mailing: Mar. 24
Mar. 31	Mar. 10	Power Semiconductors, Memory/Graphics, Fiber Optics	
Apr. 14	Mar. 23	Communication Technology Special Issue, Communication Systems	Closing: Mar. 31 Mailing: Apr. 21
Apr. 28	Apr. 7	Software, Industrial Computers, Interface ICs	
May 12	Apr. 21	Analog Technology Special Issue, Analog Converters	Closing: Apr. 28 Mailing: May 19
May 26	May 5	CAE, Software, Sensors/Transducers	
June 9	May 19	CAE, Analog ICs, Test & Measurement	Closing: May 29 Mailing: June 16
June 23	June 2	Data Communications, DSP, Components	
July 7	June 14	Product Showcase—Vol. I, Power Sources, Software	Closing: June 23 Mailing: July 14
July 21	June 30	Product Showcase—Vol. II, CAE, Test & Measurement	

Call today for information:

East Coast: Janet O. Penn (201) 228-8610

West Coast: Dan Brink (714) 851-9422

National: Roberta Renard (201) 228-8602

ENGINEERS

At Northern Telecom, we're exceeding our own goals, achieving the doubling and redoubling of switching system capacity faster than our own ambitious timetable requires. Position your digital communications career a step ahead with the world's largest supplier of fully digital telecommunication systems. We currently have the following openings in the **Research Triangle Park, NC** area.

Research Triangle Park, near Raleigh, is rated among the top three areas for quality of life in the U.S. It offers a mild climate, with 4 seasons, close proximity to the Smokey Mountains and Atlantic Ocean, plus higher education opportunities at three renowned universities: Duke, NC State, and U. of N.C.

Packet Switching Engineers

Requires a degree or equivalent, plus digital telephony experience. Experience must include the operation, administration and maintenance of packet switching networks and network control centers. Must be familiar with OSI protocols such as X.25 and X.75.

ISDN Network Support Engineers

Requires a BSEE/CS or equivalent, plus experience in data and voice communications. Experience must include technical support for packet switching networks and central processing equipment. Also requires an indepth knowledge of data communications, computer protocols and telecommunications.

ISDN Network Design Analysts

Requires a BSEE/CS or equivalent, plus experience in data communications applications and design. Must be knowledgeable of OSI protocols, data transmissions media, LAN, WAN, SNA, NPSI and Packet Switching. A complete understanding of hardware/software requirements for data communications and packet switching is essential.

Artificial Intelligence Development Engineers

Responsible for developing Artificial Intelligence software to automate the switching software system testing process including execution, monitoring and analysis. Requires an applicable degree; an MB or Ph.D preferred. Experience in software development and integration required. Must have a thorough working knowledge of LISP, Pascal and Artificial Intelligence development tools. Other requirements include a working knowledge of statistics, operations research, computer algorithms, large scale software development methodologies and software load building.


Technical Support Engineers

Requires minimum 3 years recent telephony experience working with large digital central office switches of 5000 lines or more; knowledge of high level computer language (PASCAL); and experience with general telephone software. A technical degree is also required.

**To apply, call our 24 hour, 7 days per week,
toll-free number. No resume is required.
1-800-221-3333 Ext. R-14**

If unable to call, interested applicants may send a resume to: **Northern Telecom Inc., Professional Staffing, 800 Perimeter Park, Dept. 1318 (AT-702), P.O. Box 13010, Research Triangle Park, NC 27709.** An equal opportunity employer m/f/h/v.

Build Your Career in Communications.



Design Engineers

If you want to know about the quality of design opportunities at AMD today, just take a look at the projects you'll be working on.

Supernet

The Supernet family is a good example of AMD's optimum use of technologies: three of the chips are CMOS; two are bipolar. Right now we're particularly interested in engineers with experience in bipolar circuitry, preferably in analog/linear IC design. Familiarity with high-speed data acquisition and data conversion is also desirable.

TAXIchip

AMD's interface products have the speed and reliability to change the standards in PCB layout. If you'd like to be part of this, and if you can bring your experience with bipolar digital devices and familiarity with serial interface or controller products, we want to talk about the opportunities for you at AMD. Your specific responsibilities will be the design of CML & ECL logic and analog interface products, and the logic circuit, and physical design of 2500 gate interface products.

Color Graphics IC

AMD was the first to develop color palettes and our technology still leads the industry. Now we're looking to take our leadership even further. You can help us if you have CMOS analog and digital IC design experience, plus familiarity with workstation and IC design CAD tools.

In addition to advanced technologies, AMD offers design engineers real resources. For example, VALID, MENTOR, and CALMA workstations, and smart computer programs that eliminate much time-consuming backend work. You'll also find that our salary and benefits package is competitive.

Interested? If you feel your background qualifies you for these positions, then let us know right away. And if you happen to be in The Bay Area soon, please call. We'll work around your schedule to arrange a more detailed discussion about our technologies. Call Mike Gore at:

(408) 749-5555

If unable to call during business hours, please forward your resume to Advanced Micro Devices, 901 Thompson Place, MS-57/0201, P.O. Box 3453, Sunnyvale, CA 94088. We are an equal opportunity employer.



One great company

Market Development Engineer

Automotive

SGS-Thomson, a leading semiconductor manufacturer, has an immediate need for a Market Development Engineer in our corporate headquarters in Phoenix, Arizona. This excellent opportunity is for a self-starter who will be responsible for providing technical support to SGS-Thomson automotive customers including technical presentations and recommending new product development for automotive applications. Travel within the U.S. and Europe required. The successful candidate should have 3 years experience in design/applications of analog circuitry (radio, audio, motor controls preferred). BSEE or technical degree is required.

We can offer you an outstanding opportunity for personal and professional growth and development with an exceptional benefits package. For immediate consideration send your resume and salary history to: **Jerry Quinn, HR/Box EDN, SGS-Thomson, 1000 E. Bell Road, Phoenix, AZ 85022.**



SGS-THOMSON
MICROELECTRONICS

Equal Opportunity Employer


THE EDN MAGAZINE/EDN NEWS

Recruitment Package

The most cost-effective way to reach the most professionals!

EDN reaches more than 137,000 engineers and engineering managers, the largest circulation in the electronics field. EDN News reaches EDN's U.S. circulation of more than 121,500. And, when you place equivalent space in both the *Career Opportunities* section of EDN, and the *Career News* section of EDN News in the same month, you'll get a 1/3 discount off the EDN News rate!

EDN MAGAZINE/EDN NEWS
Where Advertising Works.



EMERSON ELECTRIC:



EXCELLENCE IN ACTION FROM THE GROUND UP.

At the Government and Defense Group of Emerson Electric, excellence in defense and electronics is a tradition that goes back nearly 100 years. Today, we focus our expertise on a broad range of challenges — from target detection and identification for ground and airborne systems in both the radar and infrared regions as well as producing the world's most modern anti-armor systems. Rigid standards of performance and producibility are evident in every Emerson product. That's the reason for our steady growth and profitability. And that's the stable, challenging environment you'll find now as one of the following:

SOFTWARE DESIGN ENGINEERS

Perform real-time signal processing software development in 6809, 68000 and 68020 microprocessors or assist in the design and development of test sys-

tems software and in application systems depending on your experience which must be in one or more of these languages: VAX, VMS, 1750A, FORTRAN, C, ADA, JOVIAL, FORTH, ROLM, Assembler, or ATLAS. An MS in Electrical Engineering or Computer Science/Engineering is preferred.

RADAR SYSTEMS ENGINEERS

Seeking experienced engineers to design and produce modern coherent radar systems. Responsibilities include all elements of specification and system design, routinely provide technical presentations, and serve as the interface to our customers. BS in EE, Physics, or Math and 10 years radar design experience are desired.

SENIOR SYSTEMS ENGINEERS

Lead the development of anti-armor missile launching and guidance systems as well as fire support and target acquisition systems. Experience in advanced system concepts synthesis, tradeoff studies, system error budget development, performance analysis and requirements derivation desired. MSEE/MSME (PhD desired) with 10+ years experience in optics, electro-optics, stabilization, electronic design, or real-time software would be a definite plus.

BUSINESS DEVELOPMENT ENGINEERS Radar and Armament Systems

Exciting efforts are underway to break new ground with optic, electro-optic, laser, radar, and land navigation products and programs. To make the most of these opportunities, we seek seasoned engineers to take responsibility for new product definition, market analysis, business planning, and product introduction.

To qualify, you will need a BSEE (MSEE/MBA preferred) and 10-15 years experience with all aspects of anti-armor missile launching and guidance systems and/or fire support target acquisition systems. Prior military experience would be a definite plus.

At Emerson, a century of excellence in national defense creates a future of opportunity for you. We offer you ongoing challenges, an excellent salary, and complete benefits. Plus we're located in St. Louis, one of the Midwest's most popular cities and an exciting environment for any lifestyle.

To explore these opportunities, please send your resume in complete confidence to:

Steve Borgmeyer
Emerson Electric Co.
Electronics and Space Division
Mail Station 4690, Dept. EDN
8100 W. Florissant Avenue
St. Louis, MO 63136

An equal opportunity employer. U.S. citizenship is required.



EMERSON ELECTRIC CO.
Government & Defense Group

MANAGER ADVANCED RADAR SYSTEMS

Our client, a medium sized Electronics Company, located in the Northeast, has an immediate need for an individual to manage a small group of Radar Systems Engineers. This activity is being formed to provide the company with direction in its radar systems business efforts.

The group will have responsibility for:

- the development of new concepts in radar systems.
- advising management on the expenditure of IR&D funds.
- assuming a lead position on proposal efforts.
- maintaining technical support with customers.
- technical follow of in-house radar engineering projects.

An advanced degree in Electronic Engineering or Physics is required with a minimum of ten years' experience in radar system theory, signal processing, microwave systems and antennae.

The company is located near a medium sized urban area, with a wide spectrum of recreational facilities.

Call Graham Murray collect at (215) 968-0707 or send resume to:

WALSH

Engineering Placement
Service

Continental Corporate Centre
P.O. Box 301
Newtown, PA 18940




Equal Opportunity Employer

If You're Looking
For a Job,
You've Come to
The Right Place.

EDN CAREER
OPPORTUNITIES

EDN

First in Readership Among Design
Engineers and Engineering
Managers in Electronics



E L E C T R O N I C S E N G I N E E R S

JOIN A STATE-OF-THE-ART LEADER, LOCATED IN NEW MEXICO, THE LAND OF ENCHANTMENT Heart of the Rocky Mountain Southwest

Gulton Data Systems is a leading supplier of Pulse Code Modulation (PCM) telemetry and telemetry-related equipment for major aerospace corporations and the U.S. Government. Gulton Data Systems offers a high technology environment in which to advance your professional career. Our key involvement in booster and missile systems, telemetry and command satellite systems and space instrument systems provides an ever-widening scope for career advancement and challenge.

SENIOR ELECTRONICS DESIGN ENGINEERS

BSEE or MSEE. Minimum of 8 years experience in digital and analog design involving space/aerospace systems. Experience must include at least 2 years at project engineer level.

ELECTRONICS DESIGN ENGINEERS

BSEE or MSEE. 3 to 5 years experience in digital and analog design. Some space/aerospace systems experience required.

Gulton Data Systems offers excellent benefits and a competitive salary commensurate with experience...plus ALBUQUERQUE!

Send resume to: **Personnel, Dept. 2AL7, GULTON DATA SYSTEMS, 6600 Gulton Ct., NE, Albuquerque, NM 87109.**

Gulton Data Systems is an Affirmative Action/Equal Opportunity Employer. U.S. Citizenship required.

gulton DATA SYSTEMS
A MARK IV COMPANY

EDN Databank

Professional Profile

Announcing a new placement service for professional engineers!

To help you advance your career, Placement Services, Ltd. has formed the EDN Databank. What is the Databank? It is a computerized system of matching qualified candidates with positions that meet the applicant's professional needs and desires. What are the advantages of this new service?

- It's absolutely free. There are no fees or charges.

- The computer never forgets. When your type of job comes up, it remembers you're qualified.

- Service is nationwide. You'll be considered for openings across the U.S. by PSL and its affiliated offices.

- Your identity is protected. Your resume is carefully screened to be sure it will not be sent to your company or parent organization.

- Your background and career objectives will periodically be reviewed with you by a PSL professional placement person.

We hope you're happy in your current position. At the same time, chances are there is an ideal job you'd prefer if you know about it.

That's why it makes sense for you to register with the EDN Databank. To do so, just mail the completed form below, along with a copy of your resume, to: Placement Services, Ltd., Inc.

IDENTITY

Name _____ Parent Company _____
Home Address: _____ Your division or subsidiary: _____
City _____ State: _____ Zip: _____ Location (City, State) _____
Home Phone (include area code): _____ Business Phone if O.K. to use: _____

PRESENT OR MOST RECENT EMPLOYER

EDUCATION

Degrees (List)

Major Field	GPA	Year Degree Earned	College or University

POSITION DESIRED

EXPERIENCE

Present or Most Recent Position _____ From: _____ To: _____ Title: _____

Duties and Accomplishments: _____ Industry of Current Employer: _____

Reason for Change: _____

PREVIOUS POSITION:

Job Title: _____
Employer: _____ From: _____ To: _____ City: _____ State: _____
Division: _____ Type of Industry: _____ Salary: _____
Duties and Accomplishments: _____

COMPENSATION/PERSONAL INFORMATION

Years Experience	Base Salary	Commission	Bonus	Total Compensation	Asking Compensation	Min. Compensation
Date Available	I Will Travel <input type="checkbox"/> Light <input type="checkbox"/> Moderate <input type="checkbox"/> Heavy			<input type="checkbox"/> I own my home. How long? _____ I rent my home/apt. <input type="checkbox"/>		
<input type="checkbox"/> Employed <input type="checkbox"/> Self-Employed <input type="checkbox"/> Unemployed		<input type="checkbox"/> Married <input type="checkbox"/> Single		Height _____ Weight _____		
Level of Security Clearance		<input type="checkbox"/> U.S. Citizen	<input type="checkbox"/> Non-U.S. Citizen	My identity may be released to: <input type="checkbox"/> Any employer <input type="checkbox"/> All but present employer		
<input type="checkbox"/> WILL RELOCATE		<input type="checkbox"/> WILL NOT RELOCATE		<input type="checkbox"/> OTHER _____		

EDN Databank

A DIVISION OF PLACEMENT SERVICES LTD., INC.

265 S. Main Street, Akron, OH 44308 216/762-0279

SEARCH ME



On-line technical career opportunities

Welcome to the job network of the future. A free service, with 24-hour access to on-line career information. Exclusively for experienced technical professionals. Communicate directly with high-tech and Fortune 1000 companies. From your PC or terminal at home or at work, at your leisure. Confidentially. Enter or upload your resume for fast, direct response.

Whether you're just a little curious or actively pursuing a new job, you'll find what you're looking for on-line with BPI AdLine. Explore high-tech opportunities, employee benefits, everything you need to know about today's greatest career challenges.

BPI AdLine. The smart way to stay in touch.

Created by the same people who bring you the original BPI TECH FAIRS. You can also use BPI AdLine to check on dates, times and locations of upcoming TECH FAIRS in your area.

To get on-line and
leave your resume
with BPI AdLine:



Dial 612-941-3957
on your PC or terminal
and modem. Enter the
password "BPI"

**BPI AD
LINE**

"We are not an employment agency."

Business People Inc., The Nation's Leader in Recruiting Technology, 100 North Seventh Street, Minneapolis, MN 55403 Phone 612-370-0550

ADVERTISERS INDEX

ACCEL Technologies Inc	245	Hamilton Avnet Electronics	141, 185	Sophia Computer Systems Inc	67
AIDA	116-117	Harris Semiconductor/ Linear Products Div	C2	Spectrum Software	47
Altera Corp	54-55	Heritage Systems Corp	244	Sprague Electric Co	63
Ametek Inc	152	Hewlett-Packard Co	134, 214-215	Stanford Research Systems Inc	48
AMP Inc	170-171	Hilevel Technology Inc	125	Supertex Inc	86
Amperex Electronic Corp*	183	Hitachi America Ltd*	88, 200-201	System Industries	32-33
Antona Corp	243	Houston Instrument	90	Taiwan Liton Electronic Co Ltd	202
Applied Data Systems	241, 244	Hughes Aircraft Co/ Industrial Products	228-229	TEAC Corp**	22
Applied Microsystems Corp	93	Industrial Devices Inc	127	Tektronix Inc	42-43, 58, 143-145, 231
ASIX	12-13	Information Scan Technology Inc	242	Teradyne Inc	50-51
AT&T Technologies	69-71	Inmos Corp	10-11, 195	Thorson Engineering Co	244
Atron	56	Intel Corp	98-99	Toshiba America Inc	112-113
Augat-Interconnection Systems	41	Intusoft	244	TRW/RF Devices	100
Avis Rent-A-Car	167	I/O Tech**	240A-F	TTE Inc	245
Axelen Industrial Inc	242	Janco Corp	208	United Technologies Microelectronics Center*	115
B&C Microsystems	243, 244, 245	John Fluke Manufacturing Co Inc*	22, 163	Universal Cross-Assemblers	241
Belden Electronic Wire & Cable	207	Kepeco Inc	105-110	Universal Data Systems	C3
BKL Industries	127	KeyTek Instrument Corp	36	US Instrument Rentals	245
BP Microsystems	242	Leader Instruments Corp	227	VCH International	84-85
Brooktree Corp	220-221	Linear Technology Corp	188	Westcor	6
Brown Kellogg Inc	243	Lixi Inc	232	Wintek Corp	244-245
Burr-Brown Corp	27	LKPF Co	34	Wilinx	128-129
Bytek Corp	242	Logical Devices Inc	241	XKD Corp	222
Caddock Electronics Inc	204-205	Marconi Instruments*	197	Yamaha	82-83
CADdy Corp	68	Maxtor	52	Zax Corp	72-73
Calcomp	216-217	Mepco/Centralab	249	Zericon	243
Canon USA Inc	218	Micro Seven Inc	241	Ziatech Corp	224A-F
Capital Equipment Corp	245	Microstar Laboratories	238	Zilog Inc	193
Carroll Touch Inc*	81	Midwest Components	80	Zippy Shin Jiuh Corp	243
Case Technology	235	Mini-Circuits Laboratories	3, 4, 28-29, 191		
CBM America	36	M K Hansen	242		
CDI Corp—West	243	Modutec Inc	224		
Chinon America Inc	213	Molex Inc	264		
Chomerics Inc	237	Multibus Manufacturers Group	37-40		
Clearpoint	225	National Instruments	206		
Comlinear Corp	56	National Semiconductor Corp	146-147, 186-187		
Connector Corp	68	NEC Corp	44-45		
Control Data	150-151	Nidec Torin Corp	211		
Crystal Semiconductor	16-17	Oak Switch Systems Inc	209		
Cybernetic Micro Systems	48, 238	Octagon Systems	243		
Cypress Semiconductor	25	OKI Semiconductor	130-131		
Dale Electronics Inc	1	Omaton Inc	244		
Data Display Products	199	Orion Instruments	49		
Data I/O Corp	8	Patton & Patton	245		
Dataram Corp	232	P-Cad	18-21		
Deltron Inc	210	Philips Elcoma Div**	14-15		
Design Computation Inc	242	Philips Test & Measuring Instruments Inc**	27, 81		
Digital Electronics Corp	87	Planar Systems	79		
Digital Equipment Corp*	168-169	Precision Monolithics Inc	35		
Ecco Industries	223	Prem Magnetics Inc	2		
Eldre Components Inc	244	Qua Tech Inc	241, 242		
Electro-Mechanics	244	Raytheon Semiconductor Div	61		
Emcor Products/Crenlo Inc	211	Rogers Corp	242, 245		
Emerald Computers	76	Rohm Corp	74		
Emulation Technology Inc	241	Samsung Semiconductor	94-95, 96-97		
Fujitsu Microelectronics Inc*	14-15	Schaevitz Engineering	230		
Futaba Corp of America	239	Seagate Technology	165		
Gates Energy Products Inc	174	Signal Transformer Co Inc	C4		
Gennum Corp	46	Silicon Systems Inc	102-103		
Genstar Rental Electronics	243	Single Board Solutions	243		
GE/RCA Solid State	30-31, 148-149, 172-173				
Glenrothes Development Corp	258				
Gould Inc, Test & Measurement Group	132-133				
Greatlink Electronics Taiwan Ltd**	183				

Recruitment Advertising254-261

Emerson Electric
Northern Telecom
SGS Semiconductor
Walsh Engineering Placement Services

*Advertiser in US edition

**Advertiser in International edition

This index is provided as an additional service. The publisher does not assume any liability for errors or omissions.

LOOKING AHEAD


EDITED BY CYNTHIA B RETTIG

Fax machines should see 25% annu growth through 1991

Speed, low cost, and ease of use—all of these advantages will combine to push US shipments of electronic facsimile machines to the 1,000,000 mark in the very near future, according to CAP International Inc of Marshfield, MA. CAP maintains that fax equipment is becoming as common in the office as are copiers and phone systems. Indeed, facsimile machines now present a reasonable alternative to overnight delivery systems. In 1987 alone, facsimile systems achieved an estimated 90% increase in shipments over the 1986 rate. From 1987 to 1991, the US market should experience a compounded annual growth rate of 25%.

Network providers will benefit from related opportunities. Mirroring moves by voice-system and data-telecommunications-system vendors, network vendors will begin to offer enhancements and options to their services, such as store functions and forward-messaging capacity. Within the next five to 10 years, CAP expects network providers to find high-volume applications that will use both stand-alone facsimile machines and computer-based image transmitters.

TOTAL SHIPMENT OF HUMIDITY AND MOISTURE INSTRUMENTS



Humidity/moisture devices to gross \$113.9M by 1992

Within the next few years, new technologies and improvements in old ones will substantially increase the market for instruments that measure humidity and moisture, according to a Venture Development Corp (Natick, MA) study. In 1987, the market for such instruments was about \$80.7 million; by 1992, the total number of units shipped will represent \$113.9 million in sales, reflecting a 7% projected annual growth rate.

Annual unit shipments will increase minimally throughout the forecast period, averaging just 2.9% through 1992. But revenue will grow more rapidly because, as technology improves and the use of electronic components increases, the selling price of each kind of instrument will rise proportionally.

The critical issue will be the replacement of organically based relative-humidity measurement devices with measurement devices of more sophisticated design. Despite numerous humidity-measurement applications in various products, processes, and environments, humidity remains one of the most difficult environmental conditions to measure. A great many potential users have expressed dissatisfaction with the limitations of organically based instruments and the contamination and calibration-drift problems that advanced devices currently pose.

As more sophisticated products become available, this group of potential users will prove an important source of sales for vendors—as will a second group composed of those who have yet to appreciate the cost advantages, reliability, and accuracy of these instruments.

US FAX MARKET: 1986 TO 1991

	1986	1987	1988	1989	1990	1991
YEARLY REVENUE OF BOTH FAX BOARDS AND STAND-ALONE MACHINES	\$712M	\$1093M	\$1361M	\$1542M	\$1675M	\$1723M
SHIPMENTS OF FAX BOARDS	2500	11,500	33,070	70,250	151,000	227,500
SHIPMENTS OF STAND-ALONE MACHINES	191,000	365,000	490,000	605,000	655,000	715,000


(SOURCE: CAP INTERNATIONAL INC)

Molex Is Making The Connection Between...

FLEXIBILITY & RELIABILITY

Eleven different components are your building blocks for thousands of interconnection solutions.

Molex's unique family of KK® connectors provide the flexibility you need to build interconnections precisely suited to your applications. Choose either tin or cost-effective selective gold plating, .100" or .156" center spacing. Crimp, solder, or insulation displacement termination...top, side, or bottom pin entry...break-to-size pin headers...they're all standard in thousands of demanding applications.



Gold plating placed selectively on terminal contact points means added economy.

The KK® connector is just one example of how we take a total systems approach.


The KK® System includes a complete line of wire termination tooling from simple hand crimp tools to the latest automated insulation displacement technology. The System also features sophisticated pinsetting equipment. Molex goes beyond merely supplying connectors to help today's manufacturers achieve lower installed costs.

Dependable service worldwide.

Our multi-national organization offers you interconnection design, manufacturing, and technology from around the globe, with dependable supply and local service.

Molex distributors stock the full line of flexible KK® connectors for your every need.

Intensive QC programs provide reliable connectors that stand up to tough environmental conditions in a wide range of electronic applications.



Unique break-away design allows you to order pin headers in bulk and break off the exact lengths you need to save on inventory and waste.



**Service To The
Customer...Worldwide**

Corporate Headquarters: 2222 Wellington Ct., Lisle, IL 60532 USA, (312) 969-4550 • European Headquarters: Aldershot, England, (0252)318221
Northern Asia Headquarters: Tokyo, Japan, 03-478-8777 • Southeast Asia Headquarters: Jurong Town, Singapore, 65-261-9733




Exotic Customs at UDS

The special requirements of data communications OEMs have resulted in some pretty exotic custom modem cards from Universal Data Systems.

Funny form factors are routine fare for our custom designers. Nooks, crannies and odd card configurations are no problem, given sufficient square inches of real estate. UDS engineers have even designed a circular 212A modem that fits in the back of a residential electric meter.

Non-standard modem functions are another specialty of the house. For example, UDS engineers have already designed and



For a generous sampling of UDS' custom design capabilities, ask for the new, free OEM modem brochure.

delivered a hand-held RF modem operating at 4800 bps!

UDS has successfully handled more than 3,000 custom OEM modem design assignments — and we can handle yours. To begin an exotic custom, contact Universal Data Systems, 5000 Bradford Drive, Huntsville, AL 35805. Telephone 205/721-8000; Telex 752602 UDS HTV.



Universal Data Systems



MOTOROLA INC.
Information Systems Group

UDS modems are offered nationally by leading distributors. Call the nearest UDS office for distributor listings in your area.
DISTRICT OFFICES: Apple Valley, MN, 612/432-2344 • Atlanta, GA, 404/998-2715 • Aurora, CO, 303/368-9000 • Blue Bell, PA, 215/643-2336 • Boston, MA, 617/875-8868 • Columbus, OH, 614/895-3025 • East Brunswick, NJ, 201/238-1515 • Glenview, IL, 312/998-8180 • Houston, TX, 713/988-5506 • Huntsville, AL, 205/721-8000 • Livonia, MI, 313/522-4750 • Mesa, AZ, 602/820-6611 • Milwaukee, WI, 414/273-8743 • Mission Viejo, CA, 714/770-4555 • Mountain View, CA, 415/969-3323 • Renton, WA, 206/235-9977 • Richardson, TX, 214/680-0002 • St. Louis, MO, 314/434-4919 • St. Peters, MO, 314/434-4919 • Silver Spring, MD, 301/942-8558 • Tampa, FL, 813/684-0615 • Uniondale, NY, 516/222-0918 • Van Nuys, CA, 818/891-3282 • Willowdale, Ont, Can, 416/495-0008 • Winston-Salem, NC, 919/760-4184

CIRCLE NO 79

Created by Dayner/Hall, Inc., Winter Park, Florida

Dual Personality.

Custom or standard, Signal's ingenious split bobbin designs offer flexibility - at a very rational price.

You already know that Signal is the world leader in off-the-shelf transformers. What you may not know is that we're equally dedicated to our custom business.

But it's true. You can get any of the three transformers you see here as standard - or customized to your exact specs. From the versatile Split/Tran® to the low profile Flathead® to the half-sized 2-4-1.

Whichever you choose, you'll also get Signal's innovative design.


It's become an industry standard. Because, unlike ordinary transformers which require shielding to obtain high isolation, ours separate the primary and secondary windings using the split bobbin design we pioneered. Not only does this guarantee high isolation, it delivers healthy savings as well.

As for customization, we give you the full treatment. Flexible modifications or custom designs. Fast quotes and prototypes. Even annual contracts.

Signal also meets important international standards. Our off-the-shelf units are UL recognized. Many of them meet VDE and offer optional CSA certification. What's more, every custom transformer is designed to meet UL standards, too.


And we deliver PRONTO. Standard prototypes are shipped within 24 hours. Your order is shipped factory-direct - so there's no middleman...no hidden costs.

Analyze the full line yourself. Call or write for our free catalog: Signal Transformer, 500 Bayview Avenue, Inwood, NY 11696.



SPLIT/TRAN®

2500V RMS HIPOT. Non-concentric windings and low capacitive coupling. Available with 115V or dual 115/230V primaries. Split secondary windings can be series or parallel connected.




8 pin type DST. 6 pin type ST and

FLATHEAD®

Ideal for low height, critical pc board power applications. 5 sizes from 2.5VA to 48VA.


(Semi-toroidal windings.)



2-4-1


2500V RMS HIPOT. The signal for a 50% cut in transformer size and weight at a significantly lower cost.

Six sizes from 2.4VA-100VA.



Dual primary.
Single primary also available.

BUY DIRECT
(516) 239-5777



Signal Transformer.

The American Original.

Insilco
International Specialty Companies

CIRCLE NO 66